FREQUENCY SPECIFICATIONS

FREQUENCY RANGE

Tuning Range

With internal mixer: 0.01 - 18.00 GHz.

With external mixer: 12.4 - 40 GHz.

Selectable continuous coarse (by means of pushpull knob) and fine tuning determine display center frequency.

Harmonic Mixing Mode

Signal Identification: Signal identifier separates unknown input signal in center of CRT into two images 2 divisions apart with image on left slightly less in amplitude when the calibrated frequency scale is advanced to the appropriate band.

Scan Width

- Full Scan: Inverted marker positioned by tuning control identifies the frequency that becomes the center frequency for scan width per division and zero scan modes. The width of the scan depends on mixing mode. Scan width = n \times 2000 MHz, where n is the mixing mode; e.g., for n = 2, scan width is 4 GHz.
- Per Division: 16 calibrated scan widths from 2 kHz/div to 200 MHz/div in a 2, 5, 10 sequence.
- Manual Scan: (Available with 8552B only.) Scan determined by front panel control; continuously variable across CRT in either direction.
- Zero Scan: Analyzer becomes fixed tuned receiver with frequency set by frequency and fine tune controls and selectable bandwidths by bandwidth control. Amplitude variations are displayed versus time on CRT.

FREQUENCY ACCURACY

Dial Accuracy: n x $(\pm 15 \text{ MHz})$ where n is the mixing mode.

Scan Accuracy: Frequency error between two points on the display is less than 10% of the indicated separation.

Stability:

Total Analyzer Mixing)	Residual	FM	(Fundamenta	
Stabilized		U	nstabilized	
<100 Hz		<10 kHz		
peak-to-peak	-peak peak-to-peak			
			00.77	

First LO residual FM typically 30 Hz.

Noise Sidebands: For fundamental mixing. More than 70 dB below CW signal, 50 kHz or more away from signal, with 1 kHz IF bandwidth and 100 Hz video filter.

RESOLUTION

- Bandwidth Ranges: IF bandwidths of 0.10 to 300 kHz provided in a 1, 3 sequence.
- Bandwidth Accuracy: Individual IF bandwidth 3 dB points calibrated to $\pm 20\%$. (10 kHz bandwidth $\pm 5\%$).

Bandwidth Selectivity:

IF Bandwidth	60 dB/3 dB Ba 8552A	ndwidth Ratio 8552B
10 kHz - 300 kHz	20:1	20:1
1 kHz - 3 kHz	20:1	11:1
0.1 kHz - 0.3 kHz	25:1	11:1

AMPLITUDE SPECIFICATIONS

ABSOLUTE CALIBRATION RANGE

Measurement Range



See "Input Specifications" for maximum levels to INPUT .01 - 18 GHz connector and to input mixer.

- Log Reference Level: From -130 dBm to +10 dBm, in 10 dB steps. Log reference level vernier, 0 to -12 dB continuously.
- Linear Sensitivity: From 0.1 μ V/div to 100 mV/div in a 1,2 sequence. Linear sensitivity vernier 1 to 0.25 attenuation ratio continuously.

Sensitivity

Average Noise Level: Specified for 1 kHz bandwidth. Using lower bandwidths will improve average noise level; e.g., use of 100 Hz bandwidth will improve noise level in the 1.5 to 3.55 GHz frequency range from -117 dBm to -127 dBm max.

With INTERNAL Coaxial Mixer

Frequency Range (GHz)	Mixing Mode (n)	IF Freq. (MHz)	Average Noise Level (dBm max.)
0.01 - 2.05	1-	2050	-115
1.50 - 3.55	1-	550	-117
$2.07 \cdot 6.15$	2-	2050	-108
2.60 - 4.65	1+	550	-117
4.11 - 6.15	1+	2050	-115
4.13 - 10.25	3-	2050	-103
$6.17 \cdot 10.25$	2+	2050	-105
6.19 - 14.35	4-	2050	- 95
8.23 - 14.35	3+	2050	-100
10.29 - 18.00	4+	2050	- 90

With 11517A EXTERNAL Waveguide Mixer and Appropriate Waveguide Tapers

Average Noise Level (Typ.)
-90 dBm
-85 dBm
-75 dBm

Table 1-1. 8555A/8552A/8552B Specifications (Continued)

Residual Responses: Referred to signal level at input mixer on fundamental mixing: <-90 dBm.

Display Range

- Log: 70 dB, 10 dB/div with 8552B 2 dB/div log expand on a 16 dB.display.
- Linear: From 0.1 mV to 100 mV/div in a 1, 2 sequence on an 8-division display.
- Display Uncalibrated Light: Panel light warns operator of uncalibrated amplitude display if the IF or video bandwidth selected is too narrow for combination of scan width and scan time selected.

Input Attenuator Range: 0 - 50 dB in 10 dB steps.

ABSOLUTE CALIBRATION ACCURACY

The overall absolute calibration accuracy of the spectrum analyzer in a particular application is a function of the measurement technique. The following elements also affect absolute calibration accuracy:

Frequency Response: With 10 dB input attenuator setting.

Frequency Range (GHz)	Mixing Mode (n)	IF Freq. (MHz)	Frequency Response (dB max.)
0.01 - 2.05	1.	2050	±1.0
1.50 - 3.55	1.	550	±1.0
2.07 - 6.15	2-	2050	±1.25
2.60 · 4.65	1+	550	±1.0
4.11 - 6.15	1+	2050	±1.0
4.13 - 10.25	3-	2050	±1.5
6.17 - 10.25	2+	2050	±1.5
6.19 - 14.35	4-	2050	±2.0
8.23 - 14.35	3+	2050	±2.0
10.29 - 18.00	4+	2050	±2.0

IF gain variation with different bandwidth settings: (at 20°C).

Linear: ± 5.8%.

Amplitude Display: Log ± 0.25 dB/dB but not more than ± 1.5 dB over the full 70 dB display range.

Linear: $\pm 2.8\%$ of full 8-division deflection.

- Input RF Attenuator: Frequency response typically ±0.6 dB from 10 MHz to 18 GHz.
- Log Reference Level: Accurate to ± 0.2 dB ($\pm 2.3\%$ Linear Sensitivity).
- Log Reference Level Vernier: Accurate to ± 0.1 dB (1.2%) in 0, -6, and -12 dB positions; otherwise, ± 0.25 dB ($\pm 2.8\%$).
- Calibrator Output: Amplitude -30 dBm, ±0.3 dB. Frequency 30 MHz, ±0.3 MHz (8552A),±3 kHz (8552B).

INPUT SPECIFICATIONS

Input Impedance: 50Ω nominal (0.01 - 18 GHz).

Reflection Coefficient: <0.130 (1.30 SWR) for input RF attenuator settings ≥ 10 dB.

Maximum Input Level:

DO NOT EXCEED THE FOLLOWING MAXIMUM INPUT LEVELS:

Max- imum Input dB Levels	POW	ER ¹	VOLTS ²		
	dBm	Watts	DC	Rms	Peak
Input 0.01 - 18 GHz Connec- tor	+33	2	±20	10	14.14
Incident on Input Mixer	+10	10mW	±20	0.707	1.0

¹ The INPUT ATTENUATION control must be in the 30 dB or greater position when applying +33 dBm or input mixer will be damaged. The power levels listed apply for peak or average power.

 2 Do not exceed \pm 20 volts dc. Apply only dc voltages with rise times less than 10^6 volts per second. Do not change INPUT ATTENUATION levels when dc voltages are applied to RF INPUT Connector.

RF Input Connector: Type N female.

External Mixer Input Connector: BNC female; LO power transfer to external mixer through connector as well as 2.05 GHz IF signal return to spectrum analyzer. LO power typically 0 dBm.

SCAN TIME SPECIFICATIONS

Scan Time: 16 internal scan rates from 0.1 ms/div to 10 sec/div in a 1, 2, 5 sequence.

Scan Time Accuracy: 0.1 ms/div to $20 \text{ ms/div}, \pm 10\%$, 50 ms/div to $10 \text{ sec/div}, \pm 20\%$.

GENERAL SPECIFICATIONS

Power Requirements: $115 \text{ or } 230 \text{ volts } \pm 10\%$, 50 - 60 Hz, normally less than 225 watts (varies with plug-in units used).

Dimensions: Model 140T or 141T Display Section, 9-1/16 in. H (incl. feet) x 16-3/4 in. W x 18-3/8 in. D (229 x 425 x 467 mm). Model 143S Display Section, 21 in. H (incl. feet) x 16-3/4 in. W x 18-3/8 in. D (533 x 425 x 467 mm).
Weight: Model 8555A RF Section: Net 14 lb 15 oz (6,8 kg). Model 8552A IF Section: Net 9 lb (4,1 kg).

Model 8552B IF Section: Net 9 lb (4,1 kg). Model 140T Display Section: Net 37 lb (16,8 kg). Model 141T Display Section: Net 40 lb (18 kg). Model 143S Display Section: Net 62 lb

(28, 1 kg).

Log: ±0.5 dB.