

1. Product introduction:

Dear customer, thank you for your choose our products! The machine appearance generous, novel, stable performance, unique function, easy to use. Phone choose double system (DTMF/FSK) compatible with caller display according to the keyboard, advanced microcomputer control. In order to better develop the function of this machine is superior, please read the instructions before use.

2. Functional features

• Handle the volume can be adjusted

- DTMF/FSK double standard caller id (to be automatic recognition)
- Telephone number and call time record 54 group (8) or 34 (16)
- 3 groups of single bond memory
- To number 14 (8) or 8 group (16) and the talk time record
- Real-time date and week display, LCD brightness level 5 is adjustable
- Don't disturb 1 ~ 99 hours
- 16 the first ringtones choice
- Software to set the ringing volume, buttons to set the ringing volume and speaker volume, no need to switch
- Software set up electronic anti-theft; Optional soft set P/T, do not need to switch
- The keys 4 lock function, hardware
- 90/95 100/120 180/300 600/1000 FLASH time optional ms software
- Three groups of alarm function setting, alarm sound is different in each group
- In bad forget lines or hang machine, automatic line (line no clutter interference)
- Intelligent rob line exit code 8-bit Settings
- Local code 8-bit Settings, telephone automatic filtering

3.1 set menu functions

Hot press SET button to enter setting state, under the LCD display SET 1234567 , the press numeric keys or press wave choose Settings, LCD displays the corresponding item SET at the same time, in a setting is completed, press the delete key to exit a directory, then press the number keys or going through up and down keys to choose the next SET. (use the up and down keys to select the setting item, will enter the submenu items, need to press the set key again to turn up and down keys to select, here is introduced with the digital key choice set items only). Specific set project is as follows:

3.1.1 set DATE/time: press the set key option 1, LCD will be prompted to , 1-DATE 2-CL. Option 1 to enter the date Settings, see flickering font, directly enter the Numbers at this time, press the set key again to confirm; When the date is set automatically identify the week after the completion of the program, select 2 enter the time setting, setting method is the same as the date is set. According to the hands-free sets out.

3.1.2 ring and ring volume: press the set key option 2, LCD will be prompted to r 1 t 2 VIP 3 vol, 1 into the ordinary phone ring selection, LCD display ring type 01 press up and down turn key at this time choose ringing the bell, and then press the set key to confirm, click the delete button to return to a directory; Choose 3 into the ringtone volume, LCD display ring vol 2 at this time in turning up and down keys to adjust the bell volume, according to the hands-free sets out.

3.1.3 alarm Settings, press the set key choice 3, LCD will be prompted to AL 1-2-3, choose 1 to enter the first set of alarm Settings, LCD display ALAR OFF, see OFF flashing alarm time direct input, finally press the "set" key to confirm, if you want to close the alarm to press set key to shut down after a group of selected choose OFF again with the flip up and down key; The other two groups set same as group 1 set; The first set the alarm for a one-time, 2, 3 groups for the alarm clock every day, in the process of the alarm, press any key to stop.

3.1.4 don't disturb time setting: choose 4 press set key, the LCD will display off_r 00-00, font flashing input time (maximum 99; when the maximum 59) after press the set key, press the delete key to exit. Don't disturb function starts, the LCD will display time don't disturb, cancelled automatically after the countdown to 00 00 - don't disturb, machine or a hands-free out of don't disturb. Don't disturb during calls don't ring (except VIP number).

3.1.5 special features to choose set: press the set key to select 5, LCD will be prompted to 1-2 - pt 3- d , option 1 into the flash time setting, LCD display flash 600, according to flip up and down keys to select flash time at this time. Failure time is: 90,95,100,120,180,300,600,1000 ms; Option 2 into the P - T conversion, LCD display pt tone according to turn up and down keys selection methods at this time, the initial value for audio dial-up state; Choose 3 into the security set, LCD display defend off according to turn up and down button on/off. (security code to * #),

3.1.6 local code and exit code set: choose 6 press set key, the LCD will be prompted to 1-LOC , 2-OL option 1 to enter the local code set, LCD display LOC... The direct input 1 ~ 8 digits press set key to confirm again, if you want to cancel the local code, press the delete key to delete the input when the input state number, press the set key again to confirm. Option 2 enter exit code set, screen out off, setting method and the local code setting in the same way, if you want to cancel out code, can choose off by turning up and down keys.