

PLESSEY

INTERCONNECT

Connectors—Mk 4 Brass

Dimensions and weights Brass Mark 4 Plugs and sockets

Free plugs and sockets

Fixed plugs and sockets (Round flange)

MOUNTED FROM FRONT OR REAR OF PANEL

To mount from front of panel, remove mounting ring and gasket.

To mount from rear of panel, remove thread adaptor and locking washer.

Use a panel mounting washer on panels up to 1/2" thick

| Contact Arrangement | Weight (oz.) | | Shell Size | A | B | C dia. | D |
|---------------------|--------------|------|------------|------|-----|--------|------|
| | Plug | Skt. | | | | | |
| 2-19 amp. 250 V | 2.5 | 2.5 | 1 | .87 | .34 | 1.25 | 1.02 |
| 3-5 amp. 250 V | 2.5 | 2.5 | | | | | |
| 4-5 amp. 250 V | 2.5 | 2.5 | | | | | |
| 6-5 amp. 250 V | 2.6 | 2.6 | | | | | |
| 2-35 amp. 250 V | 3.5 | 3.4 | 2 | .86 | .34 | 1.51 | 1.02 |
| 3-19 amp. 2 kV | 3.4 | 3.4 | | | | | |
| 4-19 amp. 250 V | 3.4 | 3.4 | | | | | |
| 6-5 amp. 500 V | 3.4 | 3.4 | | | | | |
| 6-5 amp. 2 kV | 3.4 | 3.4 | | | | | |
| 12-5 amp. 250 V | 3.4 | 3.4 | | | | | |
| 3-60 amp. } 250 V | 5.8 | 5.5 | 3 | 1.02 | .42 | 1.92 | 1.19 |
| 1-19 amp. } 250 V | 5.6 | 5.7 | | | | | |
| 2-60 amp. } 250 V | 5.4 | 5.4 | | | | | |
| 3-19 amp. } 250 V | 5.6 | 5.7 | | | | | |
| 6-19 amp. 2.5 kV | 5.6 | 5.6 | | | | | |
| 9-19 amp. 250 V | 5.5 | 5.5 | | | | | |
| 13-12 amp. 250 V | 5.5 | 5.5 | | | | | |
| 18-5 amp. spec. | 5.6 | 5.6 | | | | | |
| 25-5 amp. 250 V | 5.6 | 5.6 | | | | | |

| Contact Arrangement | Weights (oz.) | | Shell Size | A | B | C dia. |
|---------------------|---------------|------|------------|-----|------|--------|
| | Plug | Skt. | | | | |
| 2-19 amp. 250 V | 1.8 | 1.9 | 1 | .60 | .90 | 1.125 |
| 3-5 amp. 250 V | 1.9 | 1.8 | | | | |
| 4-5 amp. 250 V | 1.9 | 1.9 | | | | |
| 6-5 amp. 250 V | 1.9 | 1.9 | | | | |
| 2-35 amp. 250 V | 2.5 | 2.5 | 2 | .60 | .90 | 1.343 |
| 3-19 amp. 2 kV | 2.4 | 2.4 | | | | |
| 4-19 amp. 250 V | 2.5 | 2.5 | | | | |
| 6-5 amp. 500 V | 2.4 | 2.4 | | | | |
| 6-5 amp. 2 kV | 2.4 | 2.4 | | | | |
| 12-5 amp. 250 V | 2.5 | 2.5 | | | | |
| 3-60 amp. } 250 V | 4.1 | 3.9 | 3 | .67 | 1.02 | 1.718 |
| 1-19 amp. } 250 V | 4.0 | 4.1 | | | | |
| 2-60 amp. } 250 V | 3.8 | 3.8 | | | | |
| 3-19 amp. } 250 V | 4.0 | 4.1 | | | | |
| 6-19 amp. 2.5 kV | 3.6 | 3.6 | | | | |
| 9-19 amp. 250 V | 3.9 | 3.9 | | | | |
| 13-12 amp. 250 V | 3.9 | 3.9 | | | | |
| 25-5 amp. 250 V | 4.0 | 4.0 | | | | |

374

Tel. Crawley (0293) 28700 Telex 87131 **SASCO** Tel. Glasgow (041-221) 6152 Telex 778841