





Indicating Fuses • Blocks & Holders • Relays & Controls • MOVs • Medium Voltage Fuses

Local Resources for a **GLOBAL** Market

Rollingh

Littelfuse products help protect electrical equipment used in construction, general industrial, oil & gas, solar, mining, and OEM applications. We offer a broad and reliable selection of fuses, fuse blocks, protection relays, and generator controls to improve safety and reduce downtime.

For decades, we have helped OEMs, electrical installers, design engineers and end-users select the right product for their applications. Today, Littelfuse offers a broader range of products addressing protection, sensing, and control needs while still providing the same great service and support that customers have learned to expect.





Littelfuse App!

Download our free Littelfuse Catalogs and Literature App to keep our products and technical resources at your finger tips!



A Broad Portfolio of Circuit Protection Products, Relays and Controls

Fuses & Holders

UL Class Fuses Medium Voltage Fuses High-Speed Fuses UL Class Fuse Blocks Dead-Front Fuse Holders Indicating Products Power Distribution Blocks OEM Custom Products

Relays & Controls

Ground-Fault Protection Trailing Cable Protection Resistance Grounding Motor & Pump Protection Arc-Flash Protection Generator Controls Engine Control & Diagnosis Custom Products

Technical & Safety Resources

Datasheets White Papers CAD Drawings Electrical Curves Training Videos Technical Articles High Power Test Lab Technical Hotline

Table of Contents



1	Fuses
---	-------

Class L Fuses	8
Class RK1 Fuses	13
Class RK5 Fuses	16
Class K5 Fuses	20
Class J Fuses	21
Class T Fuses	
Class G Fuses	26
Class CC/CD Fuses	27
UL Supplemental/10 x 38 Fuses	

2 Electronic Fuses & Automotive Blade

Glass/Electronic Fuses	
Blade/Automotive Fuses	

3 Medium Voltage Fuses

Medium Voltage Fuses Overview	39
R-Rated Medium Voltage Fuses	40
E-Rated Medium Voltage Fuses	42

4 Telecommunication Products

Telecommunications	Power Fuses	50

5 Special Purpose Fuses

Solar Products Overview	56
1500 Vdc Solar Rated Fuses	57
1000 Vdc Solar Rated Fuses	59
Forklift/Stud Mounted Fuses	62
Plug Fuses	63
MEGA® Bolt-Down Fuses	63
In-Line Fuses & Holders	64
Cable Limiters	65
Cylindrical Fuses	66
OEM Custom Products	67
L Series (Traditional) High-Speed Fuses	69
LA Series (Alternate Dimension) High-Speed Fuses	71
Square Body High-Speed Fuses	77

6 Fuse Blocks & Holders

LF Series Fuse Blocks Overview	83
Class J Fuse Blocks	85
Class H, K5 & R Fuse Blocks	88
Class T Fuse Blocks	94
Class G Fuse Blocks	99
Class CC/CD & Midget Fuse Blocks	101
LF Series Fuse Block Covers	105
Solar Rated Fuse Blocks	
Dead Front Fuse Holders	109

Miscellaneous Fuse Blocks & Holders	116
High-Speed Semiconductor Fuse Blocks	120
Distribution & Splicer Blocks	122
In-Line Fuse Holders	132
7 Pre-Engineered Solutions	
LCP Fused Selective Coordination Panel	
LPS Series POWR-Switch (Shunt Trip Disconnect)	141
Protection Relays & Controls	
Relay & Control Products Overview	143
Feature Comparisons	146
Ground-Fault Protection	148
Trailing Cable Protection	151
Resistance Grounding & NGR Monitoring	152
Motor Protection	
Pump & Feeder Protection	156
Arc-Flash Protection	
Industrial GFCI (Shock-Block™)	157
Generator & Single-Function Protection	158
Generator Control	163
Engine Control & Diagnosis	167
Alarm Monitoring	168
Custom-Engineered Electrical Equipment	170
Relay & Control Accessories	171
Suppression Products	
Industrial Varistor Products	173
Surge Suppression Fuses	175
BVSP Suppression Fuses	176
Miscellaneous Accessories	
Fuse Reducers	
Box Cover Units	
Fuse Replacement & Custom Kit (FRCK Series)	
Fuse Display & Cabinet	
1 Technical Application Guide	

Fuseology Fundamentals	183	
Selection Considerations	184	
Time-current Curves & Peak Let-through Charts	189	
Selective Coordination	191	
UL/CSA Fuse Classes & Applications	194	
Terms & Definitions	196	
Motor Protection Tables	203	
Alphanumeric Index of Catalog Numbers	206	
Condensed Fuse Cross Reference	208	

FUSE CLASS AND SELECTION CHART

UL CLASS	LITTELFUSE SERIES	OVERLOAD CHARACTERISTICS	VOLTAGE (VOLTS)	AC RATINO CURRENT (AMPERES)	GS INTERRUPTING (AMPERES)	VOLTAGE (VOLTS)	DC RATINGS CURRENT (AMPERES)	INTERRUPTING (AMPERES)	RECOMMENDED FUSE BLOCKS AND FUSE HOLDERS	FUSE SERIES PAGE NUMBERS
	KLPC	Time-Delay	600	200 - 6000	200K / 300K*	480	200 - 6000	20,000		8
L	KLLU	Time-Delay	600	601 - 4000	200,000	300	601 - 4000	20,000	- I	9
	LDC	Fast-Acting	600	150 - 2000	200,000	600	150 - 2000	50,000		10
-	LLNRK	Time-Delay	250	0.1 - 600		125	0.1 - 600	_	LFR25	13
-	LLSRK_ID	Time-Delay	600	0.1 - 600	200K / 300K*	300	0.1 - 600	-	LFR60	13
RK1	LLSRK	Time-Delay	600	0.1 - 600		300	0.1 - 600	20,000	LFR60	13
	KLNR	Fast-Acting	250	1 - 600	000.000	125	1 - 600	-	LFR25	15
	KLSR	Fast-Acting	600	1 - 600	200,000	250 300	1 - 30 35 - 600		LFR60	15
	FLNR ID		250	35 - 600		125	35 - 600			17
ŀ	FLNR		250	0.1 - 600		125	0.1 - 600	-	LFR25	17
RK5	FLSR_ID	Time-Delay	600	0.1 - 600	200K / 300K*	300	0.1 - 600	20,000		17
	FLSR	, into boldy	600	0.1 - 600	2001() 0001(300	0.1 - 600	20,000	LFR60	17
	IDSR		600	0.1 - 600		600	0.1 - 600			16
	JTD_ID	Time-Delay	600	0.8 - 600		200	0.0 100			21
-		,			200K / 300K*	300 500	0.8 - 100 110 - 600	20,000		
J	JTD	Time-Delay	600	0.8 - 600		500	110 000		LFJ60 • LFPSJ	21
	JLS	Fast-Acting	600	1 - 600	200,000	-	-	-		22
т	JLLN	Fast-Acting	300	1 - 1200	200,000	160 125	1 - 60 70 - 1200	20,000	LFT30 • LSCR002 (700-800A)	24
•	JLLS	Tast-Acting	600	1 - 1200	200,000	300	1 - 1200	20,000	LFT60 • LSCR002 (700-800A)	24
CC	CCMR	Time-Delay	600	0.2 - 30	200K / 300K*	250 250 300 500	0.2 - 2 4.5 - 10 2.25 - 4 12 - 30	20,000	L60030C • LFPSC • LPSC • 571 • 572 •	27
	KLDR	Time-Delay	600	0.1 - 30	200,000	300	0.1 - 30		LEC • LEY	28
	KLKR	Fast-Acting	600	0.1 - 30	200,000	300	0.1 - 30			28
CD	CCMR	Time-Delay	600	35 - 60	200K / 300K*	250	35 - 60	20,000	LFC60060	27
G	SLC	Time Lag	600 480	0.5 - 20 25 - 60	100,000	170	0.5 - 60	10,000	LFG600 (½ - 20A) LFG480 (25 - 60A)	26
	SPF	Solar	-	-	-	1000	1 - 30	20,000	LFPHV	60
Solar	SPFJ	Solar	600	125-450	200,000	1000	70 - 450	20K (70 - 200A) 10K (250 - 400A) 20K (450A)	LFJ1000	61
oolui	SPFI	Solar	-	-	-	1000	2 - 30	20,000	Not Required	59
	SPXV	Solar	-	-	-	1500	6 - 30	30,000	LPXV	57
	SPXI	Solar	-	-	-	1500	2.5 - 30	30,000	Not Required	58
	NLN		250	1 - 600		250	1 - 600	20K (1 - 60A) 50K (70 - 600A)	LFH25	20
К5	NLS	Fast-Acting	600	1 - 600	50,000	600 500 400 600 500	1 - 7 8 - 30 35 - 60 70 - 200 225 - 600	20K (1 - 60A) 50K (70 - 600A)	LFH60	20
	L15S		150	1 - 1000		150	1 - 60			69
-	2.30			000		100	70 - 1000	-		
High Cared	L25S	Von Fast Astin	250	1 - 800	200.000	250 200	1 - 200 225 - 800	20.000	1000 - 1150	69
High-Speed	L50S	Very Fast-Acting	500	10 - 800	200,000	450	10 - 800	20,000	LSCR • 1LFS	69
-	L60S		600	1 - 800		-	-	1		69
ľ	L70S	1	700	10 - 800		650	10 - 800	1		69
	BLF	Fast-Acting	250 125	0.5 - 15 20 - 30	10,000	-	-	-		30
	BLN	Fast-Acting	250	1 - 30	10,000	-	_	-		30
	BLS	Fast-Acting	600 250	0.2 - 5 6 - 10	10,000	-	-	-	L60030M • LFPSM •	31
	FLA	Time-Delay	125	0.1 - 30	10,000	-	-	-	571 • 572 •	31
	FLM	Time-Delay	250	0.1 - 30	10,000	125	0.1 - 30	10,000	LEB • LEX	30
Midget	FLQ	Time-Delay	500	0.1 - 30	10,000	300	0.1 - 30	10,000		30
(Supplementary)	KLK	Fast-Acting	600	0.1 - 30	100K / 200K*	500	0.1 - 30	50,000		30
	KLKD	Fast-Acting	600	0.1 - 30	100,000	600	0.1 - 30	50,000		30
	KLQ	Time-Delay	600	1-6	10,000	-	-	- 10.000		31
	FLU	Fast-Acting	1000	0.44/ 11	10,000 20,000	1000	0.44 11	10,000 20,000	LFPHV	31
Plug	S00, T00	Time-Delay	125	0.25 - 30	10,000	-	-	-	Box Cover Units	63
ug	SLO, TLO L17T	Medium Time-Delay	125	15 - 30 —	10,000	_	_ 70 - 1200	-	LTFD Series	50
Telecom	TLN	Fast-Acting	-	-	-	170	1 - 600	100,000	LFR25	51
Telecolli	TLS	ast-Acting	_	_	_	170	1 - 125	100,000	LTFD101 •	52
	110						1 120	LFT30060 (cartridge)	52	

* Littelfuse® self-certified

Littelfuse POWR-GARD[®]– Advanced Protection and Facility Savings



Increase safety with POWR-PRO® Fuses

- Superior current-limitation from 1/10 6000 amperes
- Type 2 "No Damage" coordination with NEMA and IEC motor circuits
- Blown fuse indication (LLSRK_ID and JTD_ID Series)
- Compact motor protection (JTD/JTD_ID, CCMR Series)
- 300,000 AIR to meet trends toward higher SCCR

POWR PRO^{*} Look for the POWR-PRO[®] logo for superior protection

UL FUSE CLASS	POWR-PR0®	PAGE NUMBERS
Class L	KLPC & LDC	8, 10
Class RK1	LLNRK/LLSRK_ID	13
Class J	JTD/JTD_ID	21
Class CC / CD	CCMR (² /10-60)	27



Material Reduction Opportunity Program

Increase safety and reduce inventory with MROplus

Your detailed reports will include:

- A streamlined current-limiting fuse inventory recommendation
- A guide to reducing electrical hazards within your facility
- An annual cost savings estimate
- A detailed cross reference

All you need to do is e-mail an Excel file of your fuse inventory to **techline@littelfuse.com** or to your local sales representative. We will do the rest!

Developing Next Generation 1500 Vdc Products for High And Low Current Ratings

------- POWR-GARD® SOLAR RATED PRODUCTS =

This catalog incorporates our line of products designed specifically for the growing solar industry. As global standards are constantly changing, Littelfuse continues to develop circuit protection products that meet the requirements of the evolving photovoltaic market.



SPXV Series Space-Saving Solar Fuse57
SPXI Series In-Line Solar Fuse58
LPXV Series 1500 Vdc Fuse Holder106
New Productslittelfuse.com/solar



SPF Series 1000 Vdc 10x38mm Fuse	. 60
SPFJ Series 1000 Vdc Class J Size Fuse	61
LFPHV 1000 Vdc Fuse Holder	109
IDSR Series 600 Vdc Class RK5 Fuse	16
KLKD Series 600 Vdc 10x38mm Fuse	30
SE-601 Ground-Fault Protection Relay	148



Look for this logo to indicate products that are used in solar applications. Visit our website **littelfuse.com/solar** for the latest updates on approvals, certifications, and new products.



Littelfuse Acquires SymCom



Expanding our Line of Motor Protection Products

SymCom and SSAC manufacture robust products such as motor monitoring, protection and control relays, electronic controls, timers and flashers. SymCom and SSAC products are used to control and protect applications in the Industrial Pumping, Irrigation, Water and Waste Water, HVAC/R, Oil and Gas, Food and Beverage, and Elevator markets.

SymCom has three key brands:







SymCom and SSAC products include:



Enhanced Overload Relays

Protect motors and pumps from over/ under current, over/ under voltage, phase issues and ground faults. Communication modules also available.



Voltage/Phase Monitors

A cost-effective means to protect motors and pumps from voltage and phase issues.



Alternating Relays

Start and stop up to four pumps or use as a multi-channel switch. Intrinsically safe options available.



Pump Controllers

Balance runtime between loads and can be used in hazardous locations.



Load Sensors

Detect if the load is running or if there is an overload or underload condition.



Timers & Flashers

Delay starting and stopping loads, cycling, and sequencing of motors, pumps, compressors, heaters, and lighting.

For more information visit SymCom.com, SSAC.com or Littelfuse.com/Electrical

Meet NEC® Requirments And Save Time With Pre-Engineered Solutions

54 Littellu

LCP Series Coordination Panel

Ideal for circuits that require selective coordination such as emergency lighting circuits or essential electrical systems.

Features/Benefits

- Meets NEC[®] requirements
- Class CC & J fuse holders have open-circuit indication
- · Fast-acting fuses protect against short circuits
- Feed through/sub feed lugs and 84-circuit configuration available
- Ground and neutral bars
- Copper bus standard

littelfuse.com/LCP

See page 141

LPS Series POWR-Switch

Individual fusible shunt trip disconnect switch easily coordinates with system's overcurrent protection. Typical applications include elevator circuits.

Features/Benefits

- Pre-engineered single unit makes procurement easy
- Reduces labor costs up to 66%
- Flexibility for a variety of applications
- Control power terminal block
- UL Listed package
- Cu and AI wire rated
- Lockable operating handle meets all code and safety requirements

littelfuse.com/LPS

See page 143

Section Overview

For over 85 years Littelfuse® has been providing fuses to the electrical market. You can continue to count on our manufacturing and supply chain processes to deliver high quality fuses when you need them. At Littelfuse we leverage our global reach to stay on top of the latest applications and standards. Whether your circuit protection needs are focused on OEM, MRO, or construction, we are committed to being your circuit protection partner and appreciate your business.



🔄 FUSES 🖷

Table of Contents

JL Class L Fuses	8
JL Class RK1 Fuses	. 13
JL Class RK5 Fuses	. 16
JL Class J Fuses	. 21
JL Class T Fuses	.24
JL Class G Fuses	.26
JL Class CC & CD Fuses	.27
JL Supplementary Midget (10x38) Fuses	30

KLPC SERIES POWR-PRO® FUSES

POWR- PRO- 600 Vac • Time-Delay • 200-6000 A





Description

KLPC series POWR-PRO® fuses meet or exceed the most stringent project specifications, including silver links, silver-plated copper end bells, glass-reinforced melamine bodies, O-ring seals between body and end bells, and granular quartz fillers.

Applications

- Switchboard mains and feeders
- Motor control center mains
- Large motor branch circuits
- Protection of power circuit breakers

Features/Benefits

- POWR-PRO[®] Performance
- Best-in-class time-delay withstand
- Current-Limiting
- · Easily coordinated with other system components
- 300 kA AC Interrupting Rating (self-certified)

Specifications

Voltage Ratings	AC: 600 Vac or less
	DC: 480 V
Ampere Range	200 – 6000 A
Interrupting Ratings	AC: 200 kA rms symmetrical
	300 kA rms symmetrical
	(Littelfuse self-certified)
	DC: 20,000 A
Approvals	AC: Standard 248-10, Class L
	UL Listed 601–6000 A (File: E81895)
	UL Recognized 200–600 A (File: E71611)
	CSA Certified 601–6000 A (File: LR29862)
	Federal Specifications 700–6000 A
	(QPL-W-F-1814)
	DC: Littelfuse self-certified
Material	Melamine body, Copper caps (silver plated)
Country of Origin	Mexico

Ordering Information

AMPERE RATINGS					
200	500	800	1350	2000	3000
250	600	900	1400	2100	3500
300	601	1000	1500	2200	4000
350	650	1100	1600	2300	4500
400	700	1200	1800	2400	5000
450	750	1300	1900	2500	6000

SERIES	AMPERAGE	CATALOG NUMBER	ORDERING NUMBER
KLPC	800	KLPC800	KLPC800.X

Web Resources

Download TC Curves, CAD drawings and other technical information: **littelfuse.com/klpc**

Dimensions

Please refer to the Class L dimensions 12

Peak Let-Thru Curve



Note: For more information, see Peak Let-Thru Table on pg. 11



KLLU SERIES FUSES

600 Vac • Time-Delay • 601-4000 A





Ordering Information

AMPERE RATINGS					
601	750	1000	1400	1800	3000
650	800	1200	1500	2000	3500
700	900	1350	1600	2500	4000
SERIES	AMPERAG	GE CATAL	OG NUMBEI	R ORDERIN	IG NUMBER
KLLU	601		KLLU601	KLL	U601.X

Web Resources

Download TC Curves, CAD drawings and other technical information: **littelfuse.com/kllu**

Description

KLLU series fuses meet or exceed UL requirements for UL Class L fuses. The KLLU series offers an economical alternative to KLPC POWR-PRO® fuse with a slightly higher peak let through current.

Applications

- Service switches
- Switchboard mains and feeders
- Motor control center mains
- Large motor branch circuits
- Circuit breaker protection

Features/Benefits

- Current-Limiting
- Easily coordinated with other system components
- 200 kA AC Interrupting Rating

Specifications

Voltage Ratings	AC: 600 Vac or less
	DC: 300 V
Ampere Range	601–4000 A
Interrupting Ratings	AC: 200 kA rms symmetrical
	DC: 20 kA rms symmetrical
Approvals	Standard 248-10, Class L
	UL Listed (File: E81895)
	CSA Certified (File: LR29862)
	DC: Littelfuse self-certified
Material	Melamine body, Copper caps (silver plated)
Country of Origin	Mexico

Dimensions

Please refer to the Class L dimensions 12

Peak Let-Thru Curve



Note: For more information, see Peak Let-Thru Table on pg. 11

LDC SERIES POWR-PRO® FUSES

- POWR- PRO 600 Vac/dc • Fast Acting • 150-2000 A



UL Class L Fuses

1



Ordering Information

AMPERE RATINGS					
150	450	750	1201	1601	
200	500	800	1300	1800	
250	600	900	1350	1900	
300	601	1000	1400	2000	
350	650	1100	1500		
400	700	1200	1600		

SERIES	AMPERAGE	CATALOG NUMBER	ORDERING NUMBER
LDC	700	LDC700	OLDC700.X

Web Resources

Download TC curves, CAD drawings and other technical documents: **littelfuse.com/ldc**

Dimensions

Please refer to the Class L dimensions 12

Peak Let-Thru Curve



Note: For more information, see Peak Let-Thru Table on pg. 11

Description

High DC voltage and interrupting ratings make the POWR-PRO® LDC ideal for DC applications. The DC interrupting performance exceeds UL listing requirements.

Applications

- Solar inverter and array protection
- UPS protection especially for large battery circuits
- DC distribution and variable speed drives
- Mass transit systems

Features/Benefits

- POWR-PRO[®] Performance
- Extremely Current-Limiting
- 600 Vac/dc rated
- 200 kA AC Interrupting Rating
- 50 kA DC Interrupting Rating

Specifications

Voltage Ratings	600 Vac/dc or less
Ampere Range	150–2000 A
Interrupting Ratings	AC: 200 kA rms symmetrical
	DC: 50 kA
Time Constant	16 ms
Approvals	Standard 248-10, Class L
	UL Listed 601–2000 A (File: E81895)
	UL Recognized 150–600 A (File: E71611)
	CSA Certified (File: LR29862)
Material	Melamine body, Copper caps (silver plated)
Country of Origin	Mexico



CLASS L CURRENT-LIMITING EFFECTS

Current-Limiting Effects of KLPC (600 V) Fuses

SHORT CIRCUIT	APPARENT RMS SYMMETRICAL CURRENT FOR VARIOUS FUSE RATINGS							
CURRENT*	800 A	1200 A	1600 A	2000 A	3000 A	4000 A	5000 A	6000 A
5,000	5,000	5,000	5,000	5,000	5,000	5,000	5,000	5,000
10,000	8,800	10,000	10,000	10,000	10,000	10,000	10,000	10,000
15,000	10,500	13,500	15,000	15,000	15,000	15,000	15,000	15,000
20,000	12,000	15,000	19,000	20,000	20,000	20,000	20,000	20,000
25,000	13,000	16,000	21,000	24,000	25,000	25,000	25,000	25,000
30,000	14,000	18,000	23,000	26,000	30,000	30,000	30,000	30,000
35,000	15,000	19,000	24,000	27,000	32,000	35,000	35,000	35,000
40,000	16,000	20,000	25,000	28,000	34,000	40,000	40,000	40,000
50,000	17,000	22,000	27,000	31,000	37,000	42,500	50,000	50,000
60,000	18,000	24,000	29,000	34,000	40,000	46,000	52,000	60,000
80,000	20,000	26,000	32,000	37,000	44,000	51,000	57,000	70,000
100,000	21,000	27,000	34,000	40,000	46,000	57,000	65,000	75,000
150,000	23,000	31,000	38,000	44,000	54,000	67,000	75,000	87,000
200,000	24,000	34,000	42,000	46,000	57,000	70,000	80,000	95,000

Current-Limiting Effects of KLLU (600 V) Fuses

SHORT-CIRCUIT	APPARENT RMS SYMMETRICAL CURRENT FOR VARIOUS FUSE RATINGS								
CURRENT*	800 A	1200 A	1600 A	2000 A	3000 A	4000 A			
5,000	5,000	5,000	5,000	5,000	5,000	5,000			
10,000	10,000	10,000	10,000	10,000	10,000	10,000			
15,000	11,900	15,000	15,000	15,000	15,000	15,000			
20,000	13,000	18,500	20,000	20,000	20,000	20,000			
25,000	14,000	20,000	25,000	25,000	25,000	25,000			
30,000	14,500	21,000	26,500	30,000	30,000	30,000			
35,000	15,000	22,000	28,500	34,000	35,000	35,000			
40,000	16,000	23,000	30,000	35,000	37,000	40,000			
50,000	17,000	24,000	32,000	38,000	39,000	44,000			
60,000	18,000	26,000	34,000	42,000	43,000	50,000			
80,000	19,000	28,000	36,000	44,000	46,000	54,500			
100,000	21,000	30,000	38,000	46,000	48,000	57,500			
150,000	24,000	35,000	44,000	50,000	51,000	68,000			
200,000	26,000	38,000	48,000	53,000	60,000	74,000			

Current-Limiting Effects of LDC (600 V) Fuses

SHORT CIRCUIT	APPARENT RMS SYMMETRICAL CURRENT FOR VARIOUS FUSE RATINGS							
CURRENT*	800 A	1200 A	1600 A	2000 A				
5,000	5,000	5,000	5,000	5,000				
10,000	8,500	10,000	10,000	10,000				
15,000	9,750	14,000	15,000	15,000				
20,000	10,500	15,000	19,000	20,000				
25,000	11,500	16,000	21,000	25,000				
30,000	12,000	17,000	22,000	26,000				
35,000	12,500	18,000	23,000	28,000				
40,000	13,500	19,000	24,000	30,000				
50,000	14,000	21,000	26,000	32,000				
60,000	15,000	22,000	28,000	34,000				
80,000	16,000	24,000	30,000	36,000				
100,000	18,000	25,000	33,000	40,000				
150,000	20,000	30,000	38,000	44,000				
200,000	23,000	32,000	41,000	46,000				

*Prospective RMS Symmetrical Amperes Short-Circuit Current Note: Data derived from Peak Let-Thru Curves

CLASS L SERIES DIMENSIONS

Dimensions

AMPERES	FIG.							DIMENS	IONS IN	CHES (mr	n)			
AWPERES	N0.	А	В	С	D	E	F	G	Н	J	К	L	М	N
150-800	1	3 ³ ⁄4 (95.3)	5 ³ ⁄4 (146.1)	6 ³ ⁄4 (171.5)	—	—	8 ⁵ ⁄8 (219.1)	—	—	2 (50.8)	2½ (63.5)	³ ⁄8 (9.5)	⁵ ∕8 x 1⅓ (15.9) x (28.6)	—
900-1200	2	3 ³ ⁄4 (95.3)	5 ³ ⁄4 (146.1)	6 ³ ⁄4 (171.5)	9 ¹ ⁄4 (235.0)	9½ (241.3)	10 ³ ⁄4 (273.1)	—	_	2 (50.8)	2½ (63.5)	³ ⁄8 (9.5)	⁵ ⁄8 x ³ ⁄4 (15.9) x (19.1)	5∕% x 1⅓ (15.9) x (28.6)
1300-1600	2	3 ³ ⁄4 (95.3)	5 ³ ⁄4 (146.1)	6 ³ ⁄4 (171.5)	9¼ (235.0)	9½ (241.3)	10 ³ / ₄ (273.1)	—	—	2 ³ ⁄/8 (60.3)	3 (76.2)	⁷ ⁄ ₁₆ (11.1)	⁵ ⁄ ₈ x ³ ⁄ ₄ (15.9) x (19.1)	5∕% x 1⅓ (15.9) x (28.6)
1800-2000	2	3 ³ ⁄4 (95.3)	5 ³ ⁄4 (146.1)	6 ³ ⁄4 (171.5)	9¼ (235.0)	9½ (241.3)	10 ³ / ₄ (273.1)	—	_	2 ³ ⁄4 (69.9)	3½ (88.9)	½ (12.7)	⁵ ⁄ ₈ x ³ ⁄ ₄ (15.9) x (19.1)	5∕% x 1⅓ (15.9) x (28.6)
2100-2500	3	4 (101.6)	5 ³ ⁄4 (146.1)	6 ³ ⁄4 (171.5)	9¼ (235.0)	9½ (241.3)	10 ³ / ₄ (273.1)	1 ⁵ ⁄/8 (41.3)	1 ³ ⁄4 (44.5)	3½ (88.9)	5 (127.0)	³ ⁄ ₄ (19.1)	⁵ ⁄⁄ ₈ x ³ ⁄ ₄ (15.9) x (19.1)	⁵ ⁄8 x 1 ¹ ⁄8 (15.9) x (28.6)
2501-3000	3	4 (101.6)	5 ³ ⁄4 (146.1)	6 ³ ⁄4 (171.5)	9¼ (235.0)	9½ (241.3)	10 ³ / ₄ (273.1)	1 ⁵ ⁄/8 (41.3)	1 ³ ⁄4 (44.5)	4 (101.6)	5 (127.0)	³ ⁄ ₄ (19.1)	⁵ ⁄ ₈ x ³ ⁄ ₄ (15.9) x (19.1)	⁵ ⁄8 x 1 ¹ ⁄8 (15.9) x (28.6)
3500-4000	4	4 (101.6)	5 ³ ⁄4 (146.1)	6 ³ ⁄4 (171.5)	9¼ (235.0)	9½ (241.3)	10 ³ / ₄ (273.1)	1³⁄4 (44.5)	3¼ (82.6)	4 ³ ⁄ ₄ (120.7)	5 ³ ⁄4 (146.1)	³ ⁄ ₄ (19.1)	⁵⁄≋ x 1³⁄≋ (15.9) x (34.9)	⁵ ⁄8 x 1 ³ ⁄8 (15.9) x (34.9)
4500-5000	5	4 (101.6)	5 ³ ⁄4 (146.1)	_	9¼ (235.0)	—	10 ³ / ₄ (273.1)	15⁄/8 (41.3)	3¼ (82.6)	5¼ (133.4)	7½ (181.0)	1 (25.4)	⁵⁄ଃ DIA. (15.9)	—
6000	5	4 (101.6)	5 ³ ⁄4 (146.1)	_	9¼ (235.0)	—	10 ³ ⁄4 (273.1)	1 ⁵ ⁄/8 (41.3)	3¼ (82.6)	5¼ (133.4)	7½ (181.0)	1 (25.4)	⁵⁄₃ DIA. (15.9)	—



FIG.1





FIG. 3









LLNRK / LLSRK / LLSRK_ID SERIES INDICATOR[®] FUSES

POWR- PRO^{*} 250/600 Vac • Dual Element • Time-Delay • 1/10-600 A





Description

RK1 fuses are extremely current-limiting fuses meaning they greatly reduce or eliminate damage to circuits and equipment under shortcircuit conditions. Replacing existing Class H, K and RK5 fuses with RK1 fuses is one of the easiest ways to immediately improve the protection of plant workers and equipment.

Applications

- All general purpose circuits ٠
- Motors
- Transformers •
- ٠ Safety upgrades

Features/Benefits

- POWR-PRO® Performance •
- Indicator and Non-Indicator versions available
- Dual-element design •
- Extremely Current-Limiting IEC Type 2 "No Damage" protection to IEC and • NEMA type motor starters
- Indicating and DIN mount fuse holders available

Specifications

Voltage Ratings	AC: 600 Vac or less (LLSRK/LLSRK_ID) 250 Vac or less (LLNRK) DC: 300 Vdc (LLSRK/LLSRK ID)
Ampere Range Interrupting Ratings	125 Vdc (LLNRK) 1/10 – 600 A AC: 200 kA rms symmetrical 300 kA rms symmetrical (Littelfuse self-certified)
Approvals	DC: 20 kA AC: Standard 248-12, Class RK1 UL Listed (File: E81895) CSA Certified (File: LR29862)
Material	DC: Littelfuse self-certified Federal Specification WF-1814 (QPL- W-F-1814) LLNRK: 1/10-30 A: Fiber body, Bronze cap 35-60 A: Composite body, Bronze cap (nickel plated) 70-600 A: Composite body, Bronze cap (nickel plated) 70-600 A: Composite body, Bronze cap (nickel plated) 70-600 A: Composite body, Copper cap
Country of Origin	Mexico

Ordering Information

AMPERE RATINGS									
1/10	1	2 8/10	6 1/4	20	75 ⁺	225			
15/100	1 1/8	3	7	25	80	250			
² /10	1 1/4	3 ²/10	7 1/2*	30	90	300			
1/4	1 4/10	3 1/2	8	35	100	350			
3/10	1 6/10	4	9	40	110	400			
4/10	1 8/10	4 1/2	10	45	125	450			
1/2	2	5	12	50	150	500			
6/10	2 1/4	5 6/10	15	60	175	600			
8/10	2 1/2	6	17 1/2	70	200				

Note: All LLSRK_ID fuses rated 1 amp and above are Indicator® fuses. *7.5 A is only available for the ID versions

[†]75 A is only available for the 600 V

VOLTAGE	SERIES	AMP	INDICATION	CATALOG NUMBER	ORDERING NUMBER
600	LLSRK_ID	60	•	LLSRK060ID	LSRK060.TXID
600	LLSRK	60	-	LLSRK060	LSRK060.T
250	LLNRK	80	-	LLNRK080	LNRK080.V

Web Resources

Download TC Curves, CAD drawings and other technical information: littelfuse.com/llsrk

littelfuse.com/llnrk

Recommended Fuse Blocks

88 Jone
_

nensions

Please refer to the Class R dimensions 1	9
--	---

Peak Let-Thru Curve (600 V)



Note: For more information, see Peak Let-Thru Table on pg. 14

Current-Limiting Effects of LLSRK and LLSRK_ID (600 V) Fuses

SHORT CIRCUIT	APPARENT RMS SYMMETRICAL CURRENT FOR VARIOUS FUSE RATINGS							
CURRENT*	30 A	60 A	100 A	200 A	400 A	600 A		
5,000	1,060	1,600	2,100	2,600	4,100	—		
10,000	1,350	2,000	2,800	3,400	5,250	8,000		
15,000	1,600	2,300	3,200	3,900	6,000	9,000		
20,000	1,700	2,600	3,600	4,500	6,700	10,000		
25,000	1,900	2,800	3,800	4,800	7,500	11,000		
30,000	2,000	3,000	4,100	5,200	8,000	12,000		
35,000	2,100	3,100	4,400	5,700	8,500	12,500		
40,000	2,200	3,300	4,600	6,000	9,000	13,000		
50,000	2,400	3,500	4,900	6,500	9,500	14,000		
60,000	2,500	3,800	5,200	7,000	10,000	15,000		
80,000	2,700	4,000	5,700	7,750	11,000	17,000		
100,000	2,900	4,200	6,200	8,500	12,000	18,000		
150,000	3,200	4,600	7,300	10,000	14,000	21,000		
200,000	3,300	4,700	8,000	11,000	16,000	23,000		

Current-Limiting Effects of LLNRK (250 V) Fuses

SHORT CIRCUIT	APPARENT RMS SYMMETRICAL CURRENT FOR VARIOUS FUSE RATINGS							
CURRENT*	30 A	60 A	100 A	200 A	400 A	600 A		
5,000	900	1,400	2,000	2,700	4,800	5,000		
10,000	1,100	1,900	2,700	3,500	6,200	8,500		
15,000	1,250	2,100	3,100	4,200	7,000	9,500		
20,000	1,400	2,400	3,500	4,600	8,000	10,800		
25,000	1,500	2,600	3,900	5,000	8,300	11,500		
30,000	1,600	2,800	4,000	5,250	9,000	12,000		
35,000	1,700	2,850	4,300	5,500	9,500	12,500		
40,000	1,800	3,000	4,600	5,800	9,800	13,500		
50,000	1,900	3,200	4,800	6,300	10,200	14,000		
60,000	2,000	3,500	5,200	6,700	11,000	15,000		
80,000	2,200	3,900	5,700	7,200	12,200	16,000		
100,000	2,300	4,000	6,000	8,100	12,700	17,000		
150,000	2,500	4,500	6,700	9,100	14,000	19,000		
200,000	2,600	4,800	7,000	9,700	15,000	20,000		

*Prospective RMS Symmetrical Amperes Short-Circuit Current Note: Data derived from Peak Let-Thru Curves

LLSRK_ID Fuses—Quality Construction

for performance you can rely on...

Littelfuse LLSRK_ID Fuses feature true dual-element construction. This robust design withstands repeated surges within rated time delay without opening needlessly, eliminating downtime caused by power surges or equipment demands. Granular Quartz Filling Granular Quartz Filling Hown Fuse Indicator Assembly Fiberglass Reinforced Pultruded Body Elastomeric Silicone Overload Section



KLNR / KLSR SERIES FUSES

250/600 Vac • Fast-Acting • 1-600 A





Description

KLSR and KLNR series are en economical design providing the safety of a RK1 fuse. The single element design provides fast-acting overload and short-circuit protection.

Use POWR-PRO[®] LLNRK and LLSRK series RK1, dualelement, time-delay fuses in all new applications requiring the current-limiting ability of UL Class RK1 fuses or in existing applications where fast-acting RK1 or RK5 fuses have been opening on harmless system surges such as motor starting currents.

Applications

- Resistance heaters
- Lighting circuits
- Non-inductive loads

Features/Benefits

- Extremely Current-Limiting
- Indicating and DIN mount fuse blocks available

Specifications

Voltage Ratings	AC: 600 Vac or less (KLSR)
	250 Vac or less (KLNR)
	DC: 250 V (1 – 30 A KLSR);
	300 V (35 – 600 A KLSR)
	125 V (KLNR)
Ampere Range	1 – 600 A
Interrupting Ratings	AC: 200 kA rms symmetrical
	DC: 20 kA
Approvals	AC: Standard 248-12, Class RK1
	UL Listed (File: E81895)
	CSA Certified (File: LR29862)
	DC: Littelfuse self-certified
Material	1-60 A: Composite body, Bronze cap (nickel plated)
	70-100 A: Composite body, Copper caps
	110-600 A: Melamine body, Copper caps
Country of Origin	Mexico

Ordering Information

AMPERE RATINGS								
1	10	40	100	250				
2	12	45	110	300				
3	15	50	125	350				
4	20	60	150	400				
5	25	70	175	450				
6	30	80	200	500				
8	35	90	225	600				

VOLTAGE	SERIES	AMP	CATALOG NUMBER	ORDERING NUMBER
600	KLSR	90	KLSR090	KLSR090.V
250	KLNR	90	KLNR090	KLNR090.V

Web Resources

Download TC Curves, CAD drawings and other technical information: **littelfuse.com/klsr littelfuse.com/klnr**

Recommended Fuse Blocks

Dimensions

Peak Let-Thru Curve (600 V)



IDSR SERIES INDICATOR® POWR-PRO® FUSES

- POWR- PRO[®] 600 Vac/dc • Dual Element • Time-Delay • 1/10-600 A





Description

The IDSR combines 600 Vdc capability with indication to provide an ideal solution for many DC applications.

Applications

- DC circuits
- Solar inverters
- Motors
- Transformers
- Solenoids
- Fluorescent lighting

Features/Benefits

- POWR-PRO® Performance
- Current limiting
- Indication

Specifications

AC: 600 Vac or less
DC: 600 Vdc or less
1/10 - 600 A
AC: 200 kA rms symmetrical
300 kA rms symmetrical
(Littelfuse self-certified)
DC: 20 kA
Standard 248-12, Class RK5
UL Listed (File: E81895)
CSA Certified (File: LR29862)
1/10-60 A: Composite body, Bronze caps
70-600 A: Composite body, Copper caps
Mexico

Ordering Information

AMPERE RATINGS									
1/10	6/10	1 8/10	4	8	30	80	225		
1/8	8/10	2	4 1/2	9	35	90	250		
15/100	1	2 1/4	5	10	40	100	300		
2/10	1 1/8	2 1/2	5 6/10	12	45	110	350		
1/4	1 1/4	2 8/10	6	15	50	125	400		
3/10	1 4/10	3	6 1/4	17 1/2	60	150	450		
4/10	1 1/2	3 ²/10	7	20	70	175	500		
1/2	1 6/10	3 1/2	7 1/2	25	75	200	600		

Note: All fuses rated 1A and above are Indicator® fuses.

VOLTAGE	SERIES	AMP	CATALOG NUMBER	ORDERING NUMBER
600	IDSR	30	IDSR030	IDSR030.T

Web Resources

Download TC Curves, CAD drawings and other technical information: **littelfuse.com/idsr**

Recommended Fuse Blocks

LFR S	Series	
-------	--------	--

Dimensions

Please refer to the Class R dimensions...... 19

Peak Let-Thru Curve





FLNR_ID / FLSR_ID SERIES INDICATOR® FUSES

250/600 Vac • Dual Element • Time Delay • 1/10-600 A

(₩) (∰ QPL (∈



Description

Available in both Indicating and Non-Indicating versions, the FLNR/FLSR series of fuses set the standard for general purpose fuses. The dual-element design provides advanced short circuit and overload protection. FLSR series fuses provide excellent protection for all types of circuits especially those containing motors.

Applications

- Service entrance switches
- Switchboard mains and feeders
- Motor control central mains and motor branch circuits
- All general purpose circuits

Features/Benefits

- Indicator and Non-Indicator versions available
- Dual-element design
- Current limiting

Specifications

- Voltage Ratings	AC: 600 Vac or less (FLSR_ID)
	250 Vac or less (FLNR_ID)
	DC: 300 V (FLSR_ID)
	125 V (FLNR 1/10 – 30 A);
	125 V (FLNR_ID 35 – 600 A)
Ampere Range	¹ / ₁₀ - 600 A
Interrupting Ratings	AC: 200 kA rms symmetrical
	300 kA rms symmetrical
	(Littelfuse self-certified)
	DC: 20 kA
Approvals	Standard 248-12, Class RK5
	UL Listed (File: E81895)
	CSA Certified (File: LR29862)
	Federal Specification WF-1814
	(QPL- W-F-1814)
Material	FLSR: 1/10-60 A: Composite body, Bronze caps
	70-600 A: Composite body, Copper caps
	FLNR: 1/10-60 A: Fiber body, Bronze caps
	70-600 A: Composite body, Copper caps
Country of Origin	Mexico

Ordering Information

AMPERE RATINGS										
1/10	6/10	1 8/10	4	8	30	80	225			
1/8*	8/10	2	4 1/2	9	35	90	250			
15/100	1	2 1/4	5	10	40	100	300			
2/10	1 1/8	2 1/2	5 ⁶ /10	12	45	110	350			
1/4	1 1/4	2 ⁸ /10	6	15	50	125	400			
³ /10†	1 ⁴ /10	3	6 ¹ /4	17 ¹ /2	60	150	450			
4/10	1 1/2	3 ²/10	7	20	70	175	500			
1/2	1 6/10	3 1/2	7 1/2	25	75**	200	600			

Note: For 1/10 – 30A 250 volt fuses, order non-indicating FLNR series fuses. *FLNR only. †FLNR, FLSR, FLSR_ID only. *

*FLNR, FLSR, FLSR_ID only

VOLTAGE	INDICATION	SERIES	AMP	CATALOG NUMBER	ORDERING NUMBER
600 V	-	FLSR	15	FLSR015	FLSR015.T
600 V	•	FLSR_ID	15	FLSR015ID	FLSR015.TXID
250 V	-	FLNR	60	FLNR060	FLNR060.T
250 V	•	FLNR_ID	60	FLNR060ID	FLNR060.TXID

Web Resources

Download TC Curves, CAD drawings and other technical information: **littelfuse.com/flsr**

littelfuse.com/flnr

Recommended Fuse Blocks

Please refer to the Class R dimensions	19
Refer to FLNR dim. for FLNR_ID and the FLSR dim. for FLSR_ID.	

Peak Let-Thru Curve (600 V)



Note: For more information, see Peak Let-Thru Table on pg. 18

CLASS RK5 CURRENT-LIMITING EFFECTS

Current-Limiting Effects of IDSR (600 V) Fuses

SHORT CIRCUIT CURRENT*	APPARENT RMS SYMMETRICAL CURRENT FOR VARIOUS FUSE RATINGS							
	15 A	30 A	60 A	100 A	200 A	400 A	600 A	
5,000	800	1,100	2,100	3,200	5,000	5,000	5,000	
10,000	1,100	1,600	2,900	4,300	7,300	10,000	10,000	
15,000	1,300	1,900	3,400	5,000	8,600	13,700	15,000	
20,000	1,400	2,200	3,800	5,600	9,500	15,500	19,000	
25,000	1,500	2,500	4,100	6,100	10,300	16,700	21,500	
30,000	1,600	2,700	4,500	6,500	11,000	17,700	23,500	
35,000	1,700	2,900	4,700	6,800	11,600	18,600	25,200	
40,000	1,800	3,100	5,000	7,200	12,100	19,400	26,600	
50,000	1,900	3,400	5,400	7,800	13,100	20,800	29,500	
60,000	2,000	3,600	5,800	8,300	13,900	22,000	30,600	
80,000	2,200	4,000	6,300	9,100	15,400	24,000	33,200	
100,000	2,300	4,200	6,800	9,800	16,700	25,500	35,100	
150,000	2,600	4,500	7,700	11,200	19,300	28,100	38,000	
200,000	2,800	4,600	8,400	12,400	21,400	30,000	39,600	

Current-Limiting Effects of FLSR and FLSR_ID (600 V) Fuses

SHORT-CIRCUIT CURRENT*		APPARENT RMS	SYMMETRICAL CU	RRENT FOR VARIOUS	S FUSE RATINGS	
Show one of content	30 A	60 A	100 A	200 A	400 A	600 A
5,000	1,250	2,100	3,200	5,000	5,000	5,000
10,000	1,600	2,850	4,300	7,250	10,000	10,000
15,000	1,800	3,400	5,000	8,500	13,500	15,000
20,000	2,250	3,800	5,500	9,500	15,750	19,000
25,000	2,450	4,100	5,700	10,250	17,000	21,000
30,000	2,700	4,500	6,400	10,750	18,000	23,000
35,000	2,900	4,800	6,700	11,500	19,000	24,250
40,000	3,000	5,000	7,250	12,000	19,500	27,000
50,000	3,400	5,250	7,750	13,000	21,000	29,000
60,000	3,600	5,750	8,100	14,000	22,000	30,500
80,000	3,900	6,250	9,000	15,000	24,000	33,000
100,000	4,300	6,750	9,750	16,500	26,000	35,000
150,000	4,500	7,600	11,100	19,000	28,000	38,000
200,000	4,600	8,400	12,250	21,500	30,000	40,000

Current-Limiting Effects of FLNR and FLNR_ID (250V) Fuses

SHORT-CIRCUIT CURRENT*	APPARENT RMS SYMMETRICAL CURRENT FOR VARIOUS FUSE RATINGS									
SHOIT-CINCOTT COMILINT	30 A	60 A	100 A	200 A	400 A	600 A				
5,000	1,400	2,100	3,100	5,000	5,000	5,000				
10,000	1,550	2,500	3,900	6,500	9,500	10,000				
15,000	2,000	3,150	4,400	7,250	10,500	14,000				
20,000	2,250	3,400	5,000	8,250	12,000	16,000				
25,000	2,400	3,750	5,250	9,000	12,500	16,500				
30,000	2,550	4,100	5,600	9,500	13,500	18,000				
35,000	2,650	4,300	5,800	9,750	14,000	19,000				
40,000	2,800	4,400	6,250	10,250	15,000	20,000				
50,000	3,000	5,000	6,500	10,500	16,000	21,000				
60,000	3,200	5,250	7,000	11,500	17,000	23,000				
80,000	3,400	5,750	7,500	12,500	19,000	25,500				
100,000	3,850	6,000	8,000	13,500	21,000	27,500				
150,000	4,100	7,000	9,000	15,200	24,000	31,500				
200,000	4,300	7,500	9,750	16,500	26,000	34,000				

*Prospective RMS Symmetrical Amperes Short-Circuit Current Note: Data Derived from Peak Let-Thru Curves



CLASS R SERIES DIMENSIONS

Dimensions



AMPS	FIGURE	SERIES	DIMENSIONS INCHES (mm)									
/	NUMBER	0EIIIE0	А	В	С	D	E	F	G	Н	J	К
./		LLNRK KLNR FLNR	2 (50.8)	1⁄2 (12.7)	1⁄2 (12.7)	⁹ ⁄16 (14.3)	⁵ ⁄ ₆₄ (2.0)	⁵∕₃₂ (4.0)	³ ⁄⁄8 (9.5)	—	_	_
1/10—30	1	LLSRK KLSR FLSR IDSR	5 (127.0)	³ ⁄4 (19.1)	⁵∕% (15.9)	¹³ ⁄ ₁₆ (20.6)	³ ⁄ ₃₂ (2.4)	³ ∕16 (4.8)	⁵∕% (15.9)			_
35 – 60	1	llnrk Klnr Flnr	3 (76.2)	³ ⁄4 (19.1)	⁵ ⁄⁄8 (15.9)	¹³ ⁄16 (20.6)	³ / ₃₂ (2.4)	³ ⁄16 (4.8)	⁵ ⁄⁄8 (15.9)	—	_	_
55 - 60		LLSRK KLSR FLSR IDSR	5½ (139.7)	1 (25.4)	⁵ ⁄⁄8 (15.9)	11⁄16 (27.0)	³ ⁄ ₃₂ (2.4)	1⁄4 (6.4)	7⁄8 (22.2)	_	_	_
70 – 100	2	LLNRK KLNR FLNR	57⁄8 (149.2)	1 (25.4)	11⁄16 (27.0)	11⁄16 (27.0)	1⁄8 (3.2)	³ ⁄4 (19.1)	_	1⁄4 (6.4)	⁹ ⁄32 (7.1)	1⁄2 (12.7)
70 - 100	Z	LLSRK KLSR FLSR IDSR	71⁄8 (200.0)	1¼ (31.8)	11⁄16 (27.0)	15⁄16 (33.3)	1⁄8 (3.2)	³ ⁄4 (19.1)		1⁄4 (6.4)	⁹ ⁄32 (7.1)	1⁄2 (12.7)
110 – 200	2	LLNRK KLNR FLNR	71⁄8 (181.0)	1½ (38.1)	115/32 (37.3)	1 ¹⁹ ⁄ ₃₂ (40.5)	³ ⁄16 (4.8)	11⁄8 (28.6)	_	7∕16 (11.1)	⁹ ⁄32 (7.1)	¹¹ ⁄16 (17.5)
110 - 200	Z	LLSRK KLSR FLSR IDSR	95⁄% (244.5)	13⁄4 (44.5)	1 ¹⁵ ⁄32 (37.3)	127/32 (46.8)	³ ⁄16 (4.8)	11⁄8 (28.6)	_	7∕16 (11.1)	⁹ ⁄ ₃₂ (7.1)	¹¹ ⁄16 (17.5)
225 – 400	2	LLNRK KLNR FLNR	85 (219.1)	2 (50.8)	1 ¹⁵ ⁄ ₁₆ (49.2)	2 ³ ⁄ ₃₂ (53.2)	1⁄4 (6.4)	151⁄8 (41.3)	_	⁵⁄⊮ (15.9)	¹³ ⁄ ₃₂ (10.3)	¹⁵ ⁄ ₁₆ (23.8)
223 - 400	Z	LLSRK KLSR FLSR IDSR	115⁄⁄8 (295.3)	2½ (63.5)	2 (50.8)	2 ¹⁹ / ₃₂ (65.9)	1⁄4 (6.4)	15⁄% (41.3)		⁵⁄శ (15.9)	¹³ ⁄32 (10.3)	¹⁵ ⁄16 (23.8)
450 — 600	2	LLNRK KLNR FLNR	10 ³ ⁄/8 (263.5)	2½ (63.5)	2 ³ ⁄⁄8 (60.3)	2 ¹⁹ ⁄32 (65.9)	1⁄4 (6.4)	2 (50.8)	_	³ ⁄4 (19.1)	¹⁷ / ₃₂ (13.5)	11⁄8 (28.6)
400 - 000	Z	LLSRK KLSR FLSR IDSR	13 ³ ⁄⁄8 (339.7)	3 (76.2)	2 ¹³ / ₃₂ (61.1)	3 ³ ⁄32 (78.6)	¹ ⁄4 (6.4)	2 (50.8)	_	³ ⁄4 (19.1)	¹⁷ ⁄ ₃₂ (13.5)	11⁄8 (28.6)

NLN / NLS SERIES (ONE-TIME) FUSES

250/600 Vac • "One-Time" • 1-600 A





Description

NLN and NLS fuses provide low cost protection for general purpose feeder and branch circuits when available short circuit currents are less than 50 kA.

Note: Canadian Electrical Code NLKP Type P fuse available. Visit littelfuse.com/nlkp

Applications

General purpose residential and commercial circuits with little or no motor load.

Features/Benefits

- Economical •
- 50 kA interrupting rating
- Indicating and DIN mount holders available •

Web Resources

Download TC Curves, CAD drawings and other technical information: littelfuse.com/nln littelfuse.com/nls

Dimensions



 — A —	 E→
Å ⊳	
۲	
	ш

FIG. 2

AMPERES	REFER TO	SERIES	DIMENSIONS INCHES (mm)						
AIVIFENES	FIG. NO.	SENIES	А	В	С	D	E	F	G
1 – 30	1	NLN	2 (50.8)	1⁄2 (12.7)	1⁄2 (12.7)	⁹ /16 (14.3)	—	—	—
1 - 30		NLS	5 (127.0)	³ / ₄ (19.1)	⁵ ⁄/8 (15.9)	¹³ / ₁₆ (20.6)	—	—	
35 - 60	1	NLN	3 (76.2)	³ ⁄4 (19.1)	⁵ ⁄/8 (15.9)	¹³ /16 (20.6)	—	—	_
35 - 60	I	NLS	5½ (139.7)	1 (25.4)	⁵ ⁄/8 (15.9)	11/16 (27.0)	—	—	—
70 – 100	2	NLN	51/8 (149.2)	1 (25.4)	1 (25.4)	11/16 (27.0)	1/8 (3.2)	3/4 (19.1)	15/16 (33.3)
70 - 100		NLS	71⁄8 (200.0)	1 ¹ ⁄4 (31.8)	1 (25.4)	15/16 (33.3)	1/8 (3.2)	³ / ₄ (19.1)	19/16 (39.7)
110 - 200	2	NLN	71⁄/8 (181.0)	1½ (38.1)	13/8 (34.9)	1%16 (39.7)	³ /16 (4.8)	11/8 (28.6)	11/8 (47.6)
110 - 200	2	NLS	95/8 (244.5)	13⁄4 (44.5)	13/8 (34.9)	1 ²⁷ / ₃₂ (46.8)	³ /16 (4.8)	1 ¹ / ₈ (28.6)	23/32 (53.2)
225 – 400	2	NLN	85/8 (219.1)	2 (50.8)	11⁄/8 (47.6)	23/32 (53.2)	1⁄4 (6.4)	15/8 (41.3)	2 ¹³ /32 (61.1)
225 - 400	2	NLS	115⁄/8 (295.3)	21⁄2 (63.5)	11⁄/8 (47.6)	2 ¹⁹ /32 (65.9)	1⁄4 (6.4)	15/8 (41.3)	21/8 (73.0)
450 - 600	2	NLN	103/8 (263.5)	21⁄2 (63.5)	21⁄4 (57.2)	2 ¹⁹ / ₃₂ (65.9)	1⁄4 (6.4)	2 (50.8)	21/8 (73.0)
450 - 600	2	NLS	133⁄8 (339.7)	3 (76.2)	21⁄4 (57.2)	3 ³ /32 (78.6)	1⁄4 (6.4)	2 (50.8)	37/16 (87.3)

Specifications

Voltage Ratings	AC: 600 Vac or less (NLS) 250 Vac or less (NLN) DC: 400 V (NLS 35 – 60 A) 500 V (NLS 8 – 30 A) (NLS 225 – 600 A) 600 V (NLS 1 – 7 A) (NLS 70 – 200 A) 250 V (NLN))
Ampere Range	1 – 600 A
Interrupting Ratings	AC: 50 kA rms symmetrical
	DC: 20 kA (1 – 60 A)
	50 kA (70 – 600 A)
Approvals	Standard 248-9, Class K5
	UL Listed (File: E81895)
	CSA Certified (File: LR29862)
Material	NLS: 1-15 A: Fiber body, Bronze cap
	20-60 A: Composite body, Bronze cap
	70-600 A: Fiber body, Copper cap (tin plated)
	NLN: 1-30 A: Ceramic body
	35-60 A: Fiber body, Bronze cap
	70-600 A: Fiber body, Copper cap (tin plated)
Country of Origin	Mexico
	tion

Ordering Information

AMPERE RATINGS										
1	7	*25	*60	125	300					
2	8	*30	70	150	350					
3	10	*35	80	175	400					
4	12	*40	90	200	450					
5	*15	*45	100	225	500					
6	*20	*50	110	250	600					

*NLKP series available only in those amperages preceded by an asterisk.

VOLTAGE	SERIES	AMP	CATALOG NUMBER	ORDERING NUMBER
600	NLS	20	NLS020	ONLS020.T
250	NLN	15	NLN015	ONLN015.T

Recommended Fuse Blocks

LFH Series

1

G



JTD_ID SERIES INDICATOR® POWR-PRO® FUSES

- POWR- PRO 600 Vac • Time Delay • 8/10-600 A





Description

The Littelfuse POWR-PRO[®] JTD Class J fuse is available with visual blown fuse indication or in standdard non-indicating versions. The current-limiting time delay JTD_ID offers a patented design which reduces nuisance fuse openings.

Features/Benefits

- POWR-PRO® Performance
- Current-Limiting
- IEC Type 2 Protection
- Indication and non-indication versions available

Applications

- Fused combination motor controllers and control centers
- Transformer protection
- Protection for series rated molded case circuit-breaker panels

General purpose circuits

Specifications

Voltage Ratings	AC: 600 Vac or less DC: 300 V (%/₀–100 A) 500 V (110–600 A)
Ampere Range Interrupting Rating	⁸ ∕₁0−600 A AC: 200 kA rms symmetrical 300 kA rms symmetrical DC: 20 kA
Material	Body: Melamine Caps: Nickel-plated Bronze (%/10-60 A) Brass (70-200 A) Brass Cap & Copper Blade (225-600 A)
Approvals	AC: Standard 248-8, Class J UL Listed (File: E81895) CSA Certified (File: LR29862)
Material	DC: Littelfuse self-certified 8/10-60 A: Melamine body, Bronze cap (nickel plated) 70-200 A: Melamine body, Brass cap 225-600 A: Melamine body, Copper cap
Country of Origin	Mexico

Ordering Information

	AMPERE RATINGS												
8/10	2	31/2	7	171⁄2	45	100	225	500					
1	21/4	4	8	20	50	110	250	600					
11⁄4	21/2	41/2	9	25	60	125	300						
11/2	2 8/10	5	10	30	70	150	350						
16/10	3	5 ⁶ /10	12	35	80	175	400						
18/10	3 ² /10	6	15	40	90	200	450						

VOLTAGE	SERIES	AMP	INDICATION	CATALOG NUMBER	ORDERING NUMBER
600	JTD_ID	60	•	JTD60ID	OJTD060.TXID
600	JTD	60	-	JTD060	OJTD060.T

Web Resources

Download TC Curves, CAD drawings and other technical information: **littelfuse.com/jtd**

Recommended Fuse Holders

LFJ60 Series	85
LFPSJ Series (%/10-60 A)	111

Dimensions

Please refer to the Class J dimensions23
--

Peak Let-Thru Curve



Note: For more information, see Peak Let-Thru Table on pg. 23

600 Vac • Fast-Acting • 1-600 A





Description

JLS series fuses provide space saving, fast-acting overload and short-circuit protection for non-inductive loads. For applications where short-duration surges and spikes may cause nuisance fuse opening, consider the use of Littelfuse POWR-PRO® JTD or JTD_ID series time-delay fuses.

Applications

- General purpose circuits with little or no motor load.
- Resistive loads, such as resistance electric heat.
- Loads requiring fast-acting overload protection, such as equipment containing solid-state devices.

Specifications

Voltage Ratings Ampere Range Interrupting Ratings Approvals	600 Vac or less 1–600 A 200 kA rms symmetrical Standard 248-8, Class J UL Listed (File: E81895) CSA Certified (File: LR29862) Federal Specification WF-1814
Material	(QPL-W-F-1814) 1-60 A: Melamine body, Bronze cap (nickel plated) 70-400 A: Melamine body Brass cap 450-600 A: Melamine body Copper cap
Country of Origin	Mexico
Dimensions	

Dimensions

Ordering Information

		AMPERE	RATINGS			
1	20	45	90	175		350
3	25	50	100	200		400
6	30	60	110	225		450
10	35	70	125	250		500
15	40	80	150	300		600
VOLTAGE	SERIES	AMP			RDERING UMBER	
600	JLS	110	JLS110		0,	JLS110.X

Web Resources

Download TC curves, CAD drawings and other technical information: **littelfuse.com/jls**

Recommended Fuse Holders

LFJ60 Series	
LFPSJ Series (%/10-60 A)	111

Peak Let-Thru Curve





Н

CLASS J DIMENSIONS AND CURRENT-LIMITING EFFECTS

Dimensions Inches (mm)





Fig. 2

Dimensions of JTD_ID, JTD and JLS

Fig. 1

AMPERES	FIGURE		DIMENSIONS INCHES (mm)						
AIMFERES	NUMBER	А	В	С	D	Е	F	G	Н
1 - 30	1	2¼ (57.2)	—	1⁄2 (12.7)	¹³ ⁄16 (20.6)	—	—	—	—
35 - 60	1	2 ³ /8 (60.3)	—	5⁄8 (15.9)	1 ¹ /16 (27.0)	—	—	—	—
70 - 100	2	25⁄/8 (66.7)	3 ¹⁷ / ₃₂ (89.7)	3 ²³ / ₃₂ (94.5)	45⁄/8 (117.5)	11⁄8 (28.6)*	³ / ₄ (19.1)	⁹ /32 (7.1)	1⁄/8 (3.2)
110 - 200	2	3 (76.2)	4 ⁹ /32 (108.7)	4 ¹⁵ /32 (113.5)	5 ³ /4 (146.1)	11⁄2 (38.1)	11⁄8 (28.6)	⁹ /32 (7.1)	³ /16 (4.8)
225 - 400	2	33⁄/8 (85.7)	51⁄8 (130.2)	5 ³ /8 (136.5)	71⁄8 (181.0)	2 (50.8)	15⁄/8 (41.3)	¹³ /32 (10.3)	1⁄4 (6.4)
450 - 600	2	33⁄4 (95.3)	5 ²⁷ /32 (148.4)	6 ⁵ /32 (156.4)	8 (203.2)	2½ (63.5)	2 (50.8)	¹⁷ /32 (13.5)	³ ⁄8 (9.5)

*70-100 A JLS dimension = 1 (25.4)

Current-Limiting Effects of JTD_ID (600 V) Fuses

SHORT CIRCUIT		APPAREN	IT RMS SYMMETR	ICAL CURRENT FOF	R VARIOUS FUSE R	ATINGS	
CURRENT [†]	15 A	30 A	60 A	100 A	200 A	400 A	600 A
5,000	565	750	1,500	1,800	2,800	4,800	5,000
10,000	675	925	1,900	2,450	3,600	5,700	7,750
15,000	775	1,050	2,100	2,800	4,100	6,500	9,000
20,000	825	1,125	2,300	3,000	4,400	7,250	9,700
25,000	900	1,200	2,500	3,300	5,000	8,000	10,500
30,000	950	1,300	2,600	3,500	5,100	8,400	11,000
35,000	1,000	1,350	2,700	3,700	5,400	9,000	12,000
40,000	1,050	1,400	2,800	3,900	5,600	9,200	12,500
50,000	1,100	1,500	3,000	4,200	6,000	10,000	13,000
60,000	1,200	1,600	3,200	4,500	6,400	10,500	14,000
80,000	1,300	1,700	3,400	4,900	7,200	11,200	15,500
100,000	1,375	1,800	3,600	5,200	7,800	12,200	16,500
150,000	1,500	2,000	3,950	6,000	9,000	14,500	19,000
200,000	1,600	2,175	4,000	6,500	10,000	16,000	20,500

†Prospective RMS Symmetrical Amperes Short-Circuit Current Note: Data derived from Peak Let-Thru Curves

JLLN / JLLS SERIES FUSES

300/600 Vac • Fast-Acting • 1-1200 A





Description

JLLN / JLLS fuses are less than 1/3 the size of comparable Class R fuses and are typically used for short circuit protection of drives and surge sensitive components. When rated in accordance with the NEC[®], JLLN / JLLS fuses provide fast-acting overload and short circuit protection for non-inductive circuits and equipment.

Features/Benefits

- Extremely current-limiting
- Compact design
- 200 kA Interrupting Rating
- JLLN 35-60 A available with PCB mounts (see datasheet)

Applications

- Variable speed drive protection
- Compact mains switches

Specifications

Voltage Ratings	AC: 300 V (JLLN) 600 V (JLLS) DC: 125 V (JLLN 70 – 1200 A) 160 V (JLLN 1 – 60 A) 300 V (JLLS)
Interrupting Ratings	AC: 200 kA rms symmetrical
	DC: 20 kA (JLLN 35-1200 A only)
Ampere Range	1 – 1200 A
Approvals	AC: Standard 248-15, Class T UL Listed (File: E81895): JLLN (1 – 1200 A) JLLS (1 – 1200 A) CSA Certified (File: LR29862) JLLN/JLLS (1 – 600 A) DC: UL Listed (File: E81895): JLLN (35 – 1200 A) Littelfuse self-certified JLLN (1 – 30 A) JLLS (1 – 1200 A)
Material	JLLN: 1-30 A: Melamine body, Bronze caps 35-1200 A: Melamine body, Copper caps JLLS: 1-30 A: Melamine body, Copper caps 35-60 A: Melamine body, Bronze caps 70-1200 A: Melamine body, Copper caps
Environmental	RoHS Compliant

Ordering Information

		AMPERE	RATINGS		
1	25	70	175	450	1100
2	30	80	200	500	1200
3	35	90	225	600	
6	40	100	250	700	
10	45	110	300	800	
15	50	125	350	900*	
20	60	150	400	1000	

*JLLS only

Part Numbering System



SERIES	AMP	PACK SIZE	PLATING SUFFIX	MOUNT SUFFIX	CATALOG NUMBER	ORDERING NUMBER
JLLS	6	Т	-	-	JLLS006	JLLS006.T
JLLN	35	V	-	ΧL [†]	JLLN035L	JLLN035.VXL
JLLN	100	V	XP	-	JLLN100P	JLLN100.VXP

⁺Option is available for JLLN 35-60 A only. Premium plating is standard

Web Resources

Download TC Curves, CAD drawings and other technical information: **littelfuse.com/jlln littelfuse.com/jlls**

Recommended Fuse Holders

LFT30 Series	94
LFT60 Series	94
LSCR Series for 70-800 A	

Dimensions

Please refer to the Class T dimensions	25
Please refer to the JLLN datasheet for PCB mount	
dimensions: littelfuse.com/jlln	



CLASS T DIMENSIONS AND CURRENT-LIMITING EFFECTS

Dimensions Inches (mm)



AMPERES	REFER TO	SERIES							
AWPENES	FIG. NO. A		В	С	D	E	F	G	
1 – 30	1	JLLN	.875 (22.2)	—	.281 (7.1)	.406 (10.3)	—	—	_
1 – 30	1	JLLS	1.500 (38.1)	—	.281 (7.1)	.562 (14.3)	—	_	—
35 – 60	1	JLLN	.875 (22.2)	—	.281 (7.1)	.562 (14.3)	—	—	—
35-60	2	JLLS	1.562 (39.7)	.812 (20.6)	.406 (10.3)	.994 (25.2)	.062 (1.6)	1.094 (27.8)	—
70 – 100	3	JLLN	2.156 (54.8)	1.562 (39.7)	.750 (19.1)	.812 (20.6)	.830 (21.1)	.281 (7.1)	.125 (3.2)
70-100	3	JLLS	2.953 (75.0)	2.352 (59.7)	.750 (19.1)	.828 (21.0)	1.625 (41.3)	.281 (7.1)	.125 (3.2)
110 – 200	3	JLLN	2.437 (61.9)	1.687 (42.9)	.875 (22.2)	1.062 (27.0)	.830 (21.1)	.343 (8.7)	.187 (4.8)
110 - 200	5	JLLS	3.250 (82.6)	2.507 (63.7)	.875 (22.2)	1.078 (27.4)	1.656 (42.1)	.343 (8.7)	.187 (4.8)
225 – 400	3	JLLN	2.750 (69.9)	1.843 (46.8)	1.000 (25.4)	1.312 (33.3)	.828 (21.0)	.406 (10.3)	.250 (6.4)
223 - 400	5	JLLS	3.625 (92.1)	2.718 (69.1)	1.000 (25.4)	1.593 (40.5)	1.712 (43.5)	.406 (10.3)	.250 (6.4)
450 - 600	3	JLLN	3.062 (77.8)	2.031 (51.6)	1.250 (31.8)	1.593 (40.5)	.875 (22.2)	.484 (12.3)	.312 (7.9)
450 - 600	3	JLLS	3.984 (101.2)	2.953 (75.0)	1.250 (31.8)	2.062 (52.4)	1.765 (44.8)	.484 (12.3)	.312 (7.9)
700 – 800	3	JLLN	3.375 (85.7)	2.218 (56.4)	1.750 (44.5)	2.062 (52.4)	.875 (22.2)	.546 (13.9)	.375 (9.5)
700-800	3	JLLS	4.328 (109.9)	3.171 (80.6)	1.750 (44.5)	2.500 (63.5)	1.860 (47.2)	.546 (13.9)	.375 (9.5)
900 - 1200	2	JLLN	4.000 (101.6)	2.531 (64.3)	2.000 (50.8)	2.500 (63.5)	1.033 (26.2)	.609 (15.5)	.437 (11.1)
900 - 1200	3	JLLS	5.271 (133.9)	3.801 (96.5)	2.000 (50.8)	2.625 (66.7)	2.303 (58.5)	.609 (15.5)	.437 (11.1)

Current-Limiting Effects of JLLN (300 V) fuses

SHORT CIRCUIT	APPARENT RMS SYMMETRICAL CU VARIOUS FUSE RATINGS								
CURRENT*	30 A	60 A	100 A	200 A	400 A	600 A	800 A	1200 A	
5,000	700	775	1,100	1,650	3,500	4,000	5,000	5,000	
10,000	900	1,000	1,400	2,100	4,400	5,100	6,750	8,250	
15,000	1,000	1,100	1,600	2,400	5,000	5,900	7,750	10,000	
20,000	1,100	1,250	1,800	2,700	5,500	6,500	8,750	11,000	
25,000	1,230	1,300	1,950	2,900	6,000	7,000	9,500	12,000	
30,000	1,300	1,475	2,050	3,100	6,400	7,500	10,000	12,500	
35,000	1,330	1,575	2,150	3,300	6,750	7,750	10,500	13,500	
40,000	1,430	1,600	2,300	3,500	7,000	8,000	11,000	14,000	
50,000	1,500	1,750	2,400	3,700	7,500	8,750	12,000	15,000	
60,000	1,700	1,900	2,700	4,000	8,000	9,500	12,500	16,000	
80,000	1,850	2,100	2,800	4,400	9,000	10,500	14,000	17,500	
100,000	2,000	2,250	3,150	4,800	9,750	11,500	15,000	18,500	
150,000	2,300	2,600	3,600	5,500	11,000	13,000	17,500	22,000	
200,000	2,600	2,800	3,900	6,000	12,000	14,500	19,500	24,000	

^{*}Prospective RMS Symmetrical Amperes Short-Circuit Current Note: Data Derived from Peak Let-Thru Curves

Current-Limiting Effects of JLLS (600 V) fuses

SHORT CIRCUIT	APPARENT RMS SYMMETRICAL CURRENT VARIOUS FUSE RATINGS							R
CURRENT*	30 A	60 A	100 A	200 A	400 A	600 A	800 A	1200 A
5,000	750	1,225	1,810	2,500	4,600	5,000	5,000	5,000
10,000	945	1,525	2,300	3,150	6,000	8,500	9,400	10,000
15,000	1,050	1,700	2,610	3,600	6,600	9,750	10,500	13,000
20,000	1,150	1,900	2,900	3,950	7,250	10,500	11,000	14,750
25,000	1,300	2,050	3,100	4,250	8,000	11,500	12,500	15,500
30,000	1,375	2,150	3,300	4,500	8,250	12,000	13,750	16,500
35,000	1,400	2,250	3,500	4,750	8,500	13,000	14,000	17,000
40,000	1,425	2,400	3,650	4,950	8,700	14,000	14,750	18,000
50,000	1,600	2,450	3,900	5,350	9,500	14,500	16,000	20,000
60,000	1,650	2,625	4,150	5,650	10,000	15,500	17,300	21,000
80,000	1,825	2,800	4,570	6,250	11,000	17,000	18,750	23,000
100,000	2,000	3,100	4,950	6,700	12,000	18,000	20,000	25,000
150,000	2,250	3,400	5,650	7,700	13,000	21,000	23,000	28,500
200,000	2,450	3,800	6,200	8,450	15,000	23,000	25,000	31,000

*Prospective RMS Symmetrical Amperes Short-Circuit Current Note: Data Derived from Peak Let-Thru Curves

SLC SERIES FUSES

480/600 Vac • Time-Delay • 1/2-60 A





Description

Littelfuse SLC fuses provide cost effective branch circuit protection. Fuse length varies to prevent over-fusing. Compact Class G fuses were the first fuse series to approach midget fuse dimensions and meet NEC[®] requirements for branch-circuit protection.

Features/Benefits

- Branch circuit rated
- Current-limiting
- 100 kA interrupting rating
- 600 Vac rated 1/2-20 A

Applications

• Branch circuit protection

Specifications

Voltage Ratings	AC: 600 Vac or less (1/2 – 20 A) 480 Vac or less (25 – 60 A) DC: 170 Vdc (Littelfuse self-certified)
Ampere Range	¹ / ₂ - 60 A
Interrupting Ratings	AC: 100 kA rms symmetrical DC: 10 kA
Approvals	Standard 248-5, Class G UL Listed (File: E81895) CSA Certified (File: LR29862) Federal Specification WF-1814 (QPL-W-F-1814)
Material	1/2-30 A: Melamine body, Bronze cap (nickel plated) 35-60 A: Melamine body Brass cap (silver plated)
Environmental	RoHS Compliant

Ordering Information

AMPERE RATINGS						
1/2	3	6	12	25	40	60
1	4	8	15	30	45	
2	5	10	20	35	50	

SERIES	AMP	CATALOG NUMBER	ORDERING NUMBER
SLC	10	SLC010	OSLC010.T

Web Resources

Download TC Curves, CAD drawings and other technical information: **littelfuse.com/slc**

Recommended Fuse Holders

LFG60 Series (1-20 A)	
LFG48 Series (25-60 A)	

Dimensions



AMPERES	DIMENSIONS INCHES (mm)						
AIVII EIIES	А	В	С	D			
1/2 - 15	1 5/16 (33.3)	³ /8 (9.5)	9/32 (7.1)	13/32 (10.3)			
20	1 ¹³ /32 (35.7)	³ /8 (9.5)	⁹ /32 (7.1)	13/32 (10.3)			
25, 30	1 5/8 (41.3)	³ /8 (9.5)	⁹ /32 (7.1)	13/32 (10.3)			
35 - 60	2 1/4 (57.2)	³ /8 (9.5)	1/2 (12.7)	13/32 (10.3)			



CCMR SERIES POWR-PRO® FUSES

- POWR- PRO[®] 600 Vac • Dual Element • Time-Delay • 2/10-60 A



1



Description

The CCMR series is ideal for space saving protection of motors up to 40 hp*. It was designed specifically to withstand sustained starting currents of small motors. The CCMR 60 fuse is the smallest 60 A fuse available rated at 600 V. Compared to other UL Listed fuses, Class CC fuses are the most current-limiting, rating for rating.

Features/Benefits

- POWR-PRO® Performance •
- Extremely current-limiting •
- Ratings up to 60 Amps
- 300 kA Interrupting Rating (self-certified) ٠

Applications

• Motor and motor branch circuit protection

Specifications

Voltage Rating	AC: 600 Vac or less DC: 250 V (CCMR ² / ₁₀ - 2 A) (CCMR 4 ¹ / ₂ - 10 A) (CCMR 35-60 A) 300 V (CCMR 2 ¹ / ₄ - 4 A) 500 V (CCMR 12-30 A)
Ampere Rating	² /10 - 60 A
Interrupting Rating	AC: 200 kA rms symmetrical 300 kA Littelfuse self-certified DC: 20 kA
Approvals	AC: Standard 248-4, Class CC UL Listed ² /10-30 A (File: E81895) Standard 248, Class CD UL Listed 35-60 A (File: E81895) CSA Certified (File: LR29862) DC: Littelfuse self-certified
Material	2/10-30 A: Melamine body, Bronze cap (nickel plated)
Environmental Country of Origin	RoHS Compliant (except 35-60 A) Mexico

*Consult Motor Protection Tables on page 208 in the Technical Application Guide section for specific motor sizing information.

Ordering Information

			AMI	PERE RATI	NGS			
2/10	1	2	2	3 1/2	6 ¹ /4	1	2	35
1/4	1 1/4	2 1	/4	4	7	1	5	40
3/10	1 4/10	2	/2	4 1/2	7 1/2	17	1/2	45
1/2	1 1/2	2 8	/10	5	8	2	20	50
6/10	1 6/10	3	}	5 6/10	9	2	25	60
8/10	1 8/10	3 ²	/10	6	10	3	30	
SERIES	AMP	ROHS	CATALOG NUMBER		MBER	ORDE	RING	NUMBER
CCMR	10	•		CCMR010		C	CMR01	0.TXP
CCMR	45			CCMR045		(CCMRC)45.T

Web Resources

Download TC Curves, CAD drawings and other technical information: littelfuse.com/ccmr

Recommended Fuse Holders

LFC600 Series	101
L60030C Series	101
LFPSC Touch-Safe Series	110

Dimensions

Please refer to the Class CC/CD	dimensions 29
---------------------------------	---------------

Peak Let-Thru Curve



Note: For more information, see Peak Let-Thru Table on pg. 29

KLDR Series

KLDR / KLKR SERIES FUSES



UL Class CC Fuses

Description

600 Vac/300 Vdc • Time-Delay • 1/10-30 A

KLDR fuses are time-delay fuses designed to protect control transformers, solenoids and similar inductive components with high magnetizing currents during the first half-cycle. They provide excellent protection of motor branch circuits containing IEC or NEMA rated motor controllers or contactors.

Specifications

LDR

Voltage Rating	AC: 600 Vac or less
	DC: 300 Vdc
Ampere Range	¹ / ₁₀ - 30 A
Interrupting Rating	AC: 200 kA rms symmetrical
	DC: 20 kA
Approvals	AC: Standard 248-4, Class CC
	UL Listed 1/10-30 A (File: E81895)
	CSA Certified 1/10-30 A (File: LR29862)
	DC: Littelfuse self-certified
Material	Melamine body
	Bronze caps (nickel plated)
Environmental	RoHS Compliant
Country of Origin	Mexico

KLKR Series 600 Vac/300 Vdc • Fast-Acting • 1/10-30 A



Description

KLKR Series Class CC fuses are fast-acting fuses intended for general purpose branch circuit protection. Their compact size, fastacting overload response, and highly currentlimiting design make them ideal for use in OEM equipment and control panels.

Specifications

Voltage Rating	AC: 600 Vac or less DC: 300 Vdc
Ampere Range	$1/_{10} - 30 \text{ A}$
Interrupting Rating	AC: 200 kA rms symmetrical
·····	DC: 20 kA
Approvals	AC: Standard 248-4, Class CC
	UL Listed 1/10-30 A (File: E81895)
	CSA Certified 1/10-30 A (File: LR29862)
	DC: Littelfuse self-certified
Material	Melamine body
	Bronze caps (nickel plated)
Environmental	RoHS Compliant
Country of Origin	Mexico

Ordering Information

AMPERE RATINGS							
1/10	6/10	1 8/10	4 1/2	10			
1/8	3/4	2	5	12			
15/100	8/10	2 1/4	5 6/10	15			
3/16	1	2 ¹ /2	6	17 1/2			
2/10	1 1/8	2 8/10	6 ¹ /4	20			
1/4	1 ¹ /4	3	7	25			
3/10	1 4/10	3 ²/10	7 1/2	30			
4/10	1 1/2	3 1/2	8	—			
1/2	1 6/10	4	9	—			

SERIES	RIES AMP CATALOG NUMBER		ORDERING NUMBER		
KLDR	10	KLDR010	KLDR010.TXP		

Web Resources

For additional information, visit: **littelfuse.com/kldr**

Recommended Fuse Holders

L60030C Series	. 101
LFPSC Touch-Safe Series	. 110

Dimensions

Please refer to the Class CC dimensions...... 29



Ordering Information

AMPERE RATINGS							
1/10	1/2	2 1/2	6	12			
1/8	3/4	3	7	15			
2/10	1	3 1/2	8	20			
1/4	1 1/2	4	9	25			
3/10	2	5	10	30			

SERIES	AMP	CATALOG NUMBER	ORDERING NUMBER
KLKR	12	KLKR012	KLKR012.T

Web Resources

For additional information, visit: **littelfuse.com/klkr**

Recommended Fuse Holders

L60030C Series	101
LFPSC Touch-Safe Series	110

Dimensions

Please refer to the Class CC dimensions 29



CLASS CC / CD DIMENSIONS AND CURRENT-LIMITING EFFECTS

Dimensions Inches (mm)





Current-Limiting Effects of CCMR (600 V) fuses

SHORT CIRCUIT	APPARENT RMS SYMMETRICAL CURRENT FOR VARIOUS FUSE RATINGS																	
CURRENT*	2.25A	2.5A	3A	4A	5A	6.25A	7.5A	8A	10A	12A	15A	20A	30A	35A	40A	45A	50A	60A
5,000	203	224	287	289	460	472	442	437	359	369	435	355	621	1,170	1,240	1,320	1,070	1,525
10,000	256	282	361	364	580	595	557	551	452	465	548	447	783	1,480	1,565	1,670	1,355	1,930
15,000	293	323	413	416	664	681	637	631	517	532	627	512	896	1,695	1,795	1,915	1,555	2,200
20,000	323	356	455	458	730	750	702	694	569	585	690	563	987	1,870	1,980	2,110	1,710	2,430
25,000	348	383	490	493	787	808	756	748	613	630	743	607	1,063	2,015	2,135	2,275	1,845	2,620
30,000	370	407	521	524	836	858	803	795	651	670	790	645	1,129	2,145	2,270	2,420	1,965	2,780
35,000	389	429	548	552	880	903	845	837	686	705	832	679	1,189	2,260	2,390	2,550	2,070	2,885
40,000	407	448	573	577	920	944	884	875	717	737	870	709	1,243	2,360	2,500	2,665	2,165	3,025
50,000	438	483	617	622	991	1,017	952	942	772	794	937	764	1,339	2,545	2,695	2,875	2,330	3,200
60,000	466	513	656	661	1,053	1,081	1,012	1,001	821	844	995	812	1,423	2,705	2,865	3,055	2,480	3,350
80,000	513	564	722	727	1,159	1,190	1,114	1,102	903	929	1,096	894	1,566	2,985	3,160	3,365	2,730	3,540
100,000	552	608	778	783	1,249	1,282	1,200	1,187	973	1,001	1,180	963	1,687	3,215	3,405	3,630	2,945	3,685
150,000	632	696	890	897	1,430	1,467	1,373	1,359	1,114	1,146	1,351	1,102	1,931	3,685	3,905	4,160	3,375	4,030
200,000	696	766	980	987	1,574	1,615	1,511	1,496	1,226	1,261	1,487	1,213	2,125	4,060	4,300	4,580	3,720	4,230

*Prospective RMS Symmetrical Amperes Short-Circuit Current Note: Data Derived from Peak Let-Thru Curves

Peak Let-Thru Curve KLDR



Peak Let-Thru Curve KLKR



10 x 38mm MIDGET FUSES

KLK Series

UL Supplemental Fuses

1

Fast-Acting Fuse

600 Vac (1) (6) QPL RoHS CE

AMPERE RATINGS

AIVIFENENATIINUS								
1/ ₁₀	1	5	15					
1/ ₁₀ 1/ ₈	1 1/2	6	20					
² / ₁₀	2	7	25					
1/4	2 ¹ / ₂	8	30					
³ / ₁₀	3	9	_					
1/2	3 ¹ / ₂	10	_					
3/4	4	12						

Specifications

Fast-acting, high-interrupting capacity fuse designed for control circuits, HID lighting, street-lighting, meter circuits.

Voltage Ratings	600 Vac 500 Vdc				
Interrupting Ratings	100 kA @ 600 Vac 50 kA @ 500 Vdc				
	(capable of 200 kA)				
Approvals	UL Listed (E10480) CSA Certified (LR29862)				
Dimensions	 L 38.1mm (1 ¹/₂") D 10.31mm (¹³/₃₂") 				

littelfuse.com/klk





	AMPERE RATINGS							
1/10	1/2	2	5	12				
1/8	⁶ / ₁₀	2 1/4	5 ⁶ /10	14				
¹⁵ /100	⁸ /10	2 1/2	6	15				
3/16	1	3	6 ¹ / ₄	20				
² / ₁₀	1 ¹ / ₈	3 ²/ ₁₀	7	25				
1/4	1 ¹ / ₄	3 1/2	8	30				
³ / ₁₀	1 ¹ / ₂	4	9	—				
4/10	1 ⁶ / ₁₀	4 1/2	10	—				

Specifications

500V time-delay fuses for supplemental protection of control power transformers, solenoids, and circuits with high in-rush. Ideal for 480 V systems.

500 Vac

Voltage	Ratings

Voltago natingo	00	0 100
	30	0 Vdc self-certified @ 10 kA
Interrupting Ratings	10	kA @ 500V ac
Approvals	UL	Listed (E10480)
	CS	A Certified (LR29862)
Dimensions	L	38.1mm (1 1/2")
	D	10.31mm (13/32")
1.44 - 16 /61		

littelfuse.com/flq



AMPERE RATINGS			
1/10	1	5	15
1/8	1 1/2	6	20 25
2/10	2	7	25
1/4	2 1/2	8	30
3/10	3	9	—
1/2	3 1/2	10	—
3/4	4	12	

Specifications

Fast-acting, high DC rated fuse used in solar combiner boxes, DC control circuits, UPS protection. Available in PC board mount.

Voltage Ratings	600 Vac/dc	
Interrupting Ratings	100 kA @ 600 Vac	
	10 kA @ 600 Vdc (UL2579)	
	50 kA @ 600 Vdc (UL248-14)	
	(capable of 200 kA)	
Approvals	UL Listed (E339112 & E10480)	
	CSA Certified (LR29862)	
Dimensions	L 38.1mm (1 ¹ / ₂ ")	
	D 10.31mm (¹³ / ₃₂ ")	

littelfuse.com/klkd

BLN Series Fiber Body Fast-Acting Fuse 250 Vac



AMPERE RATINGS				
1 3 6 12 25				
1 1/2	4	8	15	30
2	5	10	20	—

Specifications

Fiber tube, 250 volt BLN fuses provide lowcost protection for military applications and control circuits.

Voltage Ratings	250 Vac
Interrupting Ratings	10 kA @ 250 Vac
Approvals	UL Listed (E10480) CSA Certified (LR29862)
Dimensions	 L 38.1mm (1 ¹/₂") D 10.31mm (¹³/₃₂")

littelfuse.com/bln

FLM Series Time-Delay Fuse 250 Vac (9) (6: OPL [RoHS] (7:) <??



AMPERE RATINGS				
1/10	8/10	2	4 1/2	10
15/100	1	2 1/4	5	12
² / ₁₀	1 ¹ /8	2 1/2	5 ⁶ /10	15
1/4	1 ¹ / ₄	2 8/10	6	20
³ /10	1 ⁴ /10	3	6 ¹ / ₄	25
4/10	1 ¹ / ₂	3 ² /10	7	30
1/2	1 ⁶ /10	3 ¹ / ₂	8	—
⁶ / ₁₀	1 ⁸ /10	4	9	—

Specifications

250V time-delay fuses used to protect circuits with high in-rush. Especially suited for supplemental protection of small motors.

Voltage Ratings	250 Vac 125 Vdc self-certified @ 10 kA
Interrupting Ratings	10 kA @ 250 Vac
Approvals	UL Listed (File: E10480) CSA Certified (029862_0_000)
Dimensions	L 38.1mm (1 ¹ / ₂ ") D 10.31mm (¹³ / ₃₂ ")
littelfuse.com/flm	

BLF Series Laminated Fast-Acting Fuse 125/250 Vac



AMPERE RATINGS			
1/2	3	7	15
1	4	8	20
1 1/2	5	9	25
2	6	10	30
2 1/2	6 1/4	12	—

Specifications

Laminated tube BLF fuses are the lowest price midget fuse. They are suitable for control circuit and instrument protection in dry locations.

Voltage Ratings	250 Vac 1/2 - 15 A	
	125 Vac 20 - 30 A	
Interrupting Ratings	10 kA @ rated Vac	
Approvals	UL Listed (E10480)	
	CSA Certified (LR29862)	
Dimensions	L 38.1mm (1 1/2")	
	D 10.31mm (¹³ / ₃₂ ")	

littelfuse.com/blf



10 x 38mm MIDGET FUSES

BLS Series Fast-Acting Fuse 600 Vac / 250 Vac (Ge RoHS



AMPERE RATINGS			
² / ₁₀	1	3	8
4/10	1 ¹ / ₂	4	10
1/2	1 ⁶ /10	5	—
3/4	1 8/10	6	—
8/10	2	7	—

Specifications

Slightly shorter than a traditional 10 x 38, BLS fuses provide space saving protection for low amperage applications.

Voltage Ratings	600 Vac ² /10 - 5 A	
	250 Vac 6 - 10 A	
Interrupting Ratings	10 kA @ rated Vac	
Approvals	UL Listed (E10480)	
	CSA Certified (LR29862)	
Dimensions	L 34.9 mm (1 ³ /8")	
	D 10.31 mm (¹³ / ₃₂ ")	

littelfuse.com/bls

KLQ Series Increased Time-Delay 600 Vac (Ge RoHS



1 2	5
1 ⁶ / ₁₀ 3	6

Specifications

Same physical size as the BLS fuse with more time delay. Designed to protect gaseous vapor fixtures, HID ballasts and other electronic lighting circuits.

Voltage Ratings	60	0 Vac
Interrupting Ratings	10 kA @ rated Vac	
Approvals		L Listed (E10480)
	С	SA Certified (LR29862)
Dimensions	L	34.9 mm (1 3/8")
	D	10.31 mm (13/32")
littelfuse.com/klq		

FLA Series Time-Delay Pin Indicating Fuse 125 Vac () 🕲



AMPERE RATINGS				
1/10	8/10	2	4 1/ ₂	12*
¹⁵ /100	1	2 1/4	5	15*
² / ₁₀	1 ¹ /8	2 ¹ / ₂	5 ⁶ /10	20*
1/4	1 1/4	2 8/10	6	25*
3/10	1 ⁴ /10	3	6 ¹ / ₄	30*
4/10	1 1/2	3 ² /10	7	—
1/2	1 ⁶ /10	3 1/2	8	
6/10	1 8/10	4	10	_

*12-30 A are dual tube design

Specifications

Pin indicating time-delay fuses. Use in conjunction with special fuse blocks to operate mechanical signal switches or energize alarm circuits.

Voltage Ratings	125 Vac
Interrupting Ratings	10 kA @ rated Vac
Approvals	UL Listed (E10480)
Dimensions	L 38.1 mm (1 1/2")
	D 10.31 mm (¹³ / ₃₂ ")

littelfuse.com/fla

PC BOARD MOUNT FUSE BLOCK

L60030MPCB

pg. 103

LFPHV (1000 V)

pg. 109



LFPSM (600 V) pg. 110

Section Overview

Diverse application needs require a broad range of fuses. Littelfuse offers a full line of fuses for various applications. As the market leader in Automotive and Electronics fuses, we are able to deliver innovative circuit protection solutions to our customers. Visit **littelfuse.com** for our full line of Automotive and Electronics solutions.



ELECTRONIC FUSES AND BLADE FUSES

Table of Contents

Glass /	' Electronic Fuses	33



HIGH DC VOLTAGE AND PC BOARD MOUNT FUSES



littelfuse.com/505 *Bulk configurations only

273 Series

2/3 Series Very Fast-Acting Microfuse



AMPERE RATINGS					
.002	.031	.125	.400	.750	2
.005	.050	.200	.500	.800	3
.010	.062	.250	.600	1	4
.015	.100	.300	.700	1.5	5

Specifications

Similar to 272 and 278 series, except has transparent cap for visual indication of fuse status. *See web for approvals by part.

Voltage Rating	125 Vac/dc	
Sample Part	0273002.V	
littelfuse.com/273		



477 Series 5 x 20 mm Slo-Blo® Fuse N ©



AMPERE RATINGS				
.5	2	5	10	
.8	3.15	6.3	12	
1	4	8	16	

Specifications

500 Vac/400 Vdc rated, 5 x 20 mm, time-lag, surge withstand ceramic body fuse. **Voltage Rating** 500 Vac

	400 Vdc	
Sample Part	0477002.MXP*	
Axial Lead	477_XEP Series	
Dimensions	L 20 mm (.79")	
	D 5.2 mm (.20")	
littelfuse.com/477		

*Bulk configurations only

Bulk configurations only

251 Series Fast-Acting Pico® II Fuse



AMPERE RATINGS				
.062	.500	1.25	3	7
.125	.630	1.5	3.5	10
.250	.750	2	4	12
.375	1	2.5	5	15

Specifications

Subminiature fuse for soldered mounting on printed circuit boards. Available on tape and reel for automatic insertion. *See web for approvals by part.

Voltage Ratings 125 Vac/dc ^{1/16} - 10 A 32 Vac/dc 12 - 15 A

Sample Part 0251001.NAT1L littelfuse.com/251



Dimensions mm (inches)







451 Series NANO^{2®} Very Fast-Acting



AMPERE RATINGS					
0.062	0.25	0.630	1.5	3.15	7
0.1	0.315	0.750	1.6	3.5	8
0.125	0.375	0.800	2	4	10
0.160	0.400	1	2.5	5	12
0.2	0.5	1.25	3	6.3	15

Specifications

The Nano² SMF Fuse is a very small, Wire-in-Air (WIA) square shape surface mount fuse which is very suitable for the secondary side circuit over-current protection applications and is designed for PCB using surface mount technology

*See web for approvals by part.

Voltage Rating	65 – 125 V
Sample Part	0451.125MP

littelfuse.com/451

LEADED AND CARTRIDGE FUSES

312/318 Series **3AG Fast-Acting**

(h) (h. Rohs



AMPERE RATINGS							
.062	.200	.750	1.8	5	15		
.100	.250	1	2	6	20		
.125	.300	1.25	2.25	7	25		
.15	.375	1.5	2.5	8	30		
.175	.500	1.6	3	10	35		
.187	.600	1.75	4	12	—		

Specifications

Designed for fast-acting protection of electronic equipment and appliances. The "standard" fast-acting, glass tube fuse.

Voltage Ratings	250 Vac ¹ / ₁₀₀ – 10 A 32 Vac 12 – 35 A
Dimensions	L 31.75 mm (1.25")
Comula Davi	D 6.35 mm (.25") 0312005.VXP
Sample Part For fuses with axial leads,	
For fuses with axial leads,	request 318 Series.

littelfuse.com/312

326/325 Series **3AB Slo-Blo®** (U) (Rohs



AMPERE RATINGS						
.010	.187	.600	1.5	4	15	
.031	.200	.700	1.6	5	20	
.062	.250	.750	2	6.25	25	
.100	.300	.800	2.5	7	30	
.125	.375	1	2.8	8	—	
.150	.400	1.2	3	10	—	
.175	.500	1.25	3.2	12	_	

Specifications

The 326 series fuse has time-delay similar to the 313 series, but the ceramic body permits higher voltage ratings for the 8 – 30 ampere sizes and faster opening of short-circuits.

Voltage Ratings	250 Vac 1/100 - 30 A
	125 Vdc 1/4 – 3 A
	125 Vdc 12 – 30 A
Dimensions	L 31.75 mm (1.25")
	D 6.35 mm (.25")
Sample Part	0326.100VXP
For fuses with axial leads,	request 325 Series.
littelfuse.com/326	

Note: All fuses on this page are available in packaged and bulk configurations

littelfuse.com

313/315 Series **3AG Slo-Blo®** (I) (Rohs



AMPERE RATINGS						
.010	.175	.500	1.25	2.8	7	30
.031	.187	.600	1.5	3	8	—
.040	.200	.700	1.6	3.2	10	—
.062	.250	.750	1.8	4	12	—
.100	.300	.800	2	5	15	—
.125	.375	1	2.25	6.25	20	—
.150	.400	1.2	2.5	6.3	25	—

Specifications

313 and 315 series fuses have time-delay in the overload range, providing superior protection for inductive loads. ID feature available which discolors upon opening. 00 – 8 A

Voltage Ratings	250 Vac 1/ ₁₀₀ – 8 A
	32 Vac 10 – 30 A
Dimensions	L 31.75 mm (1.25")
	D 6.35 mm (.25")
Sample Part	0313005.VXP
For fuses with axial lead	s, request 315 Series.
For Fuses with ID, add "I	D″ suffix.

littelfuse.com/313

229/230 Series **2AG Slo-Blo®** 🕒 🚯 поны 🁕



AMPERE RATINGS					
.250	.750	2	4		
.350	.800	2.25	5		
.375	1	2.5	6		
.500	1.25	3	7		
.600	1.5	3.5			

Specifications

2AG indicating fuses instantly identify themselves upon opening by showing a discoloration of their glass bodies, eliminating guesswork. This unique design offers the same quality performance characteristics as the standard 2AG fuse design.*

Voltage Ratings	250 Vac 1/4 – 3 1/2 A
	125 Vac 4 – 7 A
	125 Vdc 1/4 – 7 A
Dimensions	L 14.48 mm (.57")
	D 4.5 mm (.177")
Sample Part	02291.25VXP
For fuses with axial leads	, request 230 Series.
*Must add "S" suffix when o	rdering indicating fuse

34

littelfuse.com/229

.375	2	6	12
.500	3	7	15
.750	4	8	20
1	5	10	25
o			

314/324 Series

(U) (Rohs

3AB Fast-Acting

Specifications

Similar to 312 series, but ceramic tube permits higher interrupting ratings and voltage ratings: 250 volt ratings to 40 amps.

AMPERE RATINGS

30

40

Voltage Rating	250 Vac 3/ ₈ – 40 A
	125 Vdc 3/8 - 30 A
	150 Vdc 40 A
Dimensions	L 31.75 mm (1.25")
	D 6.35 mm (.25")
Sample Part	03145005.VXP
For fuses with axial leads,	, request 324 Series.
littalfusa sam /214	

littelfuse.com/314

225/224 Series **2AG Fast-Acting** (I) (I Rohis



AMPERE RATINGS						
.375	1	2.5	4	7		
.500	1.5	3	5	8		
.750	2	3.5	6	10		

Specifications

Fast-acting performance of the 312 series 3AG fuses in less than one-third the space. For protection of electronic equipment and appliances.

Voltage Ratings $250 \text{ Vac } \frac{3}{8} - 3 \frac{1}{2}$	А
125 Vac 4 – 10 A	
125 Vdc ³ / ₈ - 3 ¹ / ₂	А
Dimensions L 14.48 mm (.57")	
D 4.5 mm (.177")	
Sample Part 0225003.VXP	
For fuses with axial leads, request 224 Series	

littelfuse.com/225

Glass / Electronic Fuses


5 x 20 mm IEC LEADED AND CARTRIDGE FUSES

215 Series

5 x 20 mm IEC Slo-Blo®



	AMPERE RATINGS					
.125	.315	.800	2	5	12	
.160	.400	1	2.5	6.3	15	
.200	.500	1.25	3.15	8	16	
.250	.630	1.6	4	10	20	

Specifications

Time-delay protection of electronic equipment and appliances when fuses to International Standards are required. Replacement fuse for foreign equipment.

Voltage Rating Dimensions	250 Vac L 20 mm (.79")
	D 5.2 mm (.20")
Sample Part	0215005.VXP
For fuses with axial leads	s, request 215_XEP series.

littelfuse.com/215

216 Series

5 x 20 mm IEC Fast-Acting



AMPERE RATINGS						
.050	.125	.315	1	2.5	6.3	16
.063	.160	.500	1.25	3.15	8	—
.080	.200	.630	1.6	4	10	—
.100	.250	.800	2	5	12.5	—

Specifications

Fast-acting protection of electronic equipment and appliances when fuses to International Standards are required. Replacement fuse for foreign equipment.

Voltage Rating Dimensions	250 Vac 60 Vdc (1.25-3.15, 4-6.3 A only) L 20 mm (.79")
Sample Part	D 5.2 mm (.20") 0216005.VXP
	ads, request 216_XEP series.

littelfuse.com/216

0216005.VXP axial leads, request 216_XEP series. m/216

217 Series

5 x 20 mm IEC Fast-Acting

AMPERE RATINGS						
.032	.100	.250	.630	1.6	4	10
.050	.125	.315	.800	2	5	15
.063	.160	.400	1	2.5	6.3	
.080	.200	.500	1.25	3.15	8	—

Specifications

Fast-acting protection of electronic equipment and appliances when fuses to International Standards are required. Replacement fuse for foreign equipment.

Voltage Rating	250 Vac
	75Vdc (2-3.15 A only)
	60 Vdc (6.3, 25 A only)
Dimensions	L 20 mm (.79")
	D 5.2 mm (.20")
Sample Part	0217005.VXP
For fuses with axial leads	, request 217_XEP series.
littelfuse.com/217	

218 Series 5 x 20 mm IEC Slo-Blo[®] (\$) (\$) Finits



AMPERE RATINGS					
.032	.100	.315	1	3.15	10
.040	.125	.400	1.25	4	12.5
.050	.160	.500	1.6	5	15
.063	.200	.630	2	6.3	16
.080	.250	.800	2.5	8	—

Specifications

Time-delay protection of electronic equipment and appliances when fuses to International Standards are required. Replacement fuse for foreign equipment.

Voltage Rating	250 Vac
Dimensions	L 20 mm (.79")
	D 5.2 mm (.20")
Sample Part	0218005.VXP
For fuses with axial leads	, request 218_XEP series.
144-16	

littelfuse.com/218

235 Series 5 x 20 mm UL/CSA Fast-Acting (€ C € ^{™®}



AMPERE RATINGS					
.100	.300	.700	1.60	3.5	7
.125	.400	.800	2	4	—
.200	.500	1	2.5	5	_
.250	.600	1.25	3	6	—

Specifications

5 x 20 mm fuses designed to UL and CSA standards. Fast-acting protection of electronic equipment and appliances.

Voltage Ratings	250 Vac 1/10 – 3 1/2 A
	125 Vac 4 – 7 A
Dimensions	L 20 mm (.79")
	D 5.2 mm (.20")
Sample Part	0235005.VXP
For fuses with axial leads	, request 235_XEP series.
littelfuse.com/235	

239 Series 5 x 20 mm UL/CSA Slo-Blo[®] (9) (9): C € [895]



AMPERE RATINGS						
.080.	.200	.500	.800	2	3.20	7
.100	.250	.600	1	2.5	3.50	—
.125	.300	.700	1.25	3	4	
.150	.400	.750	1.60	3.15	5	—

Specifications

5 x 20 mm fuses designed to UL and CSA standards. Time-delay protection of electronic equipment and appliances.

Voltage Ratings	250 Vac ² / ₁₀ – 3 ¹ / ₂ A
	125 Vac 4 – 7 A
Dimensions	L 20 mm (.79")
	D 5.2 mm (.20")
Sample Part	0239005.VXP
For fuses with axial leads	s, request 239_XEP series.

littelfuse.com/239

Note: All fuses on this page are available in packaged and bulk configurations

Fuses – Blade / Automotive

BLADE FUSES

MINI[®] Smart Glow



2

Blade / Automotive Fuses

Specifications

Smart Glow fuses are innovative automotive style fuses (ATO, MINI, and MAXI) that feature an indicator light that glows when the fuse is blown, saving time to troubleshoot an open circuit.

Voltage Rating Sample Part

14 Vdc 0MIN010.VPGL0

MINI Fuses are available in packaged and bulk configurations. See 297 series on web.

ATO[®] Smart Glow

Specifications

Smart Glow fuses are innovative automotive style fuses (ATO, MINI, and MAXI) that feature indicator light that glows when the fuse is blown, saving time to troubleshoot an open circuit.

14 Vdc

0AT0010.VPGL0

ATO Fuses are available in packaged and bulk configurations. See 287 series on web.

Voltage Rating Sample Part

MAXI™

Smart Glow

Specifications

Smart Glow fuses are innovative

automotive style fuses (ATO, MINI, and

MAXI) that feature an indicator light that

14 Vdc 0MAX030.XPGL0

glows when the fuse is blown, saving

time to troubleshoot an open circuit.

MINI® Fast-Acting

🕕 Rohs 🕅

Specifications

ATO[®] Fast-Acting

Specifications

Voltage Rating

littelfuse.com/ato

Sample Part

The ATO® Fuse was designed and

the standard for automotive circuit

patented by Littelfuse in 1976 and set

protection. It features industry standard

color coding to indicate amperage rating.

32 Vac/dc

0AT0020.V

(IL) ROHS 🕅

The MINI® Fuse, with its miniature design patented by Littelfuse, meets the need for more circuits to be protected while utilizing less space. **Voltage Rating** 32 Vdc 0MIN020 V Sample Part littelfuse.com/mini

Fuses Rated 58 V Low Profile MINI® RoHS (P)



Specifications

The low profile MINI has similar performance as the standard mini fuse. The lower overall height allows for more space and weight savings. Voltage Rating 58 Vdc Sample Part I MIN010 V littelfuse.com/Imin

MINI dimensions in mm



Low Profile MINI dimensions in mm (inches)



ATO[®] / MINI[®] Color Key



1 A or 40 A

MAXI™ **Color Key**



MAXI[™] Slo-Blo RoHS



Specifications

Designed and patented by Littelfuse, the MAXI™ Fuse is ideal for motor powered applications which have large inrush currents.

Voltage Rating 32 Vdc 0MAX030.X Sample Part

littelfuse.com/maxi

MAXI Fuses are available in packaged and bulk configurations. See 299 series on web.

Voltage Rating

Sample Part

ATO dimensions in mm (inches)



MAXI dimensions in mm (inches)

29.21 (1.15')

21.59

12.70 (.50*)



BLADE FUSES

FHA Blade Fuse Holders—In-Line Fuse Holder for ATO[®] Style Blade Fuse

FHM Blade Fuse Holders-In-Line Splash-Waterproof

PART NUMBER

0FHM0001_

0FHM0002_

Fuse Holder for MINI[®] Style Blade Fuse



Used with ATO Fuse 1 to 20 A or 25 A and 30 A. Supplied with two 4" (102mm) wire leads.

littelfuse.com/fha

RoHS



PART NUMBER	DESCRIPTION	FUSE RATING
0FHA0001_	16AWG/1.3mm ² STRANDED BLACK WIRE	20 A
0FHA0002_	12AWG/3.3mm ²	30 A

DESCRIPTION 14AWG/2.1mm² STRANDED BI ACK WIRE

12AWG/3.3mm² STRANDED ORANGE WIRE

Wire length, color and diameter can be

customized upon request.

Wire length, color and diameter can be customized upon request.

FHAC Blade Fuse Holders—In-Line Splash-Waterproof Fuse Holder for ATO[®] Style Blade Fuse [RoHS]

Dimensions in mm



Used with ATO Fuse 1 to 20 A or 25 A and 30 A. Supplied with two 4" (102mm) wire leads. Includes protective cover for harsh environments. **littelfuse.com/fha**

PART NUMBER	DESCRIPTION	FUSE RATING
FHAC0001_	16AWG/1.3mm ² STRANDED BLACK WIRE	20 A
FHAC0002_	12AWG/3.3mm ² STRANDED ORANGE WIRE	30 A
Wire length,	color and diameter can be	

MAH Blade Fuse Holders—In-Line Fuse Holder for MAXI[™] Style Blade Fuse

customized upon request.

Dimensions in mm



PART DESCRIPTION FUSE NUMBER DESCRIPTION FUSE NUMBER 60A

Supplied with two 6," 6-gauge wire leads for up to 60 A MAXI Fuse applications, this In-Line Fuse holder also provides a protective cover for harsh under-the-hood environments. Mounting hole permits easy bulkhead installation.

littelfuse.com/mah

JCASE® Cartridge Fuse Rated 32 V

Used with MINI Fuse 1 to 20 A

or 25 A and 30 A. Supplied with

two 4.78" (122 mm) wire leads.

Includes protective cover for

harsh environment.

littelfuse.com/fhm



Specifications

The JCASE is a cartridge style fuse with female terminal design. JCASE provides both increased time delay and low voltage drop to protect high current circuits. JCASE has the ability to handle in-rush currents. The JCASE was designed and patented by Littelfuse.

littelfuse.com/jcase

Low Profile JCASE® Fuse Rated 58 V

FUSE RATING

20 A

30 A



Specifications

The Low Profile JCASE fuse has similar performance characteristics as the standard JCASE fuse. The lower overall height reduction allows for more space and weight savings and also allows for a shorter male blade terminal, saving additional weight and material savings in fuse box designs.





Low Profile JCASE® 58 V Dimensions in mm



JCASE[®] Color Key



Blade / Automotive Fuses

2

 \prod

Section Overview

Littelfuse is your source for a fast replacement of E- and R-rated medium voltage fuses. Our emergency service gets you the fuses you need quickly to minimize downtime of your critical operations.



🔆 MEDIUM VOLTAGE FUSES 🖷

Table of Contents

Medium Voltage Fuses Overview	39
R-Rated Medium Voltage Fuses	40
E-Rated Medium Voltage Fuses	42
Medium Voltage Live Parts	48



MEDIUM VOLTAGE FUSES

2,400-38,000 Vac • Current-Limiting



Description

Littelfuse® offers a selection of E- and R-rated medium voltage fuses for the protection of transformers, potential transformers, feeders, and motor circuits. Single, double, and triple barrel designs are available to cover a wide range of current, voltage, and interrupting ratings. Conventional ferrule type, clip lock, and bolt-in mounting configurations are available for virtually any application. Hermetically sealed fuses for use in hazardous environments are also offered.

Contact the factory or your local Littelfuse representative for additional fuse ratings or custom mounting configurations.

24-Hour Emergency Service - Call 800-227-0029

Applications

- Power Transformer Protection
- Potential Transformer Protection
- Motor Controller Back-up Protection
- Fused Switches
- Feeder Circuits



Current-limiting E- and R-rated fuses are equipped with a mechanical indicator or striker pin that protrudes through the fuse cap upon operation of the fuse. This provides visual identification of a blown fuse and can be used as a trigger for external devices.

Note: Extension distance 1/2" minimum; extension force 2 lb. minimum.

General Information

The terms "Medium Voltage" and "High Voltage" have been used interchangeably by many people to describe fuses operating above 600 volts. Technically speaking, medium voltage fuses are those intended for the voltage range from 2,400 to 38,000 Vac. High voltage fuses are for circuits carrying voltages greater than 38,000 Vac.

E-rated fuses are considered to be general purpose fuses and can be used to protect against low and high values of fault current. R-rated fuses are designed for back-up protection. They must be used in series with other devices such as motor overload relays in order to achieve both overload and short-circuit protection.

Medium voltage fuses are not intended to provide overload protection in the same sense as fuses rated 600 volts or less. Medium voltage fuse current ratings do not have the same meanings as the ampere ratings of low voltage fuses.

All medium voltage fuses are limited in their ability to interrupt low value overcurrents, especially those between 100% and 200% of the fuse's continuous current rating. They are designed to carry their rated current without exceeding the temperature rise permitted by NEMA and ANSI standards.



Bolt-in Mount Fuses

Description

R-rated fuses provide required short-circuit protection for medium voltage motors, motor controllers and associated circuitry. These components have limited ability to absorb the energy of large short-circuit currents. Medium voltage motor controllers contain overload relays which provide both overload protection and locked rotor protection to the motor. The controllers are also intended to interrupt low value short-circuits within the capability of the motor controller. This protects the medium voltage fuse from sustained overcurrents which are less than their minimum interrupting rating.

NEMA Standards for R-rated medium voltage power fuses require they operate within 15-35 seconds when subjected to an rms current 100 times the R rating. For example, a fuse with a 2R rating will open within 15 to 35 seconds on an applied current of $2 \times 100 = 200$ amperes.

Ordering Number



9 75

Figure 3

Dimensions







Sample Part #: 130-4R-1B-5.5



Inverted-Bolt "IB" Sample Part #: 130-4R-11B-5.5

Characteristics

Voltage Ratings	2,750 V – 8,250 V
Current Range	2R – 36R

Options

- Hermetically sealed for use in hazardous locations (add "S" suffix to part number)
- Bolt-in mounting configurations



Hookeye Feature*

For hookeye attachment; add "W" suffix to part number

*See web for Bolt Mount, Inverted Bolt Mount, and Bolt-In dimensions

Medium Voltage Fuse Protection

POWR-GARD® medium voltage fuses provide short-circuit protection for motors and transformers rated 2,400 to 38,000 volts AC.



Visit **littelfuse.com/MediumVoltage** to download the white paper featuring protection tables, sizing recommendations, and applications.



Sample Part #: 130-4R-1BI-5.5

R RATED	ORDERING/ CATALOG NUMBER	SIZE	MAXIMUM CONTINUOUS CURRENT @ 40 DEGREES C°	DIM. A (INCHES)	DIM. B (INCHES)	MINIMUM INTERRUPTING RATING RMS AMPS	MAXIMUM INTERRUPTING RATING RMS (ASYM)*	FIGURE NUMBER
	702R1C2.75	2R	70	7"	10.875"	170	80,000	1
	1003R1C2.75	3R	100	7"	10.875"	250	80,000	1
	1304R1C2.75	4R	130	7"	10.875"	340	80,000	1
>	1505R1C2.75	5R	150	7"	10.875"	390	80,000	1
2.75 KV	1706R1C2.75	6R	170	7"	10.875"	500	80,000	1
2.7	2009R1C2.75	9R	200	7"	10.875"	760	80,000	1
	23012R1C2.75	12R	230	7"	10.875"	1000	80,000	1
-	39018B2C2.75	1211 18R	390	7"	10.875"	1500	80,000	2
	45024R2C2.75	24R	450	7"	10.875"	1950	80,000	2
	4002411202.70	2711	400	1	10.070	1000	00,000	2
R RATED	ORDERING/ CATALOG NUMBER	SIZE	MAXIMUM CONTINUOUS CURRENT @ 40 DEGREES C°	DIM. A (INCHES)	DIM. B (INCHES)	MINIMUM INTERRUPTING RATING RMS AMPS	MAXIMUM INTERRUPTING RATING RMS (ASYM)*	FIGURE NUMBER
	702R1C5.5	2R	70	12"	15.875"	170	80,000	1
	1003R1C5.5	3R	100	12"	15.875"	250	80,000	1
	1304R1C5.5	4R	130	12"	15.875"	340	80,000	1
	1505R1C5.5	5R	150	12"	15.875"	390	80,000	1
	1706R1C5.5	6R	170	12"	15.875"	500	80,000	1
	2009R1C5.5 23012R1C5.5	9R 12R	200 230	12" 12"	15.875" 15.875"	760 1000	80,000 80,000	1
2	39018R2C5.5	12N	390	12"	15.875"	1500	80,000	2
5.5 KV	45024R2C5.5	24R	450	12"	15.875"	1950	80,000	2
ů.	48026R2C5.5	26R	480	12"	15.875"	2100	80,000	2
	55030R2C5.5	30R	550	12"	15.875"	2400	80,000	2
	60032R2C5.5	32R	600	12"	15.875"	2600	80,000	2
	65036R2C5.5	36R	650	12"	15.875"	2900	80,000	2
	55030R3C5.5	30R	550	12"	15.875"	2400	80,000	3
	60032R3C5.5	32R	600	12"	15.875"	2600	80,000	3
	65036R3C5.5	36R	650	12"	15.875"	2900	80,000	3
R RATED	ORDERING/ CATALOG NUMBER	SIZE	MAXIMUM CONTINUOUS CURRENT @ 40 DEGREES C°	DIM. A (INCHES)	DIM. B (INCHES)	MINIMUM INTERRUPTING RATING RMS AMPS	MAXIMUM INTERRUPTING RATING RMS (ASYM)*	FIGURE NUMBER
	702R1C5.5X	2R	70	14"	17.875"	170	80,000	1
	1003R1C5.5X	3R	100	14"	17.875"	250	80,000	1
BS	1304R1C5.5X	4R	130	14"	17.875"	340	80,000	1
. KV CENTERS	1505R1C5.5X	5R	150	14"	17.875"	390	80,000	1
5 KV	1706R1C5.5X	6R	170	14"	17.875"	500	80,000	1
5.5	2009R1C5.5X	9R	200	14"	17.875"	760	80,000	1
5.5 14"CLIP	23012R1C5.5X	12R	230	14"	17.875"	1000	80,000	1
14	39018R2C5.5X	18R 24R	390	14" 14"	17.875"	1500	80,000	2
	45024R2C5.5X 55030R2C5.5X	30R	450 550	14	17.875" 17.875"	1950 2400	80,000 80,000	2
	00000H200.0A	JUN	550	14	17.075	2400	00,000	Z
R RATED	ORDERING/ CATALOG NUMBER	SIZE	MAXIMUM CONTINUOUS CURRENT @ 40 DEGREES C°	DIM. A (INCHES)	DIM. B (INCHES)	MINIMUM INTERRUPTING RATING RMS AMPS	MAXIMUM INTERRUPTING RATING RMS (ASYM)*	FIGURE NUMBER
	702R1C8.25	2R	70	12"	15.875"	190	80,000	1
	1003R1C8.25	3R	100	12"	15.875"	225	80,000	1
	1304R1C8.25	4R	130	12"	15.875"	330	80,000	1
≥	1505R1C8.25	5R	150	12"	15.875"	440	80,000	1
8.25 KV	1706R1C8.25	6R	170	12"	15.875"	500	80,000	1
α	2009R1C8.25	9R	200	12"	15.875"	740	80,000	1
	23012R1C8.25	12R	230	12"	15.875"	955	80,000	1
	39018R2C8.25 45024R2C8.25	18R 24R	390 450	12" 12"	15.875" 15.875"	1440 1910	80,000 80,000	2
	4002411200.20	2411	400	١Z	13.075	1310	00,000	2

* RMS Asymmetrical amperes = RMS Symmetrical amperes x 1.6 For hookeye attachment add "W" suffix to part number

Description

E-rated fuses have time current characteristics designed to provide current-limiting protection for power transformers, potential transformers, power centers, feeder centers, and unit sub stations. When properly applied, they can protect against high and low fault currents.

NEMA Standards for E-rated medium voltage fuses require that fuses rated 100E or less open within 300 seconds (5 minutes) when subjected to an RMS value of 200-240% of the fuse continuous current rating; and fuses with an E rating larger than 100E must open within 600 seconds (10 minutes) when subjected to an RMS current of 220-240% of the fuse's continuous current rating. These values establish one point on the time-current curve.

Application Note

Since these fuses are used for the protection of general purpose circuits which may contain transformers, motors, and other equipment producing in-rush and/or overload currents, fuses should generally be rated at 140% of the normal full load current, and circuits should be analyzed to ensure that system load currents will not exceed the current rating of the fuse.

Characteristics

Voltage Ratings	2,750 V – 38,000 V
Current Range	10E - 600E

Options

- Hermetically sealed for use in hazardous locations (add "S" suffix to part number)
- Clip-lock (CL) available.

Dimensions





E-RATED	ORDERING/CATALOG NUMBER	SIZE	DIM. A (INCHES)	DIM. B (INCHES)	MAX INTERRUPTING RATING RMS (ASYM)*	FIGURE NUMBER
	10E1C2.75	10E	7"	10.875"	80,000	4
	15E1C2.75	15E	7"	10.875"	80,000	4
	20E1C2.75	20E	7"	10.875"	80,000	4
	25E1C2.75	25E	7"	10.875"	80,000	4
	30E1C2.75	30E	7"	10.875"	80,000	4
	40E1C2.75	40E	7"	10.875"	80,000	4
	50E1C2.75	50E	7"	10.875"	80,000	4
	65E1C2.75	65E	7"	10.875"	80,000	4
\geq	80E1C2.75	80E	7"	10.875"	80,000	4
	100E-1C2.75	100E	7"	10.875"	80,000	4
AA I	125E1C2.75	125E	7"	10.875"	80,000	4
2.75 MAX.	150E1C2.75	150E	7"	10.875"	80,000	4
2.7	200E1C2.75	200E	7"	10.875"	80,000	4
	125E2C2.75	125E	7"	10.875"	80,000	5
	150E2C2.75	150E	7"	10.875"	80,000	5
	200E2C2.75	200E	7"	10.875"	80,000	5
	250E2C2.75	250E	7"	10.875"	80,000	5
	300E2C2.75	300E	7"	10.875"	80,000	5
	350E2C2.75	350E	7"	10.875"	80,000	5
	400E2C2.75	400E	7"	10.875"	80,000	5
	450E2C2.75	450E	7"	10.875"	80,000	5

* RMS Asymmetrical amperes = RMS Symmetrical amperes x 1.6



E-RATED	ORDERING/CATALOG NUMBER	SIZE	DIM. A (INCHES)	DIM. B (INCHES)	MAX INTERRUPTING RATING RMS (ASYM)*	FIGURE NUMBER
	10E1C5.5	10E	12"	15.875"	80,000	4
	15E1C5.5	15E	12"	15.875"	80,000	4
	20E1C5.5	20E	12"	15.875"	80,000	4
	25E1C5.5	25E	12"	15.875"	80,000	4
	30E1C5.5	30E	12"	15.875"	80,000	4
	40E1C5.5	40E	12"	15.875"	80,000	4
	50E1C5.5	50E	12"	15.875"	80,000	4
	65E1C5.5	65E	12"	15.875"	80,000	4
	80E1C5.5	80E	12"	15.875"	80,000	4
	100E1C5.5	100E	12"	15.875"	80,000	4
≥	125E1C5.5	125E	12"	15.875"	80,000	4
	150E1C5.5	150E	12"	15.875"	80,000	4
(A)	175E1C5.5	175E	12"	15.875"	80,000	4
5.5 MAX.	200E1C5.5	200E	12"	15.875"	80,000	4
5.	125E2C5.5	125E	12"	15.875"	80,000	5
	150E2C5.5	150E	12"	15.875"	80,000	5
	200E2C5.5	200E	12"	15.875"	80,000	5
	250E2C5.5	250E	12"	15.875"	80,000	5
	300E2C5.5	300E	12"	15.875"	80,000	5
	350E2C5.5	350E	12"	15.875"	80,000	5
	400E2C5.5	400E	12"	15.875"	80,000	5
	450E2C5.5	450E	12"	15.875"	80,000	5
	500E3C5.5	500E	12"	15.875"	80,000	6
	550E3C5.5	550E	12"	15.875"	80,000	6
	600E3C5.5	600E	12"	15.875"	80,000	6

E-RATED	ORDERING/CATALOG NUMBER	SIZE	DIM. A (INCHES)	DIM. B (INCHES)	MAX INTERRUPTING RATING RMS (ASYM)*	FIGURE NUMBER
	5NLE10E	10E	14″	171⁄8"	80,000	4
	5NLE15E	15E	14"	171/8"	80,000	4
	5NLE20E	20E	14″	171/8"	80,000	4
	5NLE25E	25E	14″	171/8"	80,000	4
	5NLE30E	30E	14″	171/8"	80,000	4
	5NLE40E	40E	14″	171/8"	80,000	4
	5NLE50E	50E	14″	17%"	80,000	4
	5NLE65E	65E	14"	171/8"	80,000	4
\geq	5NLE80E	80E	14″	171/8"	80,000	4
X.	5NLE100E	100E	14″	171/8"	80,000	4
5.5 MAX.	5NLE125E	125E	14"	171/8"	80,000	4
5.5	5NLE150E	150E	14″	17%"	80,000	4
	5NLE175E	175E	14″	171/8"	80,000	4
	5NLE200E	200E	14″	171/8"	80,000	4
	5NLE2225E	225E	14″	171/8"	80,000	5
	5NLE2250E	250E	14"	171/8"	80,000	5
	5NLE2300E	300E	14″	171/8"	80,000	5
	5NLE2350E	350E	14"	171/8"	80,000	5
	5NLE2400E	400E	14″	171/8"	80,000	5
	5NLE2450E	450E	14"	17%"	80,000	5

* RMS Asymmetrical amperes = RMS Symmetrical amperes x 1.6

E-RATED	ORDERING/CATALOG NUMBER	SIZE	DIM. A (INCHES)	DIM. B (INCHES)	MAX INTERRUPTING RATING RMS (ASYM)*	FIGURE NUMBER
	10E1C8.25	10E	12"	15 1/8"	80,000,	4
	15E1C8.25	15E	12"	151⁄8"	80,000	4
	20E1C8.25	20E	12"	157⁄8"	80,000	4
	25E1C8.25	25E	12"	15 7⁄8"	80,000	4
	30E1C8.25	30E	12"	157⁄8"	80,000	4
	40E1C8.25	40E	12"	157%"	80,000	4
	50E1C8.25	50E	12"	15 7/8"	80,000	4
5	65E1C8.25	65E	12"	15%"	80,000	4
×	80E1C8.25	80E	12"	157/8"	80,000	4
8.25 MAX. KV	100E1C8.25	100E	12"	157%"	80,000	4
Σ	125E1C8.25	125E	12"	15 7/8"	80,000	4
.25	150E1C8.25	150E	12"	15%	80,000	4
~	125E2C8.25	125E	12"	1578	80,000	5
	150E2C8.25	150E	12"	15%"	80,000	5
	200E2C8.25	200E	12"	15%"	80,000	5
	250E2C8.25	250E	12"	15%"	80,000	5
	300E2C8.25	300E	12"	151⁄8"	80,000	5
	350E3C8.25	350E	12"	151⁄8"	80,000	6
	400E3C8.25	400E	12"	157⁄8"	80,000	6
E-RATED	ORDERING/CATALOG NUMBER	SIZE	DIM. A (INCHES)	DIM. B (INCHES)	MAX INTERRUPTING RATING RMS (ASYM)*	FIGURE NUMBER
	8NLE10E	10E	14"	17 ⁷ /8"	80,000	4
	8NLE15E	15E	14"	17 1/8"	80,000	4
	8NLE20E	20E	14"	17 1/8"	80,000	4
	8NLE25E	25E	14"	17 1/8"	80,000	4
	8NLE30E	30E	14"	17 7/8"	80,000	4
>	8NLE40E	40E	14"	17 7/8"	80,000	4
×	8NLE50E	50E	14"	17 7/8"	80,000	4
8.25 MAX. KV				17 7/8"		4
Σ	8NLE65E	65E	14"		80,000	
25	8NLE80E	80E	14"	17%"	80,000	4
ೲ	8NLE100E	100E	14"	17 1/8"	80,000	4
	8NLE2100E	100E	14"	17 1/8"	80,000	5
	8NLE2125E	125E	14"	17 1/8"	80,000	5
	8NLE2150E	150E	14"	17 1/8"	80,000	5
	8NLE2200E	200E	14"	17 1/8"	80,000	5
	8NLE2250E	250E	14"	17%"	80,000	5
E-RATED	ORDERING/CATALOG NUMBER	SIZE	DIM. A (INCHES)	DIM. B (INCHES)	MAX INTERRUPTING RATING RMS (ASYM)*	FIGURE NUMBER
	10E1C15.5	10E	15"	18.875"	80,000	4
	15E1C15.5	15E	15"	18.875"	80,000	4
	15E1C15.5 20E1C15.5		15"	18.875" 18.875"	80,000 80,000	
	20E1C15.5	20E	15"	18.875"	80,000	4
	20E1C15.5 25E1C15.5	20E 25E	15" 15"	18.875" 18.875"	80,000 80,000	4
	20E1C15.5 25E1C15.5 30E1C15.5	20E 25E 30E	15" 15" 15"	18.875" 18.875" 18.875"	80,000 80,000 80,000	4 4 4
	20E1C15.5 25E1C15.5 30E1C15.5 40E1C15.5	20E 25E 30E 40E	15" 15" 15" 15"	18.875" 18.875" 18.875" 18.875"	80,000 80,000 80,000 80,000	4 4 4 4
	20E1C15.5 25E1C15.5 30E1C15.5 40E1C15.5 50E1C15.5	20E 25E 30E 40E 50E	15" 15" 15" 15" 15"	18.875" 18.875" 18.875" 18.875" 18.875" 18.875"	80,000 80,000 80,000 80,000 80,000 80,000	4 4 4 4 4 4
X	20E1C15.5 25E1C15.5 30E1C15.5 40E1C15.5 50E1C15.5 65E1C15.5	20E 25E 30E 40E 50E 65E	15" 15" 15" 15" 15" 15" 15"	18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875"	80,000 80,000 80,000 80,000 80,000 80,000	4 4 4 4 4 4
X. KV	20E1C15.5 25E1C15.5 30E1C15.5 40E1C15.5 50E1C15.5 65E1C15.5 80E1C15.5	20E 25E 30E 40E 50E 65E 80E	15" 15" 15" 15" 15" 15" 15" 15"	18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875"	80,000 80,000 80,000 80,000 80,000 80,000 80,000	4 4 4 4 4 4 4 4
AAX. KV	20E1C15.5 25E1C15.5 30E1C15.5 40E1C15.5 50E1C15.5 65E1C15.5 80E1C15.5 100E1C15.5	20E 25E 30E 40E 50E 65E 80E 100E	15" 15" 15" 15" 15" 15" 15" 15" 15"	18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875"	80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000	4 4 4 4 4 4 4 4 4
5 MAX. KV	20E1C15.5 25E1C15.5 30E1C15.5 40E1C15.5 50E1C15.5 65E1C15.5 80E1C15.5 100E1C15.5 65E2C15.5	20E 25E 30E 40E 50E 65E 80E 100E 65E	15" 15" 15" 15" 15" 15" 15" 15" 15"	18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875"	80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000	4 4 4 4 4 4 4 4 4 5
15.5 MAX. KV	20E1C15.5 25E1C15.5 30E1C15.5 40E1C15.5 50E1C15.5 65E1C15.5 80E1C15.5 100E1C15.5 65E2C15.5 80E2C15.5	20E 25E 30E 40E 50E 65E 80E 100E 65E 80E	15" 15" 15" 15" 15" 15" 15" 15" 15" 15"	18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875"	80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000	4 4 4 4 4 4 4 4 5 5 5
15.5 MAX. KV	20E1C15.5 25E1C15.5 30E1C15.5 40E1C15.5 50E1C15.5 65E1C15.5 80E1C15.5 100E1C15.5 65E2C15.5 80E2C15.5 80E2C15.5 100E2C15.5	20E 25E 30E 40E 50E 65E 80E 100E 65E 80E 100E	15" 15" 15" 15" 15" 15" 15" 15" 15" 15"	18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875"	80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000	4 4 4 4 4 4 4 4 5 5 5 5 5
15.5 MAX. KV	20E1C15.5 25E1C15.5 30E1C15.5 40E1C15.5 50E1C15.5 65E1C15.5 80E1C15.5 100E1C15.5 65E2C15.5 80E2C15.5 100E2C15.5 125E2C15.5	20E 25E 30E 40E 50E 65E 80E 100E 65E 80E 100E 125E	15" 15" 15" 15" 15" 15" 15" 15" 15" 15"	18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875"	80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000	4 4 4 4 4 4 4 4 5 5 5 5 5 5 5
15.5 MAX. KV	20E1C15.5 25E1C15.5 30E1C15.5 40E1C15.5 50E1C15.5 65E1C15.5 80E1C15.5 100E1C15.5 65E2C15.5 80E2C15.5 100E2C15.5 125E2C15.5 150E2C15.5	20E 25E 30E 40E 50E 65E 80E 100E 65E 80E 100E 125E 150E	15" 15"	18.875" 18.875"	80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000	4 4 4 4 4 4 4 4 5 5 5 5 5 5 5 5 5 5
15.5 MAX. KV	20E1C15.5 25E1C15.5 30E1C15.5 40E1C15.5 50E1C15.5 65E1C15.5 80E1C15.5 80E1C15.5 100E1C15.5 65E2C15.5 80E2C15.5 100E2C15.5 125E2C15.5 150E2C15.5 175E2C15.5	20E 25E 30E 40E 50E 65E 80E 100E 65E 80E 100E 125E 150E 175E	15" 15"	18.875" 18.875"	80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000	4 4 4 4 4 4 4 4 5 5 5 5 5 5 5 5 5 5 5 5
15.5 MAX. KV	20E1C15.5 25E1C15.5 30E1C15.5 40E1C15.5 50E1C15.5 65E1C15.5 80E1C15.5 100E1C15.5 65E2C15.5 80E2C15.5 100E2C15.5 125E2C15.5 150E2C15.5	20E 25E 30E 40E 50E 65E 80E 100E 65E 80E 100E 125E 150E	15" 15"	18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875"	80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000	4 4 4 4 4 4 4 4 5 5 5 5 5 5 5 5 5 5 5 5
15.5 MAX. KV	20E1C15.5 25E1C15.5 30E1C15.5 40E1C15.5 50E1C15.5 65E1C15.5 80E1C15.5 80E1C15.5 100E1C15.5 65E2C15.5 80E2C15.5 100E2C15.5 125E2C15.5 150E2C15.5 175E2C15.5	20E 25E 30E 40E 50E 65E 80E 100E 65E 80E 100E 125E 150E 175E	15" 15"	18.875" 18.875"	80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000	4 4 4 4 4 4 4 4 5 5 5 5 5 5 5 5 5 5 5 5
15.5 MAX. KV	20E1C15.5 25E1C15.5 30E1C15.5 40E1C15.5 50E1C15.5 65E1C15.5 80E1C15.5 80E1C15.5 100E1C15.5 65E2C15.5 80E2C15.5 100E2C15.5 125E2C15.5 150E2C15.5 175E2C15.5 200E2C15.5	20E 25E 30E 40E 50E 65E 80E 100E 100E 125E 150E 175E 200E	15" 15"	18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875" 18.875"	80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000 80,000	4 4 4 4 4 4 4 4 5 5 5 5 5 5 5 5 5 5 5 5

* RMS Asymmetrical amperes = RMS Symmetrical amperes x 1.6



E-RATED	ORDERING/CATALOG NUMBER	SIZE	DIM. A (INCHES)	DIM. B (INCHES)	MAX INTERRUPTING RATING RMS (ASYM)*	FIGURE NUMBER
	15GSE65E	65E	18"	21 7⁄8"	60,000	4
Ž	15GSE80E	80E	18"	21 7⁄8"	60,000	4
×	15GSE100E	100E	18"	21 7/8"	60,000	4
MA	15GSE2125E	125E	18"	21 7⁄8"	60,000	5
2	15GSE2150E	150E	18"	21 7⁄8"	60,000	5
15.	15GSE2175E	175E	18"	21 7⁄8"	60,000	5
	15GSE2200E	200E	18"	21 1/8"	60,000	5

E-RATED	ORDERING/CATALOG NUMBER	SIZE	DIM. A (INCHES)	DIM. B (INCHES)	MAX INTERRUPTING RATING RMS (ASYM)*	FIGURE NUMBER
	15NLE10E	10E	20"	23%"	60,000	4
	15NLE15E	15E	20"	23 ⁷ /8"	60,000	4
	15NLE20E	20E	20"	23 1/8"	60,000	4
	15NLE25E	25E	20"	23 1/8"	60,000	4
	15NLE30E	30E	20"	23 1/8"	60,000	4
	15NLE40E	40E	20"	231⁄8"	60,000	4
	15NLE50E	50E	20"	23 7⁄8"	60,000	4
>	15NLE65E	65E	20"	23 ⁷ /8"	60,000	4
. K	15NLE80E	80E	20"	23 ⁷ /8"	60,000	4
MAX.	15NLE100E	100E	20"	23 7⁄8"	60,000	4
Σ	15NLE280E	80E	20"	237⁄8"	60,000	5
15.5	15NLE2100E	100E	20"	231⁄8"	60,000	5
=	15NLE2125E	125E	20"	23 7⁄8"	60,000	5
	15NLE2150E	150E	20"	23 ⁷ /8"	60,000	5
	15NLE2175E	175E	20"	23 7⁄8"	60,000	5
	15NLE2200E	200E	20"	231/8"	60,000	5
	15NLE3150E	150E	20"	231⁄8"	60,000	6
	15NLE3175E	175E	20"	23 7/8"	60,000	6
	15NLE3250E	250E	20"	23 1/8"	60,000	6
	15NLE3300E	300E	20"	231/8"	60,000	6

E-RATED	ORDERING/CATALOG NUMBER	SIZE	DIM. A (INCHES)	DIM. B (INCHES)	MAX INTERRUPTING RATING RMS (ASYM)*	FIGURE NUMBER
	15E1C25.8	15E	21"	241/8"	40,000	4
	20E1C25.8	20E	21"	241/8"	40,000	4
₹	25E1C25.8	25E	21"	241/8"	40,000	4
×	30E1C25.8	30E	21"	241⁄8″	40,000	4
MAX.	40E1C25.8	40E	21"	241⁄8″	40,000	4
∞.	50E1C25.8	50E	21"	241⁄8″	40,000	4
25.	65E2C25.8	65E	21"	241⁄8″	40,000	5
	80E2C25.8	80E	21"	241⁄8″	40,000	5
	100E2C25.8	100E	21"	241⁄8″	40,000	5

E-RATED	ORDERING/CATALOG NUMBER	SIZE	DIM. A (INCHES)	DIM. B (INCHES)	MAX INTERRUPTING RATING RMS (ASYM)*	FIGURE NUMBER
	3E1C38.0	3E	27"	301/8"	20,000	4
	7E1C38.0	7E	27"	301/8″	20,000	4
	10E1C38.0	10E	27"	301/8″	20,000	4
≥	15E1C38.0	15E	27"	301⁄8″	20,000	4
	20E1C38.0	20E	27"	301/8″	20,000	4
MAX.	25E1C38.0	25E	27"	301⁄8″	20,000	4
	30E1C38.0	30E	27"	301⁄8″	20,000	4
8	40E1C38.0	40E	27"	301/8″	20,000	4
	50E2C38.0	50E	27"	301/8″	20,000	5
	65E2C38.0	65E	27"	301/8″	20,000	5
	80E2C38.0	80E	27"	301⁄%"	20,000	5

45

* RMS Asymmetrical amperes = RMS Symmetrical amperes x 1.6

Clip Lock Design

The clip lock type designs ensures a positive contact between the fuse and the connection cam. The fuse's clip lock tab slides in between the clip casting and the cam to prevent the fuse from slipping or blowing out of the holder. This positive contact improves heat dissipation and allows fuses to run cooler.



Dimensions in inches

E-RATED	ORDERING/CATALOG NUMBER	SIZE	DIM. A (INCHES)	DIM. B (INCHES)	MAX INTERRUPTING RATING RMS (ASYM)*	FIGURE NUMBER
	10E1CL5.5	10E	16.38"	15.13"	80,000	7
	15E1CL5.5	15E	16.38"	15.13"	80,000	7
	20E1C5.5	20E	16.38"	15.13"	80,000	7
	25E1CL5.5	25E	16.38"	15.13"	80,000	7
	30E1CL5.5	30E	16.38"	15.13"	80,000	7
	40E1CL5.5	40E	16.38"	15.13"	80,000	7
	50E1CL5.5	50E	16.38"	15.13"	80,000	7
-	65E1CL5.5	65E	16.38"	15.13"	80,000	7
5.5 MAX. KV CLIP LOCK	80E1CL5.5	80E	16.38"	15.13"	80,000	7
	100E1CL5.5	100E	16.38"	15.13"	80,000	7
Α⊐	125E1CL5.5	125E	16.38"	15.13"	80,000	7
≥e	150E1CL5.5	150E	16.38"	15.13"	80,000	7
5.5	225E2CL5.5	225E	17.38"	16.13"	80,000	8
Б	250E2CL5.5	250E	17.38"	16.13"	80,000	8
	300E2CL5.5	300E	17.38"	16.13"	80,000	8
	350E2CL5.5	350E	17.38"	16.13"	80,000	8
	400E2CL5.5	400E	17.38"	16.13"	80,000	8
	450E2CL5.5	450E	17.38"	16.13"	80,000	8
-	500E3CL5.5	400E	17.38"	16.13"	80,000	9
						9
	550E3CL5.5 600E3CL5.5	550E 600E	17.38" 17.38"	16.13" 16.13"	80,000	9 9
	ORDERING/CATALOG				80,000 MAX INTERRUPTING	FIGURE
E-RATED	NUMBER	SIZE	DIM. A (INCHES)	DIM. B (INCHES)	RATING RMS (ASYM)*	NUMBER
	10E1CL8.25	10E	17.38"	16.13"	80,000	7
	15E1CL8.25	15E	17.38"	16.13"	80,000	7
	20E1C8.25	20E	17.38"	16.13"	80,000	7
	25E1CL8.25	25E	17.38"	16.13"	80,000	7
	30E1CL8.25	30E	17.38"	16.13"	80,000	7
	40E1CL8.25	40E	17.38"	16.13"	80,000	7
8.25 MAX. KV CLIP LOCK	50E1CL8.25	50E	17.38"	16.13"	80,000	7
్రార్	65E1CL8.25	65E	17.38"	16.13"	80,000	7
29	80E1CL8.25	80E	17.38"	16.13"	80,000	7
≥⊾	100E1CL8.25	100E	17.38"	16.13"	80,000	7
<u>ا</u> ا	125E2CL8.25	125E	17.38"	16.13"	80,000	8
8.2	150E2CL8.25	150E	17.38"	16.13"	80,000	8
	175E2CL8.25	175E	17.38"	16.13"	80,000	8
	200E2CL8.25	200E	17.38"	16.13"	80,000	8
	225E2CL8.25	225E	17.38"	16.13"	80,000	8
	250E2CL8.25	250E	17.38"	16.13"	80,000	8
	300E2CL8.25	300E	17.38"	16.13"	80,000	8
ŀ	350E3CL8.25	350E	17.38"	16.13"	80,000	9
	ORDERING/CATALOG				MAX INTERRUPTING	FIGURE
E-RATED	NUMBER	SIZE	DIM. A (INCHES)	DIM. B (INCHES)	RATING RMS (ASYM)*	NUMBER
	10E1CL15.5	10E	19.8"	18.1"	60,000	7
	15E1CL15.5	15E	19.8"	18.1"	60,000	7
	20E1CL15.5	20E	19.8"	18.1"	60,000	7
	25E1CL15.5	25E	19.8"	18.1"	60,000	7
	30E1CL15.5	30E	19.8"	18.1"	60,000	7
	40E1CL15.5	40E	19.8"	18.1"	60,000	7
$\geq \sim$	50E1CL15.5	50E	19.8"	18.1"	60,000	7
ĴĴ.	65E1CL15.5	65E	22.81"	21.13"	60,000	7
E F	80E1CL15.5	80E	22.81"	21.13"	60,000	7
15.5 MAX. K CLIP LOCK	100E1CL15.5	100E	22.81"	21.13"	60,000	7
5.1	125E2CL15.5	125E	22.81"	21.13″	60,000	8
C 15	150E2CL15.5	150E	22.81"	21.13"	60,000	8
	175E2CL15.5	175E	22.81"	21.13"	60,000	8
	200E2CL15.5	200E	22.81"	21.13"	60,000	8
	150E3CL15.5	150E	22.81"	21.13	60,000	9
					60.000	9
	200E20115.5	7000				
	200E3CL15.5	200E	22.81"	21.13"		
	200E3CL15.5 250E3CL15.5 300E3CL15.5	200E 250E 300E	22.81" 22.81" 22.81"	21.13 21.13" 21.13"	60,000	9

* RMS Asymmetrical amperes = RMS Symmetrical amperes x 1.6

E-RATED POTENTIAL TRANSFORMER FUSES

Description

Potential Transformer (PT) fuses are current-limiting fuses with high interrupting ratings designed for the protection of potential transformers.

Application Note

When applying fuses for the protection of transformers, the magnetizing current in-rush must be considered. The characteristics of the in-rush, which can be matched with a fuse time-current curve, should be available from the transformer manufacturer.

Characteristics

Voltage Ratings	625 Vac – 25,800 Vac
Current Range	1⁄2E – 10E

Dimensions



E-RATED	ORDERING/CATALOG NUMBER	SIZE	LENGTH DIM. A (INCHES)	DIAMETER DIM. B (INCHES)	MAX INTERRUPTING RATING RMS (ASYM)*
	3E4PT.6	3E	4.6″	0.8125"	37,500
625 VOLT	5E4PT.6	5E	4.6″	0.8125″	37,500
	7E4PT.6	7E	4.6"	0.8125"	37,500
	10E4PT.6	10E	4.6"	0.8125″	37,500
	500E4PT2.4	1⁄2E	4.6″	0.8125″	37,500
2.75 MAX. KV	1E4PT2.4	1E	4.6"	0.8125″	37,500
~~2	2E4PT2.4	2E	4.6″	0.8125″	37,500
	1E6PT2.75	1E	7.4"	1.5625″	37,500
>	2E6PT2.75	2E	7.4″	1.5625″	37,500
5. X	3E6PT2.75	3E	7.4″	1.5625″	37,500
2.75 MAX.KV	1E8PT2.75	1E	9.5″	1.5625″	37,500
Σ	2E8PT2.75	2E	9.5″	1.5625″	37,500
	3E8PT2.75	3E	9.5″	1.5625″	37,500
4.8 MAX. KV	1E5PT4.8	1E	5.6″	0.8125″	50,000
4.2×	2E5PT4.8	2E	5.6″	0.8125"	50,000
	500E6PT5.5	1⁄2E	7.4″	1.5625″	50,000
	1E6PT5.5	1E	7.4″	1.5625″	50,000
	2E6PT5.5	2E	7.4″	1.5625″	50,000
	3E6PT5.5	3E	7.4″	1.5625″	50,000
5.5 MAX. KV	5E6PT5.5	5E	7.4″	1.5625″	50,000
5.5 X.	500E8PT5.5	1⁄2E	9.5″	1.5625″	50,000
MA	1E8PT5.5	1E	9.5″	1.5625″	50,000
	2E8PT5.5	2E	9.5″	1.5625″	50,000
	3E8PT5.5	3E	9.5″	1.5625″	50,000
	5E8PT5.5	5E	9.5″	1.5625″	50,000
	10E8PT5.5	10E	9.5″	1.5625″	50,000
	500E8PT8.25	1⁄2E	9.5″	1.5625″	50,000
£XX>	1E8PT8.25	1E	9.5″	1.5625″	50,000
8.25 MAX. KV	2E8PT8.25	2E	9.5″	1.5625″	50,000
	3E8PT8.25	3	9.5″	1.5625″	50,000
	500E11PT15.5	1⁄2E	12.8″	1.5625″	35,000
>	1E11PT15.5	1E	12.8″	1.5625″	35,000
15.5 MAX. KV	2E11PT15.5	2E	12.8″	1.5625″	35,000
15 AX	3E11PT15.5	3E	12.8″	1.5625″	35,000
Σ	3E16PT15.5	3E	17.5″	1.5625″	35,000
	5E16PT15.5	5E	17.5″	1.5625″	35,000
∞×>	500E16PT25.5	1⁄2E	17.5″	1.5625″	32,000
25.8 MAX. KV	1E16PT25.5	1E	17.5″	1.5625″	32,000

* RMS Asymmetrical amperes = RMS Symmetrical amperes x 1.6

LIVE PARTS



Description

Live parts are available for mounting E, R, and PT single, double, and triple barrel fuses. Mounting clips are available for ferrule type and clip lock style fuses. All clips are sold in pairs.



For use with 19/16" (1.5625") to 15/8" (1.625") diameter PT fuses.



Dimensions in inches

Part Number 700-500 Ordering Number 0700500.Z

For use with all ¹³/₁₆" (.8125") diameter PT fuses





Part Number 700-300 Ordering Number 0700300.Z

For use with 3" diameter fuses.



Part Number 700-530 Ordering Number 0700530.Z

For use with all 3" diameter fuses.



Part Number 700-520-CL

Ordering Number 0700520.ZXCL

Clip Lock Design



Mounting Details for Clip Lock

-.08

CATALOG NUMBER	DIMENSION A (INCHES)
10E1CL5.5 thru 150E1CL5.5	12.88
225E2CL5.5 thru 600E3CL5.5	13.88
10E1CL8.25 thru 350E3CL8.25	13.88
10E1CL15.5 thru 50E1CL15.5	16.25
65E1CL15.5 thru 300E3CL15.5	19.25



Dimensions for reference only.

Section Overview

Rely on Littelfuse for short circuit protection of telecommunications circuits and sensitive DC power distribution circuits.



🕂 TELECOM PRODUCTS 🖷

....

Table of Contents

L17T Series Telecommunications Power Fuse	50
TLN Series Telecommunications Power Fuse	51
TLS Series Telecommunications Power Fuse	52
Alarm Indicating Fuses	53
LTFD101 Telecommunication Disconnect Switch	54

L17T SERIES TELECOM POWER FUSE

170 Vdc • Current-Limiting • 70-1200 A





Ordering Information

AMPERE RATINGS								
70	125	20	00	300	450	800		1100
90	150	225		350	500	9	00	1200
100	175	250		400	600	10	000	—
SERIES	VOLTA	GE	AMPERAGE		CATAL NUMB			DERING UMBER
L17T	170		1200		L17T 12	00	L1	7T1200V

Dimensions Inches (mm)



AMPERE	DIMENSIONS INCHES (mm)							
RATING	А	В	С	D	E	F	G	Н
70 – 250	1 ⁵ ⁄32 (29.4)	17⁄8 (47.6)	2³⁄16 (55.6)	2 ²¹ / ₃₂ (67.5)	1 (25.4)	⁷ ⁄8 (22.2)	⁵ ⁄16 (7.9)	³ ⁄ ₁₆ (4.8)
300 - 800	1¼ (31.8)	1 ¹⁵ ⁄16 (49.2)	2 ⁹ ⁄16 (65.1)	3½ (88.9)	1½ (38.1)	1 (25.4)	¹³ / ₃₂ (10.3)	¹ ⁄4 (6.35)
900–1200	1 ¹¹ ⁄ ₃₂ (34.0)	—	—	4½ (103.1)	2 (50.8)	1½ (38.1)	—	¹ ⁄ ₄ (6.35)

Web Resources

For additional information, visit: **littelfuse.com/l17t**

Description

Specifically designed for short-circuit protection of telecommunications circuits, the Littelfuse L17T series fuses provide reliable protection of sensitive DC power distribution systems. Constructed with silver plated elements for low I²t and peak let-through, these advanced fuses virtually eliminate equipment damage due to surges and spikes. The L17T series fuse unique element geometry also provides cooler running temperatures, helping to minimize heat within enclosures.

Features

- Low I²t
- Extremely current-limiting
- Low operating temperature
- 170 Vdc rating

Specifications

Voltage Rating Interrupting Rating Ampere Range Approvals 170 Vdc 100 kA 70 – 1200 A UL Recognized (File: E71611) CSA Recognized (File: LR29862)



TLN SERIES TELECOM POWER FUSE

170 Vdc • Current-Limiting • 1-600 A



Specifications

Voltage Rating	170 Vdc
Interrupting Rating	100 kA
Ampere Range	1 – 600 A
Approvals	UL Recognized (File: E71611

Ordering Information

AMPERE RATINGS								
1	15	40	80	150	300	600		
3	20	45	90	175	350			
5	25	50	100	200	400	_		
6	30	60	110	225	450			
10	35	70	125	250	500			

SERIES	VOLTAGE	AMP	CATALOG NUMBER	ORDERING NUMBER
TLN	170VDC	6	TLN006	OTLN006.T

Replaces competitors' TPN and TGN Series.

Web Resources

For additional information, visit: **littelfuse.com/tln**

Recommended Fuse Holders

LFR25 Series

Description

The TLN Series fuses are specifically designed for the protection of telecommunications DC power distribution circuits.

Features

- 170 Vdc rating
- Fast-acting and current-limiting
- 1 to 600 amperes rating
- Dimensionally similar to 250 V Class R fuses

Dimensions Inches (mm)



FIG. 1



FIG. 2

AMPERES	FIGURE NUMBER	DIMENSIONS INCHES (mm)									
		А	В	С	D	E	F	G	Н	J	К
1 - 30	1	2 (50.8)	1⁄2 (12.7)	1⁄2 (12.7)	⁹ ⁄16 (14.3)	5/64 (2.0)	⁵ / ₃₂ (4.0)	³ / ₈ (9.5)		—	—
35 - 60	1	3 (76.2)	³ / ₄ (19.1)	5⁄% (15.9)	¹³ / ₁₆ (20.6)	³ / ₃₂ (2.4)	³ /16 (4.8)	⁵ ⁄/8 (15.9)	—	—	—
70 - 100	2	51/8 (149.2)	1 (25.4)	11/16 (27.0)	11/16 (27.0)	1⁄8 (3.2)	³ / ₄ (19.1)	1¼ (31.6)	1⁄4 (6.4)	⁹ /32 (7.1)	1⁄2 (12.7)
110 - 200	2	71⁄8 (181.0)	1½ (38.1)	1 ¹⁵ /32 (37.3)	119/32 (40.5)	³ /16 (4.8)	11⁄8 (28.6)	1 ²⁷ / ₃₂ (46.8)	7/16 (11.1)	⁹ /32 (7.1)	¹¹ /16 (17.5)
225 - 400	2	851/8 (219.1)	2 (50.8)	1 ¹⁵ /16 (49.2)	2 ³ / ₃₂ (53.2)	1⁄4 (6.4)	15⁄/8 (41.3)	211/32 (59.5)	5⁄/8 (15.9)	¹³ / ₃₂ (10.3)	¹⁵ ⁄16 (23.8)
450 - 600	2	103⁄8 (263.5)	21⁄2 (63.5)	23⁄8 (60.3)	2 ¹⁹ / ₃₂ (65.9)	1⁄4 (6.4)	2 (50.8)	227/32 (72.2)	³ / ₄ (19.1)	¹⁷ / ₃₂ (13.5)	11⁄8 (28.6)

91 C E

TLS SERIES TELECOM POWER FUSE

170 Vdc • Current-Limiting • 1-125 A



Felecom Products

Description

Littelfuse TLS Series fuses are designed specifically for the protection of telecommunications equipment. TLS fuses have been engineered to operate up to 170 Vdc to provide current-limiting short-circuit protection for cables and components found in the DC power distribution circuits of telecommunications systems. The compact design and multiple mounting configurations of the TLS series allow it to be used in a variety of applications.

Features

- 170 Vdc rating
- Current-limiting
- 1 to 125 amperes rating
- Multiple mounting configurations
- RoHS Compliant

Specifications

Voltage Rating Ampere Range Interrupting Rating Approvals Construction 170 Vdc 1 – 125 A 100 kA UL Recognized (File: E71611) Body: Glass melamine Caps: Silver-plated brass RoHS Compliant, Lead (Pb) Free

Rohs 🕅

Environmental

Ordering Information

AMPERE RATINGS								
1	6 25 50 90							
2	10	30	60	100				
3	15	35	70	110*				
5	20	40	80	125*				

*Available in cartridge only.

Note: To order leaded versions of TLS fuses, add suffix V, L, LB, or LS to part number.

SERIES	VOLTAGE	AMP	CATALOG NUMBER	ORDERING NUMBER
TLS	170VDC	6	TLS006V	OTLS006.TXV

Replaces competitors' TPS and TGS Series.

Web Resources

For additional information, visit: littelfuse.com/tls

Recommended Fuse Holders

LFT30060 for TLS series cartridge style fuse94



Dimensions Inches (mm)



481 SERIES ALARM INDICATING FUSES

Alarm Indicating Fuses



481 Series Alarm Indicating Fuses

Description

481 Series alarm indicating fuses are designed to reduce down time by immediately pinpointing the blown (open) circuit while triggering an LED or audio alarm. This item requires 482 Series mating fuse holder.

All ranges of 481 Series fuses are available as our original design, and the 2-20 amp range is now available as a RoHS compliant option (use the "P" designator when ordering). See the part numbering section of the datasheet for related ordering instructions.

Specifications



Voltage Rating	
Approvals	

125 Vac/dc UL Recognized (File: E71611) CSA Recognized (File: LR29862)

Ordering Information

AMPERE RATINGS									
18/100	3/8	3/4		1	1/2	3	5	12	
1/5	1/2	1		2		3 1/2	7 1/2	15	
1/4	65/ ₁₀₀	1 1/3		2	1/2	4	10	20	
SERIES	VOLTA	GE	AN	1P		ATALOG IUMBER		ERING MBER	
481	125 ac/	125 ac/dc		2		481002L		0481002.VXL	

Note: For 481 Dummy fuse, order 481000.

Recommended Fuse Holders

482 Series, see website: littelfuse.com/482

Available 1-20 pole with PCB or panel mounting. To order with protective lens add suffix XL.

Web Resources

For additional information, visit: littelfuse.com/481



LTFD 101 SERIES TELECOM DISCONNECT SWITCH

80 Vdc • 1-125 A

Αľ

52



Specifications

Voltage Rating	80 Vdc
Ampere Range	1–125 A
Approvals	UL Recognized (File: E122674)

Recommended Fuses

Littelfuse TLS Series fuses	
-----------------------------	--

Ordering Information

SERIES	AMPERAGE	CATALOG NUMBER	ORDERING NUMBER	TERMINAL TYPE
LTFD	125 A MAX	LTFD101-1	LTFD0101ZX1	BULLET
LTFD	125 A MAX	LTFD101-2	LTFD0101ZX2	SCREW
LTFD	125 A MAX	LTFD101-3	LTFD0101ZX3	STUD
LTFD	70 A MAX	LTFD101-4	LTFD0101ZX4	CLIP

Web Resources

For additional information, visit: **littelfuse.com/ltfd101**

4

Description

Littelfuse compact LTFD 101 fuse holders for TLS fuses are designed for quick installation into telecom equipment panels. Their modular design fits into spaces originally designed for circuit breakers and can be front panel mounted or rear mounted using bullet connectors. The innovative new pull-out design eliminates the need for tools to replace fuses and includes an alarm signaling circuit to identify the blown fuse.

Features

- Extremely compact
- Quick mounting
- Replaces circuit breakers
- Includes alarm signaling circuit

Dimensions Inches (mm)



Dimensions for reference only. For additional options and dimensions, contact the factory.

Section Overview

Whether you are protecting solar equipment or finding a replacement fuse for an aging HVAC unit, Littelfuse carries the breadth of fuses to meet your needs. Our "special purpose" fuse section includes application-specific products to meet all of your application needs.







Table of Contents

-	and the second
	Norther Street Street Street
	ACCOUNTS ON ANY

POWR-GARD® Circuit Protection

Littelfuse engineering is constantly developing new products to meet the needs of the photovoltaic industry. For the latest information on the growing POWR-GARD Product portfolio, visit: **littelfuse.com/solar**

Solar Rated Products Overview
1500 Vdc Solar Rated Fuses 57
1000 Vdc Solar Rated Fuses 59
Forklift / Stud Mounted Fuses 62
Plug Fuses
MEGA® Bolt-Down Fuses
In-Line Fuses And Holder64
Cable Limiters
Cylindrical Fuses
OEM Custom Products



SOLAR PRODUCTS BY APPLICATION

- 1. SPXV 1500 V 6-30 A Fuse
- 2. SPXI 1500 V 2.5-30 A In-Line Fuse
- 3. SPFJ 1000 V 70-450 A Fuse
- 4. SPF 1000 V 1-30 A Fuse
- 5. SPFI 1000 V 2-30 A In-Line Fuse
- 6. KLKD 600 V 1/10-30 A Fuse
- 7. IDSR & LDC 600 V Fuse and Holder

- 3. LFJ1000 Fuse Block for SPFJ Fuse
- . LFPHV & LFPSM Touch-Safe Fuse Holder
- 10. Busbar for Touch-Safe Fuse Holders
- 11. Power Distribution Block
- 12. SE-601 DC Ground-Fault Relay
- 13. TVS Diodes / SCRs
- 14. Varistor Products





SPXV SERIES SOLAR FUSES

1500 Vdc • 6 - 30 A





Description

The Littelfuse SPXV solar string fuse is designed specifically for 6-30 A 1500 Vdc applications.

Features/Benefits

- 10 x 85 mm package size
- UL 2579 Listed
- Meets IEC 60269-6 electrical performance requirements •
- 30,000 A interrupting rating •

Applications

Inverters •

6 – 20 A

25 – 30 A

Combiner boxes •

Recommended Fuse Holder

Littelfuse LPXV Solar Series	
------------------------------	--

Web Resources

Download the complete datasheet and other technical documents: littelfuse.com/spxv

Dimensions mm (inches)



84.65

Specifications

Voltage Rating Amperage Rating Interrupting Rating

Time Constant Material

Approvals **Environmental**

Country of Origin

Part Numbering System



1500 Vdc 6, 8, 10, 12, 15, 20, 25, 30 A 15 kA (UL 2579) 30 kA (Self-Certified) ≤ 1ms Body: Melamine Caps: Copper Alloy (Nickel Plated) UL 2579 Listed (File: E339112) **RoHS** Compliant REACH Mexico



SERIES	AMP	PACKAGE QUANTITY	CATALOG NUMBER	ORDERING NUMBER
SPXV	6 10		SPXV006	SPXV006.T
SPXV	20	50	SPXV020	SPXV020.L

SERIES	SERIES AMP PACKA		CATALOG NUMBER	ORDERING NUMBER
SPXV	6	10	SPXV006	SPXV006.T
SPXV	20	50	SPXV020	SPXV020.L

SPXI SERIES IN-LINE SOLAR FUSES

1500 Vdc • 2.5 - 30 A • Patent Pending



* Description

The Littelfuse SPXI solar fuse is designed to integrate into an in-line assembly within a wire harness. The fuse provides photovoltaic (PV) protection that meets UL 2579 for photovoltaic applications. The SPXI can be electrically insulated by either overmolding or using approved heat-shrink.

Features/Benefits

- UL 2579 Recognized
- Meets IEC 60269-6 electrical performance requirements
- 30,000 A interrupting rating
- No fuse holder required

Applications

• Photovoltaic wire harness

Recommended Crimping Tool

T&B Sta-Kon ERG4002

Dimensions mm (in)



Voltage Rating: Amperage Rating: Interrupting Ratings:

Time Constant Material:

Approvals: Environmental:

Country of Origin:

Part Numbering System



1500 Vdc

≤ 1ms

Mexico

15 kA (UL 2579)

Body: Melamine

RoHS Compliant REACH

30 kA (Self-Certified)

SERIES	QUANTITY		NUMBER	NUMBER
SPXI	3.5	10	SPXI03.5	SPXI03.5T
SPXI	4	10	SPXI004	SPXI004.T
SPXI	20	50	SPXI020	SPXI020.L

Web Resources

Download additional technical information and view the complete solar portfolio: **littelfuse.com/spxi**





2.5, 3.5, 4, 6, 8, 10, 12, 15, 20, 25, 30 A

Caps: Copper Alloy (Nickel Plated) UL 2579 Recognized (File: E339112)

SPFI SERIES IN-LINE SOLAR FUSES

1000 Vdc • 2 - 30 A • Patent Pending









Description

The Littelfuse SPFI solar fuse has been designed to integrate into an in-line assembly within a wire harness. The fuse provides photovoltaic (PV) protection is UL 2579 Recognized for photovoltaic applications. The SPFI can be electrically insulated by either overmolding or using approved heat-shrink.

Features/Benefits

- UL 2579 Recognized
- Meets IEC 60269-6 electrical performance requirements
- 20,000 A Interrupting Rating
- No fuse holder required

Applications

• Photovoltaic wire harness

Recommended Crimping Tool

T&B Sta-Kon ERG4002

Web Resources

Download the complete datasheet and other technical documents: **littelfuse.com/spfi**

Dimensions mm (in)





Look for this logo to indicate products that are used in solar applications. Visit our website **littelfuse.com/solar** for the latest updates on approvals, certifications, and new products.

5

Specifications Voltage Rating

J	
Amperage	Rating

Interrupting Rating Time Constant Material

Approvals Environmental

Country of Origin

*Visit littelfuse.com/solar for the newest available amperages

Part Numbering System



1000 Vdc

20 kA

≤ 1ms

Mexico

2, 2.5, 3, 3.5, 4, 5, 6, 8, 10, 12, 15, 20, 25, 30 A*

Body: Melamine

RoHS Compliant REACH

Caps: Copper Alloy (Nickel Plated)

UL 2579 Recognized (File: E339112)

Refer to datasheet for amp code

SERIES	AMP	PACKAGE QUANTITY	CATALOG NUMBER	ORDERING NUMBER
SPFI	2	10	SPFI002	SPFI002.T
SPFI	3.5 10	10	SPFI03.5	SPFI03.5T
SPFI	20	50	SPFI020	SPFI020.L

SPF SERIES SOLAR FUSES

1000 Vdc • 1-30 A



Description

The SPF Solar Protection Fuse series has been specifically designed for the protection of photovoltaic (PV) systems. This series of Midget style fuses (10 x 38 mm) can safely protect PV modules and conductors from reverse-overcurrent conditions.

As PV systems have grown in size, so have the corresponding voltage requirements. This increase in system voltage has typically been intended to minimize power loss associated with long conductor runs. Standard circuit protection devices are not designed to completely protect photovoltaic panels. However, the SPF series is UL Listed to safely interrupt faulted circuits up to this demanding voltage level.

Features/Benefits

- Meets UL, IEC and VDE photovoltaic standards
- UL 2579 Listed 1000 Vdc maximum
- 1-30 A ratings available
- 20,000 A Interrupting Rating
- Both PCB mount and dead-front holder options available

Applications

- Inverters
- Combiner boxes
- Battery charge controllers

Recommended Fuse Holders

Web Resources

Download the complete datasheet and other technical documents: **littelfuse.com/spf**



Specifications

Voltage Rating Amperage Rating Max. Interrupting Rating Time Constant Material

Approvals

1000 Vdc 1, 2, 3, 3.5, 4, 5, 6, 8, 10, 12, 15, 20, 25, 30 20 kA ≤ 2ms Body: Melamine Caps: Copper Alloy UL 2579 Listed (File: E339112) IEC 60269-6 (1-25 A) VDE Certified (No. 40033098) CSA Certified (File: 029862_0_000) RoHS Compliant Mexico

Environmental Country of Origin

Part Numbering System



SERIES	AMP	PACKAGE QUANTITY	MOUNTING METHOD	CATALOG NUMBER	ORDERING NUMBER
SPF	2	10	FERRULE	SPF002	OSPF002.T
SPF	3.5	10	FERRULE	SPF03.5	0SPF03.5T
SPF	30	100	PCB TABS	SPF030R	OSPF030.HXR

Dimensions Inches (mm)

Ferrule Version

PCB Version





SPFJ SERIES SOLAR FUSES

1000 Vdc • 70-450 A



Description

The SPFJ series is the smallest 1000 Vdc 70-450 A photovoltaic fuse available in the market. The SPFJ series is manufactured in Class J case sizes that allows for both fuse holder and busbar mounting configuration. The SPFJ meets both UL and IEC requirements.

Features/Benefits

- Meets UL and IEC photovoltaic standards
- VDE certified specifications
- Small footprint reduces panel size
- Flexibility of fuse holder or busbar mounting
- Higher amperage solar fuses in standard sizes
- UL Listed branch and feeder circuit rated
- Class J case sizes for the 70-450 A ratings

Applications

- Inverters
- Re-combiner boxes

Recommended Fuse Holders

Littelfuse LFJ1000 Solar Series......107

Web Resources

Download the complete datasheet and other technical documents: **littelfuse.com/spfj**



Specifications

Voltage Rating
Amperage Rating
Interrupting Rating

Time Constant Material

Approvals

1000 Vdc 600 Vac (125-450 A) 70, 80, 90, 100, 125, 160, 200, 250, 300, 350, 400, 450 AC: 200 kAIC (125-450 A) DC: 70-200 A: 20 kAIC 250-400 A: 10 kAIC 450 A: 20 kAIC

≤ 1ms Body: Melamine End Bells: Copper Alloy UL 2579 Listed (File: E339112) UL 248-8, Class J (125-450 A) C UL (125-450 A) IEC 60269-6 (125-450 A) VDE Certified (125-450 A) (No. 40033659, 40033660, 40033661) RoHS Compliant Mexico

Environmental Country of Origin

Part Numbering System



SERIES	AMP	PACKAGE QUANTITY	MOUNTING METHOD	CATALOG NUMBER	ORDERING NUMBER
SPFJ	70	1	CLASS J	SPFJ070	SPFJ070.X
SPFJ	200	1	LARGE	SPFJ200	SPFJ200.XXL

Dimensions Inches (mm)





AMPERAGE			DIME	NSIONS IN INCHES	(MM)		
AIVIFENAUE	А	В	С	D	E	F	G
70-100	3.02 (76.5)	4.38 (111.3)	5.75 (146.1)	1.5 (38.1)	1.125 (28.3)	.335 (8.5)	.189 (4.8)
125-200	3.02 (76.5)	4.38 (111.3)	5.75 (146.1)	1.5 (38.1)	1.125 (28.3)	.281 (7.1)*	.189 (4.8)
250-400	3.37 (85.7)	5.25 (133.4)	7.125 (181.0)	2.0 (50.8)	1.63 (41.3)	.406 (10.3)	.252 (6.4)
450	3.75 (95.3)	5.98 (152.0)	8.0 (203.2)	2.5 (63.5)	2.0 (50.8)	.531 (13.5)	.374 (9.5)

* SPFJ L option = 8.5 mm (UL 2579 approval only)

FORK-LIFT STUD-MOUNTED FUSES

32/48/80 Vdc • Fast-Acting and Very Fast-Acting • 35-800 A







CNN_E, CNN & CNL Limiter Fuses

Description

CNN_E fuses are rated for applications up to 80 Vdc. As fork lift trucks voltages increase, circuit protection needs to be rated higher than the standard CNN products to handle the increased voltage. The CNN_E is considered very fast-acting for quicker reaction time.

Specifications

Voltage Ratings

 Ampere Ratings
 10 - 800 A*

 Max. Interrupting Rating
 2,500 A

 Approval
 UL Recognizi

 Environmental
 RoHS Compl

 Country of Origin
 Mexico (CNN

CNN_E: 80 Vdc / 125 Vac CNN: 48 Vdc / 125 Vac CNL: 32 Vdc / 32 Vac 10 – 800 A* 2,500 A UL Recognized (File: E71611) RoHS Compliant, Lead (Pb) Free Mexico (CNN_E only) ages by series

*See ordering information table for available amperages by series



HAZGARD[™] Forklift Fuses

Description

HAZGARD fuses are designed to provide overcurrent protection for low voltage equipment used in hazardous operations. It is UL 248 recognized and has been evaluated for the use in UL 583 type EE and ES applications. Unique design does not require an additional enclosure as is needed with a standard forklift fuse, saving assembly time and costs.

Ordering Information

SERIES	AMPERAGE	CATALOG NUMBER	ORDERING NUMBER
581	200	581200	0581200.X

Ordering Information

AMPERE RATINGS CNN_E & CNN								
10†	60	125	225	325	600			
35	80	150	250	350	700			
40	90	175	275	400	800			
50	100	200	300	500	—			
10111 0 ·								

[†]CNN Series only

AMPERE RATINGS CNL (32 Vdc)						
35 80 150 250 350						
40	100	175	275	400		
50	125	200	300	500		
60	130	225	325	—		

SERIES	ТҮРЕ	VOLT DC	AMP	CATALOG NUMBER	ORDERING NUMBER
CNN_E	VERY-FAST-ACTING	80	200	CNN200E	OCNN200E.V
CNN	VERY FAST-ACTING	48	125	CNN125	0CNN125.V
CNL	FAST-ACTING	32	50	CNL050	0CNL050.V

Recommended Fuse Holders

Web Resources littelfuse.com/ForkLift





Lift trucks, scissor lifts, pallet movers, and other low voltage battery operated equipment used to move hazardous materials.

Features/Benefits

- Evaluated for use in UL 583 hazardous applications
- Easily upgrade Type E and ES equipment to Type EE
- Does not require an external enclosure

Specifications

Applications

Voltage Ratings	48 Vac/dc
Interrupting Rating	2,500 A
Ampere Rating	35 – 800 A
Approval	UL Recognized (File: E71611)
Torque	90 in-Ib
Fuse Holder	LFFB003
Environmental	RoHS Compliant
Country of Origin	Mexico

AMPERE RATINGS				
100	250	500		
125	300	750*		
150	400	800*		
200	425			
	100 125 150	100 250 125 300 150 400		

*Contact factory for availability



PLUG FUSES AND BOLT-DOWN FUSES

125 Vac • 2-30 A





Edison-base plug fuses **Description**

Littelfuse Plug fuses provide overcurrent protection to general purpose circuits and small motor loads. Edison-base Plug fuses (TOO and TLO series) feature metal threads similar to incandescent lamp bases.

Type S Plug fuses (SOO and SLO series) utilize a nonmetallic threaded base and must be used with Type S adapters (SAO series).

The National Electrical Code[®] permits Edison base Plug fuses to be used for replacement purposes only. Type S fuses and adapters prevent shunting open fuses and over-fusing.

Specifications

Voltage Rating	125 Vac
Interrupting Rating	10 kA rms symmetrical
Approvals	UL Listed 248-11

TOO Fuses are dual-element time-delay Edison-base fuses designed for motor and motor branch circuit protection; also suitable for all general purpose circuits.

TOO Fuses	

Sample Part # 0T00020.Z

AMPERE RATINGS					
2 6 1/4 12 25					
4	8	15	30		
5	10	20	—		

TLO Fuses are medium time-delay Edison-base fuses designed for general purpose branch circuit protection.

TLO Fuses		Sample	Part # 0TL0020.Z	
AMPERERATINGS				
15	20	25	30	

Web Resources

Fine more information: **littelfuse.com/plug**

32 Vac/dc • 100-300 A



MEGA® SLO-BLO® bolt-on fuse

Description

The MEGA Fuse is designed for the protection of high current applications. Designed and patented by Littelfuse, it is ideal for battery and alternator protection and other heavy gauge cable applications.

Specifications

Voltage Rating	32 Vac/dc
Interrupting Rating	2000 A @ 32 Vdc

Ordering Information

CATALOG NUMBER	ORDERING NUMBER	AMPERAGE RATING	VOLTAGE RATING	COLOR CODE
MEG100	0MEG100.X	100	32	
MEG125	0MEG125.X	125	32	
MEG150	0MEG150.X	150	32	
MEG175	0MEG175.X	175	32	
MEG200	0MEG200.X	200	32	
MEG225	0MEG225.X	225	32	
MEG250	0MEG250.X	250	32	
MEG300	0MEG300.X	300	32	

Recommended Fuse Holders

Part Number - 298900, see website: littelfuse.com/mega

Web Resources

Find more information: littelfuse.com/mega

LGR / LMF IN-LINE FUSES & LHR FUSE HOLDER



LGR Fuses

Fast-Acting • 300 Vac

Used as in-line protection for fluorescent fixtures, this fast-acting fuse is ideal for increasing the safety and reliability of lighting fixtures.



Specifications

Voltage Rating		
Interrupting Rating		
Approvals		

300 Vac 10 kA Standard 248-14 UL Listed (File: E10480) CSA Certified (File: LR29862)

(IL) St C € RoHS

Ordering Information

AMPERE RATINGS							
1/2	1 6/10	3	6	9	15		
1	2	4	7	10	_		
1 1/2	2 ^{1/2}	5	8	12	—		

SERIES	AMPERAGE	CATALOG NUMBER	ORDERING NUMBER
LGR	5	LGR005	OLGR005.V

LMF Fuses

Time-Delay • 300 Vac

Perfect for use in lighting systems, this 300 Vac timedelay fuse is designed to handle ballast transformer in-rush currents.



Specifications

Voltage Rating Interrupting Rating Approvals



(In the second second

Ordering Information

	•							
	AMPERE RATINGS							
3/10	⁸ /10	1 6/10		2 ⁸ /10	4	7		
1/2	1	2		3	5	8		
6/10	1 1/4	2 ¹ / ₂		3 ²/10	6 ¹ /4	10		
SERIES	AMPER	AGE CATA		LOG NUMBE	R ORDERIN	IG NUMBER		
LMF	5			LMF005	OLN	1F005.V		

300 Vac

LHR000 10 A

LHR001 10 A

UL Recognized

CSA Certified

(File: 73160)

UL94 V-0

OLHROO1T

LHR001



LHR Fuse Holder

Used as in-line protection for fluorescent fixtures, the Littelfuse LGR and LMF series fuses and LHR holder offer increased safety and reliability to lighting systems.

By individually fusing fixtures, electrical problems are isolated from the rest of the circuit. The added benefits of this is the ability to quickly identify the problem fixture and reduce the repair time.

Fuse holders are rated up to 10 amperes at 300 volts and are equipped with 7" 18 AWG leads. Order part number LHR000 for two leads, and part number LHR001 for one lead; with the other terminal used for insertion of 18 AWG ballast lead.

Specifications

Voltage Rating Ampere Rating Approvals **Flammability Rating Example part number Ordering number**

Mounting Information

LHR001/LHR000 will fit keyhole punch or 0.875" knock-out hole. Anti-rotation feature is provided when used with keyhole punch.

A "U-shaped" clip is available for panel mounting (packaged 10 clips per bag): Order part number LHROCA.





Knock-out Hole



Keyhole Punch







LFCL • CABLE LIMITERS 250/600 VAC



TYPE	TERMINATION	VOLTAGE RATING	COPPER CABLE SIZE	ORDERING NUMBER
		600 VAC	4 AWG	LFCL0004ZC1
		600 VAC	3 AWG	LFCL0003ZC1
		600 VAC	2 AWG	LFCL0002ZC1
		600 VAC	1 AWG	LFCL0001ZC1
	~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~	600 VAC	1/0 AWG	LFCL01/0ZC1
	200	600 VAC	2/0 AWG	LFCL02/0ZC1
1	CABLE TO CABLE	600 VAC	3/0 AWG	LFCL03/0ZC1
1	GADLE TU GADLE	600 VAC	4/0 AWG	LFCL04/0ZC1
		600 VAC	250 kcmil	LFCL0250ZC1
		600 VAC	350 kcmil	LFCL0350ZC1
		600 VAC	500 kcmil	LFCL0500ZC1
		600 VAC	600 kcmil	LFCL0600ZC1
		600 VAC	750 kcmil	LFCL0750ZC1
		600 VAC	1000 kcmil	LFCL1000ZC1
		600 VAC	12 AWG	LFCL0012ZC3
		600 VAC	10 AWG	LFCL0010ZC3
		600 VAC	6 AWG	LFCL0006ZC3
	CABLE TO OFFSET BUS	600 VAC	4 AWG	LFCL0004ZC3
		600 VAC	2 AWG	LFCL0002ZC3
		600 VAC	1 AWG	LFCL0001ZC3
		600 VAC	1/0 AWG	LFCL01/0ZC3
3		600 VAC	2/0 AWG	LFCL02/0ZC3
		600 VAC	3/0 AWG	LFCL03/0ZC3
		600 VAC	4/0 AWG	LFCL04/0ZC3
		600 VAC	250 kcmil	LFCL0250ZC3
		600 VAC	350 kcmil	LFCL0350ZC3
		600 VAC	500 kcmil	LFCL0500ZC3
		600 VAC	600 kcmil	LFCL0600ZC3
		600 VAC	750 kcmil	LFCL0750ZC3
	~~	250 VAC	2/0 AWG	LFCL-UHA*
	a a	250 VAC	3/0 AWG	LFCL-UHJ-M*
	-	250 VAC	350 kcmil	LFCL-UHJ-T*
	STRAIGHT BUS	250 VAC	600 kcmil	LFCL-UHJ-W*
5	TO OFFSET BUS	600 VAC	4/0 AWG	LFCL04/0ZC5*
		600 VAC	250 kcmil	LFCL0250ZC5*
		600 VAC	350 kcmil	LFCL0350ZC5*
		600 VAC	500 kcmil	LFCL0500ZC5*
		600 VAC	750 kcmil	LFCL0750ZC5*
	2	600 VAC	4/0 AWG	LFCL04/0ZC6
6	-	600 VAC	250 kcmil	LFCL0250ZC6
	MOLE TO CABLE	600 VAC	500 kcmil	LFCL0500ZC6

*Suitable for use with aluminum cables / conductors. For sizing contact Tech-Line at 800-TEC-EUSE

#### Description

Cable limiters are fusible devices that provide very fast short-circuit protection, primarily to faulted cables, but also to other conductors such as busway. Cable limiters do not have an ampere rating, and cannot be used to provide overload protection. They are instead selected by cable size; for example, a 500 kcmil cable requires a 500 kcmil cable limiter. Their main use is to isolate faulted cables in circuits containing three or more parallel conductors per phase. They may be installed on the line side of the main service to provide shortcircuit protection to the service conductors. This is especially important when service conductors are tapped from large low voltage networks or from large low impedance transformers.

Cable limiters have terminals which permit them to be installed in a variety of equipment. The most common configuration is the offset blade on one end and the crimp terminal on the other end. This permits the limiter to replace a cable terminal (lug).

### **Applications**

- Service Entrance Conductors
- Between Transformer or network bus and bus-way terminal boxes as secondary ties.
- Feeders with three or more conductors per phase to share heavier load in large commercial and industrial installations
- Multiple Single conductor services, tapped from single (utility) transformer in multi-family residential and small commercial installations.

#### **Features**

- Current-limiting characteristics provide protection to conductor insulation and reduce damage when faults occur.
- Properly applied cable limiters may permit the use of equipment with reduced withstand ratings
- Wide variety of terminations and cable ratings permit use in almost every situation.

#### **Specifications**

**Voltage Ratings** Interrupting Rating **Cable Size Range** Approvals Recommended Installation Tool

250 VAC, 600 VAC 100 kA (250 VAC), 200 kA (600 VAC) 12 AWG - 1000Kcmil Copper Contact Tech-Line at 800-TEC-FUSE

Make: Thomas & Betts Crimp Tool: TBM14_, TBM15_

## Web Resources

For additional information, see website: littelfuse.com/lfcl

## Fuses — Special Purpose

# CYLINDRICAL FUSES

500 Volts • 0.5 -100 A





#### Description

Littelfuse fast acting (gL-gG) fuses are used for the protection of cables against short-circuits. Time-lag (aM) fuses are used for protection of motors.

#### **Specifications**

Standards

10x38 mm: IEC 60269 14x51 mm / 22x58mm: IEC 269-2-1

#### **Ordering Information**

BASE PART NUMBER	SIZE (mm)	CURRENT RANGE	VOLTAGE (AC)	INTERRUPTING RATING
		0.5-16 A	500 V	120 kA
CY10X38	10 x 38	20-25 A (aM)	400 V	120 kA
0110/00		20-25 A (gL-gG)	500 V	120 kA
		32 A	400 V	120 kA
	14 x 51	2-25 A	690 V	80 kA
CY14X51		32-40 A	500 V	120 kA
		50 A	400 V	120 kA
CY22X58	22 x 58	16-63 A	690 V	80 kA
U122X58	ZZ X 58	80-100 A	500 V	120 kA

AMPERAGE	gL-gG ORDERING NUMBERS			aM ORDERING NUMBERS		
AWPERAGE	10 X 38	14 X 51	22 X 58	10 X 38	14 X 51	22 X 58
0.5	CY10X38G05	—	—	CY10X38M05	—	—
1	CY10X38G1	—		CY10X38M1	—	—
2	CY10X38G2	CY14X51G2	—	CY10X38M2	CY14X51M2	—
4	CY10X38G4	CY14X51G4	—	CY10X38M4	CY14X51M4	—
6	CY10X38G6	CY14X51G6	—	CY10X38M6	CY14X51M6	—
8	CY10X38G8	CY14X51G8	_	CY10X38M8	CY14X51M8	—
10	CY10X38G10	CY14X51G10	—	CY10X38M10	CY14X51M10	—
12	CY10X38G12	CY14X51G12	_	CY10X38M12	CY14X51M12	—
16	CY10X38G16	CY14X51G16	CY22X58G16	CY10X38M16	CY14X51M16	CY22X58M16
20	CY10X38G20	CY14X51G20	CY22X58G20	CY10X38M20	CY14X51M20	CY22X58M20
25	CY10X38G25	CY14X51G25	CY22X58G25	CY10X38M25	CY14X51M25	CY22X58M25
32	CY10X38G32	CY14X51G32	CY22X58G32	CY10X38M32	CY14X51M32	CY22X58M32
40	_	CY14X51G40	CY22X58G40	—	CY14X51M40	CY22X58M40
50	_	CY14X51G50	CY22X58G50	—	CY14X51M50	CY22X58M50
63	—	—	CY22X58G63	—	—	CY22X58M63
80	—	—	CY22X58G80	—	—	CY22X58M80
100	-	—	CY22X58G100	—	—	CY22X58M100

#### **Dimensions**

	DIMENSIONS mm				
FUSE SIZE	A	В			
10 X 38	10	38			
14 X 51	14	51			
22 X 58	22	58			

#### Web Resources

For additional product information Fuses: littelfuse.com/cy Fuse Holders: littelfuse.com/lfpsm littelfuse.com/cyh

# 

#### **Fuse Holders**

AMP RATING	POLES	SIZE	CATALOG / ORDERING #	TERMINAL TYPE	DIN RAIL MOUNT
32 A	1	10 X 38	LFPSM0001Z	Pressure Plate	•
32 A	2	10 X 38	LFPSM0002Z	Pressure Plate	•
32 A	3	10 X 38	LFPSM0003Z	Pressure Plate	•
32 A	4	10 X 38	LFPSM0004Z	Pressure Plate	•
32 A	1	10 X 38	LFPSM0001ZXID*	Pressure Plate	•
32 A	2	10 X 38	LFPSM0002ZXID*	Pressure Plate	•
32 A	3	10 X 38	LFPSM0003ZXID*	Pressure Plate	•
32 A	4	10 X 38	LFPSM0004ZXID*	Pressure Plate	•
50 A	1	14 X 51	CYH14511	Pressure Plate	•
50 A	2	14 X 51	CYH14512	Pressure Plate	•
50 A	3	14 X 51	CYH14513	Pressure Plate	•
125 A	1	22 X 58	CYH22581	Pressure Plate	•
125 A	2	22 X 58	CYH22582	Pressure Plate	•
125 A	3	22 X 58	CYH22583	Pressure Plate	•

* Indicating



## **OEM CUSTOM PRODUCTS**



To speak with a sales associate regarding your application needs, call 800-TEC-FUSE (800-382-3873) or email techline@littelfuse.com.

#### Description

We understand that existing solutions don't always solve your current problems. Building on more than 85 years of circuit protection experience, the Littelfuse engineering team collaborates with customers to develop customized solutions for applications such as solar panels, HVAC systems, lift trucks, lighting fixtures, industrial restaurant equipment and power converters.

#### **Process**

The custom product design process begins with a situation analysis from our experienced engineers followed by our 4-step collaborative product development process.

- 1. Initial concept sketch created
- 2. CAD drawings to formalize the product description
- 3. 3D solid prototype to verify design
- 4. Final production parts that meet your design needs and specifications

#### **Additional Customized Products**

HAZGARD Fork Lift Fuse ......62

#### **Web Resources**

To learn more and contact our OEM team, visit: **littelfuse.com/industrialoem** 

## Examples





#### **Two-Pole Combination Block**

Save space and money by combining multiple components in one unit. Littelfuse collaborated with the customer to develop a cost effective UL listed component that combined a 600 Volt 100A two-pole Class T fuse block with a two-openings-per-pole splicer block.

#### **Custom-Leaded Fuse**

Save space and reduce cost by eliminating the fuse block component. Littelfuse designed a series of custom through-hole PC-board mountable KLKD Midget fuses for a consumer application where reduced cost was more important than replaceability.

#### **Section Overview**

Littelfuse high-speed fuses protect critical power semiconductors against short circuits in applications including inverters, variable-speed drives, UPS and DC drive systems.

For the complete portfolio of high-speed products visit: **littelfuse.com/High-Speed** 



# HIGH-SPEED FUSES #

#### **Table of Contents**

L Series (Traditional) High-Speed Fuses
LA Series (Alternate Dimension) High-Speed Fuses71
Square Body High-Speed Fuses



#### POWR-GARD[®] High-Speed Circuit Protection

Littelfuse engineering is constantly developing new products to meet the needs of the industry. For the latest information on the growing POWR-GARD Product portfolio, visit: **littelfuse.com/High-Speed** 



150/250/500/600/700 Vac • Very Fast-Acting • 1-1200 A



L70S

ttelfuse®

Answers Delivered



#### **Specifications**

Voltage Ratings	
L15S:	150 Vac/dc (1 – 60 A)
	150 Vac (70 – 1000 A)
	100 Vdc (70 - 1000 A)
L25S:	250 Vac/dc (1 – 200 A)
	250 Vac (225 – 800 A)
	200 Vdc (225 – 800 A)
L50S:	500 Vac/450 Vdc
L60S:	600 Vac
KLC:	600 Vac
L70S:	700 Vac/650 Vdc

L25S series fuses are Littelfuse Certified for DC ratings shown in Rating Table.

#### Interrupting Rating

AC:	200 kA rms
DC:	(L15S series 100 kA) 20 kA
Ampere Range	1 – 1200 A See Rating Table for ratings available in each series.
Approvals	UL Recognized (File: E71611) CSA Recognized (File: LR29862)

#### **Recommended Fuse Holders**

1LFS101/1LFS102	121
LSCR001/LSCR002	120

#### Web Resources

For additional information, visit: **littelfuse.com/high-speed** 

	LISS	L255	L902	L002	KLC*	L/US
1	L15S001	L25S001	-	L60S001	KLC001	-
2	L15S002	L25S002	-	L60S002	KLC002	-
3	L15S003	L25S003	-	L60S003	KLC003	-
4	L15S004	L25S004	-	L60S004	KLC004	-
5	L15S005	L25S005	-	L60S005	KLC005	-
6	L15S006	L25S006	-	L60S006	KLC006	-
7	L15S007	-	-	-	KLC007	-
8	L15S008	L25S008	-	L60S008	KLC008	-
9	L15S009	-	-	-	-	-
10	L15S010	L25S010	L50S010	L60S010	KLC010	L70S010
12	L15S012	L25S012	L50S012	L60S012	KLC012	-
15	L15S015	L25S015	L50S015	L60S015	KLC015	L70S015
171⁄2	-	-	-	L60S17.5	KLC17.5	-
20	L15S020	L25S020	L50S020	L60S020	KLC020	L70S020
25	L15S025	L25S025	L50S025	L60S025	KLC025	L70S025
30	L15S030	L25S030	L50S030	L60S030	KLC030	L70S030
35	L15S035	L25S035	L50S035	L60S035	KLC035	L70S035
40	L15S040	L25S040	L50S040	L60S040	KLC040	L70S040
45	L15S045	L25S045	-	L60S045	KLC045	-
50	L15S050	L25S050	L50S050	L60S050	KLC050	L70S050
60	L15S060	L25S060	L50S060	L60S060	KLC060	L70S060
70	L15S070	L25S070	L50S070	L60S070	KLC070	L70S070
80	L15S080	L25S080	L50S080	L60S080	KLC080	L70S080
90	L15S090	L25S090	L50S090	L60S090	KLC090	L70S090
100	L15S100	L25S100	L50S100	L60S100	KLC100	L70S100
110	-	-	-	-	KLC110	-
125	L15S125	L25S125	L50S125	L60S125	KLC125	L70S125
150	L15S150	L25S150	L50S150	L60S150	KLC150	L70S150
175	-	L25S175	L50S175	L60S175	KLC175	L70S175
200	L15S200	L25S200	L50S200	L60S200	KLC200	L70S200
225	-	L25S225	L50S225	L60S225	KLC225	L70S225
250	L15S250	L25S250	L50S250	L60S250	KLC250	L70S250
275	-	L25S275	L50S275	-	-	-
300	L15S300	L25S300	L50S300	L60S300	KLC300	L70S300
350	L15S350	L25S350	L50S350	L60S350	KLC350	L70S350
400	L15S400	L25S400	L50S400	L60S400	KLC400	L70S400
450	L15S450	L25S450	L50S450	L60S450	KLC450	L70S450
500	L15S500	L25S500	L50S500	L60S500	KLC500	L70S500
550	-	-	L50S550	-	-	-
600	L15S600	L25S600	L50S600	L60S600	KLC600	L70S600
700	-	L25S700	L50S700	L60S700	KLC700	L70S700
800	L15S800	L25S800	L50S800	L60S800	KLC800	L70S800
900	-	-	-	-	-	-
1000	L15S1000	-	-	-	-	-

SERIES ORDERING NUMBER

L50S

L60S

KLC‡

#### **Ordering Information**

L15S

L25S

AMPERE

RATINGS

⁺ KLC series fuses are recommended for replacement use only.

# TRADITIONAL HIGH-SPEED FUSES

## Dimensions

AMPERE	FIG.	DIMENSIONS INCHES (mm)							
RATING	N0.	А	В	С	D	E	F	G	Н
L15S Series, 150 Vac									
1 - 30	1	1½ (38.1)	_	³ ⁄8 (9.5)	¹³ / ₃₂ (10.3)	—	—	—	—
31 – 60	1	2 (50.8)	—	⁵∕⁄ଃ (15.9)	¹³ ⁄16 (20.6)	—	—	—	—
61 - 450	3	15/32 (29.4)	1 ⁷ ⁄8 (47.6)	2³⁄16 (55.6)	2 ²¹ / ₃₂ (67.5)	1 (25.4)	⁴³ ⁄64 (17.1)	⁵ ⁄16 (7.9)	³ ⁄16 (4.8)
451 - 1000	3	1¼ (31.8)	115/16 (49.2)	2 ⁹ ⁄16 (65.1)	31⁄2 (88.9)	1½ (38.1)	1 (25.4)	¹³ /32 (10.3)	1⁄4 (6.4)
L25S Series, 250 Vac									
1 - 30	1	2 (50.8)	—	1⁄2 (12.7)	⁹ ⁄16 (14.3)	—	—	—	—
31 - 60	2	15⁄8 (41.3)	21⁄4 (57.2)	21⁄2 (63.5)	3 ³ ⁄16 (81.0)	¹³ ⁄16 (20.6)	²³ / ₃₂ (18.3)	¹¹ / ₃₂ (8.7)	1⁄8 (3.2)
61 – 200	3	15⁄/8 (41.3)	25/16 (58.7)	21/16 (61.9)	31⁄8 (79.4)	1 ⁷ ⁄ ₃₂ (31.0)	1 (25.4)	⁵ ⁄16 (7.9)	³ ⁄16 (4.8)
201 - 700	3	1 ¹⁹ ⁄ ₃₂ (40.5)	2 ⁹ / ₃₂ (57.9)	229/32 (73.8)	327/32 (97.6)	1½ (38.1)	1 (25.4)	¹³ / ₃₂ (10.3)	1⁄4 (6.4)
701 - 800	3	1 ¹⁹ / ₃₂ (40.5)	2 ⁹ / ₃₂ (57.9)	229/32 (73.8)	3 ²⁷ / ₃₂ (97.6)	2 (50.8)	1½ (38.1)	¹³ / ₃₂ (10.3)	1⁄4 (6.4)
L50S Series, 500 Vac / 450 Vdc									
10 - 30	1	2 (50.8)	—	1⁄2 (12.7)	⁹ ⁄16 (14.3)	—	—	—	—
31 - 60	2	15⁄/8 (41.3)	21⁄4 (57.2)	2½ (63.5)	3 ³ /16 (81.0)	¹³ ⁄16 (20.6)	²³ / ₃₂ (18.3)	¹¹ /32 (8.7)	1⁄8 (3.2)
61 - 100	3	2 ¹ /8 (54.0)	211/16 (68.3)	3 (76.2)	35⁄8 (92.1)	1 (25.4)	.670 (17.0)	¹¹ /32 (8.7)	1⁄8 (3.2)
101 - 200	3	21⁄8 (54.0)	2 ¹³ /16 (71.4)	2 ¹⁵ ⁄16 (74.6)	35⁄8 (92.1)	11/32 (31.0)	.895 (22.7)	⁵ ⁄16 (7.9)	³ ⁄16 (4.75)
201 - 400	3	2 ³ / ₃₂ (53.2)	2 ²⁵ / ₃₂ (70.6)	313/32 (86.5)	4 ¹¹ / ₃₂ (110.3)	1½ (38.1)	1 (25.4)	¹³ / ₃₂ (10.3)	1⁄4 (6.4)
401 - 600	3	2 ⁷ / ₃₂ (56.4)	2 ²⁹ /32 (73.8)	317/32 (89.7)	415/32 (113.5)	2 (50.8)	1½ (38.1)	¹³ / ₃₂ (10.3)	1⁄4 (6.4)
601 - 800	3	2 7/32 (56.4)	4%32 (108.7)	45⁄% (117.5)	6 ¹⁵ / ₃₂ (164.3)	2½ (63.5)	2 (50.8)	¹⁷ /32 (13.5)	³ ⁄8 (9.5)
L60S Series, 600 Vac									
1 - 30	1	5 (127.0)	_	⁵∕ଃ (15.9)	¹³ ⁄16 (20.6)	—	—	—	_
31 – 60	2	2 ²⁵ /32 (70.6)	37/16 (87.3)	311/16 (93.7)	4 ³ /8 (111.1)	¹³ ⁄16 (20.6)	²³ /32 (18.3)	¹¹ /32 (8.7)	1⁄8 (3.2)
61 - 100	2	2 ²⁹ /32 (73.8)	317/32 (89.7)	325/32 (96.0)	4 ¹⁵ /32 (113.5)	1 ¹ ⁄16 (27.0)	²³ /32 (18.3)	¹¹ /32 (8.7)	1⁄8 (3.2)
101 – 200	2	2 ²⁹ /32 (73.8)	3 ⁹ /16 (90.5)	33⁄4 (95.3)	4 ¹³ /32 (111.9)	15⁄16 (33.3)	1 (25.4)	⁵ ⁄16 (7.9)	³ ⁄16 (4.8)
201 - 400	2	2 ²⁹ /32 (73.8)	3 ³¹ / ₃₂ (100.8)	45/32 (105.6)	51⁄8 (130.2)	1 ³⁷ ⁄64 (40.1)	1 (25.4)	¹³ /32 (10.3)	1⁄4 (6.4)
401 - 600	2	21/8 (73.0)	331/32 (100.8)	4%4 (105.2)	51⁄8 (130.2)	2 ¹ ⁄16 (52.8)	1½ (38.1)	¹³ ⁄32 (10.3)	1⁄4 (6.4)
601 - 800	2	3 ¹ / ₃₂ (77.0)	55/32 (133.4)	5 ¹¹ / ₃₂ (135.7)	7¼ (184.2)	2½ (63.5)	2 (50.8)	¹⁷ ⁄32 (13.5)	³ ⁄8 (9.5)
L70S Series, 700 Vac / 650 Vdc									
10 - 30	1	2 (50.8)	_	1⁄2 (12.7)	⁹ ⁄16 (14.3)	_	_	_	_
31 – 60	2	2 ⁷ ⁄8 (73.0)	37/16 (87.3)	3 ³ ⁄4 (95.3)	4 ³ /8 (111.1)	1 (25.4)	⁴³ ⁄64 (17.1)	¹¹ ⁄32 (8.7)	¹ ⁄8 (3.2)
61 - 100	2	21⁄8 (73.0)	3 ⁹ /16 (90.5)	311/16 (93.7)	4 ³ /8 (111.1)	1 ⁷ /32 (31.0)	²⁹ /32 (22.9)	⁵ ⁄16 (7.9)	³ ⁄16 (4.8)
101 – 200	2	2 ²⁷ /32 (72.2)	317/32 (89.7)	4 5/32 (105.6)	5 ³ / ₃₂ (129.4)	1½ (38.1)	1(25.4)	¹³ ⁄32 (10.3)	1⁄4 (6.4)
201 - 400	2	2 ²⁷ / ₃₂ (72.2)	317/32 (89.7)	45/32 (105.6)	5 ³ / ₃₂ (129.4)	2 (50.8)	1½ (38.1)	¹³ /32 (10.3)	1⁄4 (6.4)
401 - 600	2	2 ²⁷ / ₃₂ (72.2)	4 ²⁹ / ₃₂ (124.6)	5¼ (133.4)	7 ³ / ₃₂ (180.2)	2½ (63.5)	2 (50.8)	¹⁷ ⁄32 (13.5)	³ ⁄8 (9.5)
601 - 800	4	3 ⁵ ⁄16 (84.1)	55⁄16 (134.9)	6 ¹³ ⁄16 (173.0)	_	21⁄8 (73.0)	2 (50.8)	⁵⁄⁄8 (15.9)	H: ¾ (9.5) J: ⁵⁄16 (7.9)
KLC Series, 600 Vac									
1 - 30	2	11⁄3 (47.6)	2½ (63.5)	—	21⁄8 (73.0)	⁹ ⁄16 (14.3)	¹³ /32 (10.3)	1⁄4 (6.4)	³ ⁄64 (1.2)
31 – 60	2	2 ³ ⁄4 (69.9)	3 ³ ⁄8 (85.7)	3 ⁵ ⁄8 (92.1)	4 5⁄16 (109.5)	¹³ ⁄16 (20.6)	²³ ⁄ ₃₂ (18.3)	¹¹ ⁄32 (8.7)	1⁄8 (3.2)
61 – 100	3	21⁄8 (73.0)	3 ²¹ / ₃₂ (92.9)	41⁄16 (103.2)	5 (127.0)	1 (25.4)	³ ⁄4 (19.1)	¹³ ⁄32 (10.3)	1⁄8 (3.2)
101 - 200	3	2 ²⁷ / ₃₂ (72.2)	317/32 (89.7)	4 ³ /8 (111.1)	5 ³ ⁄ ₃₂ (129.4)	1½ (38.1)	1 (25.4)	¹³ ⁄ ₃₂ (10.3)	1⁄4 (6.4)
201 - 400	3	2 ²⁷ / ₃₂ (72.2)	4 ²¹ / ₃₂ (118.3)	4 ²⁷ / ₃₂ (123.0)	6¼ (158.8)	2 (50.8)	15⁄8 (41.3)	⁹ ⁄16 (14.3)	1⁄4 (6.4)
401 - 800	3	2 ²⁷ / ₃₂ (72.2)	4 ²¹ / ₃₂ (118.3)	511/32 (135.7)	6¼ (158.8)	2½ (63.5)	2 (50.8)	⁹ ⁄ ₁₆ (14.3)	³ ⁄8 (9.5)



**FL** ()







Fig. 4


## **ALTERNATE DIMENSION HIGH-SPEED FUSES**

150 Vac • Very Fast-Acting • 1-6000 A

## **LA15QS Series**

AMPERE RATING	CATALOG NUMBER	MOUNTING TYPE	MAXIMUM CLEARING I ² t@ 150 Vac (A ² s x 10 ³ )	WATTS LOSS @ RATED CURRENT (W)
1	LA150S1-2	2	0.0002	0.68
3	LA150S3-2	2	0.003	1.7
4	LA150S4-2	2	0.007	2.1
5	LA150S5-2	2	0.012	2.8
6	LA150S6-2	2	0.022	3.1
7	LA150S7-2	2	0.011	2.2
8	LA150S8-2	2	0.015	2.5
10	LA15QS10-2	2	0.019	2.6
12	LA150S12-2	2	0.030	3
15	LA15QS15-2	2	0.042	3
25	LA150S25-2	2	0.14	5.2
30	LA150S30-2	2	0.25	5.6
35	LA15QS35-1	1	0.21	9
40	LA150S40-1	1	0.28	10
40	LA15QS40-4TI	4TI	0.39	3.1
45	LA150S45-1	1	0.34	12
50	LA15QS50-1	1	0.47	13
50	LA150S50-4	4	0.64	4
55	LA15QS55-1	1	Contact Factory	Contact Factory
60	LA15QS60-1	1	0.94	14
70	LA150S70-4	4	2	5.6
70	LA15QS70-4TI	4TI	2	5.6
80	LA150S80-4	4	2.5	8
80	LA15QS80-4TI	4TI	2.5	8
90	LA150S90-4	4	3.1	9
100	LA15QS100-4	4	3.6	10
100	LA15QS100-4TI	4TI	3.6	10
130	LA150S130-4	4	5.3	14
130	LA15QS130-4TI	4TI	5.3	14
150	LA150S150-4	4	6.8	16
150	LA150S150-4IL	4IL	6.8	16
150	LA150S150-4TI	4TI	6.8	16
200	LA150S200-4	4	9	22
200	LA15QS200-4IL	4IL	9	22

AMPERE RATING	CATALOG NUMBER	MOUNTING TYPE	MAXIMUM CLEARING I ² t @ 150 Vac (A ² s x 10 ³ )	WATTS LOSS @ RATED CURRENT (W)
250	LA150S250-4	4	15	22
250	LA150S250-4TI	4TI	15	27
300	LA150S300-4	4	22	33
300	LA150S300-4IL	4IL	22	33
300	LA15QS300-4TL	4TI	22	33
350	LA15QS350-4	4	32	40
350	LA150S350-4TI	4TI	32	40
400	LA150S400-4	4	40	45
400	LA15QS400-4IL	4IL	40	45
400	LA15QS400-4TI	4TI	40	45
450	LA150S450-4	4	50	50
450	LA15QS450-4IL	4IL	50	50
500	LA150S500-4	4	90	30
500	LA150S500-4IL	4IL	90	30
600	LA150S600-4	4	130	35
600	LA15QS600-4IL	4IL	130	35
800	LA15QS800-4	4	290	57
1000	LA15QS1000-4	4	520	75
1000	LA150S1000-4IL	4IL	520	75
1000	LA15QS1000-4TI	4TI	520	75
1000	LA15QS1000-128	128	540	88
1000	LA15QS1000-128IL	128IL	540	88
1200	LA15QS1200-128	128	680	100
1200	LA15QS1200-128IL	128IL	680	100
1500	LA15QS1500-128	128	1200	130
1500	LA15QS1500-128IL	128IL	1200	130
2000	LA15QS2000-128	128	1900	165
2000	LA150S2000-128IL	128IL	1900	165
2500	LA15QS2500-128	128	3200	195
2500	LA150S2500-128IL	128IL	3200	195
3000	LA15QS3000-128	128	4800	240
3000	LA15QS3000-128IL	128IL	4800	240
3500	LA15QS3500-128	128	6500	260
4000	LA15QS4000-128	128	8500	270
4000	LA150S4000-128IL	128IL	8500	270
5000	LA15QS5000-128	128	Contact Factory	Contact Factory
6000	LA15QS6000-128	128	Contact Factory	Contact Factory

## **Specifications**

Voltage Rating	AC: 150 V			
	DC: 150 V			
Interrupting Rating	100 kA			
Ampere Range	1 – 6000 A			
Approvals	UL Recognized			

### Web Resources

For additional information, visit: littelfuse.com/la15qs

150 V 150 V



Figure 1

Α





Figure 4



#### Dimensions for reference only.

## Dimensions

AMPERE	MOUNTING	FIGURE		DIMENSIONS INCHES (mm)							TAP
RATINGS	TYPE	NO.	А	В	С	D	E	F	G	Н	
1 - 30	2	1	1.50 (38.1)	0.41 (10.4)	-	-	-	-	-	-	-
35-60	1	1	2.00 (50.8)	0.81 (20.6)	-	-	-	-	-	-	-
40 - 450	4, 4TI*, 4IL*	2	2.66 (67.6)	1.13 (28.7)	1.16 (29.5)	2.19 (55.6)	1.91 (48.5)	0.31 (7.9)	0.88 (22.4)	0.19 (4.8)	-
500 - 1000	4, 4TI*, 4IL*	2	3.50 (88.9)	1.50 (38.1)	1.25 (31.8)	2.56 (65.0)	1.94 (49.3)	0.41 (10.4)	1.00 (25.4)	0.25 (6.4)	-
750 - 2000	128, 128IL*	3	1.88 (47.9)	2.00 (50.8)	1.63 (41.4)	1.75 (44.5)	1.00 (25.4)	-	-	-	3/8-24-1/2 deep
2500 - 3000	128, 128IL*	3	1.88 (47.9)	3.00 (76.2)	1.63 (41.4)	2.50 (63.5)	1.50 (38.1)	-	-	-	1/2-20-1/2 deep
3500 - 4000	128, 128IL*	4	1.88 (47.9)	3.50 (88.9)	1.63 (41.4)	3.00 (76.2)	1.06 (27.0)	1.06 (27.0)	-	-	1/2-20-1/2 deep
5000 - 6000	128	5	2.38 (60.5)	5.75 (146)	1.88 (47.7)	5.00 (127)	1.50 (38.1)	1.50 (38.1)	-	-	1/2-20-1/2 deep

*Optional Trigger Actuator (IL). Optional Trigger Indicator (TI) see web for dimensions.

5

**High-Speed Fuses** 

## **ALTERNATE DIMENSION HIGH-SPEED FUSES**

300 Vac • Very Fast-Acting • 35-4500 A

## **LA30QS Series**

AMPERE RATING	CATALOG NUMBER	MOUNTING TYPE	MAXIMUM CLEARING I ² t @300 VAC (A ² s X 10 ³ )	WATTS LOSS @ RATED CURRENT (W)
35	LA30QS35-4	4	0.9	6.4
40	LA30QS40-4	4	1.2	7
50	LA30QS50-4	4	2	9.9
60	LA30QS60-4	4	2.7	11.6
70	LA30QS70-4	4	1.6	11
80	LA30QS80-4	4	2.6	11
90	LA30QS90-4	4	3.2	13
100	LA30QS100-4	4	4.1	13
100	LA30QS100-4TI	4TI	4.1	13
125	LA30QS125-4	4	6.3	16
130	LA30QS130-4	4	6.3	16
150	LA30QS150-4	4	9.3	19
150	LA30QS150-4TI	4TI	9.3	19
175	LA30QS175-4	4	10	27
200	LA30QS200-4	4	15	30
200	LA30QS200-4TI	4TI	15	30
225	LA300S225-4	4	22	33
250	LA30QS250-4	4	25	41
250	LA300S250-4TI	4TI	25	41
300	LA30QS300-4	4	37	47
300	LA30QS300-4TI	4TI	37	47
350	LA30QS350-4	4	62	49
400	LA30QS400-4	4	83	56
400	LA30QS400-4IL	4IL	83	56
400	LA30QS400-4TI	4TI	83	56
450	LA30QS450-4	4	130	53

AMPERE RATING	CATALOG NUMBER	MOUNTING TYPE	MAXIMUM CLEARING I ² t @300 VAC (A ² s X 10 ³ )	WATTS LOSS @ RATED CURRENT (W)
500	LA30QS500-4	4	160	59
550	LA30QS550-4	4	190	65
600	LA30QS600-4	4	230	69
600	LA30QS600-4TI	4TI	230	69
600	LA30QS600-4IL	4IL	230	69
700	LA30QS700-4	4	260	90
700	LA30QS700-128	128	260	73
800	LA30QS800-4	4	330	108
800	LA30QS800-4IL	4IL	330	108
800	LA30QS800-128	128	330	84
1000	LA30QS1000-128	128	460	105
1000	LA30QS1000-128IL	128IL	460	105
1200	LA30QS1200-128	128	880	110
1500	LA30QS1500-128	128	1400	140
1500	LA30QS1500-128IL	128IL	1400	140
1600	LA30QS1600-128	128	1690	150
2000	LA300S2000-128	128	2600	190
2000	LA30QS2000-128IL	128IL	2600	190
2500	LA300S2500-128	128	4000	230
2500	LA30QS2500-128IL	128IL	4000	230
3000	LA30QS3000-128	128	4700	340
3500	LA30QS3500-128	128	6500	380
3500	LA30QS3500-128IL	128IL	6500	380
4000	LA300S4000-128	128	8600	450
4500	LA30QS4500-128	128	11000	500

## **Description**

Littelfuse LA30QS series High-Speed protection fuses are intended for the protection of Power Semiconductors such as diodes, phase control SCR's and other power high-speed devices. The LA30QS is recommended for new applications providing solutions for your critical protection needs for 300V and less semiconductors.

## **Specifications**

Voltage Rating	
Interrupting Rating Ampere Range Approvals	

### Web Resources

**Dimensions** 

For additional information, visit: littelfuse.com/la30qs

AC: 300 V DC: 300 V

200 kA 35 – 4500 A **UL** Recognized









#### Dimensions for reference only.

21

AMPERE	MOUNTING	FIGURE		DIMENSIONS INCHES (mm)							TAP
RATING	TYPE	NO.	А	В	С	D	E	F	G	Н	171
35 - 60	4	1	3.19 (81.0)	0.81 (20.6)	1.63 (41.4)	2.50 (63.5)	2.25 (57.5)	0.34 (8.6)	0.72 (18.3)	0.13 (3.3)	-
70 - 200	4	2	3.13 (79.5)	1.22 (31.0)	1.63 (41.4)	2.44 (62.0)	2.31 (58.7)	0.31 (7.9)	1.00 (25.4)	0.19 (4.8)	-
225 - 800	4, 4IL*	2	3.84 (97.5)	1.50 (38.1)	1.59 (40.1)	2.91 (73.9)	2.28 (57.9)	0.41 (10.4)	1.00 (25.4)	0.25 (6.4)	-
800 - 1200	128	3	2.59 (65.8)	3.00 (76.2)	2.34 (59.4)	2.50 (63.5)	1.50 (38.1)	-	-	-	³ /8-24- ¹ /2 deep
1500 - 2500	128, 128IL*	4	2.59 (65.8)	3.50 (88.9)	2.34 (59.4)	3.00 (76.2)	1.50 (38.1)	1.50 (38.1)	-	-	³ /8-24- ¹ /2 deep
3000 - 4500	128, 128IL*	4	2.59 (65.8)	4.50 (114)	2.34 (59.4)	3.75 (95.3)	1.50 (38.1)	1.50 (38.1)	-	-	1/2-20-1/2 deep
*0											

*Optional Trigger Actuator (IL). Optional Trigger Indicator (TI) see web for dimensions.



**FL** ()

## ALTERNATE DIMENSION HIGH-SPEED FUSES

500 Vac • Very Fast-Acting • 35-1200 A

## **LA50QS Series**

AMPERE RATING	CATALOG NUMBER	MOUNTING TYPE	MAXIMUM CLEARING I ² t @500 VAC (A ² s X 10 ³ )	WATTS LOSS @ RATED CURRENT (W)
35	LA50QS35-4	4	0.56	6
40	LA50QS40-4	4	0.69	7
50	LA50QS50-4	4	1.1	8
60	LA50QS60-4	4	1.6	10
70	LA50QS70-4	4	1.9	12
80	LA50QS80-4	4	2.6	14
90	LA50QS90-4	4	3.6	15
100	LA50QS100-4	4	4.4	17
125	LA50QS125-4	4	5.6	21
150	LA50QS150-4	4	9	25
175	LA50QS175-4	4	15	29
200	LA50QS200-4	4	20	33
225	LA50QS225-4	4	25	37
250	LA50QS250-4	4	29	41
300	LA50QS300-4	4	55	49
350	LA50QS350-4	4	88	57
400	LA50QS400-4	4	98	65
450	LA50QS450-4	4	130	69
500	LA50QS500-4	4	160	77
600	LA50QS600-4	4	220	92
700	LA50QS700-4	4	270	110
800	LA50QS800-4	4	360	130
900	LA50QS900-4	4	500	140
1000	LA50QS1000-4	4	560	160
1200	LA50QS1200-4	4	930	175

## Description

Littelfuse LA50QS series fuses were developed to improve the overall performance of high-speed fuses. The LA50QS provides the high performance protection characteristics including lower I2t, longer life when subjected to cyclic loading and lower watts loss. LA50QS is the leading choice for the protection of dynamic solid state equipment.

## **Specifications**

Voltage Rating	AC: 500 V
	DC: 500 V
Interrupting Rating	AC: 200 kA
	DC: 100 kA
Ampere Range	35 – 1200 A
Approvals	UL Recognized
	CSA Certified

### Web Resources

For additional information, visit: littelfuse.com/la50qs

## Dimensions



AMPERE	MOUNTING		DIMENSIONS INCHES (mm)								
RATING	TYPE	А	В	С	D	E	F	G	Н		
35 - 100	4	3.63 (92.2)	1.00 (25.4)	2.13 (54.1)	2.94 (74.7)	2.75 (69.9)	0.31 (7.9)	0.75 (19.1)	0.13 (3.3)		
125 – 200	4	3.63 (92.2)	1.22 (31.0)	2.13 (54.1)	2.94 (74.7)	2.81 (71.4)	0.31 (7.9)	1.00 (25.4)	0.19 (4.8)		
225 - 400	4	4.34 (110)	1.50 (38.1)	2.09 (53.1)	3.41 (86.6)	2.78 (70.6)	0.41 (10.4)	1.00 (25.4)	0.25 (6.4)		
450 - 600	4	4.47 (114)	2.00 (50.8)	2.22 (56.4)	3.53 (89.7)	2.91 (73.9)	0.41 (10.4)	1.50 (38.1)	0.25 (6.4)		
700 - 800	4	6.47 (164.3)	2.50 (63.5)	2.22 (56.4)	5.00 (127.0)	3.44 (87.3)	0.53 (13.5)	1.50 (38.1)	0.25 (6.4)		
900 - 1200	4	6.97 (177.0)	3.00 (76.2)	3.22 (81.8)	5.47 (138.9)	4.47 (113.5)	0.63 (15.9)	2.38 (60.3)	0.44 (11.1)		

Contact Littelfuse for characteristic curves.

Dimensions for reference only.

## ALTERNATE DIMENSION HIGH-SPEED FUSES

600 Vac/dc • Very Fast-Acting • 5-40 A

## LA60Q Series High-Speed Fuses

AMPERE RATING	CATALOG NUMBER	MOUNTING TYPE	MAXIMUM CLEARING I ² t @600 VAC (A ² s)	WATTS LOSS @ RATED CURRENT (W)
5	LA6005-2	2	60	0.7
8	LA60Q8-2	2	70	1.1
10	LA60Q10-2	2	110	1.6
12	LA60012-2	2	150	2
15	LA60Q15-2	2	180	3
20	LA60020-2	2	330	4.4
25	LA60025-2	2	440	5.5
30	LA60Q30-2	2	860	5.6
35	LA60Q35-2	2	1300	6.4
40	LA60Q40-2	2	1800	7

## **Specifications**

**Voltage Rating** AC: 600 V DC: 600 V **Interrupting Rating** AC: 200 kA DC: 100 kA **Ampere Range** 5-40 A Approvals **UL** Recognized

## **Description**

Littelfuse LA60Q high-speed protection fuses feature a 600 volt ac/dc rating in a compact size (1  $\frac{1}{2}$ " x  $\frac{13}{32}$ "). LA60Q also has the lowest I²t of all similar fuses and excellent cycling ability. Applications include inverters and small equipment requiring extremely fast response to faults, without the need to carry sustained heavy overloads.

## **Dimensions Inches**



### Web Resources

For additional information, visit: littelfuse.com/la60q

Contact Littelfuse for characteristic curves.

## 690 Vac/700 Vdc • Very Fast-Acting • 10-100 A

## LA70QSF Series French Cylindrical Fuses

AMPERE RATING	CATALOG NUMBER (NO STRIKER)	CATALOG NUMBER (WITH STRIKER)	BODY SIZE	MAXIMUM CLEARING I ² t @700 VAC (A ² s X 10 ³ )	WATTS LOSS @ RATED CURRENT (W)
10	LA70QS10-14F	LA70QS10-14FI	14 x 51	0.04	3.5
12	LA70QS12-14F	LA70QS12-14FI	14 x 51	0.06	4.4
16	LA70QS16-14F	LA70QS16-14FI	14 x 51	0.10	4.8
20	LA70QS20-14F	LA70QS20-14FI	14 x 51	0.16	5.2
25	LA70QS25-14F	LA70QS25-14FI	14 x 51	0.27	5.8
32	LA70QS32-14F	LA70QS32-14FI	14 x 51	1.50	7.0
40	LA70QS40-14F	LA70QS40-14FI	14 x 51	0.70	10.7
50	LA70QS50-14F	LA70QS50-14FI	14 x 51	1.50	11.6
20	LA70QS20-22F	LA700S20-22FI	22 x 58	0.076	8.0
25	LA70QS25-22F	LA700S25-22FI	22 x 58	0.125	10.0
32	LA70QS32-22F	LA700S32-22FI	22 x 58	0.27	11.0
40	LA70QS40-22F	LA70QS40-22FI	22 x 58	0.48	13.0
50	LA70QS50-22F	LA700S50-22FI	22 x 58	0.80	14.9
63	LA70QS63-22F	LA700S63-22FI	22 x 58	1.85	16.0
80	LA70QS80-22F	LA700S80-22FI	22 x 58	3.80	17.8
100	LA70QS100-22F	LA70QS100-22FI	22 x 58	8.00	19.0

## **Specifications**

Voltage Rating	AC: 690 V
	DC: 700 V
Interrupting Rating	AC: 200 kA
	DC: 100 kA
Ampere Range	10 – 100 A
Approvals	UL Recognized
	CSA Certified

## **Description**

Littelfuse French Cylindrical style high-speed fuses are an extension to the LA70QS series. They offer a solid-fill design with high interrupting ratings and an optional striker for visual or remote blown fuse indication.

### Web Resources

For additional information, visit: littelfuse.com/semi

## **Dimensions**



FUSE SIZE	DIMENSIONS mm								
FUSESIZE	А	B C D E   51 14 - -   58 16 - -   51 14 7.5 3.8	E						
14x51	14	51	14	-	-				
22x58	22	58	16	-	-				
14x51 Striker	14	51	14	7.5	3.8				
22x58 Striker	22	58	16	7.5	3.8				

**FL** &



**FL** ()

## **ALTERNATE DIMENSION HIGH-SPEED FUSES**

700 Vac/dc • Very Fast-Acting • 35-800 A

## LA70QS Series High-Speed Fuses

AMPERE RATING	CATALOG NUMBER	MOUNTING TYPE	MAXIMUM CLEARING I ² t @700 VAC (A ² s X 10 ³ )	WATTS LOSS @ RATED CURRENT (W)
35	LA70QS35-4	4	0.47	6.2
40	LA70QS40-4	4	0.58	7.5
50	LA70QS50-4	4	0.86	9.8
60	LA70QS60-4	4	1.2	12
70	LA70QS70-4	4	1.8	15
80	LA70QS80-4	4	2.3	18
90	LA70QS90-4	4	3	20
100	LA70QS100-4	4	3.6	24
125	LA70QS125-4	4	6.9	22
125	LA70QS125-4K	4K	6.9	22
150	LA70QS150-4	4	11	29
150	LA70QS150-4K	4K	11	29
175	LA70QS175-4	4	14	35
175	LA70QS175-4K	4K	14	35
200	LA70QS200-4	4	19	41
200	LA70QS200-4K	4	19	41
250	LA70QS250-4	4	42	42
300	LA70QS300-4	4	55	53
350	LA70QS350-4	4	72	64
400	LA70QS400-4	4	99	75
450	LA70QS450-4	4	125	78
450	LA70QS450-4K	4K	125	78
500	LA70QS500-4	4	160	92
500	LA70QS500-4K	4K	160	92
600	LA70QS600-4	4	222	116
600	LA70QS600-4K	4K	222	116
700	LA70QS700-4	4	332	125
800	LA70QS800-4	4	433	143

## Description

Littelfuse LA70QS high-speed fuses were developed to provide improved performance required by today's new equipment. The LA70QS features lower I²t, improved cycling, and lower watts loss. It is the best choice for the protection of dynamic solid-state equipment.

### **Features/Benefits**

- I²t improved protection of equipment.
- Superior cycling ability for long, reliable life on high cycling loading.
- Lower watts loss for cooler operation.
- 700 Volt ac/dc rating provides greater design versatility
- Compact sizes allow downsizing of equipment

## **Specifications**

Voltage Rating	AC: 700 V
	DC: 700 V
Interrupting Rating	AC: 200 kA
	DC: 100 kA
Ampere Range	35 – 800 A
Approvals	UL Recognized
	CSA Certified

### Web Resources

For additional information, visit: littelfuse.com/la70qs

## Dimensions



MOUNTING **DIMENSIONS INCHES (mm)** AMPERES ТҮРЕ А В С D Е F G Н 35 - 100 1.00 (25.4) 2.88 (73) 3.69 (93.6) 3.50 (88.9) 0.31 (7.9) 0.75 (19.0) 0.13 (3.2) 4 4.38 (111) 1.00 (25.4) 125 - 200 4.38 (111) 1.22 (31.0) 2.88 (73) 3.69 (93.6) 3.56 (90.5) 0.31 (7.9) 0.19 (4.8) 4 125 - 200 4K 5.09 (129) 1.22 (31.0) 2.88 (73) 4.19 (106) 3.50 (88) 0.41 (10.3) 1.00 (25.4) 0.19 (4.8) 5.09 (129) 1.50 (38.1) 2.84 (72.2) 4.16 (106) 3.53 (89.7) 0.40 (10.3) 1.50 (38.1) 0.25 (6.4) 225 - 4004 450-600 4 5.09 (129) 2.00 (50.8) 2.84 (72.2) 4.16 (106) 3.53 (89.7) 0.41 (10.3) 1.50 (38.1) 0.25 (6.4) 450 - 6004K 7.09 (180) 2.00 (50.8) 2.84 (72.2) 6.16 (156) 3.53 (89.7) 0.53 (13.5) 1.50 (38.1) 0.25 (6.4) 700 - 8004 7.09 (180) 2.50 (63.5) 2.84 (72.2) 5.28 (134) 4.91 (125) 0.53 (13.5) 2.00 (50.8) 0.38 (9.5)

Contact Littelfuse for characteristic curves.

Dimensions for reference only.

## **ALTERNATE DIMENSION HIGH-SPEED FUSES**

## 1000 Vac • Very Fast-Acting • 15-1000 A

## LA100P Series High-Speed Fuses

AMPERE RATING	CATALOG NUMBER	MOUNTING TYPE	MAXIMUM CLEARING I ² t @1000 Vac (A ² s X 10 ³ )	WATTS LOSS @ RATED CURRENT (W)
15	LA100P15-1	1	0.6	3.4
20	LA100P20-1	1	0.8	5.9
25	LA100P25-1	1	1,3	9
30	LA100P30-1	1	1.5	12.8
35	LA100P35-4	4	2.2	7.3
40	LA100P40-4	4	2.9	8.3
50	LA100P50-4	4	4.5	11
60	LA100P60-4	4	6.5	13
80	LA100P80-4	4	12	14
100	LA100P100-4	4	18	18
125	LA100P125-4	4	28	23
150	LA100P150-4	4	41	28
200	LA100P200-4	4	72	36
225	LA100P225-4	4	91	40
250	LA100P250-4	4	110	46
300	LA100P300-4	4	160	55
350	LA100P350-4	4	220	65
400	LA100P400-4	4	290	70
500	LA100P500-4	4	450	90
600	LA100P600-4	4	650	110
650	LA100P650-4	4	780	120
700	LA100P700-4	4	880	125
800	LA100P800-4	4	1200	140
1000	LA100P1000-4	4	1900	190

### **Description**

Littelfuse LA100P high-speed protection fuses are rated 1000 Vac, extending the range of protection for UPS systems, AC and DC drives, reduced voltage motor starters and similar applications where lower I²t and superior reliability are needed. With ratings from 15-1000 amperes, a wide range of high voltage applications can be served.

Ъ.

### **Features/Benefits**

- Low I²t minimizes damage to protected components • on short-circuit.
- Controlled arc voltage reduces stress to circuit components during fuse clearing.

#### **Specifications**

Voltage Rating	AC: 1000 V
	DC: 750 V
Interrupting Rating	100 kA
Ampere Range	15 – 1000 A
Approvals	UL Recognized

### Web Resources

For additional information, visit: littelfuse.com/la100p

## **Dimensions**

#### Figure 1

#### Figure 2







Figure 3



Figure 4



#### Dimensions for reference only.

AMPERES	MOUNTING	FIGURE	DIMENSIONS INCHES (mm)									
	TYPE	NO.	А	В	С	D	E	F	G	Н	J	
15 — 30	1	1	2.53 (66.8)	0.56 (14.2)	-	-	-	-	-	-	-	
35 - 60	4	2	5.00 (127)	1.00 (25.4)	3.50 (88.9)	4.31 (109)	4.19 (106)	0.31 (7.9)	0.75 (19.1)	0.13 (3.3)	-	
65 - 100	4	2	5.00 (127)	1.22 (31)	3.50 (88.9)	4.31 (109)	4.19 (106)	0.31 (7.9)	1.00 (25.4)	0.19 (4.8)	-	
125 - 200	4	2	5.72 (145)	1.50 (38.1)	3.47 (88.1)	4.78 (121)	4.16 (106)	0.41 (10.4)	1.00 (25.4)	0.25 (6.4)	-	
225 - 400	4	2	5.72 (145)	2.00 (50.8)	3.47 (88.1)	4.78 (121)	4.16 (106)	0.41 (10.4)	1.50 (25.4)	0.25 (6.4)	-	
500 - 600	4	2	7.72 (196)	2.50 (63.5)	3.47 (88.1)	5.88 (149)	5.56 (147)	0.53 (13.5)	2.00 (50.8)	0.38 (9.7)	-	
650 - 800	4	3	7.44 (189)	2.88 (73.2)	3.94 (100)	5.94 (151)	-	0.63 (16)	2.00 (50.8)	0.38 (9.7)	0.31 (7.9)	
1000	4	4	8.22 (209)	3.50 (88.9)	4.47 (114)	6.59 (167)	5.84 (148)	0.63 (16)	2.75 (69.9)	0.50 (12.7)	1.38 (35.1)	

Optional Trigger Indicator (TI) for 50 A - 1000 A available

Contact Littelfuse for characteristic curves.

700/1300 Vac • Very Fast-Acting • 63-2500 A





## **Ordering Information**



## Description

Littelfuse North American style square body high-speed fuses provide maximum flexibility in equipment design and ultimate protection for today's power conversion equipment. Available in different body sizes and multiple mounting styles, the broad range of ampere ratings allows great flexibility in equipment design.

Engineered to provide state-of-the-art protection for SCRs, diodes, thyristors, GTOs, and IGBT devices, Littelfuse square body fuses have pure die-cut elements embedded in solidified sand to control arcing and lower I²t. All fuses are also equipped with a blown fuse trip indicator.

## Features

- Choice of mounting styles provides a wide choice for equipment design.
- Broad range of ampere ratings in a given body size for design flexibility.
- Very low I²t minimizes damage to protected components.
- Superior cycling ability for long, reliable life on high cyclic loading.
- Extremely fast-acting and current-limiting for improved protection to equipment.

## Applications

Protection of rectifiers, inverters, DC drives, UPS systems, reduced voltage motor starters, and other equipment in globally accepted applications.

## **Specifications**

Voltage Rating	AC: 700 V (LA070)
	1300 V (LA130)
	DC: Contact factory
Interrupting Rating	AC: 200 kA (LA070)
	100 kA (LA130)
	DC: Contact factory
Ampere Range	63 – 2500 A
Approvals	UL Recognized Component

## Dimensions

## Web Resources

For additional information, visit: littelfuse.com/la070

700/1300 Vac • Very Fast-Acting • 63-2500 A

BODY SIZE	AMPERE RATING	RATED VOLTAGE	MELTING I ² T (A ² S X 10 ³ )	@ RATED VOLTAGE (A ² S X 10 ³ )	*WATTS LOSS @ RATED CURRENT (W)	LONG BLADE CATALOG NUMBER TYPE LI	SHORT BLADE CATALOG NUMBER TYPE KI	TAPPED TERMINAL CATALOG NUMBER TYPE TTI
	63	700	0.2	1.2	14	LA070URD30LI0063	LA070URD30K10063	LA070URD30TTI0063
	80	700	0.33	1.9	19	LA070URD30LI0080	LA070URD30K10080	LA070URD30TTI0080
	100	700	0.47	2.7	26	LA070URD30LI0100	LA070URD30KI0100	LA070URD30TTI0100
	125	700	0.85	4.9	30	LA070URD30LI0125	LA070URD30KI0125	LA070URD30TTI0125
	160	700	1.6	9.2	37	-	LA070URD30KI0160	LA070URD30TTI0160
	200	700	3	16.7	42/43	LA070URD30LI0200	LA070URD30KI0200	LA070URD30TTI0200
30	250	700	5.8	32.4	48/50	LA070URD30LI0250	LA070URD30KI0250	LA070URD30TTI0250
	315	700	12	67	53/55	LA070URD30LI0315	LA070URD30KI0315	LA070URD30TTI0315
	350	700	15.5	86	57/60	LA070URD30LI0350	LA070URD30KI0350	LA070URD30TTI0350
	400	700	23	130	60/65	LA070URD30LI0400	LA070URD30KI0400	LA070URD30TTI0400
	450	700	26	165	80/88	LA070URD30LI0450	LA070URD30KI0450	LA070URD30TTI0450
	500	700	41	264	80/88	LA070URD30LI0500	LA070URD30KI0500	LA070URD30TTI0500
	550	700	52	330	80/90	LA070URD30LI0550	LA070URD30KI0550	LA070URD30TTI0550
	200	700	2.5	14.6	45	LA070URD31LI0200	LA070URD31KI0200	LA070URD31TTI0200
	250	700	4.7	27	52	LA070URD31LI0250	LA070URD31KI0250	LA070URD31TTI0250
	315	700	7.5	43	65	LA070URD31LI0315	LA070URD31KI0315	LA070URD31TTI0315
	350	700	10.5	59	67	LA070URD31LI0350	LA070URD31KI0350	LA070URD31TTI0350
	400	700	19	110	68	LA070URD31LI0400	LA070URD31KI0400	LA070URD31TTI0400
31	450	700	26.5	150	70	LA070URD31LI0450	LA070URD31KI0450	LA070URD31TTI0450
	500	700	37	210	70/72	LA070URD31LI0500	LA070URD31KI0500	LA070URD31TTI0500
	550	700	52	300	70/75	LA070URD31LI0550	LA070URD31KI0550	LA070URD31TTI0550
	630	700	75	421	75/85	LA070URD31LI0630	LA070URD31KI0630	LA070URD31TTI0630
	700	700	95	530	85/95	LA070URD31LI0700	LA070URD31KI0700	LA070URD31TTI0700
	800	700	140	880	105/120	LA070URD31LI0800	LA070URD31KI0800	LA070URD31TTI0800
	400	700	15	86	72/75	LA070URD32LI0400	LA070URD32KI0400	LA070URD32TTI0400
	450	700	22	124	77/80	LA070URD32LI0450	LA070URD32KI0450	LA070URD32TTI0450
	500	700	28	157	85/90	LA070URD32L10500	LA070URD32KI0500	LA070URD32TTI0500
	550	700	37	211	90/95	LA070URD32LI0550	LA070URD32KI0550	LA070URD32TTI0550
	630	700	54	302	95/105	LA070URD32LI0630	LA070URD32KI0630	LA070URD32TTI0630
	700	700	76	432	100/110	LA070URD32LI0700	LA070URD32KI0700	LA070URD32TTI0700
32	800	700	115	648	110/120	LA070URD32LI0800	LA070URD32KI0800	LA070URD32TTI0800
	900	700	170	972	110/125	LA070URD32LI0900	LA070URD32KI0900	LA070URD32TTI0900
	1000	700	240	1350	115/135	LA070URD32LI1000	LA070URD32KI1000	LA070URD32TTI1000 LA065URD32TTI1100
	1100	650	270	1620	140/165	LA065URD32LI1100	-	
	1250	600	410 555	2100	150/180	LA060URD32LI1250	-	LA060URD32TTI1250
	1400	550 550	870	2600 4000	160/190 165/195	LA055URD32LI1400 LA055URD32LI1600	-	LA055URD32TTI1400 LA055URD32TTI1600
	1600 1800	500	1050	4000		LA050URD32L11800	-	LA050URD32TT11800
	500	700	1050	108	195/330 105	LA070URD33L10500	 LA070URD33KI0500	LA070URD32T11800
	550	700	27	108	105/110	LA070URD33L10550	LA070URD33KI0550	LA070URD33TT10550
	630	700	40	227	110/120	LA070URD33L10630	LA070URD33KI0550	LA070URD33TT10550
	700	700	55	324	115/125	LA070URD33L10030	LA070URD33K10030	LA070URD33TT10030
	800	700	95	529	120/130	LA070URD33L10800	LA070URD33K10800	LA070URD33TTI0800
	900	700	135	760	120/130	LA070URD33L10900	LA070URD33K10900	LA070URD33TT10800
	1000	700	170	970	135/155	LA070URD33LI1000	LA070URD33KI1000	LA070URD33TT11000
33	1100	700	240	1360	135/155	LA070URD33LI1000	LA070URD33KI1000	LA070URD33TTI1000
35	1250	700	350	2000	150/180	LA070URD33LI1250	LA070URD33KI1250	LA070URD33TTI1250
	1400	700	480	2700	160/200	LA070URD33LI1200	LA070URD33KI1200	LA070URD33TTI1230
	1400	650	555	3250	210/240	LA065URD33LI1600		LA065URD33TTI1600
	1800	650	720	4330	210/240	LA065URD33LI1800	_	LA065URD33TT11800
	2000	600	950	5000	250/290	LA060URD33LI2000	-	LA060URD33TTI2000
	2250	550	1250	5900	280/230	LA055URD33LI2250	-	LA055URD33TTI2000
	2500	500	1870	7600	280/330	LA050URD33LI2500	_	LA050URD33TTI2500
	2000	000	1070	,000	200,000	2/1000011200012000		2.10000112000

*Watts loss data is published for both blade and tapped style mounting configurations.

When two watts loss values are shown, this represents tapped/blade values respectively.

Contact Littelfuse for characteristic curves.



700/1300 Vac • Very Fast-Acting • 63-2500 A

#### **TYPES KI AND LI**





### North American Straight Blade, Type KI **Dimensions**

Dimensions							Dimension	is for refer	ence only.		
CATALOG NUMBER		DIMENSIONS INCHES (mm)									
CATALOG NOWIDEN	А	В	С	D	E	F	G	Н	J		
LA070URD30KI (63-550)	1.57	0.98	0.49	0.83	0.71	2.68	4.21	5.08	0.41		
	(40)	(25)	(12.5)	(21)	(18)	(68)	(107)	(129)	(10.5)		
LA070URD31KI (200-800)	2.01	0.98	0.49	1.0	0.89	2.66	4.22	5.07	0.56		
	(51)	(25)	(12.5)	(25.5)	(22.5)	(67.6)	(107.1)	(128.8)	(14.3)		
LA070URD32KI (400-1000)	2.36	1.26	0.63	1.18	1.06	2.92	4.29	5.28	0.57		
	(60)	(32)	(16)	(30)	(27)	(74.2)	(109)	(134)	(14.6)		
LA070URD33KI (500-1400)	2.93	1.57	0.79	1.46	1.35	2.97	4.24	5.28	0.63		
	(74.5)	(40)	(20)	(37.2)	(34.2)	(75.4)	(107.6)	(134)	(15.9)		

### North American Straight Blade, Type LI

#### **Dimensions**

Dimensions						Dimensior	ns for refer	ence only.		
CATALOG NUMBER	DIMENSIONS INCHES (mm)									
CATALOG NOMBEN	А	В	С	D	E	F	G	Н	J	
LA070URD30LI (63-550)	1.57 (40)	0.98 (25)	0.49 (12.5)	0.83 (21)	0.71 (18)	3.45 (87.6)	4.98 (126.6)	5.85 (148.6)	0.41 (10.5)	
LA070URD31LI (200-800)	2.01 (51)	0.98 (25)	0.49 (12.5)	1.0 (25.5)	0.89 (22.5)	3.61 (91.6)	4.82 (122.4)	5.85 (148.6)	0.57 (14.6)	
LA070URD32LI (400-1000)			1.26 0.63		1.06	3.71	5.08	6.02		
LA060URD32LI (1250)	2.36			1.18					0.57	
LA055URD32LI (1400-1600)	(60) (32)		(30)	(30) (27)	7) (94.2)	(129)	(153)	(14.6)		
LA050URD32LI (1800)										
LA070URD33LI (500-1400)									0.63 (15.9)	
LA065URD33LI (1600-1800)	0.00	4 57	0.70		4.05					
LA060URD33LI (2000)	2.93	1.57	0.79	1.46 (37.2)	1.35 (34.2)	3.72 (94.4)	4.98 (126.6)	6.02 (153)		
LA055URD33LI (2250)	(74.5)	(74.5) (40)	(20)	(37.2)	(34.2)	(34.4)	(120.0)	(155)		
LA050URD33LI (2500)										

#### ΤΥΡΕ ΤΤΙ



### North American Flat Single Hole, Type TTI

## Dimensions

Dimensions Dimensions for reference							
CATALOG NUMBER	DIMENSIONS INCHES (mm)						
UNITALOG NOMBEN	А	В	С				
LA070URD30TTI (100-550)	1.57 (40)	1.00 (25)	⁵⁄16-18 x 0.35				
LA070URD31TTI (200-800)	2.00 (50.8)	1.19 (30.2)	⁵⁄16-18 x 0.35				
LA070URD32TTI (400-1000) LA065URD32TTI (1100) LA060URD32TTI (1250) LA055URD32TTI (1400-1600)	2.37 (60.3)	1.50 (38.1)	³⁄⊮-16 x 0.35				
LA060URD33TTI (1800) LA070URD33TTI (500-1400) LA065URD33TTI (1600) LA060URD33TTI (2000) LA055URD33TTI (2250) LA050URD33TTI (2500)	2.94 (74.5)	1.81 (46)	½-18 x 0.35				

## © 2015 Littelfuse POWR-GARD® Products Catalog

700/1300 Vac • Very Fast-Acting • 63-2500 A

BODY SIZE	AMPERE RATING	RATED VOLTAGE	MELTING I ² T (A ² S X 10 ³ )	TOTAL I ² T @ RATED VOLTAGE (A ² S X 10 ³ )	*WATTS LOSS @ RATED CURRENT (W)	LONG BLADE CATALOG NUMBER TYPE LI/LLI	TAPPED TERMINAL CATALOG NUMBER TYPE TTI
	63	1300	0.21	1.8	26	LA130URD70LI0063	LA130URD70TTI0063
	80	1300	0.47	4	27	LA130URD70LI0080	LA130URD70TTI0080
	100	1300	0.83	7.2	30	LA130URD70LI0100	LA130URD70TTI0100
	125	1300	1.3	11	38	LA130URD70LI0125	LA130URD70TTI0125
70	160	1300	2.5	22	45	LA130URD70LI0160	LA130URD70TTI0160
	200	1300	4.7	40	54/56	LA130URD70LI0200	LA130URD70TTI0200
	250	1300	9.6	82	58/61	LA130URD70LI0250	LA130URD70TTI0250
	315	1300	20	172	66/72	LA130URD70LI0315	LA130URD70TTI0315
	350	1200	28	205	68/75	LA120URD70LI0350	LA120URD70TTI0350
	160	1300	2.6	22	46	LA130URD71LLI0160	LA130URDT1TTI0160
	200	1300	4.7	40	54	LA130URD71LLI0200	LA130URD71TTI0200
	250	1300	8.9	76	61	LA130URD71LLI0250	LA130URD71TTI0250
	280	1300	12	102	68/70	LA130URD71IL0280	LA130URD71TTI0280
	315	1300	16	138	73/76	LA130URD71LLI0315	LA130URD71TTI0315
	350	1300	22	190	76/80	LA130URD71LLI0350	LA130URD71TTI0350
71	400	1300	38	330	76/80	LA130URD71LLI0400	LA130URD71TTI0400
	450	1300	47	405	87/95	LA130URD71LLI0450	LA130URD71TTI0450
	500	1200	68	500	90/100	LA120URD71LLI0500	LA120URD71TTI0500
	550	1200	84	620	98/112	LA120URD71LLI0550	LA120URD71TTI0550
	630	1100	125	930	105	LA110URD71LLI0630	_
	630	1200	125	930	120	_	LA120URD71TTI0630
	280	1300	10	90	72	LA130URD72LI0280	LA130URD72TTI0280
	315	1300	15	130	76	LA130URD72LI0200	LA130URD72TTI0315
	350	1300	21	180	77	LA130URD72LI0350	LA130URD72TTI0350
	400	1300	32	285	80	LA130URD72LI0400	LA130URD72TTI0400
	450	1300	44	380	87/89	LA130URD72LI0450	LA130URD72TTI0450
	500	1300	57	500	94/98	LA130URD72LI0500	LA130URD72TTI0500
72	550	1300	68	590	110/120	LA130URD72LI0550	LA130URD72TTI0550
12	630	1200	105	920	113	LA120URD72LI0630	
	630	1300	105	920	125	-	LA130URD72TTI0630
	700	1100	145	1040	123	LA110URD72LI0700	
	700	1200	145	1040	140		LA120URD72TTI0700
	800	1100	215	1590	125	LA110URD72LI0800	
	800	1200	215	1590	146		LA120URD72TTI0800
	315	1300	12	102	84	LA130URD73LI0315	LA130URD73TTI0315
	350	1300	17	150	86	LA130URD73LI0350	LA130URD73TTI0350
	400	1300	25	220	93	LA130URD73LI0400	LA130URD73TTI0400
	400	1300	35	310	99/100	LA130URD73LI0450	LA130URD73TTI0400
	500	1300	44	390	110/112	LA130URD73LI0430	LA130URD73TTI0500
	550	1300	57	500	116/120	LA130URD73LI0550	LA130URD73TT10550
	630	1300	84	730	125/132	LA130URD73LI0530	LA130URD73TT10530
	700	1300	110	960	135/146	LA130URD73LI0700	LA130URD73TT10700
	800	1200	190	1630	136	LA120URD73LI0800	_
73	800	1300	190	1630	148		LA130URD73TTI0800
	900	1100	250	2160	140	LA110URD73LI0900	_
	900	1000	250	2160	170		LA100URD73TTI0900
	1000	1000	370	2430	152/174	LA100URD73LI1000	LA100URD73TT10000
	1100	1000	445	2580	168/208	LA100URD73LI1100	LA100URD73TT11000
	1250	1000	585	3480	186/200	LA100URD73LI1250	LA100URD73TT11250
	1400	900	755	3880	210/228	LA090URD73LI1200	LA090URD73TTI1200
	1400	700	1430	5630	203	LA070URD73LI1400	LA0300ND73TTI1400
		1 100	1 1730	0000	200		

*Watts loss data is published for both blade and tapped style mounting configurations. When two watts loss values are shown, this represents tapped/blade values respectively. Contact Littelfuse for characteristic curves.



700/1300 Vac • Very Fast-Acting • 63-2500 A

#### **TYPES LI AND LLI**



#### North American Straight Blade, Types LI and LLI

### **Dimensions**

Dimensions Dimensions for reference only.												
CATALOG NUMBER	DIMENSIONS INCHES (mm)											
	А	В	С	D	E	F	G	Н	J			
LA130URD70LI (63-315)	1.57	0.98	0.49	0.83	0.71	3.60	5.13	6.00	0.41			
LA120URD70LI (350)	(40)	(25)	(12.5)	(21)	(18)	(91.4)	(130.4)	(152.4)	(10.5)			
LA130URD71LLI (160-450)	2.01	0.00	0.40	1.0	0.00	2.00	F 10	0.00	0.57			
LA120URD71LLI (500-550)	2.01 (51)	0.98 (25)	0.49 (12.5)	1.0 (26.5)	0.89 (22.5)	3.60 (91.4)	5.13 (130.4)	6.00 (152.4)	0.57 (14.6)			
LA110URD71LLI (630)		(23)	(12.3)	(20.0)	(22.0)	(01.1)	(100.1)	(102.1)	(14.0)			
LA130URD72LI (280-550)	0.00	1.00	0.63 (16)	1.18 (30)	1.06 (27)	3.84 (97.6)	5.2 (132.4)	6.20 (157.4)	0.57			
LA120URD72LI (800)	2.36 (60)	1.26 (32)							0.57 (14.6)			
LA110URD72LI (700-800)	(00)	(32)										
LA130URD73LI (315-700)												
LA120URD73LI (800)					1.35	3.89	5.21 (132.4)	6.20 (157.4)				
LA110URD73LI (900-1000)	2.93	1.57	0.79	1.46					0.63			
LA090URD73LI (1400)	(74.5)	(40)	(20)	(37.2)	(34.2)	(98.8)			(15.9)			
LA070URD73LI (1600)												
LA065URD73LI (1800)												

### North American Flat Single Hole, Type TTI

## **Dimensions**

Dimensions	Dimensions Dimensions for reference o							
CATALOG NUMBER	DIMENSIONS INCHES (mm)							
CATALOG NOMBEN	A	В	С					
LA130URD70TTI (63-315)	1.57	1.00	⁵ ∕16-18 x 0.23 DP					
LA120URD70TTI (350)	(40)	(26.4)	716-10 X 0.23 DI					
LA130URD71TTI (160-450)	2.01	1.19	5∕16-18 x 0.36 DP					
LA120URD71TTI (550-630)	(51)	(30.2)	716-10 X 0.30 DI					
LA130URD72TTI (280-630)	2.36	1.50	³ ⁄8-18 x 0.36 DP					
LA120URD72TTI (700-800)	(60)	(38.1)	78-10 X U.30 DF					
LA130URD73TTI (315-900)								
LA120URD73TTI (1000)								
LA110URD73TTI (1250)	2.93	1.81	½-18 x 0.36 DP					
LA090URD73TTI (1400)	(74.5)	(46)	72-10 X U.30 DF					
LA070URD73TTI (1600)								
LA065URD73TTI (1800)								

#### **TYPE TTI**





### **Section Overview**

Littelfuse[®] offers a wide variety of open-face and dead-front fuse blocks, in addition to a variety of in-line fuse holders, distribution/splicer blocks, fuse pullers and accessories.



# BLOCKS AND HOLDERS

## **Table of Contents**

LF Series Fuse Blocks Overview	83
Class J Fuse Blocks	85
Class H/K5 and R Fuse Blocks	88
Class T Fuse Blocks	94
Class G Fuse Blocks	99
Class CC/CD and Midget Fuse Blocks	101
LF Series Fuse Block Covers	105
Solar Rated Fuse Blocks	106
Dead Front Fuse Holders	109
Miscellaneous Fuse Blocks and Holders	116
High-Speed Fuse Blocks	120
Distribution and Splicer Blocks	122
In-Line Fuse Holders	132



## FUSE BLOCK OVERVIEW



### Description

Littelfuse offers a comprehensive line of fuse blocks that incorporate many benefits such as indication, snap torelease, DIN-Rail mounting and universal mounting holes.

## **New Options Available**

- Reduced Footprint—Save space with designs up to 35% smaller in width
- Indication—Increase safety and reduce downtime with built-in local indication
- Universal Mounting Holes—Simplify replacement with universal mounting options
- DIN Rail Mountable—Ease installation with a 35 mm hat DIN Rail mounting option
- One-Hand Release—Save time by using only one hand for a simple release from DIN Rail

## **Fuse Block Selection**

The following guidelines should help simplify the selection of proper fuse blocks:

**1. Determine the system voltage**—Since fuses are selected on the basis of system voltage, fuse blocks are selected to match the voltage rating of the fuse.

**2. Determine the design short-circuit current**—If available short-circuit current cannot be determined, or if it will vary with equipment location, select fuses with a 200,000 ampere interrupting rating (A.I.R.) and mating fuse blocks with a withstand rating of 200,000 amperes for maximum safety.

#### 3. Determine the type and ampere rating of the fuse

**to be used**—The fuse ampere rating, opening characteristics (fast acting or time-delay) and size are important considerations in fuse selection. Fuse blocks may be used with a fuse rated at the corresponding amperage rating or below. For example, a fuse block rated at 30 amperes may be used with a fuse rated from 0 to 30 amperes.

**4. Determine if NEC®, CSA, UL, or other requirements are applicable**—Any of these requirements should be obtained from the approving agency in advance of fuse and fuse block selection.

#### 5. Select the type of wire termination

Three types of wire termination are available:

- Screw*—for use with spade lugs or ring terminals
- Screw with Pressure Plate*—for use with solid or stranded wire without terminal. Recommended where vibration will be a factor
- Box Lug—for use with all types of solid wire and Class B and Class C stranded wire. The most durable, but not for use with welding cable or other rope-stranded conductors.

*¼" Quick Connect terminals are available on the Midget and Class CC fuse blocks.



#### 6. Decide on the number of poles in each block—The

number of poles for each set of fuses is determined by the characteristics of the circuit.

#### 7. Determine if block should be DIN Rail mounted—Many

of the new Littelfuse fuse blocks are DIN Rail mountable. Be sure to look to corresponding ordering tables to match the correct part number on the following product pages.

#### 8. Determine if fuse clips need to be reinforced

Fuse clips may have a tendency to lose some of their tension over a period of time. This may be prevented by specifying reinforced fuse clips.

## **Ordering Information**

The Littelfuse fuse block part number consists of the below skeleton. Please refer to UL Class Tables for specific information.



[†]These new fuse blocks replace previous Littelfuse fuse blocks that had very similar part numbers for customer convenience. The only change is an "F" has been added as the second character in the new block part numbers.

Caution: Littelfuse indicating fuse blocks are intended to quickly identify open fuses while power is still applied. Only qualified electrically trained technicians should replace fuses and follow standard OSHA and NFPA 70E safe work practices, such as Lock-Out and Tag-Out procedures and verification before replacing any fuses in indicating fuse blocks.



## LF SERIES INDICATING FUSE BLOCKS







DIN-Rail Mounting Eases Installation

**:**↑

Indication Improves Functionality

## An Indication of Value

The Littelfuse LF Series Fuse Blocks and Covers offer generous space savings and a greater value over previous generations. View the different series classes for available indication, snap-to-release DIN rail mounting, universal mounting holes and touch-safe covers.

600 V





## Ñ **Description**

The Littelfuse 600 V Class J blocks offer generous space savings and enhanced value over previous generations, such as indication, snap-to-release DIN rail mounting and universal mounting holes.

## **Features/Benefits**

- Space-saving design up to 45% smaller
- · Universal mounting holes for easy replacement
- Indication offered on all versions except 200-600 A
- One hand release from DIN rail for ferrule style fuses
- Reinforced fuse clips are standard on all Class J blocks
- Covers available for up to 100 A to enhance safety ٠

## **Ordering Information (Class J 600 V)**

## **Specifications**

Voltage Ratings	600 V
Ampere Ratings	0-600 A
Leakage Current	<0.6 mA at 600 V
Flammability Rating	UL94 V-0
Approvals	UL Listed (File: E14721)
	CSA Certified (File: LR7316)
Environmental	RoHS Compliant, Lead (Pb) Free

**Environmental** 

### **Recommended Fuses**

#### **Time Delav**

Series: JTD_ID	
Series: JTD	

#### Fast Acting

5	
Series: JLS	 22

### Web Resources

Download CAD drawings, fuse block cover datasheet and other technical information: littelfuse.com/lfj

		0	ORDERING NUMBER										z					
AMP	POLES	ES	ES	ES	ES	BASE	TERI	MINAL SUF	FIX	TORQUE	IINA	WIRE RANGE			BASE	DIN	ATIO	COVER
RATING		PART NUMBER	BOX LUG	PRESSURE PLATE	SCREW	TUNUUE	TRNINGE WIRE RANGE		WIKE TYPE		TEMP RATING	RAIL	INDICATION	ORDERING NUMBER*				
	1	LFJ600301	CID	PID	SID		С	6-14 AWG										
30	2	LFJ600302	CID	PID	SID	2.8 N-m (25 in-lbs)	Р	10-14 AWG	CU Only		125°C	•	•	LFJ60030FBC				
	3	LFJ600303	CID	PID	SID		S	10-22 AWG										
	1	LFJ600601	CID	—	—	5.6 N-m (50 in-lbs)		2-4 AWG										
60	2	LFJ600602	CID			2.8 N-m (25 in-lbs)		6-14 AWG	CU-AL		125°C	•	•	LFJ60060FBC				
	3	LFJ600603	CID	—	_					g								
	1	LFJ601001	CID	_	—	13.6 N-m (120 in-lbs)	2	2/0-6 AWG		Stranded								
100						4.5 N-m (40 in-lbs)		8 AWG	CU-AL	Stra	130°C	—	•	LFJ60100FBC				
	3	LFJ601003	CID	—	—	4.0 N-m (35 in-lbs)	1	0-14 AWG		Solid /								
200	1	LFJ602001	C	—	—	01.1 N (075 : Ib)				N N	130°C							
200	3	LFJ602003	С	—	—	31.1 N-m (275 in-lbs)	4	250 kcmil-6	CU-AL		130 6	_	_					
400	1	LFJ604001	С	_	—	21.1 N m (275 in lba)	(2)	250 komil 1/0			120°0							
400	3	LFJ604003	С	_	_	31.1 N-m (275 in-lbs)	(2)	350 kcmil-1/0	CU-AL		130°C	_	_					
600	1	LFJ606001	С	—	—	42.4 N m (27E in the)	(0)	E00 komil 4			120°C							
600	3	LFJ606003	С	_	_	42.4 N-m (375 in-lbs)	(2)	500 kcmil-4	CU-AL		130°C		_					

Note: Reinforcing springs standard on all Class J fuse blocks. *Covers sold individually. One cover needed for each pole.

## **CLASS J FUSE BLOCK DIMENSIONS**

## **Dimensions mm (inches)**

600 V 30 A





6

**Fuse Blocks and Holders** 



<b>-</b> —50.8 (2.00)— <b>-</b>
Verser

-81.2 (3.20)











## CLASS J FUSE BLOCK DIMENSIONS

## **Dimensions mm (inches)**

#### 600 V 200 A





-15.9 (.63)

#### 600 V 400 A







250 V • 600 V





## **D**escription

The Littelfuse Class R and H/K5 blocks offer many benefits such as indication, snap-to-release DIN rail mounting and universal mounting holes. Class H and Class R fuse blocks are dimensionally the same, but Class R blocks incorporate a rejection feature, which only allows Class R fuses to be inserted.

## **Features/Benefits**

- Universal mounting holes for easy replacement
- Indication offered on most 250 V and 600 V versions
- One hand release from DIN rail for ferrule style fuses
- Reinforced fuse clips are standard on all Class H and Class R fuse blocks
- Covers available for 100 A and lower to enhance safety

## Web Resources

Download CAD drawings, fuse block cover datasheet and other technical information: **littelfuse.com/lfr littelfuse.com/lfh** 

## Specifications

Voltage Rating	250 V, 600 V
Ampere Ratings	0-600 A
Leakage Current	<0.6 mA at 600 V
Withstand Rating	Class H: 10 kA RMS SYM Class R: 200 kA RMS SYM
Flammability Rating	UL94 V-0
Approvals	UL Listed (File: E14721) CSA Certified (File: LR7316)
Environmental	RoHS Compliant, Lead (Pb) Free

## **Recommended Fuses**

#### 250 – Class R Blocks

250 V – Class H / K5 Blocks	20
FLNR/FLNR_ID	
KLNR	
LLNRK	13

#### 600 V – Class R Blocks

LLSRK/LLSRK_ID
KLSR
IDSR
FLSR/FLSR_ID17
·

#### 

## Ordering Information (Class H 250 V)

	~	OR	DERINO	G NUMBER			IAL				BASE		NOI	COVER
AMP RATING	POLES	BASE PART NUMBER	BOX LUG	SUFFIX PRESSURE PLATE	SCREW			WIRE RANGE	WIRE	TYPE	TEMP RATING	DIN RAIL	INDICATION	ORDERING NUMBER*
	1	LFH250301	С	Р	S		С	6-14 AWG	]					
30	2	LFH250302	С	Р	S	2.8 N-m (25 in-lbs)	Р	10-14 AWG	CU Only		125°C	•	—	LFH25030FBC
	3	LFH250303	С	Р	S		S	10-22 AWG						
	1	LFH250601	CID	—	—	5.6 N-m (50 in-lbs)		2-4 AWG						
60	2	LFH250602	CID	—	—				CU-AL		125°C	•	•	LFH25060FBC
	3	LFH250603	CID		—	2.8 N-m (25 in-lbs)		6-14 AWG						
100	1	LFH251001	CID	—	—	13.6 N-m (120 in-lbs) 4.5 N-m (40 in-lbs)		2/0-6 AWG 8 AWG	CU-AL	Solid/	130°C		•	LFH25100FBC
100	3	LFH251003	CID	—	_	4.0 N-m (35 in-lbs)		10-14 AWG	CO-AL	Stranded	130 0			
200	1	LFH252001	С	_	_	21.1  N = (27E  in   ha)		2E0 komil 6	CU-AL		130°C			
200	3	LFH252003	С		_	31.1 N-m (275 in-lbs)		250 kcmil-6	GU-AL		130 6			
400	1	LFH254001	С	—	—	31.1 N-m (275 in-lbs)	(2)	350 kcmil-1/0	CU-AL		130°C			
400	3	LFH254003	С		_	31.1 N-III (273 III-ID8)	(2)	550 KCIIII-1/0	CO-AL		130 0			
600	1	LFH256001	С	—	—	42.4 N-m (375 in-lbs)		2) 500 kcmil-4	CU-AL		130°C			
000	3	LFH256003	С	_	_	42.4 11-111 (373 11-103)	(2	.) JUU KUIIII-4	UU-AL		100 0			

Note: Reinforcing springs standard on all Class H fuse blocks.

*Covers sold individually. One cover needed for each pole.



## Ordering Information (Class H 600 V)

		OR	DERIN	G NUMBER			AL				BASE	SNAP	CATION	COVER
AMP	ILES	BASE		SUFFIX		TORQUE	N	WIRE	WIRE TYPE		TEMP	TO	AT	ORDERING
RATING	PO	ORDERING NUMBER	BOX LUG	PRESSURE PLATE	SCREW		TERMINAL	RANGE			RATING	RELEASE	INDIC	NUMBER*
	1	LFH600301	CID	PID	SID		С	6-14 AWG						
30	2	LFH600302	CID	PID	SID	2.8 N-m (25 in-lbs)	Р	10-14 AWG	CU Only		130°C	•	•	LFH60030FBC
	3	LFH600303	CID	PID	SID		S	10-22 AWG						
	1	LFH600601	CID	—	—	5.6 N-m (50 in-lbs)	2	2-4 AWG						
60	2	LFH600602	CID	—	—				CU-AL		130°C	•	•	LFH60060FBC
	3	LFH600603	CID	—	—	2.8 N-m (25 in-lbs)		-14AWG						
100	1	LFH601001	CID	—	—	13.6 N-m (120 in-lbs)	-	/0-6AWG		Solid/	10000			
100	3	LFH601003	CID	_	_	4.5 N-m (40 in-lbs) 4.0 N-m (35 in-lbs)		8 AWG )-14 AWG	CU-AL	Stranded	130°C		•	LFH60100FBC
000	1	LFH602001	С	_	_						100%0			
200	3	LFH602003	С		_	31.1 N-m (275 in-lbs)	23	50 kcmil-6	CU-AL		130°C		-	—
400	1	LFH604001	С	—	_	21.1 N m (27E in the)	(2) 2	E0 komil 1/0	CU-AL		130°C			
400	3	LFH604003	С	—	_	31.1 N-m (275 in-lbs)	(2) 3	50 kcmil-1/0	UU-AL		130 6	_	<u> </u>	
600	1	LFH606001	С	—	—	42.4 N-m (375 in-lbs)	(2)	500 kcmil-4	CU-AL		130°C			
000	3	LFH606003	С	_	_	42.4 11-111 (373 111-108)	(2)	JUU KUIIII-4	CO-AL		130 0			

Note: Reinforcing springs standard on all Class H fuse blocks.

### **Ordering Information (Class R 250 V)**

	6	OR	DERIN	G NUMBER			IAL				BASE	SNAP	TION	COVER
AMP RATING	POLES	BASE ORDERING NUMBER	BOX LUG	SUFFIX PRESSURE PLATE	SCREW	TORQUE	TERMINAL	WIRE RANGE	WIRE	TYPE	TEMP RATING	TO RELEASE	INDICAT	ORDERING NUMBER*
	1	LFR250301	С	Р	S		С	6-14 AWG						
30	2	LFR250302	C	Р	S	2.8 N-m (25 in-lbs)	P	10-14 AWG	CU Only		125°C	•	—	LFH25030FBC
	3	LFR250303 LFR250601	CID	Р	S		S	10-22 AWG						
60	$\frac{1}{2}$	LFR250602	CID			5.6 N-m (50 in-lbs)		2-4 AWG	CU-AL		125°C	•		LFH25060FBC
00	3	LFR250603	CID		_	2.8 N-m (25 in-lbs)	6	-14 AWG	00712		120 0			211120000100
100	1	LFR251001	CID	—	—	13.6 N-m (120 in-lbs) 4.5 N-m (40 in-lbs)	2	/0-6 AWG 8 AWG	CU-AL	Solid/	130°C			LFH25100FBC
100	3	LFR251003	CID	—	_	4.0 N-m (35 in-lbs)	1	0-14 AWG	UU-AL	Stranded	130 0	_	•	
200	1	LFR252001	С	—	—	31.1 N-m (275 in-lbs)	2	50 kcmil-6	CU-AL		130°C			
200	3	LFR252003	С	—	—	31.1 14-111 (273 111-108)	2	JU KUIIII-U	GO-AL		130.0		_	
400	1	LFR254001	С	—	—	31.1 N-m (275 in-lbs)	(2) 3	50 kcmil-1/0	CU-AL		130°C	_		_
100	3	LFR254003	С	—	-		(2)0		00 ML		100 0			
600	1	LFR256001 LFR256003	C C			42.4 N-m (375 in-lbs)	(2)	500 kcmil-4	CU-AL		130°C	_	—	—

Note: Reinforcing springs standard on all Class R fuse blocks.

## Ordering Information (Class R 600 V)

AMP	LES	OR BASE	DERIN	G NUMBER SUFFIX		TORQUE	TERMINAL	WIRE	WIRE TYPE		BASE TEMP	SNAP TO	<b>ATION</b>	COVER ORDERING
RATING		ORDERING NUMBER	BOX LUG	PRESSURE PLATE	SCREW	TUNUUE	TERN	RANGE	VVIN	WINE THE		RELEASE	INDICA.	NUMBER*
	1	LFR600301	CID	PID	SID		С	6-14 AWG						
30	2	LFR600302	CID	PID	SID	2.8 N-m (25 in-lbs)	Р	10-14 AWG	CU Only		130°C	•	٠	LFH60030FBC
	3	LFR600303	CID	PID	SID		S	10-22 AWG						
	1	LFR600601	CID	—		5.6 N-m (50 in-lbs)		2-4 AWG						
F	2	LFR600602	CID	—		2.0 N			CU-AL		130°C	•	٠	LFH60060FBC
	3	LFR600603	CID	—	—	2.8 N-m (25 in-lbs)		6-14 AWG						
100	1	LFR601001	CID	—	—	13.6 N-m (120 in-lbs)	2	/0-6 AWG		Solid/	10000			
100	3	LFR601003	CID	_		4.5 N-m (40 in-lbs) 4.0 N-m (35 in-lbs)	1	8 AWG 0-14 AWG	CU-AL	Stranded	130°C	_	•	LFH60100FBC
	1	LFR602001	0	_			1	0-14 AVVG						
200	3	LFR602003	C C			31.1 N-m (275 in-lbs)	2	50 kcmil-6	CU-AL		130°C	—	—	—
100	1	LFR604001	C	_	_		(0) 0				10000			
400	3	LFR604003	C	_		31.1 N-m (275 in-lbs)	(2) 3	350 kcmil-1/0	CU-AL		130°C	-		
600	1	LFR606001	С	_	—	42.4 N-m (375 in-lbs)	(2)	500 kcmil-4	CU-AL		130°C			
000	3	LFR606003	С	_	_	42.4 N-III (373 III-IDS)	(2)	JUU KUIIII-4	UU-AL		130 0			

Note: Reinforcing springs standard on all Class R fuse blocks. *Covers sold individually. One cover needed for each pole.



## Dimensions mm (inches)



6

**Fuse Blocks and Holders** 



## **Dimensions mm (inches)**





## **Dimensions mm (inches)**





## **Dimensions mm (inches)**



6

**Fuse Blocks and Holders** 





## **Description**

The Littelfuse Class T fuse blocks offer many advantages such as space saving design, universal mounting holes, snap-to-release DIN rail mounts and available covers.

## **Features/Benefits**

- Space-saving design
- Universal mounting holes for easy replacement
- One hand release from DIN rail for 30-60 A fuses •
- Reinforced fuse clips are standard
- Covers available for most amperages to enhance safety

### **Ordering Information (Class T 300 V)**

### **Specifications**

Voltage Ratings	300 Vac/600 Vac
Ampere Ratings	0-600 A
Leakage Current	<0.6 mA at 600 V
Withstand Rating	200 kA RMS SYM
Flammability Rating	UL94 V-0
Approvals	UL Listed (File: E14721)
	CSA Certified (File: LR7316)
Environmental	RoHS Compliant, Lead (Pb) Free

Environmental

## **Recommended Fuses**

300 V JLLN	24
600 V JLLS	24

## Web Resources

Download CAD drawings, fuse block cover datasheet and other technical information: littelfuse.com/lft

		•			-		-								
	G			ORDI	ERING	NUMBE	R						TEMP	AIL	COVER
MP	E	BASE	SF POLES		;	TEI	RMINAL SU	FIX	TORQUE	WIRE	WI		μΞ	22	ORDERING
AMP	RA ⁻	ORDERING NUMBER	1	2	3	BOX LUG	PRESSURE PLATE	SCREW	Tonaol	RANGE	ΤY	PE	BASE RAT	DIN R/ MOUI	NUMBER*
3(	n	LFT30030	1	2	3	C			5.6 N-m (50 in-lbs)	2-4 AWG			125°C	•	LET30030EBC
0	0	LI 130030	,	2	5	L L			2.8 N-m (25 in-lbs)	6-14 AWG			123 0	•	LI 1300301DC
60	n	LFT30060	1	2	3	C			5.6 N-m (50 in-lbs)	2-4 AWG		p	125°C	•	LFT30060FBC
00	0	LI 130000	1	2	5	L L			2.8 N-m (25 in-lbs)	6-14 AWG		Stranded	123 0	•	LI 1300001 DC
									13.6 N-m (120 in-lbs)	2/0-6 AWG	CU-AL	itra			
10	00	LFT30100	1	—	3	CS	_	_	4.5 N-m (40 in-lbs)	8 AWG	S	/	130°C	—	LFT30100FBC
									4.0 N-m (35 in-lbs)	10-14 AWG		olid			
20	)0	LFT30200	1		3	CS	_	—	31.1 N-m (275 in-lbs)	250 kcmil-6		Š	130°C	—	—
40	00	LFT30400	1	_	3	CS	_	—	(2) 31.1 N-m (275 in-lbs)	250 kcmil-6			130°C		—
60	)0	LFT30600	1	—	3	CS	_	—	(2) 42.4 N-m (375 in-lbs)	500 kcmil-6			130°C	—	—

## **Ordering Information (Class T 600 V)**

	ے ORDERING NUMBER		IAL					GMP	≓⊨	COVER							
AMP RATING	BASE	F	POLES	S	TEF	RMINAL SUI	SUFFIX		SUFFIX		TORQUE	WIRE	WIRE			A N	ORDERING
BA	ORDERING NUMBER	1	2	3	BOX LUG	PRESSURE PLATE	SCREW	TORQUE TORQUE		RANGE	TYPI	-	BASE TEMP RATING	DIN RAIL MOUNT	NUMBER*		
20	1 5700000	1	2	0	0	р	0	С	2.5 N-m (25 in-lbs) 5.6 N-m (50 in-lbs)	6-14 AWG 2-4 AWG	CU-AL		105%0				
30	LFT60030	I	2	3	С	P	S	Р	2.8 N-m (25 in-lbs)	10-14 AWG	CU Only		125°C	•	LFT60030FBC		
								S	2.8 N-m (25 in-lbs)	10-22 AWG	CU Only	ъ					
60	LFT60060	1	2	3	С				5.6 N-m (50 in-lbs)	2-4 AWG		Stranded	125°C	•	LFT60060FBC		
00		1	2	5	U				2.8 N-m (25 in-lbs)	6-14 AWG		trar	120.0	•			
									13.6 N-m (120 in-lbs)	2/0-6 AWG							
100	LFT60100	1	—	3	CS	—	—		4.5 N-m (40 in-lbs)	8 AWG	CU-AL	Solid	130°C	—	LT60100FBC		
									4.0 N-m (35 in-lbs)	10-14 AWG	CC	S					
200	LFT60200	1	—	3	CS	-	—		31.1 N-m (275 in-lbs)	250 kcmil-6			130°C	—	LT60200FBC		
400	LFT60400	1	—	3	CS		—	(	2) 31.1 N-m (275 in-lbs)	250 kcmil-6			130°C	—	LT60400FBC		
600	LFT60600	1	—	3	CS	_	—	(	2) 42.4 N-m (375 in-lbs)	500 kcmil-6			130°C		LT60600FBC		

* Covers sold individually. One cover needed for each pole.



## **Dimensions mm (inches)**

300 V 30 A









300 V 60 A



300 V 100 A





## **Dimensions mm (inches)**



6

**Fuse Blocks and Holders** 



## **Dimensions mm (inches)**



#### 600 V 60 A







## **Dimensions mm (inches)**



480 V • 600 V



(h)	<b>(</b> )
-----	------------

ttelfuse

Answers Delivered



### Description

All Littelfuse Class G fuse blocks offer snap-to-release DIN rail mounting and universal mounting holes. Class G fuse blocks are designed for use with time-delay current limiting Class G fuses.

### **Features/Benefits**

- Universal mounting holes for easy replacement
- One hand release from DIN rail for most amperages
- Meet requirements for branch circuit protection

#### **Ordering Information** (Class G 600 V)

### **Specifications**

Voltage Ratings	
Ampere Ratings Flammability Rating Approvals	

600 Vac (0–20 A) 480 Vac (25–60 A) 0–60 A UL94 V-0 UL Listed (File: E14721) CSA Certified (File: LR7091)

### **Recommended Fuses**

Time Delay	
Series: SLC	26

### **Web Resources**

Download CAD drawings and other technical information: **littelfuse.com/lfg** 

-		
ġ		
4		
-		

AMP RATING		C		5.4.25		TERMINAL INFORMATION														
	MP TING	POLES	BASE PART NUMBER	BOX LUG	SUFFIX PRESSURE PLATE	SCREW	WIRE TYPE		BASE TEMP RATING	DIN RAIL MOUNT	TERMINAL	WIRE RANGE	TORQUE							
		1	LFG600151	CDINR	PQDINR	SQDINR		/ Strande	1 \			Box Lug	6-14 AWG	4.0 N-m (35 in-lbs)						
1	5	2	LFG600152	CDINR	PQDINR	SQDINR	1			1 \	150° C	150° C	150° C	$\sim$	g 150° C	150° C	•	Pressure Plate	10-14 AWG	2.3 N-m (20 in-lbs)
		3	LFG600153	CDINR	PQDINR	SQDINR					1 \	1 \				Screw	10-14 AWG	2.3 N-m (20 in-lbs)		
		1	LFG600201	CDINR	PQDINR	SQDINR									~	<u> </u>		Box Lug	6-14 AWG	4.0 N-m (35 in-lbs)
20	2	LFG600202	CDINR	PQDINR	SQDINR		Solid	150° C	•	Pressure Plate	10-14 AWG	2.3 N-m (20 in-lbs)								
		3	LFG600203	CDINR	PQDINR	SQDINR						Screw	10-14 AWG	2.3 N-m (20 in-lbs)						

## Ordering Information (Class G 480 V)

	POLES	ORDERING NUMBER				RΔ		BASE		TERMINAL INFORMATION								
AMP RATING		DLES	BASE		SUFFIX		WIRE TYPE		TEMP	DIN RAIL MOUNT								
NATING		PART NUMBER	BOX LUG	PRESSURE PLATE	SCREW		-	RATING	WOONT	TERMINAL	WIRE RANGE	TORQUE						
30	1	LFG480301	CDINR	PQDINR	SQDINR				g 150° C				Box Lug	6-14 AWG	4.0 N-m (35 in-lbs)			
	2	LFG480302	CDINR	PQDINR	SQDINR	CU Only	ded	150° C		•	Pressure Plate	10-14 AWG	2.3 N-m (20 in-lbs)					
	3	LFG480303	CDINR	PQDINR	SQDINR		Stranded			Screw	10-14 AWG	2.3 N-m (20 in-lbs)						
	1	LFG480601	CDINR	—	—		lid /				2-4 AWG	5.6 N-m (50 in-lbs)						
60	2	LFG480602	CDINR	—	_	CU/AI					125° C	125° C	125° C			•	Box Lug	
	3	LFG480603	CDINR	_	_						6-14 AWG	2.8 N-m (25 in-lbs)						



## **Dimensions mm (inches)**





40.9 (1.61)

İF

25.8 (1.02)

6.8 (0.27)

6.8 (0.27)

R2.3 (0.09)

TYP.

15.1 (0.59)

25.8 (1.02)

15.1 (0.59)

6.8 (0.27)

480 V 60 A

21.8 (0.86)

8.3 (0.33)

55.1 (2.17)

95.3 (3.75)

3.7 (0.15)



– 35.6 (1.40) –

— 59.9 (2.36) 44.9 (1.77) —

E

db

## LF SERIES CLASS CC/CD AND MIDGET (10X38 mm) FUSE BLOCKS

### 600 V



## Description

The Littelfuse Class CC, CD and midget blocks offer generous space savings and enhanced value. DIN rail mounting and universal mounting holes are available as well as an indication feature on all Class CD fuse blocks.

## **Features/Benefits**

- Space-saving design
- Universal mounting holes for easy replacement
- Indication offered on CD blocks
- One hand release from DIN rail optional
- Rejection feature that prevents the insertion of fuses with lower interrupting rating or voltage ratings
- Clip design reduces resistance and heat
- Non DIN Rail fuse blocks have interlocking feature allowing ganging for any number of poles
- Covers available for all amperages to enhance safety



Voltage Rating Ampere Ratings	600 Vac/dc L600M Midget (10x38): 30 A L600C Class CC: 30 A LFC Class CD: 60 A				
Dielectric strength	1200 V mi	nimum			
Material	Base: Thermoplastic Clip/Terminals: Copper alloy (tin plated) Box Lug: Copper Screw & Pressure Plate: Steel (zinc plated)				
Flammability Rating	UL94 V-0				
Approvals	L600M:	UL Recognized (File: E14721) CSA Certified (File: LR7316)			
	L600C:	UL Listed (File: E14721) CSA Certified (File: LR7316)			
	LFC:	UL Listed (File: E14721) CSA Certified (File: LR7316)			
Environmental	RoHS Cor	npliant, Lead (Pb) Free			

## **Recommended Fuses**

#### Class CC & CD

30
28
27

### Web Resources

Download CAD drawings, fuse block cover datasheet and other technical information: **littelfuse.com/fuseblocks** 

## Ordering Information (L600C Class CC and L600M Midget 30 A)

4 9	ŝ	CLASS CC ORDERING NUMBER		MIDGET ORDE	RING NUMBER	CONNECTOR		WIRE			BASE	COVER
AMP RATING	POLES	NON-DIN*	DIN-RAIL	NON-DIN*	DIN-RAIL	TYPE	TORQUE	RANGE	WIRE	TYPE	TEMP	ORDERING NUMBER [†]
	1	L60030C1C	L60030C1CDINR	L60030M1C	L60030M1CDINR		4.0 N-m (35 in-lbs)					
30	2	L60030C2C	L60030C2CDINR	L60030M2C	L60030M2CDINR	Box Lug				led	125°C	SPL001
	3	L60030C3C	L60030C3CDINR	L60030M3C	L60030M3CDINR		(00 11 103)					
	1	L60030C1PQ	L60030C1PQDINR	L60030M1PQ	L60030M1PQDINR	Duese une Diete	0.0 N		Only	Stranded		
30	2	L60030C2PQ	L60030C2PQDINR	L60030M2PQ	L60030M2PQDINR		2.3 N-m (20 in-lbs) 10-14 AWG	l o	/ Sti	125°C	SPL001	
	3	L60030C3PQ	L60030C3PQDINR	L60030M3PQ	L60030M3PQDINR	w/ c.o. forminar	(20 11 103)		CU	Solid /		
	1	L60030C1SQ	L60030C1SQDINR	L60030M1SQ	L60030M1SQDINR	0	0.0 N			So		
30	2	L60030C2SQ	L60030C2SQDINR	L60030M2SQ	L60030M2SQDINR	Screw w/Q.C. Terminal	2.3 N-m (20 in-lbs)	2.3 N-m 10-14 AWG			125°C	SPL001
	3	L60030C3SQ	L60030C3SQDINR	L60030M3SQ	L60030M3SQDINR	w/ c.o. forminar	(2011103)					

## **Ordering Information (LFC Class CD 60 A)**

	AMP RATING	POLES	ORDERING NUMBER	CONNECTOR TYPE	TORQUE	WIRE RANGE	WIR	E TYPE	BASE TEMP RATING	DIN RAIL MOUNT	INDICATION	COVER ORDERING NUMBER [†]						
	1	LFC600601CID		Box Lug	Box Lug													
	60	2	LFC600602CID			5.6 N-m (50 in-lbs)	2.8 N-m (50 in-lbs)		-	2-4 AVVG 6-14 AWG	2-4 AWG	CU-AL	Solid / Stranded	125°C	•	•	LFC60060FBC	
	3	LFC600603CID		2.0 IN-III (23 III-IDS)	0-14 AVVU	Stranded												

* Gangable

⁺ Covers sold individually. One cover needed for each pole.

## LF SERIES CLASS CC/CD AND MIDGET (10X38 mm) FUSE BLOCKS

## **Dimensions mm (inches)**

#### CLASS CC / MIDGET DIN RAIL 600 V 30 A





38.10





6

**Fuse Blocks and Holders** 













CLASS CD DIN RAIL 600 V 60 A











٩Ľ

## BOARD MOUNT MIDGET (10X38 mm) FUSE HOLDER

#### 600 V



## Description

The PC board-mounted midget fuse holder is a one-piece holder designed to provide a more robust and secure solution. It offers a smaller footprint and flexible mounting options.

For use with Midget-style fuses and fuse covers, it is UL Recognized and can be covered for additional protection.

## **Features/Benefits**

- Through hole PCB mounting
- Robust and secure block design
- All-in-one package offers easy installation
- Space saving footprint
- Touch Safe cover/puller available
- 3-pole configurations

## **Applications**

- HVAC market
- Industrial manufacturing
- Mass production facilities

## SPL001PCB Cover



## **Specifications**

Voltage Rating	600 Vac/dc
Amperage Rating	30 A
Approval	UL Recognized (File: E14721)
Mounting Method	Through hole solder/PCB

## **Ordering Information**

	CATALOG NUMBER	ORDERING NUMBER
Block	L60030M3PCB	L60030M3PCB
Cover*	SPL001PCB	SPL0001PCBT

*Covers are single pole—need to order a quantity of 3 for each block.

## **Recommended Fuses**

Midget (10 x 38 mm) series	
----------------------------	--

#### Web Resources

Download CAD drawings and other technical information: **littelfuse.com/fuseblocks** 

## Dimensions mm (inches)







## CLASS CC AND MIDGET FUSE BLOCK ACCESSORIES

## FBDIN1 Rail Adapter



### **Features/Benefits**

- DIN Rail adaptor for 30 A Midget, Class CC and Class G fuse blocks
- Patented design with no tools necessary for installation
- Permits snap-mounting of 30 A Midget, Class CC and Class G fuse blocks to standard and low profile 35 mm symmetrical DIN rails and 32 mm asymmetrical DIN rails
- Easy removal via disconnect tab

#### **Web Resources**

For additional technical information visit: **littelfuse.com/fbdin1** 

### **Dimensions Inches**







## **Recommended Fuse Blocks**

Midget-Style and Class CC Class G	
New DIN rail mountable fuse holders available on page 101	

### **Dimensions Inches**





## **Recommended Fuse Blocks**

L60030C	101
L60030M	101

#### Web Resources

For additional technical information visit: littelfuse.com/spl001

6

## SPL001 Cover Puller



## **Features/Benefits**

- 600 V ¹/₁₀-30 A Class CC and Midget fuse cover puller that offers increased protection when removing fuses
- Simple removal without the need for a separate puller
- Meets Dead Front requirements
- Easily gangable with 1/8" diameter wire
- For use with all 600 V Class CC and Midget  $^{1\!\!/_{10}}$  -30 A fuses
- Label provided for easy fuse identification



## LF SERIES FUSE BLOCK COVERS





### **Description**

Littelfuse fuse block covers protect personnel from accidentally coming into contact with energized parts. Covers are for use with Littelfuse LF Series UL class fuse blocks.

Contact the Littelfuse Tech-Line (800-TEC-FUSE) for block and cover compatibility questions.

## **Ordering Information**

## **Specifications**

Connection	Snap to fuse body				
Material	Black thermoplastic				
Flammability Rating	UL94 V-0				
Approvals	UL Listed (File: E184929)				
	CSA Certified				
	(File: 007316_0_000 Class 6225-01)				

### **Features/Benefits**

- Added safety to personnel
- Ventilation helps avoid fuse derating
- Reusable and convenient snap-on design
- UL listed and CSA certified
- Available for Class H/R, Class J, Class T and Class CD
- Allows visibility of LF series fuse block indicator

#### Web Resources

For dimensions, cad drawings and additional technical information visit: **littelfuse.com/fuseblocks** 

<b>UL CLASS</b>	FUSE BLOCK BASE PART NUMBER*	VOLTAGE	AMPERAGE	COVER ORDERING NUMBER		
Class H/R	LFH25030 / LFR25030	250	30	LFH25030FBC		
Class H/R	LFH25060 / LFR25030	250	60	LFH25060FBC LFH25100FBC		
Class H/R	LFH25100 / LFR25100	250	100			
Class H/R	ss H/R LFH60030 / LFR60030		30	LFH60030FBC		
Class H/R	LFH60060 / LFR60060	600	60	LFH60060FBC		
Class H/R	LFH60100 / LFR60100	600	100	LFH60100FBC		
Class J	LFJ60030	600	30	LFJ60030FBC		
Class J	LFJ60060	600	60	LFJ60060FBC		
Class J	LFJ60100	600	100	LFJ60100FBC ⁺		
Class T	LFT30030	300	30	LFT30030FBC		
Class T	LFT30060	300	60	LFT30060FBC		
Class T	LFT30100	300 100		LFT30100FBC		
Class T	LFT60030	600 30		LFT60030FBC		
Class T	Class T LFT60060		60	LFT60060FBC		
Class T	Class T LFT60100		100	LT60100FBC		
Class T	LFT60200	600 200		LT60200FBC		
Class T	LFT60400	600	400	LT60400FBC		
Class T	Class T LFT60600		600	LT60600FBC		
Class CD	LFC60060	600	60	LFC60060FBC		
Class CC	Class CC L60030C		30	SPL001		

* Part number shown excludes reference to number of poles and terminal type

t Cover is not compatible with 70-100 A JLS series fuses

## LPXV TOUCH-SAFE FUSE HOLDERS

1500 Vdc • 30 A





## Description

The Littelfuse LPXV fuse holder is designed to hold 1500 Vdc 10x85mm fuses.

## **Features/Benefits**

- Finger-Safe design offers personnel protection
- No fuse pullers or tools required for fuse removal
- 35 mm DIN Rail Mountable
- Compact design

## **Recommended Fuses**

## Web Resources

For additional technical informations, visit: **littelfuse.com/lpxv** 

## **Specifications**

Voltage Ratings
Amperage Rating
SCCR Rating
Fuse Type
Material
Flammability Rating
Temperature Stability
Approvals

30 A 15 kA 10x85mm Thermoplastic UL94 V-0 Body: 125° C Carrier: 140° C UL 4248-18 Listed (File: E345481) IEC 60269-1 & IEC 60269-2 RoHS compliant, Lead (Pb) free

1500 Vdc

Environmental

## **Dimensions Inches (mm)**





## **Ordering Information**

SERIES	VOLTAGE	POLES	CATALOG NUMBER	ORDERING NUMBER	PACK QTY	TERMINAL INFORMATION				
	VOLTAGE (Vdc)					TERMINAL TYPE	WIRE TYPE	NUMBER OF WIRES	WIRE SIZE	TORQUE
LPXV 1500		1500 1 1	LPXV001 LPXV0001Z				00° Mari	1	6-4 AWG (16-25 mm ² )	22-26 lb-in (2.5-3 N-m)
	1500			5	Box Lug	90° Max CU Only Stranded	1	18-8 AWG (.75-10 mm ² )	18-22 lb-in (2-2.5 N-m)	
							Stranueu	2*	18-6 AWG (.75-16 mm ² )	18-22 lb-in (2-2.5 N-m)

*Must be the same cross-sectioned size



Look for this logo to indicate products that are used in solar applications. Visit our website **littelfuse.com/solar** for the latest updates on approvals, certifications, and new products.
# LFJ1000 SERIES SOLAR FUSE BLOCKS

1000 Vdc • Clip-to-Box • Stud-to-Stud • Clip-to-Stud





# Description

The LFJ1000 series fuse block is specifically designed for the Littelfuse SPFJ 1000 V Solar Fuse. It meets UL electrical requirements, is available in multiple amperages, and comes in a variety of fuse mounting and termination configurations; fuse clip to box lug, fuse stud to wire stud and fuse clip to wire stud.

#### **Features/Benefits**

- Narrow width increases space savings
- Range of amperages to match all SPFJ fuse options
  Bay Lug termination at the assemmedators a wide
- Box Lug termination style accommodates a wide range of cable sizes
- Stud-mounted option increases convenience
- Approval for use with copper or aluminum lugs allowing for design flexibility

#### Ordering Information (Clip-to-Box Lug 1000 V)

AMPERAGE	ORDERING NUMBER	INTERRUPT RATING	WIRE RANGE STANDARD (METRIC)	WIR	E TYPE	RECOMMENDED TORQUE				
200	LFJ102001C	20 kA	250 kcmil - #6 (127mm ² - 16mm ² )			275 in-lb (31.1 N-m)				
400	LFJ104001C	10 kA	350 kcmil - 1/0 (177mm ² - 55mm ² )	Cu/Al	Solid/ Stranded	275 in-lb (31.1 N-m)				
450	LFJ104501C	20 kA	500 kcmil - #4 (253mm ² - 25mm ² )		otranada	375 in-lb (42.4 N-m)				

#### (Stud-to-Stud 1000 V)

AMPERAGE	ORDERING	INTERRUPT	RECOMMEN	DED TORQUE	MAX. BUSBAR	RECOMMENDED BASE TORQUE		
AWFENAGE	NUMBER	RATING	FUSE	TERMINAL	THICKNESS	BOLT SIZE	TORQUE	
200	LFJ102001STST	20 kA	65 in-lb (7.3 N-m)	200 in-lb (22.6 N-m)	.774" (19.66 mm)			
400	LFJ104001STST	10 kA	170 in-lb (19.2 N-m)	200 in-lb (22.6 N-m)	.555" (14.10 mm)	1/4" 5/16"	30-40 in-lb 40-50 in-lb	
450	LFJ104501STST	20 kA	300 in-lb (33.9 N-m)	300 in-lb (33.9 N-m)	.570" (14.18 mm)	6,10	10 00 11 15	

#### (Clip-to-Stud 1000 V)

AMPERAGE	ORDERING NUMBER	INTERRUPT RATING	RECOMMENDED TORQUE TERMINAL	MAX. BUSBAR THICKNESS	RECOMMENDED BASE TORQUE BOLT SIZE TORQUE		
	INUIVIDEN	NATINU	IENIVIINAL	INICKINESS	DULI SIZE	IUNUUE	
200	LFJ102001CST	20 kA	200 in-Ib (22.6 N-m)	.774" (19.66 mm)			
400	LFJ104001CST	10 kA	200 in-Ib (22.6 N-m)	.555" (14.10 mm)	1/4" 5/16"	30-40 in-lb 40-50 in-lb	
450	LFJ104501CST	20 kA	300 in-lb (33.9 N-m)	.570" (14.18 mm)	6, 10		

# Specifications

Voltage Katings
Ampere Ratings
Flammability Rating
Termination Type
Base Temp Rating
Approvals

Environmental

1000 Vdc 200, 400, 450 A UL94 V-0 Box Lug or Stud Mount 130° C UL 4248-18 Listed File: E345481 Vol. 1 RoHS Compliant

### **Recommended Fuses**

### **Web Resources**

Download CAD drawings, dimensions and other technical information: **littelfuse.com/LFJ1000** 



# LF SERIES SOLAR FUSE BLOCKS

# 1000 Vdc

# **Dimensions mm (inches)**

#### Clip-to-Box







200 A

400 A

#### 450 A

#### Stud-to-Stud



200 A



400 A



Clip-to-Stud









Look for this logo to indicate products that are used in solar applications. Visit our website littelfuse.com/solar for the latest updates on approvals, certifications, and new products.



(𝖳) (S͡ħ. IEC C € Rohs 🕅

# LFPHV DEAD FRONT 10x38mm (MIDGET) FUSE HOLDERS

# 1000 Vdc • 10x38mm





### Description

The Littelfuse LFPHV fuse holder is designed to house 1000 Vdc 10x38mm (midget style) fuses. It is not designed for load break but is ideal for isolating photovoltaic module strings for maintenance and meets UL requirements for 1000 Vdc solar fuse protection.

### **Features/Benefits**

- Finger-Safe design offers personnel protection
- Compact design
- 35 mm DIN Rail Mountable
- No fuse pullers or tools required for fuse removal
- Indication option available
- Approved for field wiring

#### Web Resources

Download technical documents: littelfuse.com/lfphv

### **Recommended Fuses**

SPF Solar Series	60
FLU Series (DC only)	31

# **Terminal Information**

TERMINAL TYPE	WIRE TYPE		NUMBER OF WIRES	WIRE SIZE	TORQUE					
5	Max Only	*pe	1	18-8 AWG (.7525 mm²)	18-22 lb-in (2-2.5 N-m)					
Pressure Plate	_	Stranded*	andi	ande	ande	ande	ande	1	6-4 AWG	22-26 lb-in
i idte	.06 CN		2†	18-6 AWG (.75 -10 mm ² )	18-22 lb-in (2-2.5 N-m)					

*Contact Tech-Line (800-TEC-FUSE) for other wire types. [†]Must be the same cross-sectioned size*

# Specifications

Voltage Ratings Ampere Rating SCCR Rating Power Acceptance Indication Voltage Range Terminal Type Material Flammability Rating Approval 1000 Vdc 30 A 33 kA 4W Maximum 400-1000 Vdc Pressure Plate Thermoplastic UL94 V-0, self-extinguishing UL Listed (File: E345481) CSA Certified IEC 60269 RoHS compliant, Lead (Pb) free

Environmental

# **Dimensions mm (inches)**

17.80 (0.701)









# Multi-Pole Assembly Kits

POLES	PINCER 0TY.	NIN OTY.	ASSEMBLY SETS	ORDERING NUMBER
2	20	10	10 pack	LFPHV2PAK
3	40	10	10 pack	LFPHV3PAK

Connector Pincer

_	

Handle Pin

# Ordering Information (LFPHV 10x38mm)

VOLTAGE	AMPERE	SCCR Rating	Si -		FUSE TYPE S		SERIES	NON-INDICATING		INDICATING		PACK								
VULIAGE			POI	FUSE LIPE	SERIES		ORDERING NUM.	CATALOG NUM.	ORDERING NUM.	QUANTITY										
	30 A	. 33 kA -								1		LFPHV	LFPHV001	LFPHV0001Z	LFPHV001ID	LFPHV0001ZXID	12			
1000 Vdc			2 1	10x38mm	LFPHV	LFPHV002	LFPHV0002Z	LFPHV002ID	LFPHV0002ZXID	6										
			33 KA	33 KA	33 KA	33 KA	33 KA	33 KA	33 KA	33 KA	33 KA	33 KA	3	(midget)	LFPHV	LFPHV003	LFPHV0003Z	LFPHV003ID	LFPHV0003ZXID	4
			4		LFPHV	LFPHV004	LFPHV0004Z	LFPHV004ID	LFPHV0004ZXID	3										

# LFPSC/LFPSM CLASS CC/MIDGET DEAD FRONT FUSE HOLDERS

# 600 Vac/dc



# Description

Littelfuse LFPSC Class CC and LFPSM 10x38mm dead-front holders feature optional LED indication, DIN rail mounts and a small space saving design. These high SCCR rated holders provide optimum touch-safe protection to personnel and have a large clamping range with dual wire rated terminals.

# **Features**

- Indicating and non-indicating options available ٠
- Dual LED indication distinguishes polarity in DC applications ٠
- Small compact design offers ultimate flexibility •
- 35 mm DIN-Rail Mountable •
- 1-, 2-, 3- and 4-pole configurations •
- ٠ Easy installation and fuse removal with no additional pullers or tools required

# Web Resources

Download technical documents at: littelfuse.com/lfpsc

# littelfuse.com/lfpsm

### **Recommended Fuses**

Class CC	27
Midget (10x38mm)	30

# **Terminal Information**

TERMINAL TYPE	WIRE TYPE				NUMBER OF WIRES	WIRE SIZE	TORQUE
		*	1	18-8 AWG	18-22 lb-in		
Drocouro	75° Max CU Only	eq		(.75-25 mm ² )	(2-2.5 N-m)		
Pressure Plate		Stranded*	1	6-4 AWG	22-26 lb-in		
Tidle		Stra	2†	18-6 AWG	18-22 lb-in		
			-	(.75-10 mm ² )	(2-2.5 N-m)		
*Contact Tach Line (000 TEC EUCE) for other wire types							

Contact Tech-Line (800-TEC-FUSE) for other wire types [†]Must be the same cross-sectioned size

# (UL) ( LEC C E ROHS M

17.80 (0.701)

Voltage Rating

**Specifications** 

**Ampere Rating** 

**SCCR Rating** 

**Power Acceptance Indication Voltage Range Terminal Type** Material **Flammability Rating** Approvals

UL: 600 Vac/dc IEC: 690 Vac (LFPSM) UL: 30 A IEC: 32 A (LFPSM) 200 kA (Class CC) 100 kA (Midget) 3W Maximum 110-690 Vac/dc Pressure Plate Thermoplastic UL94 V-0, self-extinguishing UL Listed (File: E14721) CSA Certified IEC 60269 (LFPSM) RoHS compliant, Lead (Pb) free

Environmental

# **Dimensions mm (inches)**









# **Multi-Pole Assembly Kits**

POLES	PINCER OTY.	PIN OTY.	ASSEMBLY SETS	ORDERING NUMBER
2	20	10	10 pack	LFPHV2PAK
3	40	10	10 pack	LFPHV3PAK

Connector Pincer

Handle Pin

# **Ordering Information (LFPSC Class CC and LFPSM Midget)**

VOLT	AGE	AMPERE		SCCR	SH FUSE TYPE		ES								NON-IND	DICATING	INDIC	ATING	РАСК				
UL	IEC	UL	IEC	Rating	POI	FUSETTE	SERIES	CATALOG NUM.	ORDERING NUM.	CATALOG NUM.	ORDERING NUM.	QUANTITY											
					1		LFPSC	LFPSC001	LFPSC0001Z	LFPSC001ID	LFPSC0001ZXID	12											
600		20 1	30 A — 200 kA	— 200 kA	— 200 kA	A — 200 kA	A 2001	200 // 4	— 200 kA	— 200 kA	— 200 kA	200 44	200 kA	200 kA	200 kA	2	Class CC	LFPSC	LFPSC002	LFPSC0002Z	LFPSC002ID	LFPSC0002ZXID	6
Vac/dc	ac/dc   30 A   200 KA						- 200 KA	200 KA				3	3	LFPSC	LFPSC003	LFPSC0003Z	LFPSC003ID	LFPSC0003ZXID	4				
					4	4	LFPSC	LFPSC004	LFPSC0004Z	LFPSC004ID	LFPSC0004ZXID	3											
					1		LFPSM	LFPSM001	LFPSM0001Z	LFPSM001ID	LFPSM0001ZXID	12											
600		690	690	690							2	10x38mm	LFPSM	LFPSM002	LFPSM0002Z	LFPSM002ID	LFPSM0002ZXID	6					
Vac/dc Vac 30 A 32 A		32 A 100 KA	30 A 32 A			32 A 100 KA	3	(Midget)	LFPSM	LFPSM003	LFPSM0003Z	LFPSM003ID	LFPSM0003ZXID	4									
								4		LFPSM	LFPSM004	LFPSM0004Z	LFPSM004ID	LFPSM0004ZXID	3								





### 600 Vac/dc



# Description

Littelfuse Class J POWR-SAFE Dead Front holders provide optimum protection to personnel and are UL Listed and CSA Certified.

# **Features**

- Indicating and non-indicating options available
- Dual LED indication distinguishes polarity in DC power applications
- Small compact design offers ultimate flexibility
- 35mm DIN Rail Mountable
- 1-, 2-, and 3-pole configurations
- Easy installation and fuse removal with no additional pullers or tools required

# **Dimensions Inches (mm)**



#### 60 Amp



Note: These dimensions are for reference only. Please contact factory for additional information.



600 Vac/Vdc

30 and 60 A

110 V - 600 V

Pressure Plate

Thermoplastic

Phillips / Slotted UL Listed (File: E14721)

**RoHS** compliant

CSA Certified (File: 2529839)

UL94 V-0

200 kA

.ittelfuse°

pertise Applied | Answers Delivered

# **Specifications**

Voltage Ratings Interrupting Rating Ampere Rating LEDs Terminal Type Material Flammability Rating Terminal Screws Approvals

#### Environmental

# **Ordering Information**

AMP	POLES	INDICATION	ORDERING NUMBER	PACK QTY.	WIRE TYPE	WIRE RANGE	TORQUE
	1	-	LFPSJ301.Z	6			
30	2	-	LFPSJ302.Z	3			
	3	-	LFPSJ303.Z	2		0.75mm ² – 1mm ² 1.5mm ² – 50mm ²	2.5 N-m 4.0 N-m
	1	•	LFPSJ301.ZXID	6		1.5mm ² – 50mm ² 18 – 1 AWG	35 lb-in
30	2	•	LFPSJ302.ZXID	3	-	10 17.000	0010111
	3	•	LFPSJ303.ZXID	2	Jabr		
	1	-	LFPSJ601.Z	6	Stranded		
60	2	-	LFPSJ602.Z	3	0)		
	3	-	LFPSJ603.Z	2		2.5mm ² – 50mm ²	4.0 N-m
	1	•	LFPSJ601.ZXID	6		14 – 1 AWG	35 lb-in
60	2	•	LFPSJ602.ZXID	3			
	3	٠	LFPSJ603.ZXID	2			

# Multi-Pole Assembly Kit

Kits are used to create multi-pole holders from 1-pole LFPSJ fuse holders. Please contact factory for more information.

Connector Pincer Handle Pin						
AMP	POLES	PINCER QUANTITY	PIN QUANTITY	ASSEMBLY SETS	ORDERING NUMBER	
30	2	30	10	10	LF3J2PAK	
30	3	60	10	10	LF3J3PAK	
60	2	30	10	10	LF6J2PAK	
60	3	60	10	10	LF6J3PAK	

# Web Resources

Download CAD drawings and other technical information: **littelfuse.com/lfpsj** 

# **Recommended Fuses**

Class J - JTD, JTD_ID, JLS ......21



# **POWR-BAR Distribution**





# Description

A key objective for panel designers is safe distribution of power to multiple fuse holders in a compact design. The Littelfuse UL 508 Listed bus bar system eliminates most wire terminations in a timesaving package. A power distribution block and associated conductors are no longer needed to feed multiple POWR-SAFE fuse holders.

### **Features/Benefits**

- Touch-safe design offers protection when replacing fuses •
- Compact design •
- 35 mm DIN Rail Mountable
- Available in one and three phase configurations
- No fuse pullers or tools required for fuse removal
- Can be cut down to optimal size

# **Recommended Fuse Holders**

LFPSM / LFPSC (600 Vac/dc)	110
LFPHV (1000 Vdc)	109

# Web Resources

Download CAD drawings, dimensions and other technical information: littelfuse.com/busbar

# **Specifications**

Voltage Ratings	600 Vac/dc 1000 Vdc*
Current Ratings	1000 100

v		
CROSS SECTION (mm ² )	18 mm ²	25 mm ²
END FED	80 A	100 A
CENTER FED	160 A	200 A
SCCR Conductor Pitch Approvals Environmental	10 kA, 100 kA [†] Copper 17.8 mm UL 508 Listed (File RoHS Compliant, L	

*1 Phase 18 mm² rated 1000 Vdc up to 160 A when center fed 1 Phase 25 mm² rated 1000 Vdc up to 200 A when center fed ¹ When protected directly upstream by Class J 175 amperes max

(18 mm² bus bar) and Class J 200 amperes max (25 mm² bus bar).

# **Ordering Information**

1 PHASE, 18 mm ²		LENGTH		1 PHASE, 25 n	nm²	m ² LENGTH	
ORDERING NUMBER	POLES	(mm)		ORDERING NUMBER	POLES	(mm)	
1PH3P18mm	3	50		1PH3P25mm	3	50	
1PH4P18mm	4	79		1PH4P25mm	4	79	
1PH6P18mm	6	104		1PH6P25mm	6	104	
1PH9P18mm	9	155		1PH9P25mm	9	155	
1PH12P18mm	12	208		1PH12P25mm	12	208	
1PH15P18mm	15	270		1PH15P25mm	15	270	
1PH57P18mm	57	1009		1PH57P25mm	57	1009	
3 PHASE, 18 r	nm²	LENGTH		3 PHASE, 25 n	1m²	LENGTH	
ORDERING NUMBER	POLES	(mm)		ORDERING NUMBER	POLES	(mm)	
3PH6P18mm	6	104		3PH6P25mm	6	104	
3PH9P18mm	9	158		3PH9P25mm	9	158	
3PH12P18mm	12	214		3PH12P25mm	12	214	
3PH15P18mm	15	266		3PH15P25mm	15	266	
3PH57P18mm	57	1009		3PH57P25mm	57	1009	

Endcaps are standard with all 3 phase configurations except 57-pole. Endcaps are not needed for the 1 phase configurations from the factory or if the copper bus is trimmed per the supplied instructions. Power feed lugs and protective covers are extra.

# **Accessories**

#### **Power Feed Lug**

PART NUMBER	AMP RATING	VOLTAGE (AC/DC)	WIRE RANGE	WIRE TYPE	TORQUE
BB17	115	1000	#10 - 1/0 AWG	CU	50 lb-in
BB18	115	1000	#10 - 1/0 AWG	CU	50 lb-in
BB19	115	1000	#10 - 1/0 AWG	CU	50 lb-in
BB20	115	1000	#10 - 1/0 AWG	CU	50 lb-in





BB19

EDCP42



BB17

Endcaps

PART NUMBER	PHASE	QUANTITY
EDCP42	Single	50
EDCP7	Three	50

BB18



PART NUMBER	QUANTITY
CTPT5	5





# LPSM QUICK CONNECT POWR-SAFE FUSE HOLDERS



# Description

NICA TO

The LPSM midget fuse holder series is a dead front design providing protection to personnel when installing and removing fuses. The compact fuse holder mounts quickly onto 35 mm DIN rail, decreasing panel layout and assembly time. This product has two Quick Connect terminals on both the top and bottom of the holder, offering an additional connection option. It is available in 1-, 2-, 3- and 4-pole configurations.

# **Features/Benefits**

- Dual ¼" Quick Connect Terminals on Top and Bottom of Holder
- Meets Dead Front requirements
- Mountable on 35 mm DIN Rail
- Neon Indication

# **Dimensions mm (inches)**





# Specifications

Voltage Rating	600 Vac/dc
Amperage Rating	30 A
Approval	UL Recognized (File No. E14721)
	CSA Certified (File No. LR7316)
	CCC Approved
Terminal Type	1/4" Quick Connect Terminals
Fuse Type	Midget (10 X 38 mm) series
Material	Thermoplastic
Flammability Rating	UL94 V-0
SCCR Rating	Same as Fuse Rating

# **Ordering Information**

POLES	CATALOG NUMBER	ORDERING NUMBER
1	LPSM001QCID	LPSM0001ZQCID
2	LPSM002QCID	LPSM0002ZQCID
3	LPSM003QCID	LPSM0003ZQCID
4	LPSM004QCID	LPSM0004ZQCID

# **Recommended Fuses**

### Web Resources

Download CAD drawings and other technical information: **littelfuse.com/lpsmqc** 

6



59.70 (2.35)

# 354 SERIES 3AG OMNI BLOCK®

# Molded Base Type Fuse Block





# **Dimensions Inches**



# **Description**

A low profile fuse block featuring individual barriers that reinforce the fuse clips while providing greater protection against clip damage and electrical shock. The unique design permits self-alignment of clips to fuse cap. This, plus a one-piece clip/terminal, assures low contact resistance.

# **Specifications**

Dielectric Strength	1500 V Minimum
Clip/Terminals	Tin-Plated Spring Brass; two different style clips can be supplied for circuit identity or polarization
Base	Glass reinforced Thermoplastic: Gray except anit-rotation series which is black
Flammability Rating	UL94 V-0
<b>Ambient Temperature</b>	-40°C to +85°C

# **Ordering Information**

CATALOG	TERMINALS	VOLTAGE	CURREN	T RATING
NUMBER	TERMINALS	VULIAGE	UL	CSA
354 000	Solder	300 V*	30 A	30 A
354 600	3/16" Q.C.	300 V	20 A	20 A
354 800	1/4″ Q.C.	300 V	20 A	20 A
354 900	1/4″ Q.C.	300 V	30 A	25 A
354 101-GY	P.C. Board	300 V	15 A	15 A

*30 A capability is based on temperature rise with #10 AWG wire properly soldered.

# **Recommended Fuses**

### Web Resources

For additional technical information visit: littelfuse.com

# **Technical Information**

SOLDER TYPE TERMINALS	3/16″ Q.C. TERMINALS⁺	1/4" Q.C. TERMINALS	1/4" Q.C. TERMINALS†	POLES	DIM "A"
354 001GY	354 601GY	354 801GY	354 901GY	1	.50″
354 002GY	354 602GY	354 802GY	354 902GY	2	1.12″
354 003GY	354 603GY	354 803GY	354 903GY	3	1.75″
354 004 GY	354 604GY	354 804GY	354 904GY	4	2.38″
354 005GY	354 605GY	354 805GY	354 905GY	5	3.00″
354 006GY	354 606GY	354 806GY	354 906GY	6	3.63″
354 007GY	354 607GY	354 807GY	354 907GY	7	4.25″
354 008GY	354 608GY	354 808GY	354 908GY	8	4.88″
354 009GY	354 609GY	354 809GY	354 909GY	9	5.50″
354 010GY	354 610GY	354 810GY	354 910GY	10	6.13″
354 011GY	354 611GY	354 811GY	354 911GY	11	6.75″
354 012GY	354 612GY	354 812GY	354 912GY	12	7.38″
354 021BL*	354 621BL*	354 821BL*	354 921BL*	1	.50″
354 101GY	—	—	—	1	.50″

* NEMA style* With Anti-Rotation Boss



# **FUSE PULLERS & POWR-JAW CLIP CLAMPS**

MFP • LPFP • GFP • 097023



# Features/Benefits

- Ergonomically designed fuse pullers designed to safely remove power fuses
- Molded design offers more comfortable and natural grip than traditional pullers, increasing performance

# **Specifications**

TYPE OF FUSE PULLER	PART NUMBER	FUSE SIZE (DIAMETER)
Midget Fuse	MFP	3⁄16" - ½" fuses
Pocket Fuse	LPFP	250 V fuses from 0-200 A 600 V fuses from 0-100 A %/6" - 1 ¹⁹ /32" fuses
Giant Fuse	GFP	250 V fuses from 61-600 A 600 V fuses from 61-400 A $1^{1}_{16}$ " - $2^{19}_{32}$ " fuses
Tri-puller	097023	For ATO, MINI and glass fuses

# Web Resources

For additional technical information visit: littelfuse.com/fusepullers

# **Ordering Information**

-			
CATALOG NUMBER	ORDERING NUMBER	VOLTS	AMPERES
LCC1	OLCC1	250	0-30
LCC2	OLCC2	250	35-60
LCC2	OLCC2	600	0-30
LCC4	0LCC4	600	35-60
LCC5	OLCC5	250 or 600	70-100
LCC6	OLCC6	250 or 600	110-200
LCC7	OLCC7	250 or 600	225-400
LCC8	OLCC8	250 or 600	450-600

Note: POWR-JAW Clip Clamps are sold individually, not in pairs.

A minimum of 1/8" of clearance between the fuse block barrier and fuse clip is required to install Clip Clamps.

# **Web Resources**

For additional technical information visit: littelfuse.com/clipclamps

# LCC Series POWR-JAW



# Features/Benefits

- Improve contact between fuse and clip
- Help prevent unnecessary heat from poor contact due to the loss of spring force. This reduces:
  - 1. Nuisance fuse opening
  - 2. Premature aging of surrounding components
- High temperature phenolic resin knob for durability
- Wide range of coverage with simple design

# LFFB SERIES LIMITER BLOCK/LHFB INLINE HOLDER

LFFB



# Dimensions mm (inches)





LHFB



# Description

The Littelfuse LHFB waterproof in-line fuse holder is ideal for harsh environments. The LHFB holder features the voltage and ampere rating molded into the body, along with a wire strip gauge. It also withstands solvents and vibration.

# **Features/Benefits**

- Waterproof in-line fuse holder for harsh environments
- One-piece molded thermoplastic body
- Bright green color offers high visibility
- Voltage and ampere rating molded into body

# Description

The LFFB003 fuse block is designed to accept CNN and CNL style limiter fuses. Applications include but are not limited to forklifts, golf carts and other low-voltage battery equipment. It is specifically designed for the HAZGARD[™] fuse but can be used for CNN/CNL fuses as well.

Э.L.

# **Specifications**

Voltage Rating	
Ampere Rating	
Approvals	
Construction	

150 Vac/Vdc 800 A UL Recognized (File: E14721) Base—Thermoplastic Studs—Steel Zinc Plated

# **Ordering Information**

CATALOG NUMBER	ORDERING NUMBER
LFFB003	LFFB0003Z

# Web Resources

Sample requests and other technical information: **littelfuse.com/lffb** 

# **Recommended Fuses**

CNL/CNN Cable limiter fuses	62
HAZGARD fuse	62

# **Specifications**

Voltage Rating	32 V
Ampere Rating	30 A
Fuses	1/4" x 11/4" fuses
Wire Size	Accepts #16 to #18 gauge wire
Operating Temperature	-20° C to 80° C

# Installation Instructions

- 1. Thread wire through fuse holder body
- 2. Strip wire insulation per strip gauge
- 3. Crimp wire to fuse clip*
- 4. Pull wire through and seat fuse clip in the holder body
- 5. Insert desired fuse type and rating
- 6. Snap holder body together

*Recommended crimping tools: Thomas & Betts No. WT-111M Note: Wire is not supplied with the holder.

### Web Resources

Sample requests and other technical information: **littelfuse.com/lhfb** 



# 571 & 572 SERIES PANEL-MOUNT FUSE HOLDERS

#### 571



### Description

Panel mount fuse holders are for Midget-Style and Class CC fuses. Class CC fuses have a rejection feature on one end cap, which mates with the rejection feature of Littelfuse Class CC fuses holders to prevent the installation of fuses with lower voltage ratings or interrupting ratings. Watertight version must be front panel mounted.

# **Dimensions Inches (mm)**



# **Ordering Information**



CATALOG/ORDERING NUMBER STANDARD WATERTIGHT			BOTTOM TERMINAL	FUSE LENGTH RANGE*	FOR USE WITH	
571027	05710027L	571027P	05710027LXP	Straight	NANGE"	Midget
571028	05710028L	571028P	05710028LXP	Rt. Angle	15⁄16" - 13⁄8"	Fuses
571007	05710007L	571007P	05710007LXP	Straight		Midget
571008	05710008L	571008P	05710008LXP	Rt. Angle	1 ¹³ /32" — 1 ¹ /2"	Fuses
5710CC	057100CCL	5710CCP	057100CCLXP	Straight	11/2″	Class CC
571RCC	05710RCCL	571RCCP	05710RCCLXP	Rt. Angle	1 172	Fuses

*Fuse diameter is 13/32"

Note: Contact factory for versions with pre-assembled wire leads.

### **Specifications**

Voltage Rating	600 V
Ampere Rating	30 A for Class CC and Midget fuses
<b>Dielectric Strength</b>	4000 V Minimum
Terminals	Tin-plated brass combination solder & quick-connect
O-Rings	901-184 (body), 901-260 (knob)
Molded Parts	Black thermoplastic
Approvals	UL Recognized (File: E14721)
	UL Recognized for branch circuit protection
	(5710CC/RCC)
	CSA Certified (File: LR7316)

### Web Resources

Additional technical inform

#### 572



### Description

The 572 series panel mount fuse holders are designed to minimize installation time. Its unique design incorporates a snap-mount feature that allows the holder to be installed without any tools or mounting hardware.

# **Dimensions Inches (mm)**



# **Ordering Information**

CATALOG/ORDERING NUMBER				BOTTOM	FUSE LENGTH	FOR USE
STANDARD WAT		ERTIGHT	TERMINAL	RANGE [†]	WITH	
572027	05720027L	572027P	05720027LXP	Straight	15/16" - 13/8"	Midget
572028	05720028L	572028P	05720028LXP	Rt. Angle	1716 - 178	Fuses
572007	05720007L	572007P	05720007LXP	Straight	1 ¹³ / ₃₂ " - 1 ¹ / ₂ "	Midget
572008	05720008L	572008P	05720008LXP	Rt. Angle	1.732 - 172	Fuses
5720CC	057200CCL	5720CCP	057200CCLXP	Straight	1½"	Class CC
572RCC	05720RCCL	572RCCP	05720RCCLXP	Rt. Angle	172	Fuses

†Fuse diameter is 13/32"

Note: Contact factory for versions with pre-assembled wire leads.

# **Specifications**

Voltage Rating	600 V
Ampere Rating	30 A for Class CC and Midget fuses
<b>Dielectric Strength</b>	4000 V Minimum
Terminals	Tin-plated brass combination solder & quick-connect
Molded Parts	Black thermoplastic
Approvals	UL Recognized (File: E14721)
	UL Recognized for branch circuit protection
	(5720CC/RCC) Class CC version
	CSA Certified (File: LR7316)
Mounting	Double "D" punch - Greenlee #61092
-	(14-18 gauge panel thickness recommended)

### Web Resources

Additional technical information: littelfuse.com/572

CE 🛞 🎝	RoHS	
nation: littelfuse.com/571		
er tilleu (File. El17510)		

# 342 SERIES 3AG (1/4" X 11/4") PANEL MOUNT FUSE HOLDERS

# **Traditional Panel Mount Type**



Straight Terminal Knurled Knob



**Right Angle** Terminal Fluted Knob

# **Description**

Panel Mount Fuse holders for 3AG (1/4" x 11/4") fuses. Both fluted and knurled knob terminal options are available.

# **Ordering Information**

#### **Straight Terminal**

FLUTE	) KNOB	KNURLE		
	ORDERING 1BER	CATALOG/ORDERING NUMBER		TERMINAL
342014A	03420014X	342012A	03420012X	Solder
342038A	03420038X	342058A	03420058X	³ /16″ Q.C.
342838A	03420838X	342858A	03420858X	1/4″ Q.C.

3/16" Q.C.

020

# **Specifications**

Flectrical



LICCUICUI	
Dielectric Strength	2400 V minimum
Mounting	Withstands 15 lb-in mounting torque; maximum panel thickness .187"
Molded Parts	Black thermoplastic (UL94 V-0)
Knob	Bayonet style with lettering
Terminals	Copper & copper alloy. Tin plated, except ¼" Quick-Connect terminals are nickel plated
Ambient Temperature	-40°C to +85°C

# **Recommended Fuses**

### Web Resources

Additional technical information available at: littelfuse.com/342

Solder

### **Right Angle Terminal**

FLUTED	) KNOB	KNURLE			
CATALOG/ORDERING NUMBER		CATALOG/ORDERING NUMBER		TERMINAL	
342004	03420004X	342022A	03420022X	Solder	
342028A	03420028X	342048A	03420048X	³ /16″ Q.C.	
342828	03420828X	342848A	03420848X	1⁄4″ Q.C.	

Straight Terminal **Fuse Blocks and Holders** 







**Dimensions** in inches



3/16" Q.C.

# 342 Series (Watertight Panel Mount Type)

Additional technical information available at: littelfuse.com/342

ŧ



# **Dimensions Inches**

Web Resources



MOUNTING HOLE .<u>570</u>" .575"

#### **Specifications** Flectrical

**Right Angle Terminal** 

**(SP**) Rated at 20 A for any voltage up to 250 V

1/4" Q.C.

	hated at 20 A for any voltage up to 250 v
Dielectric Strength	1500 V minimum
Mounting	Withstands 15 lb-in mounting torque; maximum panel thickness is .250"
Molded Parts	Black thermoset (UL94 V-0)
Knob	Screw type
Seal	O-ring provides a watertight seal on the front side of the panel per MIL-PRF-19207
Terminals	Copper & copper alloy. Tin plated. Solder type
Ambient Temperature	-40°C to +85°C
Hardware	O-rings (2) and hex nut, unassembled

# **Ordering Information**

CATALOG NUMBER	ORDERING NUMBER
342006A	0342006ZXA

# **Recommended Fuses**



Po

RoHS

# 345 SERIES PANEL MOUNT FUSE HOLDERS

# International Shock-Safe Panel Mount Type

# **Description**

Designed to eliminate electrical shock as defined by IEC standards 60065 and 60127, these panelmount fuses holders offer a wide variety of options. This allows for inventory reduction and versatility.

# **Features/Benefits**

- Anti-tease feature eliminates • circuit interruption when knob is accidentally depressed
- Five fuse holder types for maximum flexibility
- Two knob styles screwdriver slot and fingergrip
- Drip proof option available on screwdriver slot knob style
- Two terminal choices depending on application

### Web Resources

For more informations, visit: littelfuse.com/shocksafe

### **Recommended Fuses**

**Ordering Information** 

Glass / Electronic Fuses	
--------------------------	--







#### **Specifications** Insul

Insulation Resistance	10,000 megaohm minimum at 500 Vdc
Contact Resistance	Less than .005 ohm average at currents up to 1 A
Mounting	Threaded styles withstand 15 in-lb mounting torque Profile panel thickness .032" min/310" max. Quick mount panel thickness .012" min/360" max. Rear mount panel thickness.012" min/260" max.
Body Material	Black glass-filled thermoplastic (UL94 V-0)
Knob Material	Grey, blue or black glass-filled thermoplastic (UL94 V-0)
Hex Nut Material	Black glass-filled thermoplastic
Knob	Finger-Grip, Fuse Extractor type or Screwdriver Slot, Fuse Extractor type with plated copper alloy insert Plated copper alloy contact clips. Spring loaded, locking mechanism provides an anti-
	tease feature and will not vibrate loose
Terminals	Copper alloy, Tin-plated
<b>Ambient Temperature</b>	-40°C to +85°C
Hardware	Threaded style fuse holders are supplied with a thermoplastic hex nut unassembled
	Quick mount style fuse holders are supplied with a push-on type retaining nut, black oxide finish, unassembled
	A synthetic rubber O-ring will be supplied only with the screwdriver slot knob when the drip-proof version is requested

AGENCY APPROVAL	FILE NUMBER	3AG	5 X 20 mm	2AG
UL	E75961	20 A 250 V	10 A 250 V	10 A 250 V
CSA	LR91788	20 A 250 V	10 A 250 V	10 A 250 V
VDE	116895E	10 A 250 V	10 A 250 V	—

Note: To order with a metal internal tooth lockwasher (L) and/or neoprene panel washer (N) and/or drip-proof synthetic rubber "O" ring with Neoprene washer (NP) [Screwdriver slot knob only], add the appropriate suffix (L, N, or NP) respectively.

Please refer to Technical Application Guide section for information on proper fuse holder de-rating.



# LSCR SERIES HIGH-SPEED FUSE BLOCKS

700 Vac/dc • 1-800A



# **Specifications**

Voltage Rating	LSCR001: 700 V LSCR002: 700 V
Ampere Ratings	LSCR001: 1 – 400 A capacity LSCR002: 70 – 800 A capacity
Approvals	UL Recognized (File: E14721), CSA Certified (File: 73160)
Stud Size	LSCR001: ¼-20 thread (Torque 61 in-lbs) LSCR002: ¾-16 thread (Torque 192 in-lbs)
Material	Base: Molded phenolic. 150° C temperature rating Terminal Construction: Plated steel. Supplied with nut and belleville washer
Environmental Country of Origin	RoHS Compliant China

# **Description**

The LSCR Series are modular fuse blocks designed to accommodate a wide range of High-Speed and Class T fuses.

# **Features/Benefits**

- Modular design reduces inventory requirements
- Sold in pairs for convenience •
- Constructed of molded phenolic (with plated steel studs) ٠

# **Dimensions mm (Inches)**



# **Recommended Fuses**

High-Speed and Class T fuses. See tables below.

#### LSCR001 High-Speed Fuse Block Selection Guide

FUSE SERIES	AMPERE RATINGS
L15S	70-400
L17T	70-250
L25S	35-200
L50S	35-200
L60S	35-200
L70S	35-100
KLC	35-60
JLLN	70-200
JLLS	70-200

#### LSCR002 High-Speed Fuse Block Selection Guide

FUSE SERIES	AMPERE RATINGS
L15S	500-800
L17T	300-800
L25S	225-800
L50S	225-800
L60S	225-800
L70S	125-800
KLC	70-800
JLLN	225-800
JLLS	225-800

# Web Resources

For more information, visit: littelfuse.com/lscr

# **1LFS SERIES HIGH-SPEED FUSE BLOCKS**

600V • 1-400 A



۶Ľ



# **Specifications**

Voltage Rating Ampere Range Approvals Material 600 V 1 – 400 A UL Recognized E14721 **Base:** 150° C general purpose phenolic **Terminal:** Tin plated aluminum

### Web Resources

Download CAD drawings and other technical information: littelfuse.com/llfs

# Description

Littelfuse modular style semiconductor fuse blocks accommodate a wide range of semiconductor fuses. Blocks are provided in pairs with fuse mounting hardware.

### **Features/Benefits**

- Modular design reduces inventory requirements
- Sold in pairs for convenience
- Constructed of general purpose phenolic (with tin plated aluminum terminations)

# **Ordering Information**

CATALOG NUMBER	AMPERE RATING	WIRE RANGE	WIRE RATING	APPROVALS
1LFS101	100 A	#2/0 - 14 CU/AL	120 in-lbs	UL Recognized
1LFS102	400 A	250MCM - #6 CU/AL	275 in-lbs	UL Recognized

# **Recommended Fuses**

#### 1LFS101

FUSE SERIES	AMPERE RATINGS
L15S	70-100
L25S	35-100
L50S	35-100
L60S	35-100
KLC	1-100

#### 1LFS102

# **Dimensions Inches (mm)**

#### 1LFS101



#### 1LFS102



### Distribution Blocks • Splicer Blocks • Covers





# Description

POWR-BLOKS[™] power distribution blocks offer a safe, convenient way of splicing cables, providing a fixed junction tap-off point or splitting primary power into secondary circuits. Lx2xxx-DIN series offers integral DIN-Rail mount and an optional hinged safety cover.

Optional power distribution block covers provide protection against accidental shorting between poles caused by loose wires, tools, or other conductive material. They also protect personnel from accidentally contacting energized connectors. To order protective covers, match the number of poles for the block to the cover.

# Applications

Typical applications include heating, air conditioning and refrigeration systems, elevator systems, material handling equipment, control panels, motor controls, switchgear, and anywhere power needs to be distributed to more than one load.

# Connectors

Box lug connectors are designed for use with a single, solid or class B or C stranded conductor. Use of more than one conductor per connector opening or use of extra-flexible, fine-stranded conductors, such as welding cable, voids the UL Listing and may cause overheating. Manufacturers of cable terminations can furnish crimp-on sleeves for fine stranded conductors which permit these conductors to be used with box lugs.

# **Ampere Ratings**

The ampere rating per pole for power distribution blocks is based on the line ampacity of 75°C insulated conductors per NEC® Table 310.15 (b)(16).* If 60°C insulated conductors are used, load must not exceed the ampacity of 60°C conductors. Use of conductors rated in excess of 75°C is permitted (for example 90°C), however, load must not exceed the ampacity of 75°C conductors.

# **Specifications**

Voltage Rating	600 V
Current Rating	Based on NEC Table 310.16, using 75°C copper wire
Material	Phenolic rated at 150°C and Thermoplastic rated at 125°C (LD1400 and LS1300 series only)
Connector	Standard: Highly conductive aluminum, tin plated
	Copper: Highly conductive copper, tin plated
Flammability Rating	UL94 V-0
Approvals	UL Recognized - LD/LS Series (File: E171395) LFD/LFS Series (File: E309688)
	CSA Certified - LD/LS Series (File: LR700111) LFD/LFS Series (File: 007316 0 000)
Environmental	RoHS compliant, Lead (Pb) free

# **Ordering Information**

See Selection Guide on next pages

# Web Resources

For technical information, visit: **littelfuse.com/powrbloks** 

#### **Hinged Plastic Covers**

CATALOG/ ORDERING NUMBER	FOR USE WITH DISTRIBUTION/SPLICER BLOCK NO.	POLES
0LCH1321Z	LD2xxx-1DIN / LS2xxx-1DIN	1
0LCH1322Z	LD2xxx-2DIN / LS2xxx-2DIN	2
0LCH1323Z	LD2xxx-3DIN / LS2xxx-3DIN	3

Note: Optional hinged covers snap on to blocks.

### **Clear Plastic Covers**

CATALOG/ ORDERING NUMBER	FOR USE WITH DISTRIBUTION/SPLICER BLOCK NO.	POLES						
LPBC02	LPBC02 LD0xxx-2 / LS0xxx-2							
LPBC03	LFD0xxx-3 / LD0xxx-3 / LS0xxx-3	3						
LPBC21	LD2xxx-1 / LS2xxx-1	1						
LPBC22	LD2xxx-2 / LS2xxx-2	2						
LPBC23	LFD2xxx-3 / LD2xxx-3 / LFS2xxx-3 / LS2xxx-3	3						
LPBC31	LD3xxx-1 / LS3xxx-1	1						
LPBC32	LD3xxx-2 / LS3xxx-2	2						
LPBC33	LFD3xxx-3 / LD3xxx-3 / LS3xxx-3	3						
LPBC41	LD4xxx-1 / LS4xxx-1	1						
LPBC42	LD4xxx-2 / LS4xxx-2	2						
LPBC43	LD4xxx-3 / LS4xxx-3	3						
LPBC51	LD5xxx-1 / LS5xxx-1	1						
LPBC52	LD5xxx-2 / LS5xxx-2	2						
LPBC53	LFD5xxx-3 / LD5xxx-3 / LS5xxx-3	3						

Note: For installation of optional clear plastic covers, use the screws provided with each cover.

# *Formerly table 210.16



# **Distribution Block Selection Guide**

AMP RATING	ES	CTOR RIAL		LINE CONNECTION LOAD CONNECTION							JRE	CATALOG/
PER POLE	POLES	CONNECTOR MATERIAL	CONNECTOR	OPENINGS PER POLE	LUG TYPE	WIRE RANGE	CONNECTOR	OPENINGS PER POLE	LUG TYPE	WIRE RANGE	FIGURE	ORDERING NUMBER
115	1			1	Slotted	#2 - #14	_ <b>32132</b> -3	4	Slotted	#10 - #18	2	0LD14001Z
115	2	AL		1	Slotted	#2 - #14		4	Slotted	#10 - #18	2	0LD14002Z
<u>115</u> 115	3			1	5/32" Hex Slotted	#2 - #14 #2 - #14	00	4	5/64" Hex Slotted	#10 - #18 #10 - #18	2	LFD14003Z 0LD14004Z
				1								
175	2	AL		1	5/16" Hex	2⁄0 - #14		6	Slotted	#4 - #14	1	0LD04012Z
175	3	,		1	3/16" Hex	2⁄0 - #14	000	6	1/8" Hex	#4 - #14	1	LFD04013Z
175	2	AL		1	5/16" Hex	2⁄0 - #14		4	Slotted	#4 - #14	1	0LD04022Z
175	3	7.12		1	5/16" Hex	2⁄0 - #14	00	4	Slotted	#4 - #14	1	0LD04023Z
310	2			1	5/16" Hex	350mcm - #6		6	Slotted	#4 - #14	1	0LD04042Z
310	3	AL		1	5/16" Hex	350mcm - #6	000	6	Slotted	#4 - #14	1	0LD04043Z
175	1			1	5/16" Hex	2⁄0 - #14		4	1/8" Hex	#4 - #14	3	0LD25701Z
175	2	AL		1	3/16" Hex	2/0 - #14		4	1/8" Hex	#4 - #14	3	LFD25702Z
175	3	712		1	3/16" Hex	2/0 - #14		4	1/8" Hex	#4 - #14	3	LFD25703Z
175	1			1	3/16" Hex	2/0 - #14		4	Slotted	#4 - #14	3	0LD29701Z
175	2	CU		1	3/16" Hex	2/0 - #14		4	Slotted	#4 - #14	3	0LD29702Z
175	3	00		1	3/16" Hex	2/0 - #14		4	Slotted	#4 - #14	3	0LD29703Z
335	1			1	5/16" Hex	400mcm - #6		4	Slotted	#2 - #14	5	0LD35521Z
335	2	AL		1	5/16" Hex	400mcm - #6		4	Slotted	#2 - #14	5	0LD35522Z
380	3	AL		1	3/8" Hex	500mcm - #6		4	5/32" Hex	#2 - #14	5	LFD35523Z
335	1			1	5/16" Hex	400mcm - #6		6	Slotted	#2 - #14	5	0LD35531Z
335	2	AL		1	5/16" Hex	400mcm - #6	000	6	Slotted	#2 - #14	5	0LD35532Z
380	3	AL		1	3/8" Hex	500mcm - #6		6	5/32" Hex	#2 - #14	5	LFD35533Z
350	1			2	5/16" Hex	2/0 - #14		6	Slotted	#4 - #14	5	0LD35551Z
350	2	AL		2	5/16" Hex	2/0 - #14	000	6	Slotted	#4 - #14	5	0LD35552Z
350	3	AL		2	3/16" Hex	2/0 - #14	000	6	1/8" Hex	#4 - #14	5	LFD35553Z
380	1			1	Slotted	500mcm - #4		6	5/32" Hex	#2 - #14	5	0LD39531Z
380	2	CU		1	Slotted	500mcm - #4	000	6	5/32" Hex	#2 - #14	5	0LD39532Z
380	3	00		1	Slotted	500mcm - #4	000	6	5/32" Hex	#2 - #14	5	0LD39533Z
350	1			2	Slotted	2/0 - #14		6	1/8" Hex	#4 - #14	5	0LD39551Z
350	2	CU		2	Slotted	2/0 - #14	000	6	1/8" Hex	#4 - #14	5	0LD39552Z
350	3	00		2	Slotted	2/0 - #14		6	1/8" Hex	#4 - #14	5	0LD39553Z
380	1			1	Slotted	500mcm - #4		6	Slotted	#2 - #14	6	0LD45511Z
380	2	AL		1	Slotted	500mcm - #4	000	6	Slotted	#2 - #14	6	0LD45512Z
380	3	/ (L		1	Slotted	500mcm - #4	000	6	Slotted	#2 - #14	6	0LD45513Z
335	1			1	Slotted	400mcm - #6		8	Slotted	#2 - #14	6	0LD45601Z
335	2	AL		1	Slotted	400mcm - #6	0000	8	Slotted	#2 - #14	6	0LD45602Z
335	3	7.12		1	Slotted	400mcm - #6	0000	8	Slotted	#2 - #14	6	0LD45603Z
380	1			1	Slotted	500mcm - #4	- <b></b>	12	Slotted	#2 - #14	7	0LD55521Z
380	2	AL		1	Slotted	500mcm - #4	000000	12	Slotted	#2 - #14	7	0LD55522Z
380	3	7.12		1	3/8" Hex	500mcm - #4	000000	12	5/32" Hex	#2 - #14	7	LFD55523Z
380	1			1	3/8" Hex	500mcm - #4	<b></b>	6	5/16" Hex	2⁄0 - #14	7	0LD55791Z
380	2	AL		1	3/8" Hex	500mcm - #4	000	6	5/16" Hex	2/0 - #14	7	0LD55792Z
380	3	7.12		1	3/8" Hex	500mcm - #4	000	6	3/16" Hex	2/0 - #14	7	LFD55793Z
760	1			2	3/8" Hex	500mcm - #4		8	5/16" Hex	2/0 - #14	7	0LD55861Z
760	2	AL		2	3/8" Hex	500mcm - #4	0000	8	5/16" Hex	2/0 - #14	7	0LD55862Z
760	3			2	3/8" Hex	500mcm - #4	0000	8	3/16" Hex	2/0 - #14	7	LFD55863Z
665	1			1	3/8" Hex	500mcm - #4		4	Slotted	2/0 - #14	7	0LD55871Z
665	2	AL		1	3/8" Hex	350mcm - #6 500mcm - #4		4	Slotted	2⁄0 - #14	7	0LD55872Z
		AL		1		350mcm - #6 500mcm - #4	0000					
665 Note: AL = 7	3	num / 011	Connor	1	3/8" Hex	350mcm - #6		4	Slotted	2⁄0 - #14	7	0LD55873Z
NULE. AL =	ruuiiili	iuiii / 603	– оорреі									

© 2015 Littelfuse POWR-GARD® Products Catalog

# **Distribution Block Selection Guide**

AMP RATING	ES	ECTOR	LINE CONNECTION LOAD CONN			OAD CONNECTION			CATALOG/			
PER POLE	POLES	CONNECTOR MATERIAL	CONNECTOR	OPENINGS PER POLE	LUG TYPE	WIRE RANGE	CONNECTOR	OPENINGS PER POLE	LUG TYPE	WIRE RANGE	FIGURE	ORDERING NUMBER
760	1		┌╴══╴══╶┐	2	3/8" Hex	500mcm-#4		12	Slotted	#4 - #14	7	0LD55921Z
760	2	AL		2	3/8" Hex	500mcm-#4		12	Slotted	#4 - #14	7	0LD55922Z
760	3			2	3/8" Hex	500mcm-#4		12	1/8" Hex	#4 - #14	7	LFD55923Z
380	1			1	3/8" Hex	500mcm-#4		8	5/32" Hex	#2 - #14	7	0LD55941Z
380	2	AL		1	3/8" Hex	500mcm-#4	0000	8	5/32" Hex	#2 - #14	7	0LD55942Z
380	3			1	3/8" Hex	500mcm-#4	0000	8	5/32" Hex	#2 - #14	7	0LD55943Z
760	1		┍╼═╼═╴┐	2	3/8" Hex	500mcm-#4		8	3/16" Hex	2⁄0 - #14	7	0LD59861Z
760	2	CU		2	3/8" Hex	500mcm-#4	0000	8	3/16" Hex	2⁄0 - #14	7	0LD59862Z
760	3			2	3/8" Hex	500mcm-#4	0000	8	3/16" Hex	2⁄0 - #14	7	0LD59863Z
760	1			2	3/8" Hex	500mcm-#4		12	Slotted	#2 - #14	7	0LD59921Z
760	2	CU		2	3/8" Hex	500mcm-#4	000000	12	Slotted	#2 - #14	7	0LD59922Z
760	3			2	3/8" Hex	500mcm-#4	[000000]	12	Slotted	#2 - #14	7	0LD59923Z
175	1		_	1	3/16" Hex	2⁄0 - #14		4	1/8" Hex	#4 - #14	4	0LD25701ZXDIN
175	2	AL		1	3/16" Hex	2⁄0 - #14		4	1/8" Hex	#4 - #14	4	0LD25702ZXDIN
175	3	AL		1	3/16" Hex	2⁄0 - #14		4	1/8" Hex	#4 - #14	4	0LD25703ZXDIN
175	Adder			1	-	2⁄0 - #14		4	-	#4 - #14	4	0LD2570AZXDIN
175	1		_	1	5/16" Hex	2⁄0 - #14	┎═══	6	1/8" Hex	#4 - #14	4	0LD25801ZXDIN
175	2	AL		1	5/16" Hex	2⁄0 - #14		6	1/8" Hex	#4 - #14	4	0LD25802ZXDIN
175	3	AL		1	5/16" Hex	2⁄0 - #14		6	1/8" Hex	#4 - #14	4	0LD25803ZXDIN
175	Adder			1	5/16" Hex	2⁄0 - #14		6	1/8" Hex	#4 - #14	4	0LD2580AZXDIN
175	1		_	1	3/16" Hex	2⁄0 - #14		4	Slotted	#4 - #14	4	0LD29701ZXDIN
175	2	CLL		1	3/16" Hex	2⁄0 - #14		4	Slotted	#4 - #14	4	0LD29702ZXDIN
175	3	CU		1	3/16" Hex	2⁄0 - #14		4	Slotted	#4 - #14	4	0LD29703ZXDIN
175	Adder			1	-	2⁄0 - #14		4	_	#4 - #14	4	0LD2970AZXDIN

Note: AL = Aluminum / CU = Copper

# Hinged Plastic Covers

# **Clear Plastic Covers**







# Splicer Block Selection Guide

AMP RATING	POLES	CONNECTOR MATERIAL		LINE CONNECTION			LOAD CONNECTION				FIGURE	CATALOG/ ORDERING
PER POLE	POI	CONN	CONNECTOR	OPENINGS PER POLE	LUG TYPE	WIRE RANGE	CONNECTOR	OPENINGS PER POLE	LUG TYPE	WIRE RANGE	FIGI	NUMBER
310	2	AL		1	5/16" Hex	350mcm-#6		1	5/16" Hex	350mcm-#6	1	0LS03032Z
310	3	AL		1	5/16" Hex	350mcm-#6		1	5/16" Hex	350mcm-#6	1	0LS03033Z
115	1			1	Slotted	#2 - #14		1	Slotted	#2 - #14	2	0LS13001Z
115	2	AL		1	Slotted	#2 - #14		1	Slotted	#2 - #14	2	0LS13002Z
115	3	AL		1	5/32" Hex	#2 - #14		1	5/32" Hex	#2 - #14	2	LFS13003Z
115	4			1	Slotted	#2 - #14		1	Slotted	#2 - #14	2	0LS13004Z
150	1		₋₽₽	1	3/16" Hex	1⁄0 - #18	┍╼══╾┑	1	3/16" Hex	1⁄0 - #18	3	0LS21211Z
150	2	CU		1	3/16" Hex	1⁄0 - #18		1	3/16" Hex	1⁄0 - #18	3	0LS21212Z
150	3			1	3/16" Hex	1⁄0 - #18		1	3/16" Hex	1⁄0 - #18	3	0LS21213Z
115	1		₋₽₽	1	Slotted	#2 - #14	₋₽₽	1	Slotted	#2 - #14	3	0LS25521Z
115	2	AL		1	Slotted	#2 - #14		1	Slotted	#2 - #14	3	0LS25522Z
115	3			1	Slotted	#2 - #14		1	Slotted	#2 - #14	3	0LS25523Z
175	1			1	5/16" Hex	2⁄0 - #14		1	5/16" Hex	2⁄0 - #14	3	0LS25721Z
175	2	AL		1	5/16" Hex	2⁄0 - #14		1	5/16" Hex	2⁄0 - #14	3	0LS25722Z
175	3			1	3/16" Hex	2⁄0 - #14		1	3/16" Hex	2⁄0 - #14	3	LFS25723Z
255	1			1	5/16" Hex	250mcm-#6		1	5/16" Hex	250mcm-#6	5	0LS31231Z
255	2	AL		1	5/16" Hex	250mcm-#6		1	5/16" Hex	250mcm-#6	5	0LS31232Z
255	3			1	5/16" Hex	250mcm-#6		1	5/16" Hex	250mcm-#6	5	0LS31233Z
255	1			1	3/8" Hex	250mcm-#6		1	3/8" Hex	250mcm-#6	5	0LS31241Z
255	2	CU		1	3/8" Hex	250mcm-#6		1	3/8" Hex	250mcm-#6	5	0LS31242Z
255	3			1	3/8" Hex	250mcm-#6		1	3/8" Hex	250mcm-#6	5	0LS31243Z
310	1			1	5/16" Hex	350mcm-#6		1	5/16" Hex	350mcm-#6	5	0LS31261Z
310	2	AL		1	5/16" Hex	350mcm-#6		1	5/16" Hex	350mcm-#6	5	0LS31262Z
310	3			1	5/16" Hex	350mcm-#6		1	5/16" Hex	350mcm-#6	5	0LS31263Z
420	1			1	1/2" Hex	600mcm-#4		1	1/2" Hex	600mcm-#4	6	0LS45571Z
420	2	AL		1	1/2" Hex	600mcm-#4		1	1/2" Hex	600mcm-#4	6	0LS45572Z
420	3			1	1/2" Hex	600mcm-#4		1	1/2" Hex	600mcm-#4	6	0LS45573Z
620	1			2	5/16" Hex	350mcm-#4		2	5/16" Hex	350mcm-#4	7	0LS51291Z
620	2	AL		2	5/16" Hex	350mcm-#4		2	5/16" Hex	350mcm-#4	7	0LS51292Z
620	3			2	5/16" Hex	350mcm-#4		2	5/16" Hex	350mcm-#4	7	0LS51293Z
760	1			2	3/8" Hex	500mcm-#4		2	3/8" Hex	500mcm-#4	7	0LS53011Z
760	2	AL		2	3/8" Hex	500mcm-#4		2	3/8" Hex	500mcm-#4	7	0LS53012Z
760	3			2	3/8" Hex	500mcm-#4		2	3/8" Hex	500mcm-#4	7	0LS53013Z
175	1			-	5/16" Hex	2⁄0 - #14		1	5/16" Hex	2⁄0 - #14	4	0LS25721ZXDIN
175	2		┌╴══╌┐	1	5/16" Hex	2/0 - #14	┌╴┻═┓	1	5/16" Hex	2/0 - #14	4	OLS25722ZXDIN
175	3	AL		1	5/16" Hex	2/0 - #14		1	5/16" Hex	2/0 - #14	4	OLS25723ZXDIN
175	Adder			1	_	2/0 - #14		1	-	2/0 - #14	4	OLS2572AZXDIN
175	1			1	5/16" Hex	2/0 - #14		1	5/16" Hex	2/0 - #14	4	0LS29721ZXDIN
175	2		┍╼┻┑	1	5/16" Hex	2/0 - #14	┌────┐	1	5/16" Hex	2/0 - #14	4	OLS297272XDIN
175	3	CU		1	5/16" Hex	2/0 - #14		1	5/16" Hex	2/0 - #14	4	OLS29723ZXDIN
175	Adder			1		2/0 - #14		1	-	2/0 - #14	4	OLS2972AZXDIN
	1/10001	(0))				40 111				40 111	r	

Note: AL = Aluminum / CU = Copper

# Distribution Block and Splicer Block Outline Drawings

# **Dimensions Inches (mm)**





# Distribution Block and Splicer Block Outline Drawings

# **Dimensions Inches (mm)**

Figure 5









Figure 6



1-pole



2-pole





Figure 7



Fuse Blocks and Holders

# TOUCH-SAFE POWR-BLOKS™

# **Global Distribution Blocks**



# Description

POWR-BLOKS[™] Global Distribution Blocks add safety and mounting versatility to our distribution block solutions. The Global Distribution Blocks are approved to UL standards. The Global Distribution Blocks are IP20 finger safe to reduce the risk of contact and eliminate the need for block or panel covers. Installation is quick and easy, all blocks can be mounted on DIN rail or to the panel.

# Features/Benefits

- Global part meeting UL standards
- Space saving design
- Integrated touch-safe cover to increase safety
- IP20 protection rating
- Mounts to DIN rail or panels
- Reliable brass connections for excellent continuity in a smaller design

# **Specifications**

Voltage Rating

Ampere Rating Material Connector

Flammability Rating Approvals

Operating Temperature Storage Temperature Relative Humidity

#### Environmental

*GDB60801Z, GDB61151Z, GDB61153Z, GDB61753Z Only

# Web Resources

For additional information visit Littelfuse.com/gdb

# **Short Circuit Current Ratings**

CATALOG/ ORDERING NUMBER	POLES	AMPS	OVERCURRENT PROTECTION FUSE REQUIRED CLASS J (JTD_ID)	SCCR IN RMS SYM AMPS
GDB60801Z	1	80	80	100,000
GDB61151Z	1	115	125	100,000
GDB61153Z	3	115	125	100,000
GDB61601Z	1	160	175	100,000
GDB61753Z	3	175	175	100,000
GDB63101Z	1	310	350	100,000

#### AMP RATING CONNECTOR MATERIAL LINE CONNECTION LOAD CONNECTION CATALOG/ **DIN RAIL** PER POLE З ORDERING PO OPENINGS OPENING W/IRF SCREW **OPENINGS OPENING** W/IRF SCREW UL IEC NUMBER TORQUE TORQUE PER POLE DIAMETER RANGE TYPE PER POLE DIAMETER RANGE TYPE 13.5 in-lbs ø0.28 in #8 - #4 (2x ø7.0 mm) (1.5 N·m) ø0.28 in 13 5 in-lbs 80 1 GDB60801Z Brass 1 #8 - #4 Slotted 6 Slotted 80 (1.5 N·m) (ø7.0 mm) ø0.18 in 7.2 in-lbs #10 - #14 4x ø4.5 mm (0.8 N·m) ø0.39 in 31 in-lbs #8-#2 Hex 4 mm (ø10.0 mm) (3.5 N·m) ø0.28 in 17.5 in-lbs 115 125 1 GDB61151Z Brass 2 6 #14 - #4 Slotted (2.0 N·m) ø0.28 in 31 in-lbs (ø7.0 mm) #10 - #6 Hex 4 mm (ø7.0 mm) (3.5 N·m) ø0.49 in 35.5 in-lbs ø0.28 in 17.5 in-lbs Hex 5 mm 6 #14 - #4 160 160 1 GDB61601Z Brass 1 #8-2/0 Slotted (ø12.5 mm) (4.0 N·m) (2.0 N·m) (ø7 0 mm) ø0.35 34.1 in-lbs #14 - #2 (2x ø9.0 mm (3.9 N·m) ø0.75 in 3/0-350 230 in-lbs ø0.25 in 19.8 in-lbs GDB63101Z Hex 8 mm Slotted 310 400 Brass 1 11 #14 - #6 1 . (5x ø6.5 mm (ø19.0 mm) kcmil (26.0 N·m) (2.2 N·m) ø0.21 19.8 in-lbs #14 - #8 (4x ø5.3 mm) (2.2 N·m) ø0.39 in ø0.25 in 17.5 in-lbs 31 in-lhs 3 GDB61153Z #8 - #2 Hex 4 mm 6 #14 - #4 115 115 Brass 1 Hex 3 (ø10.0 mm) (3.5 N·m) (ø6.5 mm) (2.0 N·m) ø0.47 in 35.5 in-lbs ø0.25 in 17.5 in-lbs 175 175 3 GDB61753Z Brass 1 #8-2/0 Hex 5 mm 6 #14 - #4 Hex 3 (ø12.0 mm) (4.0 N·m) (ø6.5 mm) (2.0 N·m)

# Ordering Information

6

#### © 2015 Littelfuse POWR-GARD® Products Catalog



UL: 600 VAC/VDCIEC: 690 VAC/VDC80 - 310 AThermoplastic Brass: Better continuity, Smaller design UL94 V-0 UL Recognized (File: E309688) c-UL Recognized* CE: IEC 60947-7-1  $-40^{\circ}C$  to  $+90^{\circ}C$  $-40^{\circ}C$  to  $+90^{\circ}C$ -50% @  $40^{\circ}C$ , 90% @  $20^{\circ}C$ 

RoHS compliant



# TOUCH-SAFE POWR-BLOKS™

# **Global Distribution Blocks**

# **Dimensions Inches (mm)**

80 A GDB60801Z









115 A GDB61151Z









160 A GDB61601Z









# TOUCH-SAFE POWR-BLOKS™

# **Global Distribution Blocks**

# **Dimensions Inches (mm)**

310 A GDB63101Z





**Fuse Blocks and Holders** 

GDB61753Z











# **IN-LINE GLASS FUSE HOLDERS**

#### 150322





# **Description**

The 150322 is a 500 Vac/125 Vdc rated inline fuse holder ideal for applications where supplemental protection is needed, such as lighting ballasts and power supplies. 8-inch pre-stripped wire leads and fuse clips come preassembled for quick installation.

# **Features/Benefits**

- Single piece body minimizes component count
- High voltage rating accommodates many power applications
- Wire leads are pre-attached to fuse clips for quick assembly
- Single piece molded body
- UL Recognized ٠

# **Recommended Fuses**

3AG (312, 313 Series) 33	
3AB (314, 326, 505 Series)	

# **Dimensions mm (inches)**





# **Specifications**

Voltage Rating	500 Vac, 125 Vdc
Ampere Rating	15 A
Fuse Type	1⁄4″ x 11⁄4″
Fuse Clips	Tin-plated brass
Wire	Black 18 AWG, 150° C Stranded
Molded Body	Single piece thermoplastic
Flammability Rating	UL94 V-0
Approvals	UL Recognized (File: E14721)
Environmental	RoHS complaint, Lead (Pb) free
Storage Temperature	-40° C to 80° C
Operating Temperature	-55° C to 125° C

# **Ordering Information**

CATALOG NUMBER	ORDERING NUMBER	STANDARD PACK		
150322	01500322H	100 PIECES		

# Web Resources

For more information, visit: littelfuse.com/150322

#### Additional In-Line Glass Fuse Holders Special Type Twist-Lock Heavy-Duty Bayonet 155 Series 155 Series 150 Series RoHS PO RoHS (PO) RoHS PO In-Line Mount In-Line Mount In-Line Mount 32 V 3AG, SFE 32 V 3AG 250 V 2AG, 5x20mm **Dimensions Inches**



# **Blocks and Holders**



# Description

Recently redesigned, the Littelfuse 600 VAC/VDC in-line watertight fuse holders allow maximum protection for high humidity and corrosive environments. The fuse holders are designed to be touch-safe and flexible for use in a variety of applications. See the list below for the redesigned part numbers.

# Applications

- Street lighting and parking lot lighting
- Sports lighting and various outdoor illuminated signs
- Boat electrical circuits, tractors/yard equipment and general outdoor circuit protection (such as traffic signals, alley lighting and electric wheelchairs)





# **Specifications**

Voltage rating Ampere rating Interrupting rating Approvals

up to 30 A 200 kA rms symmetrical (with Class CC fuses) **LEB/LEX series** UL Recognized Miscellaneous Fuse holder per UL UL 4248 (File: E14721) CSA Certified per C22.2, No. 39 (File: LR7316) **LEC/LEY series** UL Listed Class CC Branch Circuit Fuse holder per UL 512 (File: E14721) CSA Certified per C22.2, No. 39 (File: LR7316)

27

# **Features/Benefits**

• Design increases safety by individual device disconnection for easy servicing, eliminating shock risk

600 VAC/VDC

- Increases efficiency by preventing faulted ballast from severely damaging fixture or device
- Watertight seal
- Variety of terminations available for flexible design
- Insulating boots available for harsh environments

# Recommended Fuses

#### LEB/LEX series: Accepts all Littelfuse Midget and Class CC series fuses CCMR

	Z/
KLDR, KLKR	
BLF, BLN, FLM, FLQ, KLK, KLKD	30

#### LEC/LEY series:

Accepts only Littelfuse Class CC fuses	
CCMR	27
KLDR, KLKR	

### Web Resources

Download CAD drawings, dimensions and other technical information: **littelfuse.com/in-line** 

# Look for these part numbers featuring our improved design

- Better surface area for ergonomic comfort, improved grip and better torque
- More pronounced seating automatically seats as user begins twisting
- Chamfered edges for additional installation comfort

BASE PART NUMBER	PREVIOUS ORDERING NUMBER	NEW ORDERING NUMBER
LEB-AA	0LEB00AAX	OLEBOOAAXK
LEB-AA-S	OLEBOAASX	OLEBOAASXK
LEB-AB	0LEB00ABX	OLEBOOABXK
LEB-AYC-S	OLEBAYCSX	OLEBAYCSXK
LEB-BB	OLEBOOBBX	OLEBOOBBXK
LEB-JJ	OLEBOOJJX	OLEBOOJJXK
LEB-JJ-S	OLEBOJJSX	OLEBOJJSXK



# **Ordering Information**

To order Littelfuse in-line fuse holders by part number, refer to the charts on the next page.



SERIES	DESCRIPTION
LEB	One-pole in-line fuse holder for Midget and Class CC fuses
LEC	One-pole in-line fuse holder for Class CC fuses
LET	One-pole in-line fuse holder with permanently installed solid neutral
LEX	Two-pole in-line fuse holder for Midget and Class CC fuses
LEY	Two-pole in-line fuse holder for Class CC fuses



# **Recommended Crimping Tools**

The following crimping tools or equivalents may be used on either the non-breakaway or breakaway watertight in-line fuse holders.

TERMINAL SIZE	T&B PART NUMBER	BURNDY PART NUMBER
А	WT161M	-
В	WT161M	MR4C
С	M5-GREY	Hypress Y34A
D	M5-BROWN	Hypress Y34A

# **Insulating Boots**

- Molded from engineering-grade thermoplastics which provide high resistance to corrosive environments
- Standard with all breakaway style fuse holders
- For watertight protection of non-breakaway Y-pole termination, order one WPB1 and one WPB3 boot



ORDERING NUMBER	TERMINAL TYPE
WPB1	A, B, C, D, J
WPB3	Y

# **Dimensions Inches**





#### 2-Pole



#### 2-Pole Breakaway



# Ordering Information (1-Pole LEB/LEC and 2-Pole LEX/LEY for Class CC and Midget Fuses)

SINGL	E POLE	DOUBL	E POLE		LOAD TE	ERMINAL SEI	ECTION			LINE TE	ERMINAL SEL	ECTION	
STANDARD PART NUMBER	Breakaway Part Number	STANDARD PART NUMBER	Breakaway Part Number	TERMINAL TYPE	LOAD TERMINAL WIRE SIZE RANGE	NUMBER OF WIRES PER TERMINAL	SOLID WIRE	STRANDED WIRE	terminal Type	LINE TERMINAL WIRE SIZE RANGE	NUMBER OF WIRES PER TERMINAL	SOLID WIRE	STRANDED WIRE
LEB-AA LEC-AA	LEB-AA-S LEC-AA-S	LEX-AA LEY-AA	LEX-AA-S LEY-AA-S	Copper Crimp	#12 to #8 #12	1 2	•	•	Copper Crimp	#12 to #8 #12	1 2	•	•
LEB-AB LEC-AB	LEB-AB-S LEC-AB-S	LEX-AB LEY-AB	LEX-AB-S LEY-AB-S	Copper Crimp	#12 to #8 #12	1 2	•	•	Copper Crimp	#10 #6 #4	2 1 1	•	•
LEB-AC LEC-AC	_	LEX-AC LEY-AC	_	Copper Crimp	#12 to #8 #12	1 2	•	•	Copper Crimp	#8 #4	2 1	•	•
LEB-AD LEC-AD	_	LEX-AD LEY-AD	_	Copper Crimp	#12 to #8 #12	1 2	•	:	Copper Crimp	#6 #2	2 1	•	:
LEB-AJ LEC-AJ	LEB-AJ- S LEC-AJ-S	—	_	Copper Crimp	#12 to #8 #12	1 2	•	•	Copper Set-Screw	#12 to #8 #10 to #2	1 1	•	•
LEB-AYC LEC-AYC	LEB-AYC-S LEC-AYC-S	LEX-AYC LEY-AYC	LEX-AYC-S LEY-AYC-S	Copper Crimp	#12 to #8 #12	1 2	•	:	"Y" Type Copper Set-Screw	#12 to #8 #10 to #2	1 1	•	•
LEB-BA LEC-BA	LEB-BA-S LEC-BA-S	LEX-BA LEY-BA	LEX-BA-S LEY-BA-S	Copper Crimp	#10 #6 #4	2 1 1	•	•	Copper Crimp	#12 to #8 #12	1 2	•	•
LEB-BB LEC-BB	LEB-BB-S LEC-BB-S	LEX-BB LEY-BB	LEX-BB-S LEY-BB-S	Copper Crimp	#10 #6 #4	2 1 1	•	•	Copper Crimp	#10 #6 #4	2 1 1	•	•
LEB-BC LEC-BC	_	LEX-BC LEY-BC	_	Copper Crimp	#10 #6 #4	2 1 1	•	•	Copper Crimp	#8 #4	2 1	•	:
LEB-BD LEC-BD	_	LEX-BD LEY-BD	_	Copper Crimp	#10 #6 #4	2 1 1	•	•	Copper Crimp	#6 #2	2 1	•	:
LEB-BJ LEC-BJ	LEB-BJ-S LEC-BJ-S	_	=	Copper Crimp	#10 #6 #4	2 1 1	•	•	Copper Set-Screw	#12 to #8 #10 - #2	1 1	•	•
LEB-BYC LEC-BYC	LEB-BYC-S LEC-BYC-S	LEX-BYC LEY-BYC	LEX-BYC-S LEY-BYC-S	Copper Crimp	#10 #6 #4	2 1 1	•	•	"Y" Type Copper Set-Screw	#12 to #8 #10 - #2	1 1	•	•
LEB-CA LEC-CA	_	LEX-CA LEY-CA	_	Copper Crimp	#8 #4	2 1	•	:	Copper Crimp	#12 to #8 #12	1 2	•	:
LEB-CB LEC-CB	_	LEX-CB LEY-CB	_	Copper Crimp	#8 #4	2 1	•	•	Copper Crimp	#10 #6 #4	2 1 1	•	•
LEB-CC LEC-CC	_	LEX-CC LEY-CC	_	Copper Crimp	#8 #4	2 1	•	:	Copper Crimp	#8 #4	2 1	•	:
LEB-CD LEC-CD	_	LEX-CD LEY-CD	_	Copper Crimp	#8 #4	2 1	•	•	Copper Crimp	#6 #2	2 1	•	•
LEB-CJ LEC-CJ	_	LEX-CJ LEY-CJ	_	Copper Crimp	#8 #4	2 1	•	:	Copper Set-Screw	#12 to #8 #10 - #2	1 1	•	•
LEB-CYC LEC-CYC	_	LEX-CYC LEY-CYC	_	Copper Crimp	#8 #4	2 1	•	:	"Y" Type Copper Set-Screw	#12 to #8 #10 to #2	1 1	•	•
LEB-DA LEC-DA	_	LEX-DA LEY-DA	_	Copper Crimp	#6 #2	2 1	•	:	Copper Crimp	#12 to #8 #12	1 2	•	•
LEB-DB LEC-DB	_	LEX-DB LEY-DB	_	Copper Crimp	#6 #2	2 1	•	:	Copper Crimp	#10 #6 #4	2 1 1	•	•
LEB-DC LEC-DC	_	LEX-DC LEY-DC	_	Copper Crimp	#6 #2	2 1	•	:	Copper Crimp	#8 #4	2 1	•	:
LEB-DD LEC-DD	_	LEX-DD LEY-DD	_	Copper Crimp	#6 #2	2 1	•	:	Copper Crimp	#6 #2	2 1	•	:
LEB-DJ LEC-DJ	_	LEX-DJ LEY-DJ	_	Copper Crimp	#6 #2	2 1	•	:	Copper Set-Screw	#12 to #8 #10 - #8	2 1	•	:
LEB-DYC LEC-DYC	_	LEX-DYC LEY-DYC	_	Copper Crimp	#6 #2	2 1	•	:	"Y" Type Copper Set-Screw	#12 to #8 #10 to #8	1 1	•	•
LEB-JJ LEC-JJ	LEB-JJ-S LEC-JJ-S	LEX-JJ LEY-JJ	LEX-JJ-S LEY-JJ-S	Copper Set-Screw	#12 to #8 #10 to #2	1 1	•	•	Copper Set-Screw	#12 to #8 #10 to #2	1 1	•	•
LEB-JYC LEC-JYC	LEB-JYC-S LEC-JYC-S	_	_	Copper Set-Screw	#12 to #8 #10 to #2	1 1	•	•	"Y" Type Copper Set-Screw	#12 to #8 #10 to #2	1 1	•	•



# **Ordering Information** (Solid Neutral LET Fuse Holders)

				LOAD TE	ERMINAL SEL	ECTION		LINE TERMINAL SELECTION					
STANDARD PART NUMBER	BREAKAWAY PART NUMBER	FUSE TYPE	TERMINAL TYPE	LOAD TERMINAL WIRE SIZE RANGE	NUMBER OF WIRES PER TERMINAL	Solid Wire	STRANDED WIRE	TERMINAL TYPE	LINE TERMINAL WIRE SIZE RANGE	NUMBER OF WIRES PER TERMINAL	Solid Wire	STRANDED WIRE	
LET-AA	LET-AA-S	Solid Neutral	Copper Crimp	#12 to #8 #12	1 2	•	•	Copper Crimp	#12 to #8 #12	1 2	•	•	
LET-AB	LET-AB-S	Solid Neutral	Copper Crimp	#12 to #8 #12	1 2	:	:	Copper Crimp	#10 #6 #4	2 1 1	• • —	:	
LET-AYC	LET-AYC-S	Solid Neutral	Copper Crimp	#12 to #8 #12	1 2	:	•	"Y" Type Copper Set-Screw	#12 to #8 #10 to #2	1 1	•	•	
LET-BA	LET-BA-S	Solid Neutral	Copper Crimp	#10 #6 #4	2 1 1	• •	•	Copper Crimp	#12 to #8 #12	1 2	:	:	
LET-BB	LET-BB-S	Solid Neutral	Copper Crimp	#10 #6 #4	2 1 1	•	•	Copper Crimp	#10 #6 #4	2 1 1	•	•	
LET-BYC	LET-BYC-S	Solid Neutral	Copper Crimp	#10 #6 #4	2 1 1	•	:	"Y" Type Copper Set-Screw	#12 to #8 #10 to #2	1 1	•	•	
LET-JJ	LET-JJ-S	Solid Neutral	Copper Set-Screw	#12 to #8 #10 to #2	1 1	•	•	Copper Set-Screw	#12 to #8 #10 to #2	1 1	•	•	
LET-JYC	LET-JYC-S	Solid Neutral	Copper Set-Screw	#12 to #8 #10 to #2	1 1	•	•	"Y" Type Copper Set-Screw	#12 to #8 #10 to #2	1 1	•	•	

# **Ordering Information (Terminals)**

TERMINAL DESIGNATION	TERMINAL DESCRIPTION	NUMBER OF WIRES PER TERMINAL	WIRE RANGE	SOLID WIRE	STRANDED WIRE
А	Copper Crimp	1	#12-#8	•	•
A	соррег стттр	2	#12	•	•
		2	#10	•	•
В	Copper Crimp	1	#6	•	•
		1	#4	—	•
С	Copper Crimp	2	#8	•	•
C	Copper Crimp	1	#4	_	•
D	Copper Crimp	2	#6	•	•
D	Copper Crimp	1	#2	_	•
	Copper Set-Screw	1	#12-#8	•	—
J	Cohhei Ser-Sciem	1	#10-#2	_	•
Y (2 terminals)	"V" Style Coppor Set Serow	1	#12-#8	•	—
	"Y" Style Copper Set-Screw	1	#10-#2	_	•

# Two-Pole Breakaway Holder





# Description

New Littelfuse LEXT-YY-S and LEX-YYC-S series breakaway fuse holders meet state and federal highway commission safety standards requiring fuse holders to readily disconnect from power in case of a pole knockdown.

The breakaway feature consists of a receptacle permanently attached to the power line and a fuse holder with matching terminals. If a knockdown occurs, the parts separate, leaving the energized conductor recessed and unexposed.

# Applications

- Street lighting
- Marinas
- Travel trailer parks
- Physically strained fuse holders applications

# **Ordering Information**

### **Features/Benefits**

- LEXT-YY version has a permanently installed "neutral" slug to prevent the neutral from accidentally being fused
- LEX-YYC version allows for fusing of line-to-line loads or other applications requiring two fuses to disconnect under strain
- Fiberglass polymer body resists damage from impact
- Four "Y" type set-screw terminals accommodate a wide range of solid and stranded Cu conductors
- O-ring and terminal boots form watertight seal, preventing leakage

# **Specifications**

Part numbers

**Voltage Rating** 

**Ampere Rating** 

**Y** Terminals

Wire Size

Approvals

**Interrupting Rating** 

LEXT-YY-S (Solid neutral) LEX-YYC-S 600 Vac/Vdc 30 A 200 kA with Class CC Fuses Tin Plated Copper w/ set screws 1 solid #12 to #8 or 1 stranded #10 to #2 UL Recognized (File: E14721) CSA Certified (File: LR7316)

# **Recommended Fuses**

Accepts all Littelfuse Midget and Class CC series fuses	
CCMR	27
KLDR, KLKR	28
BLF, BLN, FLM, FLQ, KLK, KLKD	30

Four WPB3 insulating boots come standard with the LEXT-YY-S and LEX-YY-C-S fuse holders. Molded from non-conductive engineering grade thermoplastic to deliver a watertight seal in corrosive environments, they can be trimmed to the specific conductor size insuring a snug fit.

# Web Resources

Additional technical information: **littelfuse.com/in-line** 

			LOAD TERMINAL SELECTION				LINE TERMINAL SELECTION					
	ering 1Ber	FUSE TYPE	TERMINAL TYPE	LOAD TERMINAL WIRE SIZE RANGE	NUMBER OF WIRES PER TERMINAL	SOLID WIRE	STRANDED WIRE	TERMINAL TYPE	LINE TERMINAL WIRE SIZE RANGE	NUMBER OF WIRES PER TERMINAL	SOLID WIRE	STRANDED WIRE
LEXTYYS	LEXTOYYSX	Midget Class CC	"Y" type Copper Set-Screw	#12 to #8 #10 to #2	1	•	•	"Y" type Copper Set-Screw	#12 to #8 #10 to #2	1	•	•
LEXYYCS	OLEXYYCSX	Midget Class CC	"Y" type Copper Set-Screw	#12 to #8 #10 to #2	1	•	•	"Y" type Copper Set-Screw	#12 to #8 #10 to #2	1 1	•	•



# Two-Pole Breakaway Holder

# **Dimensions Inches**

LEX-YY-C-S



LEXT-YY-S



# **Section Overview**

POWR-GARD's Pre-Engineered Solutions include custom-built electrical panels designed specifically to meet NEC[®] requirements, as well as fused and non-fused disconnect switches.



# PRE-ENGINEERED SOLUTIONS ...

# Table of Contents

LPS Series POWR-Switch (Shunt Trip Disconnect)......141



# LCP FUSED COORDINATION PANEL

# **Selective Coordination Panel**





# Description

The Littelfuse[®] Coordination Panel provides a simple, time-saving solution for circuits that require selective coordination. This UL Listed product saves time and money, and increases safety by minimizing system downtime.

### **Applications**

- Elevators
- Hospitals
- Hotel and Entertainment Industry
- Amusement Parks and Stadiums

# **Code Requirements**

Systems required by the NEC® to be selectively coordinated include:

- Health Care Essential Electrical Systems (NEC 517.30)
- Elevators (NEC 620.62)
- Emergency Systems (NEC 700.28)
- Legally Required Standby Systems (NEC 701.27)
- Critical Operations Power Systems (NEC 708.54)

# Features/Benefits

- Meets NEC[®] requirements
- Class CC and J fuse holders have built-in open-circuit indication
- Fast-acting UL Listed fuses protect against short circuits
- Feed through/sub feed lugs and 84-circuit configuration available
- Ground and neutral bars
- Copper bus standard

# **Advanced Design Options**

- MLO, Main Circuit Breaker, or Main Fused Pullout device
- Fused Class T branch circuit pullout
- Spare fuse cabinet accessory (holds six spare fuses)
- TVSS overvoltage protection
- Any NEMA enclosure required
- High amperage sub-fed branch breakers (J60A)
- Unique Specifier Tool to easily identify panel configurations from tens of thousands of options

# Specifications

Voltage Ratings Main Bus Rating Conductor Terminals UL Listed 120/208, 120/240, 277/480 Vac 100 A - 400 A Standard 6 AWG - 300 kcmil UL 67 Panel boards and UL 50 Enclosures

# Web Resources

For more information, visit: **littelfuse.com/lcp** 

To quickly specify the LCP panel, visit **littelfuse.com/lcp** and download the Specifier Tool.

	_	-	
	- E	11	
722883	1-1-1		
and the second second	2	1.1	
The second second	- 1	11	

# **Customizable Options (select one from each column)**

NUMBER OF CIRCUITS	VOLTAGE	MAIN DEVICES	NEUTRAL RATING	PANEL MOUNTING	PANEL DOOR	FUSE HOLDERS	BRANCH CIRCUIT PROTECTION DEVICES (1-3 POLE)†	PANEL FEED	OPTIONAL LUGS	STANDARD ENCLOSURE RATING
	120/208 V 3P, 4 W	125, 225, 400 or 600 A MLO	100%	Surface	Standard	30 A Class CC	10 A-60 A fused circuit breaker 60 A-200 A	Тор	None	NEMA 1
2 - 42	120/240 V 1P, 3 W	Up to 600 A MCB	0000/				fused pullouts		Sub-Fed (MLO panels)	NEMA 3R
	277/480 V 3P, 4 W	or Main Fuse	200%	Flush	Door-in-door	60 A Class J	Sub-fed circuit breakers >60 A (not fused)	Bottom	Feed-Through	NEMA 4X

[†]Fuses quoted separately to meet panel specifications. Coordination for breakers >60 A depends on upstream and downstream devices. More specialized configurations are also available. Contact factory for more information.

Note: The Littelfuse LPS and LCP products are custom designed products that fall outside standard specifications.



# LCP FUSED COORDINATION PANEL

# **Selective Coordination Panel**

# **Dimensions mm (inches)**

#### Standard Coordination Panel Board (up to 30 circuits)



#### **Standard Coordination Panel Board (31-42 circuits)**



Catch and Lock



To quickly specify the LCP panel, visit littelfuse.com/lcp and download the Specifier Tool

Note: The Littelfuse LPS and LCP products are custom designed products that fall outside standard specifications.

Dimensions may change depending on panel components. More specialized configurations are also available. Contact factory for more information.



# LPS SERIES POWR-SWITCH

# Shunt Trip Disconnect Switch





# Description

The Littelfuse[®] POWR-Switch provides a simple and economical solution for applications that require selective coordination and shunt trip capabilities.

Utilizes Class J time-delay fuses that are easily coordinated with other system overcurrent devices. The shunt trip capability allows the POWR-Switch to meet the ANSI/ASME standard that requires power to be automatically disconnected before water is turned on by the fire safety system.

### **Applications**

- Elevator circuits
- Data processing rooms
- Building emergency systems

### Web Resources

Download technical information: littelfuse.com/lps

# Specifications (POWR-Switch)

Supply Voltage Rating*
Ampere Range
Interrupting Rating
Enclosures

Approvals

208 V, 240 V, 480 V 30 A, 60 A, 100 A, 200 A, 400 A 200 kA NEMA 1 (standard) NEMA 3R, NEMA 4, NEMA 12 (optional) UL Listed (File: E219511)

*Contact factory for 600 V options.

### Specifications (Shunt Trip)

Voltage Rating	120 V, 60 Hz
Max Inrush	4 A
Max On time	1.5 cycles
Momentary Inrush	140 VA

### **Features/Benefits**

- Pre-engineered single unit, which makes procurement easier than systems with multiple components
- Reduces labor costs up to 66% and total installation costs by over 30%
- Pre-installed UL listed Class J fuse holder unique Class J size eliminates the need for any rejection type fuse clips
- Optional features offer flexibility for a variety of applications
- Control power terminal block
- UL Listed package
- Cu and AI wire rated
- Pre-wired control circuits lower installation time
- Lockable operating handle meets all code and safety requirements (Accepts up to 3 locks)
- Every unit is fully tested before delivery

### **Options**

- Control power transformer with fuses and blocks
- Fire safety interface relay
- Key to test switch
- Pilot light "On"
- Isolated neutral lug
- Mechanical interlock auxiliary contact for hydraulic elevators with automatic recall (5 amp 120 Vac rated)
- Fire alarm voltage monitoring relay
- Option to bypass alarm when performing maintenance (-AZ option)
- XPress-Ship[™] service offers 48 Hours direct shipment service on select fully loaded LPS POWR-Switches

7

# LPS SERIES POWR-SWITCH

# Shunt Trip Disconnect Switch

(Ų.)

# **Ordering Information**

Complete catalog numbers consist of switch catalog numbers and the desired options. See example below.

#### **Example Catalog Number from Desired Options**



*Part Numbers: Any voltage can be paired with any amperage. Options can be any combination but the ratings must match the option code. Not all options are required. Contact factory for 600 V control power transformer option.

Note: When ordering - desired options must be listed in the order shown above. Typical options include Control Power Transformer, Fire Safety Interface Relay, Mechanical Interlock Auxiliary Contact and Fire Alarm Voltage Monitoring Relay.

# **Dimensions of Enclosure**

CATALOG SERIES	AMPERE RATING	NEMA 1 DIMENSIONS	NEMA 3R DIMENSIONS	NEMA 4, 12 DIMENSIONS	LUG SIZE
LPS3	30	24"H x 20"W x 9"D	24"H x 20"W x 8"D	24"H x 20"W x 10"D	#14 - #8 AL or CU
LPS6	60	24"H x 20"W x 9"D	24"H x 20"W x 8"D	24"H x 20"W x 10"D	#14 - #2 AL or CU
LPS1	100	24"H x 20"W x 9"D	24"H x 20"W x 8"D	24"H x 20"W x 10"D	#8 - 1/0 AL or CU
LPS2	200	30"H x 20"W x 9"D	30"H x 24"W x 8"D	30"H x 20"W x 10"D	#6 - 250kcmil AL or CU
LPS4	400	48"H x 36"W x 11"D	Contact Factory	Contact Factory	3/0 AL or CU

Note: Over-size enclosures used to accommodate control power transformer, interface relay and terminal blocks.

XPress-Ship [™]	AMPERE RATING	VOLTAGE RATING	CATALOG NUMBER	<b>XPress-Ship™</b> ORDERING NUMBER
Ai i coo omp	60 A	480 V	LPS6T48R1KGN6BF3-AZ	XPS6T48R1KGN6F3-AZ*
US Only	100 A	480 V	LPS1T48R1KGN1BF3-AZ	XPS1T48R1KGN1F3-AZ*
fuse XPress-Ship™ service offers 48 Hours** direct-shipment	100 A	480 V	LPS1T48R1KGN1BF3	XPS1T48R1KGN1BF3
ce on select fully-loaded LPS POWR-Switch to meet your	200 A	208 V	LPS2T20R1KGN2BF3-AZ	XPS2T20R1KGN2F3-AZ*
it system requirements on time.	200 A	480 V	LPS2T48R1KGN2BF3	XPS2T48R1KGN2BF3
as Chin™ suritahas include three ITD ID Caries				

XPress-Ship[™] switches include three JTD_ID Series fuses rated at the device's maximum ampacity.

*AZ option includes B & F3 options.

**XPress-Ship™ 48 hour service requires ordering from XPress-Ship Ordering Numbers shown above and is subject to a maximum of any combination of three switches per customer order. XPress-Ship service offers 48 hour shipment from the factory through standard ground transportation. For expedited delivery, contact your local Littelfuse Representative.

Littelfu service urgent
#### **Section Overview**

Our comprehensive line of single- and multi-function protection relays safeguard equipment and personnel in order to prevent expensive damage, downtime or injury due to electrical faults.

The features and flexibility within the products and the software allow you to select the appropriate protection for each part of your electrical system.



# PROTECTION RELAYS AND CONTROLS ...

#### **Table of Contents**

	ALC: NO	
8		
	ECONT PULL	

#### Download our Complete Relay and Controls Catalog

For more information on relays and controls or to download our fullline relay catalog (PF130N), Visit:

littelfuse.com/RelaysControls

Feature Comparisons	46
Ground-Fault Protection	48
Trailing Cable Protection1	51
Resistance Grounding and NGR Monitoring1	52
Motor Protection 1	54
Pump and Feeder Protection1	56
Arc-Flash Protection1	57
Industrial GFCI (Shock-Block™)1	57
Generator and Single-Function Protection 1	58
Generator Control 1	63
Engine Control and Diagnostics 1	67
Alarm Monitoring 1	68
Custom-Engineered Electrical Equipment1	70
Accessories1	71

# A Full Range of **PROTECTION RELAYS &**

#### Why are Protection Relays Necessary?

Protection relays safeguard critical components of an electrical circuit from damage. When the relay detects a potentially damaging or unsafe condition, the relay will send an alarm or trip signal in order to notify personnel or prevent the condition from continuing.

Protection relays increase the uptime of critical systems and enhance the safety of people and equipment during fault situations.





#### We Improve Electrical Safety and Increase Uptime

For decades, Littelfuse has been helping customers improve their electrical systems. In addition to well-designed products, our technical expertise brings years of experience and product design support to your application.

We can provide immediate access to specialized technical resources, online references or field application support. This catalog outlines the Littelfuse line of protection relays, custom-engineered electrical equipment, generator and engine controls, and alarm and annunciator systems, plus the technical capabilities we offer for your application.



### A Safety

Shock Hazard Injury to Personnel Arc-Flash Hazards Open-CT Hazards Failed Resistors



Fault Damage Equipment Replacement Calibration Costs Compliance Citations Motor Rewinds



Replacement Time Nuisance Tripping Intermittent Faults Unreliable Protection Calibration Time

#### For All Harsh Environments

Petrochemical, Oil and Gas Pipelines and Transportation Aggregate and Cement Mining Pulp and Paper Water and Waste Water Shore-to-Ship Power Marine Data Centers Semiconductor Equipment Hospitals Alternative Energy Power Generators

## **CONTROLS** for the Harshest Environments



#### **GENERATOR PROTECTION & CONTROL**

Our line of generator protection and control equipment offers synchronizing, frequency control, load sharing, power management, engine control and more for marine, emergency or power generation applications.



#### **ENGINE CONTROL & MONITORING**

These monitors can be configured from the front panel, a PC, or via an SD card, and support both digital and analog sensor inputs. Common alarms and shut-downs have large, user-friendly LED displays.



### **(7)**

#### **ARC-FLASH DETECTION**

Our Arc-Flash relays can rapidly detect developing Arc-Flash incidents and send a trip signal to interrupt power before significant damage occurs.







#### **MOTOR & PUMP PROTECTION RELAYS**

Prevent expensive damage to motors caused by overloads, jams, phase loss or unbalance, heat from non-electric sources, heavy start-ups or excessive operational cycles. Dynamic thermal curves, integrated protection, metering, and data-logging functions extend motor life and maximize process efficiency.



#### **RESISTANCE GROUNDING & MONITORING**

Overcome many of the issues experienced with solidly-grounded and ungrounded systems. High-Resistance Grounding eliminates Arc-Flash Hazards associated with ground faults and transient overvoltages, and allows for continuous operation during a ground fault.



#### **GROUND-FAULT PROTECTION RELAYS**

Improve the safety of workers and reduce incidents of Arc-Flash without affecting the uptime of critical operations. Sensitive ground-fault relays with advanced filtering will detect the breakdown in insulation resistance caused by moisture, vibration, chemicals and dust without nuisance trips.

(00)

#### FEEDER PROTECTION RELAYS

Protect feeder circuits from overcurrents, ground faults, phase loss or other detrimental conditions in critical applications and processes. They provide essential data for predictive and preventive maintenance— extending the life of equipment, enhancing safety and maximizing efficiency.

#### **GENERAL PROTECTION RELAYS**

These single-function, compact and cost-efficient relays are typically used on low-voltage applications. Most are DIN-rail mountable, easy to operate, install and commission. The wide-range power supply for AC and DC make these relays universal.

#### **ENGINE DIAGNOSTICS**

The EngineEye diagnostic unit can improve the efficiency and performance of combustion engines by measuring and analyzing the engine combustion process. It utilizes a unique handheld high-precision indicator of cylinder pressure.

#### **ALARM & ANNUNCIATOR PANELS**

These panels monitor instantaneous current, temperature or pressure, and include local indication, alarm and event logging.

### FEATURES COMPARISONS

ittelfuse[®]

rtise Applied | Answers Delivered

### 🖶 💫 🌔 Ground-Fault Protection Relays

FEATURE	SE-601	EL731	EL3100	PGR-3200	T3200	SE-502	SE-701 SE-703 SE-704	T2800	SE-105 SE-107	SE-134C SE-135	SE-145	SE-325	SE-330 SE-330HV SE-330AU
Detects GF via voltage			<b>v</b>	V		V						V	<b>v</b>
Detects GF via current	V	V				V	<ul> <li>✓</li> </ul>	V	<b>v</b>	<ul> <li>Image: A second s</li></ul>	~	V	<b>v</b>
Detects DC GF	V	<b>v</b>											
Adjustable GF pickup	V	V					<ul> <li>✓</li> </ul>	V	<b>v</b>	V	V	~	<b>v</b>
Adjustable time delay	V	<b>v</b>			<b>v</b>		<ul> <li>Image: A start of the start of</li></ul>	<b>v</b>	<b>v</b>	<b>v</b>	V	<b>v</b>	<b>v</b>
Remote reset	V	V		~		V	<ul> <li>✓</li> </ul>		<b>v</b>	<b>v</b>	V	~	<b>v</b>
Analog output	V	<b>v</b>		<b>v</b>	<b>v</b>		<ul> <li>Image: A start of the start of</li></ul>						<b>v</b>
Fail-safe option	V	V				V	<ul> <li>✓</li> </ul>		<b>v</b>	V	~	V	<b>v</b>
Harmonic filtering		<b>v</b>		V			<b>v</b>		<b>v</b>	<b>v</b>	V	V	<b>v</b>
CT-Loop monitoring		V					<b>v</b>			V	~		
Insulation monitoring				<b>v</b>	$\checkmark$	<b>v</b>							
Ground-check monitoring									V	V	~		
Grounding-resistor monitoring												V	<b>v</b>
PTC/RTD overtemperature		V											
Communications		<b>v</b>											<b>v</b>
Conformal coating	‡	V	V	‡	<b>v</b>	‡	‡	V	<ul> <li>Image: A second s</li></ul>	V	<b>v</b>	V	<b>v</b>

### 💋 Arc-Flash Relays

-		-
FEATURE	D0100	PGR-8800
Current detection		<b>v</b>
Point sensors	<ul> <li>Image: A second s</li></ul>	<b>V</b>
Fiber optic sensors		<b>v</b>
Cable monitoring on sensor inputs		<
USB		<ul> <li>Image: A second s</li></ul>
DC supply	<b>v</b>	<b>V</b>
AC supply		<b>V</b>
Data logging		¥

### 🐼 🖶 Motor & Feeder Protection Relays

FEATURE (IEEE #)	PGR-6100	PGR-6130	PGR-6150	MPU-32	MPS	PGR-6800	FPU-32	FPS
Ground fault (50G/N, 51G/N)	<b>v</b>		<ul> <li>Image: A second s</li></ul>	<	<b>v</b>		<ul> <li>Image: A second s</li></ul>	<b>v</b>
Overload (49, 51)		<b>v</b>	<b>v</b>	~	<b>v</b>	<b>v</b>	<ul> <li>Image: A start of the start of</li></ul>	<b>v</b>
Unbalance (current) (46)		<b>v</b>	<b>v</b>	~	<b>v</b>	~	<b>v</b>	V
Phase loss (current) (46)		<b>v</b>	<b>v</b>	<ul> <li>Image: A second s</li></ul>	<ul> <li>Image: A second s</li></ul>	<b>v</b>	<b>v</b>	<b>V</b>
Phase reverse (current) (46)		<b>V</b>	<ul> <li>Image: A second s</li></ul>	<ul> <li>Image: A second s</li></ul>	<b>V</b>	<b>v</b>	<b>v</b>	V
PTC overtemperature (49)		<b>v</b>	<b>v</b>	<ul> <li>Image: A second s</li></ul>	<b>v</b>		<b>v</b>	
Undercurrent (37)			<ul> <li>Image: A second s</li></ul>	<ul> <li>Image: A second s</li></ul>	<b>V</b>	<b>v</b>		
Jam			<b>v</b>	<ul> <li>Image: A second s</li></ul>	<ul> <li>Image: A set of the /li></ul>			
Overcurrent (50, 51)			<ul> <li>Image: A second s</li></ul>	<ul> <li>Image: A second s</li></ul>	<b>V</b>		<b>v</b>	¥
Failure to accelerate			<b>v</b>	<b>~</b>	<b>~</b>			
RTD temperature (38, 49)				<ul> <li>Image: A second s</li></ul>	<b>V</b>		<b>v</b>	V
Starts per hour (66)				<ul> <li>Image: A second s</li></ul>	<b>v</b>			
Differential (87)				<ul> <li>Image: A second s</li></ul>	<b>V</b>			
Reduced overcurrent setting				<ul> <li>Image: A second s</li></ul>	<ul> <li>Image: A second s</li></ul>			
Phase loss (voltage) (47)					<b>V</b>			V
Phase reverse (voltage) (47)					<ul> <li>Image: A set of the /li></ul>			<b>V</b>
Unbalance (voltage) (47)					<b>V</b>			<b>V</b>
Overvoltage (59)					<ul> <li>Image: A second s</li></ul>		<ul> <li>Image: A second s</li></ul>	<b>V</b>
Undervoltage (27)					<b>V</b>			V
Power factor (55)					<b>v</b>			<b>v</b>
Overfrequency (81)					<b>v</b>			V
Underfrequency (81)					<ul> <li>Image: A second s</li></ul>			<b>V</b>
Starter control					<b>v</b>			
Breaker control								<b>v</b>
Underspeed (14)					<b>v</b>			
Integrated CTs		<b>v</b>	<ul> <li>Image: A second s</li></ul>			<ul> <li>Image: A second s</li></ul>		
Off-line insulation monitoring	<b>v</b>							
Metering and data logging			<b>v</b>	<ul> <li>Image: A second s</li></ul>	<b>V</b>		<ul> <li>Image: A second s</li></ul>	<b>V</b>
Communications			V	<b>v</b>	V		<b>v</b>	V
Conformal coating	‡			<b>v</b>	<b>V</b>		<ul> <li>Image: A second s</li></ul>	<b>V</b>
10-year warranty				<b>v</b>	¥		<b>v</b>	V

### Alarm Monitors

FEATURE	M1000	M3000	M4200	M4500	M4600	M4700	M4780
Alarm panel	<	<b>V</b>	<ul> <li>Image: A second s</li></ul>				
Indicator panel	<b>v</b>	•	<b>v</b>	<	<b>v</b>	<b>v</b>	<b>v</b>
No. of inputs	10	24	8	6	8	20	20
Digital input	<b>v</b>	✓*	<ul> <li>Image: A second s</li></ul>	✓	<b>v</b>	<b>v</b>	<b>v</b>
No. of open collector outputs	10	14	4				
Common alarm output ⁺	1oc	1oc	2dryc			1dryc [‡]	1dryc [‡]
Siren output	1dryc	1oc	1dryc			1dryc [‡]	1dryc [‡]
LCD display		<b>v</b>					
Configure from PC	<b>v</b>	V	~				
Configure from DIP switches/ jumper	~		•			~	~
Configure from front panel							
MODBUS-RTU (RS485)	<b>v</b>	V					
LED dimming	<b>v</b>	V	<b>v</b>				
LED synchronizing	<b>v</b>		<b>v</b>				
Panel linking	<b>v</b>						
Remote reset	<b>v</b>	V	<ul> <li>Image: A start of the start of</li></ul>				
Sensor monitoring	<b>v</b>		<ul> <li>Image: A second s</li></ul>				
Insulation monitoring of supply voltage	•		•				
Monitoring of supply voltage	<b>v</b>		•				

*Both analog and digital input.

toc=open collector; dryc=dry contact

‡Optional

NOTE:

Tables are for reference only and include standard and optional configurations. Please see the respective catalog page for exact product specifications. IEEE Device Numbers are shown in parenthesis after the applicable features.



### FEATURES COMPARISONS

### **Output** Generator Protection & Single-Function Relays

FEATURE (IEEE #)	PGR-4300	G2000	G3000	G3300	T2000	T2100	T2200	T2300	T2400	T2500	T2700	T2900	T3000	T3100	T3300
Overload											<b>v</b>				
Overcurrent							~		~	~					
Undercurrent (37)															
Short circuit								V		~					
Reverse power (32)		V			<b>v</b>										
Overfrequency (81)			V										~		
Underfrequency (81)			V										~		
Overvoltage (59)				~										V	V
Undervoltage (27)				V										V	V
Excitation loss (40)						V									
Earth fault															
Differential current relay (87)												~			
Insulation monitoring relay															
Single phase measurement		~	V		V	V					~		V	~	
3-phase measurement				<b>v</b>			V	V	~	~		V			V
Conformal coating						V	V	V	V	<b>v</b>	~	V	V	V	V

### Engine Controls

FEATURE (IEEE #)	M2000	M2500	M2600
Start/stop	<b>v</b>	<b>v</b>	
Digital sensor inputs	V	V	V
Analog sensor inputs		V	
Cable monitoring on fuel/ stop solenoid output		~	~
Graphical display		V	
CAN J1939		<b>v</b>	
USB		V	
SD card slot		~	
Pick-up input	V	V	V

### **Or Generator Controls**

FEATURE (IEEE #)	T2600	T4500	T4800	T4900	T5000	E7800	T7900	M8100	T8400	C6200	S6000	S6100	S6610
3 phase true RMS measurement	<b>v</b>	<b>v</b>	<b>v</b>	<b>v</b>	<b>v</b>			~		~	<b>v</b>	<b>v</b>	
Overcurrent										V	<b>v</b>		
Short circuit										$\checkmark$	<b>v</b>		
Overload										V	<b>v</b>		
Reverse power (32)			<b>v</b>							~	<b>v</b>		
Excitation loss (40)										V	V		
Overfrequency (81)										$\checkmark$	<b>v</b>	$\checkmark$	
Underfrequency (81)										V	$\checkmark$	V	
Overvoltage (59)										<b>v</b>	<b>v</b>	<b>v</b>	
Undervoltage (27)										~	$\checkmark$	~	
ROCOF (81)										>	$\checkmark$		
Vector shift										~			
Preferential load trip										~	<b>v</b>		
Synchronizing (25)		V								V		V	
Check synchronizer (25)					<b>v</b>			<b>v</b>		>		<b>v</b>	
Active load sharing [kW]			<b>v</b>							<b>v</b>		V	
Reactive load sharing [kVAR]				<b>v</b>						<b>v</b>		$\checkmark$	
Power factor regulation				V						V		V	
Dead bus monitoring/ black out limiter								•		<b>&gt;</b>		<b>v</b>	
Load depending start/stop (PM)	~									~			<b>v</b>
Large consumer control (PM)										<b>v</b>			<b>v</b>
Dynamic grid-parallel operation control										>		~	
MODBUS RTU (RS485 interface)										>	•	•	✓
Motorized potentiometer						V							
Electronic potentiometer							<b>v</b>						
Dead bus closure									<b>v</b>				

### 🔼 Engine Diagnostics

FEATURES	BASIC E5000 & E5100	ADVANCED E5000, E5100 & E5200	PROFESSIONAL E5000, E5100, E5200 & 5300
USB	<b>v</b>	<b>~</b>	<b>v</b>
Color LCD	<b>v</b>	<ul> <li>Image: A start of the start of</li></ul>	<ul> <li>Image: A set of the /li></ul>
PC software included	<b>v</b>	<ul> <li>Image: A second s</li></ul>	✓
Upgradable	<b>v</b>	<ul> <li>Image: A set of the /li></ul>	<ul> <li>Image: A set of the /li></ul>
Temperature compensation	<b>v</b>	<ul> <li>Image: A second s</li></ul>	<ul> <li>Image: A second s</li></ul>
Calibration-check integration	<b>v</b>	~	~
Connecting sensor ports	1	2	5
Pressure graph	>	<b>v</b>	<ul> <li>Image: A start of the start of</li></ul>
MIP mode		*	<ul> <li>Image: A set of the /li></ul>
Misfire analysis		<b>~</b>	<ul> <li>Image: A second s</li></ul>
P ^{max}		<ul> <li>Image: A start of the start of</li></ul>	<ul> <li>Image: A second s</li></ul>
p/time	<b>v</b>	<ul> <li>Image: A start of the start of</li></ul>	<ul> <li>Image: A second s</li></ul>
p ^{max} bar graph		<ul> <li>Image: A start of the start of</li></ul>	<ul> <li>Image: A second s</li></ul>
p/alpha		*	<ul> <li>Image: A set of the /li></ul>
dp/alpha		*	<ul> <li>Image: A second s</li></ul>
p/V		*	<ul> <li>Image: A second s</li></ul>
Pressure sensor	<b>v</b>	<b>v</b>	<ul> <li>Image: A second s</li></ul>
Crank-angle sensor			<ul> <li>Image: A set of the /li></ul>
Maximum engines (memory)	5	10	20
Maximum cylinders/ engine (memory)	20	20	20
Maximum number of strokes (memory)	30	30	30

Protection Relays & Controls

8

NOTE: These tables are for reference only and include standard and optional configurations.

*Possible with a crank angle sensor E5300.

### **GROUND-FAULT PROTECTION**

#### SE-601 (PGR-2601) DC Ground-Fault Monitor For Ungrounded DC Systems



76G

5 Year

H 75 mm (3.0")

**W** 55 mm (2.2")

**D** 115 mm (4.5")

(ΨL) c ( B us

Input L: 208/240 Vac

Input H: 480/600 Vac

**H** 87.0 mm (3.43")

CSA certified,

5 years

W 112.5 mm (4.43") **D** 56.0 mm (2.2")

UL Listed (E340889)

Analog Output



#### Features/Benefits

- Sensitive 1- to 20-mA trip settings
- A microprocessor-based ground-fault relay for ungrounded dc systems
- 50-ms to 2.5-s time-delay settings
- Limits ground-fault current to 25 mA
- Form-A and Form-B trip contacts

#### **Specifications**

**IEEE Device Number** Dimensions

Communications Warranty

#### Web Resources

littelfuse.com/se-601

UMBER	SPECIFICATIONS	ACCESSORIES			
	24 Vdc Control Power				
	48 Vdc Control Power	SE-GRM Series Ground Reference Modules PGA-0500 Analog Current Meter			
	120/240 Vac/dc 50/60 Hz Control Power	FGA-0500 Analog Current Meter			

#### EL3100 Ground-Fault & Phase-Voltage Indicator For Grounded/Ungrounded AC Systems

0000	
S SH LIL F4 Littelfuse EL 100 SERIES	HE MA 13 12 11 18 DIVERTIDADAGEDIC CONDITIONEDAGEDIC FAULT A II C
AT 2 3 4	
- 9999	

#### **Features/Benefits**

**ORDERING NU** 

SE-601-0D SE-601-0T SE-601-0U

- Meets National Electrical Code (NEC®) Article 250.21 and Canadian Electrical Code Part 1, Section 10-106 (2) requirements for ungrounded systems
- System voltage is not present at the remote LED locations
- Indicates the presence of voltage on both grounded and ungrounded systems

#### **Specifications**

Input Voltage Dimensions

Approvals

Warranty

Web Resources littelfuse.com/el3100

ORDERING NUMBER	MOUNTING	ACCESSORIES
EL3100-00	DIN, Surface	RK-310X-0Y (optional)

#### PGR-3200 Ground-Fault Protection System For Ungrounded AC Systems



#### **Features/Benefits**

- Meets NEC Article 250.21 (B)
- Continuously monitors the insulation integrity of ungrounded electrical systems for ground faults
- Provides 2 warnings and 1 alarm
- Analog output for insulation reading

#### **Specifications**

Communications

Warrantv

**IEEE Device Number** Dimensions

27,64 **H** 75 mm (3") **W** 110 mm (3.9") **D** 110 mm (4.3") Analog Output 5 Year

Web Resources

#### littelfuse.com/pgr-3200

ORDERING NUMBER	SPECIFICATIONS	ACCESSORIES
PGR-3200	240 Vac Control Power	PGH family High Tension Couplers
PGR-3200-120	120 Vac Control Power	PGA-0510 Analog Insulation Meter



50G/N, 51G/N

**H** 75 mm (3.0")

W 55 mm (2.2")

**D** 115 mm (4.5")

Analog Output

5 Year

### **GROUND-FAULT PROTECTION**

#### SE-701 (PGR-5701) Ground-Fault Monitor For Solidly and Resistance-Grounded Systems



#### **Features/Benefits**

SE-701-0U

SE-701-0D

SE-701-0T

SE-701-03

- Choice of input CT gives wide setting range
- A microprocessor-based ground-fault relay for resistance-grounded and solidly
- grounded systemsMicroprocessor-based unit with DFT
- Non-volatile trip memory retains trip state
- Compatible with VFD applications
- Adjustable pick-up settings from 1% to 99% of CT primary rating, as low as 50 mA

120/240 Vac/dc Control Power 12/24 Vdc Control Power

48 Vdc Control Power

24 Vac Control Power

 Adjustable time-delay settings from 0.5 to 2.5 sec

ORDERING NUMBER SPECIFICATIONS

#### Specifications

IEEE Device Numbers Dimensions

Communications Warranty

#### Web Resources

littelfuse.com/se-701

#### ACCESSORIES

Ground Fault Current Transformers PGA-0500 Analog Current Meter

#### SE-703 Earth Leakage Monitor For Solidly and Resistance-Grounded Systems

#### Features/Benefits

- Provides sensitive ground-fault protection
- A microprocessor-based ground-fault relay for resistance-grounded and solidly earthed systems
- Microprocessor-based unit with DFT
- Non-volatile trip memory retains trip state
- Compatible with VFD applications
- Adjustable pick-up settings from 25 mA to 500 mA
- Adjustable time-delay settings from 50 to 500 ms

#### Specifications

IEEE Device Numbers Dimensions 50G/N, 51G/N H 75 mm (3.0") W 55 mm (2.2") D 115 mm (4.5") Analog Output 5 Year

(UL) c tus C

50G/N, 51G/N

**H** 75 mm (3.0") **W** 55 mm (2.2")

**D** 115 mm (4.5")

Analog Output

5 Year

Communications Warranty

Web Resources littelfuse.com/se-703

**Specifications** 

Communications

Web Resources

littelfuse.com/se-704

Dimensions

Warrantv

**IEEE Device Numbers** 

ORDERING NUMBER	SPECIFICATIONS	ACCESSORIES
SE-703-0U	120/240 Vac/dc Control Power	
SE-703-0D	12/24 Vdc Control Power	EFCT series Current Transformers
SE-703-0T	48 Vdc Control Power	PGA-0500 Analog Current Meter
SE-703-03	24 Vac Control Power	

#### **SE-704 (PGR-4704)** Earth Leakage Monitor For Solidly and Resistance-Grounded Systems



- Provides very sensitive groundfault protection
- Microprocessor-based unit with DFT
- Non-volatile trip memory retains trip state
- Compatible with VFD applications
  Adjustable pick-up settings from 10 mA to 5 A
- Adjustable time-delay settings from
- 0.5 to 2.5 sec

# ORDERING NUMBERSPECIFICATIONSACCESSORIESSE-704-0U120/240 Vac/dc Control PowersE-CS30 series Current TransformersSE-704-0D12/24 Vdc Control PowerSE-CS30 series Current TransformersSE-704-0T48 Vdc Control PowerPGA-0500 Analog Current MeterSE-704-0324 Vac Control PowerSE-0500 Analog Current Meter

### **GROUND-FAULT PROTECTION**

#### T2800 Earth-Fault Relay For Solidly and Resistance-Grounded Systems

# 

#### Features/Benefits

- Accepts high supply voltage variation
- Visual indication of power, pick-up and output trip
- Direct line-line or line-neutral voltage supply
- Wide range of combined current and delay settings
- DIN-rail or Screw-mount

#### Specifications

Trip Level	
Delay	
Dimensions	

#### Web Resources

littelfuse.com/t2800

0.02-0.2 x I_N or 0.2-2 x I_N 0.1-1 sec or 1-10 sec **H** 70 mm (2.76") **W** 100 mm (3.94") **D** 115 mm (4.52")

CE

ORDERING NUMBER	1	TERMINALS		I
	1-3	2-3	I _N	
T2800-00	230 V		5 A	
T2800-01	450 V	400 V	5 A	
T2800-02	127 V	120 V	5 A	
T2800-04	24V DC+AC		5 A	
T2800-05	480 V	415 V	5 A	
T2800-08	230 V		1 A	

### **EL731** AC/DC Sensitive Earth-Leakage For Solidly-Grounded Systems

E Littel	lusei	-	EL711 Magnet	7
Met	El	731		
-				

**ORDERING NUMBER** 

#### **Features/Benefits**

COMMUNICATIONS

- Microprocessor based relay that offers complete coverage for all frequencies
- Adjustable trip settings provide wide range protection and coordination
- Operate in both AC or DC mode and single or combined ranges
- LED indication for visual trip, alarm and CT

#### _

IEEE Device Numbers

**Specifications** 

**Web Resources** 

littelfuse.com/el731

Max Voltage

Dimensions

Web Resources littelfuse.com/t3200

Dimensions

Warranty

38, 49, 50G/N, 51G/N, 79G H 48 mm (1.9") W 96 mm (3.8") D 129 mm (5.0") 5 Years

EL731_00_X0	120/240 Vac/Vdc	None			
	-, ,				
EL731-01-X0	120/240 Vac/Vdc	DeviceNet™			
EL731-02-X0	120/240 Vac/Vdc	Profibus®			
EL731-03-X0	120/240 Vac/Vdc	Ethernet/IP [™]	ORDERING NUMBER	CONTROL POWER	COMMUNICATIONS
EL731-04-X0	120/240 Vac/Vdc	Modbus [®] TCP	EL731-20-X0	24 Vdc	None
EL731-10-X0	48 Vdc & 24 Vac	None	EL731-21-X0	24 Vdc	DeviceNet™
EL731-11-X0	48 Vdc & 24 Vac	DeviceNet™	EL731-22-X0	24 Vdc	Profibus®
EL731-12-X0	48 Vdc & 24 Vac	Profibus®	EL731-23-X0	24 Vdc	Ethernet/IP™
EL731-13-X0	48 Vdc & 24 Vac	Ethernet/IP [™]	EL731-24-X0	24 Vdc	Modbus®TCP
EL731-14-X0	48 Vdc & 24 Vac	Modbus®TCP			
	EL731-03-X0 EL731-04-X0 EL731-10-X0 EL731-11-X0 EL731-12-X0 EL731-13-X0	EL731-01-X0         120/240 Vac/Vdc           EL731-02-X0         120/240 Vac/Vdc           EL731-03-X0         120/240 Vac/Vdc           EL731-04-X0         120/240 Vac/Vdc           EL731-10-X0         48 Vdc & 24 Vac           EL731-11-X0         48 Vdc & 24 Vac           EL731-12-X0         48 Vdc & 24 Vac           EL731-13-X0         48 Vdc & 24 Vac	EL731-01-X0         120/240 Vac/Vdc         DeviceNet™           EL731-02-X0         120/240 Vac/Vdc         Profibus®           EL731-03-X0         120/240 Vac/Vdc         Ethernet/IP™           EL731-04-X0         120/240 Vac/Vdc         Modbus®TCP           EL731-10-X0         48 Vdc & 24 Vac         None           EL731-11-X0         48 Vdc & 24 Vac         DeviceNet™           EL731-12-X0         48 Vdc & 24 Vac         DeviceNet™           EL731-13-X0         48 Vdc & 24 Vac         Ethernet/IP™	EL731-01-X0         120/240 Vac/Vdc         DeviceNet™           EL731-02-X0         120/240 Vac/Vdc         Profibus®         ORDERING NUMBER           EL731-03-X0         120/240 Vac/Vdc         Ethernet/IP™         ORDERING NUMBER           EL731-04-X0         120/240 Vac/Vdc         Ethernet/IP™         EL731-20-X0           EL731-10-X0         48 Vdc & 24 Vac         None         EL731-21-X0           EL731-11-X0         48 Vdc & 24 Vac         DeviceNet™         EL731-22-X0           EL731-12-X0         48 Vdc & 24 Vac         Profibus®         EL731-23-X0           EL731-13-X0         48 Vdc & 24 Vac         Ethernet/IP™         EL731-23-X0	EL731-01-X0         120/240 Vac/Vdc         DeviceNet [™] EL731-02-X0         120/240 Vac/Vdc         Profibus [®] EL731-03-X0         120/240 Vac/Vdc         Ethernet/IP [™] EL731-04-X0         120/240 Vac/Vdc         Ethernet/IP [™] EL731-10-X0         48 Vdc & 24 Vac         None           EL731-11-X0         48 Vdc & 24 Vac         DeviceNet [™] EL731-12-X0         48 Vdc & 24 Vac         DeviceNet [™] EL731-12-X0         48 Vdc & 24 Vac         DeviceNet [™] EL731-12-X0         48 Vdc & 24 Vac         Profibus [®] EL731-13-X0         48 Vdc & 24 Vac         Ethernet/IP [™] EL731-13-X0         48 Vdc & 24 Vac         Ethernet/IP [™]

#### **T3200** Double Insulation Monitoring Relay For Ungrounded Systems

**CONTROL POWER** 



#### Features/Benefits

- Continuously monitors two systems galvanically separated from each other
- Ensures correct operation in spite of voltage supply fluctuations
- Visual indication of power pick-up, and output trip

ORDERING NUMBER	1-3 TERMINALS	2-3 TERMINALS	ACCESSORIES
T3200.0010	230 V		
T3200.0020	450 V	400 V	
T3200.0030	480 V	415 V	E2333 Megaohmmeter
T3200.0050	110 V	100 V	
T3200.0060	127 V	120 V	

0-5 MW 660 V H 70 mm (2.75") W 100 mm (3.94") D 115 mm (4.52") CE

8

(U) c (H us C

Specifications Insulation Level



### TRAILING CABLE PROTECTION

#### SE-105 • SE-107 Ground-Fault Ground-Check Monitor





#### **Features/Benefits**

- Adjustable pickup so unit can be used on a wide variety of trailing cable applications
- Adjustable time delay for quick protection and system coordination
- Harmonic filter prevents false operation

#### **Specifications**

IEEE Device Numbers Dimensions 3GC, 50G/N, 51G/N H 150 mm (5.9") W 109 mm (4.3") D 100 mm (4.0") 5 Years

#### Warranty

Web Resources littelfuse.com/se-105 littelfuse.com/se-107

ORDERING NUMBER	CONTROL POWER	ACCESSORIES
SE-105	120 Vac	
SE-105D	120 Vac/Vdc	CT200 Series Current Transformer
SE-105E	240 Vac	1N5339B Termination Assembly
SE-107	120 Vac	SE-TA6 Termination Assembly
SE-107D	120 Vac/Vdc	SE-TA6-SM Stud-Mount Termination Assembly
SE-107E	240 Vac	

#### SE-134C (PGM-8134C) • SE-135 Ground-Fault Ground-Check Monitor



#### **Features/Benefits**

- Fail-safe ground check circuit
- Combination ground-wire monitor and ground-fault relay
- Zener-characteristic termination device
- High-induced-ac rejection
- DFT (harmonic) filter

#### Specifications

IEEE Device Numbers Dimensions Warranty

₩ 99 mm (3.9") D 145 mm (5.7") 5 Year

#### Web Resources

littelfuse.com/se-134c littelfuse.com/se-135

ORDERING NUMBER	OPTION	POWER SUPPLY	COMM
SE-134C	Blank or XGC	0= 120/240 Vac/Vdc 1=24/48 Vdc	0=None
SE-135	Blank or XGC	0= 120/240 Vac/Vdc 1=24/48 Vdc	0=None 3=Ethernet

#### SE-145 Ground-Fault Ground-Check Monitor

#### **Features/Benefits**

- Adjustable pick can be used on a wide variety of trailing cable applications
- Adjustable time delay for quick protection and system coordination
- Separate annunciations of ground-fault and ground-check faults

#### Specifications

IEEE Device Number Dimensions 3GC, 50G, 50N, 51G, 51N H 213 mm (8.4") W 192 mm (7.6") D 176 mm (7.0") Ethernet Optional 5 Year

Communications Warranty

#### Web Resources littelfuse.com/se-145

ORDERING NUMBER	CONTROL POWER	СОММ
SE-145-00-00	120/240 Vac; 110-250 Vdc	—
SE-145-03-00	120/240 Vac; 110-250 Vdc	Modbus [®] TCP
SE-145-30-00	24 Vdc Battery Back-up	—
SE-145-33-10	24 Vdc Battery Back-up	Modbus®TCP

3GC, 50G, 50N, 51G, 51N

H 213 mm (8.4")

### RESISTANCE GROUNDING AND NGR MONITORING

#### SE-325 (PGM-8325) Neutral-Grounding-Resistor Monitor



#### Description

The SE-325 Neutral-Grounding-Resistor Monitor is used on resistance-grounded systems up to 25 kVac to monitor the integrity of the neutral-toground path for loose connection, corrosion, and ground faults.

#### **Features/Benefits**

- Adjustable ground-fault detection ٠
- Adjustable time-delay settings
- Selectable fail-safe mode
- Conformally coated circuit boards

ORDERING NUMBER	SPECIFICATIONS
SE-325	120 Vac
SE-325D	120 Vdc
SE-325E	240 Vac

#### **Specifications IEEE Device Numbers**

Dimensions

Warranty

Web Resources littelfuse.com/se-325



50G/N, 51G/N, 59N, 86, 3 H 150 mm (5.9") W 109 mm (4.3") **D** 100 mm (4.0") 5 Year

ACCESSORIES CT200 Series Current Transformers

**ER Series Sensing Resistors** 

#### SE-330AU Neutral-Grounding-Resistor Monitor

Ŧ

#### Description

An advanced ground-fault and ground-resistor monitoring relay for low and medium-voltage transformers and generators. The SE-330AU complies with AS/NZS 2081.3:2002.

#### **Features/Benefits**

- Continuous NGR monitoring Detect ground-fault anywhere on monitored system
- Adjustable pickup settings
- Adjustable time delay settings

#### **Specifications** Dimensions

Communications

**Specifications IEEE Device Numbers** 

Web Resources

littelfuse.com/se-330

Dimensions

Warranty

Warranty

Web Resources littelfuse.com/se-330au

RDERING NUMBER		POWER SUPPLY	COMM			K4 UNIT HEALTHY CONTACT			
E-330AU	-	Х	Х	-	0	Х			
			0=USB Only						
			1=DeviceNet						
E-330AU		0=120/240	3=EtherNet (Dual RJ45)			0=Normally Open			
r all apps. 35 kV or less		Vac/Vdc	4=EtherNet (SC Fiber & RJ45)			o-Normany open			
E-330HV			5=EtherNet (Dual SC Fiber)			1 Normally Closed			
r 72 kV apps.		2=48 Vdc	6=IEC61850 (Dual RJ45)			1=Normally Closed			
			7=IEC61850 (SC Fiber & RJ45)						
			8=IEC61850 (Dual SC Fiber)						

#### SE-330 (PGR-5330), SE-330HV Neutral-Grounding-Resistor Monitor

OR SE

SE for SE for



#### Description

Advanced ground-fault and grounding-resistor monitoring relay. It measures neutral current, neutral-to-ground voltage and neutral-to-ground resistance.

#### **Features/Benefits**

- Continuous NGR monitoring
- Detect ground-fault on monitored system
- Adjustable pickup (2-100%)
- Adjustable time delay (0.1 10s)

ORDERING NUMBER		POWER SUPPLY	СОММ		CERTIFICATION	K4 UNIT HEALTHY CONTACT
SE-330	-	Х	X	-	Х	Х
SE-330 for all apps. 35 kV or less SE-330HV for 72 kV apps.		0=120/240 Vac/Vdc 2=48 Vdc	0=RS-232 1=RS-232 & DeviceNet [™] 2=RS-232 & Profibus ^{®(1)} 3=RS-232 & EtherNet/IP™ & Modbus®TCP		1–054	0=Normally Open 1=Normally Closed



50G/N, 51G/N, 59N, 3, 86 H 213 mm (8.4") **W** 98 mm (3.9") **D** 132 mm (5.2") 5 Year



8

(E **C** 



5 Year



### RESISTANCE GROUNDING AND NGR MONITORING

#### NGR Series

#### **Neutral-Grounding-Resistor System**



Neutral-Grounding Resistors (NGRs) are used to ground power systems by inserting a resistor between the system neutral and ground. This lowers the prospective ground-fault current to a predetermined value.

A properly designed resistance-grounded system provides benefits over both ungrounded and solidly grounded systems. Because the system is grounded, transient overvoltages do not occur and ground-fault current can flow, allowing it to be detected and measured. Also, because a resistor is used to ground the system, the very large and destructive ground-fault currents of solidly grounded systems are absent. Ground-fault relays (such as the SE-701) can be used on feeders to provide selective coordination and the ability to quickly locate or isolate the fault.

#### Web Resources

For more information on Resistance Grounding Systems, visit littelfuse.com/NGR

	SYSTEM LINE-NEUTRAL VOLTAGE		NGR CURRENT		DUTY CYCLE		DRAWING NUMBER			COMPONENTS OSURE		OTHER OPTIONS		ENCLOSURE STYLE		
NGR	Х	-	Х	-	Х	-	XXXX-RX	-	Х	Х	-	Х	_	Х		
					C = continuous				ER/ = Includes	CT = CT200				N3R = Galvanized		
					10 = 10 seconds						Sensing Resistor	E1 = EFCT-1				NEMA 3R
					30 = 30 seconds				Blank = No	E26 = EFCT-26		ZZ = Zigzag		N3RSS = Stainless		
					60 = 60 seconds				Sensing Resistor	C26 = SE-CS30-26		transformer		Steel NEMA 3R		
	277, 347,44000		AMPERES				Assigned by factory			C70 = SE-CS30-70		(Note: may be in separate N3R				
							57 1001017			Contact factory for other choices.		enclosure)				
													Blank		lone	
										OPE	N =	None				

Note: Order SE-325, SE-330, and SE-701 separately.

#### PGN-Series Pulsing High-Resistance Grounding System



The PGN Pulsing High-Resistance-Grounding Systems are used to ground power systems by inserting a resistor between system neutral and ground to lower the ground-fault current to a predetermined value.

Properly sized Resistance Grounding Systems solve two problems of ungrounded systems—transient overvoltages and the difficulty of locating ground faults. They also significantly reduce damage caused by ground faults on solidly grounded systems. The current limitation eliminates the Arc-Flash Hazards associated with the first ground fault. The hazards associated with phase-to-phase electrical faults must still be mitigated by using current-limiting fuses and other methods. High-Resistance Grounding Systems include all necessary components to convert to a resistance grounded system.

Options include a pulsing circuit and SE-701 Ground-Fault Monitors to provide a method for locating ground faults.

#### Web Resources

For more information on Resistance Grounding Systems, visit **littelfuse.com/pgn-3000** 

### **Protection Relays & Controls**

### MOTOR PROTECTION

#### PGR-6100 (GFR-4000) Motor Ground-Fault and Insulation Relay



#### **Features/Benefits**

- Online monitoring to detect ground faults ٠
- Offline monitoring of insulation resistance Continuously monitors for predictive
- protective capabilities
- CT loop monitoring
- Individual alarm contacts (form C)
- Individual analog outputs to indicate insulation resistance and ground-fault current

#### **Specifications**

**IEEE Device Numbers** Dimensions

Communications Warranty

#### Web Resources

littelfuse.com/pgr-6100

ORDERING NUMBER	SPECIFICATIONS	ACCESSORIES
PGR-6100-120	24 Vdc/120 Vac Control Power	PGC-5000 Series Ground-Fault Transformers PGA-0500 Analog % Current Meter
PGR-6100-240	240 Vac Control Power	PGA-0510 Analog Ohm Meter PGH Family High Tension Couplers

#### PGR-6130 Electronic Overload Relay



#### **Features/Benefits**

- No external CT required for currents up to 90 A
- Cause-of-trip indication
- N.O. and N.C. alarm contacts
- Adjustable overload trip class setting
- Adjustable current pickup
- Over-temperature (PTC) protection Thermal overload protection

#### **Specifications**

IEEE Device Numbers Dimensions Warranty

Web Resources

littelfuse.com/pgr-6130

ORDERING NUMBER	SPECIFICATIONS	FULL-LOAD CURRENT	ACCESSORIES
PGR-6131-24	24 Vdc	4-16.7 A	
PGR-6131-120	120 Vac	4-16.7 A	
PGR-6131-240	240 Vac	4-16.7 A	
PGR-6132-24	24 Vdc	15-40.5 A	DCD C120 Demote Indiantian
PGR-6132-120	120 Vac	15-40.5 A	PGB-6130 Remote Indication and Reset Assembly
PGR-6132-240	240 Vac	15-40.5 A	and hose rasembly
PGR-6133-24	24 Vdc	40-91 A	
PGR-6133-120	120 Vac	40-91 A	
PGR-6133-240	240 Vac	40-91 A	

#### PGR-6150 Motor Protection System

#### **Features/Benefits**

- 13 protective functions 2 relay outputs, 1 digital input
- •
- No external CT required for currents up to 25 A Thermal protection through starting, running,
- overload and cooling cycles
- RS-485 interface with Modbus® RTU
- Optional PGR-6150-OPI Operator Interface

#### **Specifications IEEE Device Numbers**

51, 51G/N, 66 H 83 mm (3.3") RS-485 with Modbus® RTU 5 years

37, 46, 49, 50, 50G/N,

**(U**) C €

Communications Warranty

#### Web Resources

littelfuse.com/pgr-6150

ORDERING NUMBER	SPECIFICATIONS	ACCESSORIES		
PGR-6150-24	24/48 Vdc (Control Unit)			
PGR-6150-120	120/240 Vac/dc (Control Unit)	PGR-6150-OPI Operator Interface PGC-6000 Series Ground-Fault Transformer		
PGR-6150-OPI	Operator Interface			



€C€

(կ)

50G/N, 51G/N, 64, 74

H 75 mm (3.0")

**W** 100 mm (3.9")

**D** 115 mm (4.5")

5 years

46, 49, 51

5 years

**D** 99 mm (3.9")

2 Analog Outputs

8

....











### MOTOR PROTECTION

#### MPU-32 (PGR-6200) Motor Protection Unit

#### Features/Benefits

- Reduced overcurrent setting for maintenance
- Dynamic thermal modeling
- Communications for different networks
- Optional RTD protection
- Optional differential protection
- Conformal coating
- Modular system and compact design makes installation easy for new or retrofit applications

c <b>FL</b> us	c∰∙us	C	C	e
----------------	-------	---	---	---

37, 38, 46, 49, 50, 50G/N, 51, 51G/N, 66, 74, 86, 87 H 96 mm (3.78") W 96 mm (3.78") D 132 mm (5.2") RS-232 (Standard); RS-485, DeviceNet™ Ethernet (Optional) 10 years



#### MPS (PGR-6300) Motor Protection System

#### Features/Benefits

- Overcurrent reduction setting for maintenance
- Monitors voltage, current, and temperature
- 22 motor protection functions
- Conformal coating
- Dynamic thermal modeling
- Starter control, Metering, and Data Logging
- Optional RTD protection with hazardouslocation certified RTD module
- Optional differential protection
- Modular design makes installation easy

Specifications	
IEEE Device Numbers	1, 2
	37,

**Dimensions (OPI)** 

Communications

Web Resources

littelfuse.com/mps

Warranty

Specifications IEEE Device Numbers

Dimensions

Warranty

Communications

Web Resources

1, 2, 3, 5, 9, 14, 18, 19, 27, 34, 37, 38, 46, 47, 48, 49, 50, 50G, 50N, 51, 51G/N, 55, 59, 66, 74, 81, 86, 87, 94 H 98 mm (3.86") W 192 mm (7.56") D 0.42 mm (1.65") Allen-Bradley[®] DF1 & Modbus[®] RTU (Standard); DeviceNet[™], Profibus[®], Ethernet (Optional) 10 years

	 -
	SEMI
-	•

ORDERING NUMBER	COMMUNICATIONS	ACCESSORIES
MPS-CTU-01-00	RS-485	
MPS-CTU-02-00	RS-485 & DeviceNet™	Phase Current Transformers
MPS-CTU-03-00	RS-485 & Profibus®	Ground-Fault Current Transformers MPS-RTD Temperature Input Module
MPS-CTU-04-00	RS-485 & Ethernet	MPS-DIF Differential Current Module
MPS-0PI-01-00	Operator Interface	

#### MPU-32-X69X (PGR-6210) & MPS-469X (PGR-6310) Motor Protection Retrofit Kits





- Direct replacement for GE Multilin 169, 269, 369 and 469 relays
- Microprocessor-based protection
- Proven reliability
- Conformally coated circuit boards
- Pre-wired module allows minimal change-out time
- Ability to match existing overcurrent values

#### Ordering Information MPU-32-X69X

#### Ordering Information MPS-469X

		MODULE CONFIGURATION	MPS COMMUNICATION	FUTURE OPTIONS
	-	Х	Х	000
×		0 = None	1 = RS485	
469)		1 = One MPS-RTD Module	2 = RS485 & DeviceNet	
MPS-469X		2 = Two MPS-RTD Modules	3 = RS485 & Profibus	
Σ		3 = One MPS-DIF Module	4 = RS485 & Ethernet	
		4 = One MPS-RTD Module & One MPS-DIF Module		

	RTD INPUTS	MPU-32 COMMUNICATION	GROUND-FAULT CT	FUTURE OPTIONS
× -	Х	Х	Х	00
X65	0 = One Platinum 100 Ω	0 = TIA232	0 = Wired for wGround-Fault CT (50 mA Secondary)	
-32-X69X	1 = One Platinum 100 Ω & 8-input MPS-RTD Module	1 = TIA232 & TIA485	1 = Wired for 1- or 5-A Secondary Ground-Fault CT	
Ļ'		2 = TIA232 & DeviceNet		
Σ		4 = TIA232 & Ethernet		

8



c 🕀 ·us 🕑

### PUMP AND FEEDER PROTECTION

#### PGR-6800 Pump Protection Relay



#### **Features/Benefits**

- No external CT required for currents up to 90 A
- Cause-of-trip indication
- N.O. and N.C. alarm contacts
- Adjustable overload trip class setting
- Adjustable current pickup
- Undercurrent protection



**IEEE Device Numbers** Dimensions

37, 46, 49, 51 H 83 mm (3.3") W 78 mm (3.1") **D** 99 mm (3.9") 5 years

Warranty

#### Web Resources littelfuse.com/pgr-6800

ORDERING NUMBER	SPECIFICATIONS	FULL-LOAD CURRENT	ACCESSORIES	
PGR-6801-24	24 Vdc	7-19.6 A		
PGR-6801-120	120 Vac	7-19.6 A		
PGR-6801-240	240 Vac	7-19.6 A		
PGR-6802-24	24 Vdc	19-44.2 A	PGB-6800 - Remote Indication and Reset Assembly	
PGR-6802-120	120 Vac	19-44.2 A		
PGR-6802-240	240 Vac	19-44.2 A	and neset Assembly	
PGR-6803-24	24 Vdc	40-90.4 A		
PGR-6803-120	120 Vac	40-90.4 A		
PGR-6803-240	240 Vac	40-90.4 A		

#### FPU-32 (PGR-7200) Feeder Protection Unit

#### **Features/Benefits**

- Protection, metering, and data-logging functions
- Programmable using the operator interface, the TIA-232 port, or an optional communications network
- IEC & IEEE protection curves
- CT saturation compensation
- Communications for different networks
- Two set-point groups

#### **Specifications**

IEEE Device Numbers	26, 46, 49, 50, 50G/N,
	51, 51G/N, 74, 86
Dimensions	<b>H</b> 96 mm (3.78")
	<b>W</b> 96 mm (3.78")
	<b>D</b> 132 mm (5.2")
Communications	TIA-232, RS-485, DeviceNet™, Ethernet
Warranty	10 years

#### Web Resources

littelfuse.com/fpu-32

ORDERING NUMBER	SPECIFICATIONS	ACCESSORIES	
FPU-32-00-00	TIA-232 Communications		
FPU-3200-01-00	TIA-232 & RS-485 Communications	Phase Current Transformers	
FPU-3200-02-00	TIA-232 & DeviceNet™ Communications	Ground-Fault Transformer	
FPU-3200-04-00	TIA-232 & Ethernet Communications		

#### FPS (PGR-7300) Feeder Protection System

#### **Features/Benefits**

- Monitors voltage and current
- Long-time overcurrent provides thermal protection for feeder or load
- Instantaneous overcurrent to detect catastrophic failure
- Coordinations using IEEE and IEC

#### **Specifications IEEE Device Numbers**

**Dimensions (OPI)** 

Warranty

Web Resources littelfuse.com/fps



ORDERING NUMBER	SPECIFICATIONS	ACCESSORIES	
FPS-CTU-01-00	RS-485 Communications		
FPS-CTU-02-00	RS-485 & DeviceNet [™] Communications	Phase Current Transformers	
FPS-CTU-03-00	RS-485 & Profibus [®] Communications	Ground-Fault Current Transformer MPS-RTD Temperature Input Module	
FPS-CTU-04-00	RS-485 & Ethernet Communications	SE-IP65CVR-M Cover	
FPS-OPI-01-00	Recommended		



8

**Protection Relays & Controls** 





(ዚ)



### **ARC-FLASH PROTECTION AND GFCI**

#### PGR-8800 (D1000) Arc-Flash Protection Relay





#### **Ordering Information**

ORDERING NUMBER	COMMUNICATIONS
PGR-8800-00 (UL, CE, C-tick)	Multi-unit linking, Modbus® RTU
ACCESSORIES	REQUIREMENT
PGA-LS10 (A1000)	Required*
PGA-LS20 (A2000)/ PGA-LS25 (A2000.0020) PGA-LS30 (A2000.0030)	Required*
PGA-1100 (D1100)	Optional
Current Transformer	Recommended

*At least one sensor is required. However, the exact number of sensors for proper coverage depends on the application.

#### Industrial Shock-Block Ground-Fault Circuit Interruption

#### **Open-Chassis Model**



Operator Interface

Enclosed Model

#### **Ordering Information**

ORDERING NUMBER	VOLTAGE (V)	TRIP LEVEL (mA)	UL CATEGORY/CLASS	
SB6100-00x-0	208	20 (Fixed)		
SB6100-10x-0	240		UL 943C Class C special-purpose GFCI	
SB6100-20x-0	480		- Frank Frank -	
SB6100-30x-0	600		UL 943C Class D special-purpose GFCI	
SB6100-01x-0	208	6, 10, 20, 30 (Selectable)		
SB6100-11x-0	240		UL 943/UL 1053	
SB6100-21x-0	480		Equipment ground-fault protective device (EGFPD)	
SB6100-31x-0	600			

#### Description

The PGR-8800 is a microprocessor-based relay that limits arc-fault damage by detecting the light from an arc flash and rapidly tripping. Phase-current-transformer inputs are provided for current-constrained arc-flash protection and, when so equipped, a programmable definitetime overcurrent function can be enabled. An optical sensor on the PGR-8800 and adjustable trip level reduce the chance of nuisance tripping by setting a threshold for ambient light. Sensors, inputs, and connections are monitored to ensure fail-safe operation. A secondary solid-state trip circuit provides a redundant trip path. A USB port is used for configuration and access to event logs and graphs.

#### **Specifications**

**IEEE Device Numbers Input Voltage** Dimensions

**Optical Trip Settings Current Trip Setting (A) Indication Contact Mode** Trip Coil Voltage⁽¹⁾ **Expandable System** Warranty Mounting

#### Web Resources

littelfuse.com/arcflash

Overcurrent (50), Arc Flash (AFD) 100-240 Vac, 14-48 Vdc, and 110-250 Vdc **H** 130 mm (5.2"); **W** 200 mm (7.9"); **D** 54 mm (2.2") 9-25 klux, 800 us-20 s Programmable Fail-safe 24-300 Vdc. 24-300 Vac Link up to 4 PGR-8800 units 5 years DÍN (with D0050 adapter clips), Surface



#### Description

#### Special Purpose Ground-Fault Circuit Interrupter (GFCI). **Class C and Class D**

Industrial Shock Block (ISB) is a personnel protection device designed to meet the new requirements for special-purpose GFCIs defined by UL 943C. ISB is the first and only permanently connected Class C and Class D GFCI on the market. Class C GFCIs is introduced to be used on systems where the line-to-line voltage is 480 V or less with a trip level of 20 mA, while Class D GFCI is intended to be used on 600 V systems. These improvements to the standard Class A GFCI (6 mA trip level used on 240 V systems or less) were made to allow the use of GFCIs in industrial facilities.

#### **Equipment Ground-Fault Protective Device (EGFPD)**

ISB is also available with adjustable protection settings as an EGFPD. The EGFPD models can be set to trip at 6, 10, 20 or 30 mA. This offers more flexibility since GFCI devices are not allowed to have an adjustable trip level.

#### **Specifications**

**Voltage Rating Amperage Rating Short Circuit Rating Trip Level Settings Trip Time Setting** Dimensions

See ordering information 100 A (continuous) 50.000 A Selectable (6, 10, 20, 30 mA), or fixed at 20 mA Inverse time trip curve Enclosed: H 453.8 mm (17.9"); W 406.2 mm (16.0"); D 223.3 mm (8.8") Open-chassis: H 455.0 mm (17.9"); **W** 340.7 mm (13.4"); **D** 174.9 mm (6.8")

#### Web Resources

littelfuse.com/IndustrialShockBlock

8

Note: x=0 for open-chassis models and 1 for enclosed models

### **GENERATOR & SINGLE-FUNCTION PROTECTION**

#### PGR-4300 Generator Ground-Fault Relay



#### Features/Benefits

- No CTs required
- Provides a simple method for tripping a groundfault condition on generators
- Use with 3- or 4-pole transfer switches
- Monitors neutral-to-ground integrity
- Adjustable pick-up settings from 100 to 1200 A
- Adjustable time-delay settings from 0 to 1 sec

#### **Specifications**

IEEE Device Numbers Dimensions

Communications Warranty

Web Resources littelfuse.com/pgr-4300

10	ORDERING NUMBER	SPECIFICATIONS	ACCESSORIES
	PGR-4300-12	12 Vdc Control Power	
a series	PGR-4300-24	24 Vdc Control Power	PGA-0500 Analog Current Meter
•	PGR-4300-120	120 Vac Control Power	

#### G2000 Power Relay



#### Features/Benefits

- Detects power level for protection, control and monitoring
- PC configuration for forward power or reverse power functionality
- User configured scales and setpoints suits a broad variety of applications
- 63 Vac to 690 Vac systems can be monitored by the same unit

24 Vdc, 5 A Control Power

ORDERING NUMBER SPECIFICATIONS

#### Specifications

Supply Input Voltage Input Current Frequency Dimensions

Web Resources littelfuse.com/g2000 8-36 Vdc/0.75 W at 24 Vdc 63-690 Vac ± 30% 5 A CT, max. 10 A 35-75 Hz H 73 mm (2.9") W 75 mm (3.0") D 114 mm (4.5")

50G/N, 51G/N

H 75 mm (3.0")

**W** 55 mm (2.2")

**D** 115 mm (4.5")

Analog Output

5 Year

(ዚ)

CE

CE

ACCESSORIES G0100 Programming Kit

#### G3000 Frequency Relay

#### Features/Benefits

G2000.0010

- Frequency monitor generators, busbars or other distribution systems
- PC configuration for over and under frequency protection one unit
- User configured scales and setpoints suits a broad variety of applications
- 63 Vac to 690 Vac systems can be monitored by the same unit

	Sp	5	Speci	ifica	tions	
Supply	Su	S	Supply			

Input Voltage Input Current Frequency Dimensions 63-690 Vac ± 30% 5 A CT, max. 10 A 35-75 Hz H 73 mm (2.9") W 75 mm (3.0") D 114 mm (4.5")

8-36 Vdc/0.75 W at 24 Vdc

#### Web Resources littelfuse.com/g3000

ORDERING NUMBER	SPECIFICATIONS	ACCESSORIES
G3000.0010	24 Vdc Control Power	G0100 Programming Kit



### **GENERATOR & SINGLE-FUNCTION PROTECTION**

#### G3300 Voltage Relay



T2000 Reverse Power Relay

#### **Features/Benefits**

G3300.0010

- Monitors voltage on generators, busbars or other distribution systems
- PC configuration for over and undervoltage protection in one relay
- User configured scales and setpoints suits a broad variety of applications
- Phase symmetry monitor enables use in grid connection applications

ORDERING NUMBER SPECIFICATIONS

63 Vac to 690 Vac systems can be monitored by the same unit

#### **Specifications**

Supply Input Voltage Frequency Dimensions

Web Resources littelfuse.com/g3300 8-36 Vdc/0.75 W at 24 Vdc 63-690 Vac ± 30% 35-75 Hz **H** 73 mm (2.9") W 75 mm (3.0") **D** 114 mm (4.5")

ACCESSORIES G0100 Programming Kit

2-20% I

2-20 sec.

**H** 70 mm (2.8")

W 100 mm (3.9")

**D** 115 mm (4.5")

660 V

#### CE

CE

#### **Features/Benefits** Protects the generator from being run as an electric motor

24 Vdc Control Power

- Accepts high supply voltage variation to ensure correct operation in spite of voltage supply fluctuations
  - Dimensions

- Visual indication of power, pick-up and output trip provides quick and concise status information

#### Web Resources littelfuse.com/t2000

**Specifications** 

**Trip level** 

Max. Voltage

Delay

ORDERING NUMBER	<b>TERMINALS 1-3</b>	<b>TERMINALS 2-3</b>	I _N	SUPPLY
T2000.0010	230 V		5 A	L-N
T2000.0020	450 V	400 V	5 A	L-L
T2000.0030	127 V	120 V	5 A	L-N
T2000.0040	110 V	100 V	5 A	L-L
T2000.0050	110 V	100 V	5 A	L-L
T2000.0060	230 V		1 A	L-N
T2000.0070	660 V		5 A	L-L
T2000.0080	450 V	400 V	5 A	L-N
T2000.0090	127 V	120 V	5 A	L-L
T2000.0100	110 V	100 V	1 A	L-L
T2000.0110	450 V	400 V	5 A	L-L
T2000.0120	480 V	415 V	5 A	L-L
T2000.0130	230 V		5 A	L-N
T2000.0140	230 V		5 A	L-L
T2000.0150	480 V	415 V	1 A	L-L
T2000.0160	450 V	400 V	1 A	L-L

#### T2100 Excitation Loss Relay

#### Features/Benefits

**ORDERING NUMBER** 

T2100.0010

T2100.0020 T2100.0030

T2100.0040 T2100.0050

T2100.0060 T2100.0070

T2100.0080

- Protects against loss of excitation in a synchronous generator
- Accepts high supply voltage variation to ensure correct operation in spite of voltage supply fluctuations
- Visual indication of power, pick-up and output trip provides guick and concise status information

#### **Specifications** Trip level

. Delay Max. Voltage Dimensions

**TERMINALS 2-3** 

415 V

400 V

100 V

100 V

100 V

415 V

100 V

#### Web Resources littelfuse.com/t2100

0.5-1.5 x l 2-20 sec. 660 V **H** 70 mm (2.8") W 100 mm (3.9") **D** 115 mm (4.5")

I _N	SUPPLY
5 A	L-N
5 A	L-L
5 A	L-L
1 A	L-L
5 A	L-L

**TERMINALS 1-3** 

230 V

480 V

450 V

110 V

110 V 110 V

480 V

110 V

CE

8

**Protection Relays & Controls** 

BELLAC

00 00 00 00

400 V

400 V

### **GENERATOR & SINGLE-FUNCTION PROTECTION**

#### T2200 3-Phase Overcurrent Relay

#### Features/Benefits

- Designed for generator or feeder protection against overcurrent in each of the 3 phases
- Accepts high supply voltage variation to ensure correct operation in spite of voltage supply fluctuations
- Visual indication of power, pick-up and output trip provides quick and concise status information

#### **Specifications** Trip level

Web Resources

littelfuse.com/t2200

FUNCTION

Latching output, resetable

Latching output, resetable Latching output, resetable

Instantly extra output relay

Instantly extra output relay

Normally energized output, latching, resetable

Normally energized output, latching, resetable

Delay Max. Voltage

I_N

5 A

5 A

5 A

5 A

1 A

5 A

5 A

5 A

5 A

5 A

1 A

Dimensions

0.5-1.4 x I_N 3-30 sec. 660 V H 70 mm (2.8") **W** 100 mm (3.9") **D** 115 mm (4.5")



#### T2300 3-Phase Short-Circuit Relay

#### **Features/Benefits**

T2200.0100

T2200.0110

Designed for protection of generators, power transmissions and consumer's supply against short circuit

450 V

450 V

- Accepts high supply voltage variation to ensure correct operation in spite of voltage supply fluctuations
- Visual indication of power, pick-up and output trip provides guick and concise status information

#### **Specifications**

Trip level	
Delay	
Max. Voltage	
Dimensions	

1.0-4.0 x I 0.1-1.0 sec. 660 V **H** 70 mm (2.8") W 100 mm (3.9") **D** 115 mm (4.5")

Web Resources littelfuse.com/t2300

ORDERING NUMBER	<b>TERMINALS 1-3</b>	<b>TERMINALS 2-3</b>	I _N	FUNCTION
T2300.0100	230 V		5 A	
T2300.0020	450 V	400 V	5 A	
T2300.0030	24 Vdc		5 A	
T2300.0040	24 Vdc		1 A	
T2300.0050	450 V	400 V	5 A	Normally de-energized output
T2300.0060	480 V	415 V	5 A	
T2300.0070	230 V		1 A	

#### T2400 3-Phase Dual Overcurrent Relay

0 0 0

#### **Features/Benefits**

- Includes 2 combined overcurrent designed for protection or monitoring of generators and power transmissions
- Accepts high supply voltage variation to ensure correct operation in spite of voltage supply fluctuations
- Combining 2 relays is an economic solution for non-essential load tripping and occupying less space in the switch panel

ORDERING NUMBER	<b>TERMINALS 1-3</b>	<b>TERMINALS 2-3</b>	I _N
T2400.0010	230 V		5 A
T2400.0020	450 V	400 V	5 A
T2400.0030	110 V	100 V	5 A
T2400.0040	450 V	400 V	5 A
T2400.0050	480 V	415 V	5 A
T2400.0060	450 V	400 V	1 A
T2400.0070	450 V	400 V	5 A
T2400.0080	127 V	120 V	5 A
T2400.0090	24 Vdc		5 A

Specifications
Trip level
Delay
Max. Voltage
Dimensions

Web Resources

littelfuse.com/t2400

H 70 mm (2.8") W 100 mm (3.9") **D** 115 mm (4.5")

0.5-1.4 x I_N

3-30 sec.

660 V

FUNCTION
FUNCTION
Latching output on relay 1, 6-60 sec. delay on relay 1
Latching output on relay 1, normally energized relay 1



8

**Protection Relays & Controls** 

#### © 2015 Littelfuse POWR-GARD® Products Catalog

#### CE

### CE



0.5-1.4 x I_N

**W** 100 mm (3.9")

**D** 115 mm (4.5")

3-30 sec.

660 V H 70 mm (2.8")

### **GENERATOR & SINGLE-FUNCTION PROTECTION**

#### T2500 Overcurrent and Short-Circuit Relay

#### **Features/Benefits**

ORDERING NUMBER

T2500.0010

T2500.0020

T2500.0030

T2500.0040

T2500.0050

T2500.0060

T2500.0070

T2500.0080

T2500.0090

T2500.0100

T2500.0110

T2500.0120

- The short-circuit relays protects against faults causing high currents and the overcurrent relay protects against thermal damage
- Accepts high supply voltage variation to ensure correct operation in spite of voltage supply fluctuations
- Combining 2 relays is an economic solution, occupying less space in the switch panel

450 V

230 V

480 V

450 V

24 Vdc

230 V

450 V

450 V

480 V

24 Vdc

450 V

24 Vdc

**TERMINALS 1-3** 

#### Specifications

Trip level
Delay
Max. Voltage
Dimensions

#### Web Resources littelfuse.com/t2500

ei	nitem	use.com/12500
<b>TERMINALS 2-3</b>	I _N	FUNCTION
400 V	5 A	Latching output, resetable
	5 A	Latching output, resetable
415 V	5 A	Latching output, resetable
400 V	1 A	Latching output, resetable
	5 A	Latching output, resetable
	5 A	De-energized extra output relay
400 V	5 A	De-energized extra output relay
400 V	5 A	De-energized extra output relay, latching outputs
415 V	5 A	De-energized extra output relay
	1 A	De-energized extra output relay
400 V	5 A	De-energized extra output relay, latching short circuit output
	5 A	De-energized extra output relay, de-energized relay 1, no internal power backup

T2700 Power Relay



#### **Features/Benefits**

- Detects power levels for protection, control or monitoring and will protect against excessive active loads
- Accepts high supply voltage variation to ensure correct operation in spite of voltage supply fluctuations
- Visual indication of power, pick-up and output trip provides guick and concise status information

#### Specifications

**Trip level** Delay . Max. Voltage Dimensions

15-150 x I 2-20 sec. 660 V **H** 70 mm (2.8") **W** 100 mm (3.9") **D** 115 mm (4.5")

Web Resources littelfuse.com/t2700

	ORDERING NUMBER	<b>TERMINALS 1-3</b>	<b>TERMINALS 2-3</b>	I _N	SUPPLY	FUNCTION
0.0	T2700.00	230 V		5 A	L-N	
-	T2700.02	450 V	400 V	5 A	L-L	
	T2700.03	230 V	400 V	5 A	L-L	
	T2700.04	110 V	100 V	5 A	L-L	Normally energized output
	T2700-08	127 V	120 V	5 A	L-N	

#### **T2900** 3-Phase Differential Relay

#### **Features/Benefits** Monitors current leakage in generators and



#### measures the differential current of each of the 3 phases

- Accepts high supply voltage variation to ensure correct operation in spite of voltage supply fluctuations
- Visual indication of power, pick-up and output trip provides quick and concise status information

#### **Specifications** Trip le

Trip level	0.04-0.4 x I _N
Delay	1-10 sec.
	(0.1-1 sec. bridging terminals 18/19)
Max. Voltage	660 V
Dimensions	<b>H</b> 70 mm (2.8")
	<b>W</b> 100 mm (3.9")
	<b>D</b> 115 mm (4.5")
Web Bessuress	

#### Web Resources littelfuse.com/t2900

ORDERING NUMBER	TERMINALS 1-3	TERMINALS 2-3	I _N
T2900.0010	450 V	400 V	5 A
T2900.0020	230 V		5 A
T2900.0030	480 V	415 V	5 A
T2900.0040	110 V	100 V	5 A

8

CE

### **GENERATOR & SINGLE-FUNCTION PROTECTION**

#### T3000 Frequency Relay



#### Features/Benefits

- Frequency monitor generators, busbars or other distribution systems
- Accepts high supply voltage variation to ensure correct operation in spite of voltage supply fluctuations
- Visual indication of power, pick-up and output trip provides quick and concise status information
- Combining 2 relays is an economic solution for monitoring both underfrequency and overfrquency in the same unit

#### **Specifications**

**Overfrequency Level** Delay Underfrequency Level Delay Max. Voltage Dimensions

45-65 Hz 1-10 sec. 45-65 Hz 1-10 sec. 660 V H 70 mm (2.8") W 100 mm (3.9") **D** 115 mm (4.5")

Web Resources littelfuse.com/t3000

	ORDERING NUMBER	TERMINALS 1-3	TERMINALS 2-3
	T3000.0010	230 V	
	T3000.0020	450 V	400 V
	T3000.0030	110 V	100 V
	T3000.0040	480 V	415 V
	T3000.0050	127 V	120 V

#### T3100 Voltage Relay

#### Features/Benefits

- Monitors voltage on generators, busbars or other distribution systems
- Signals when voltage is out of its limits
- Consists of two, one for overvoltage and one for undervoltage monitoring
- Accepts high supply voltage variation to ensure correct operation in spite of voltage supply fluctuations

#### **Specifications**

Overvoltage level	
Delay	
Undervoltage Level	
Max. Voltage	
Dimensions	

#### 660 V H 70 mm (2.8") **W** 100 mm (3.9") **D** 115 mm (4.5")

100-120%

1-10 sec 80-100%

#### Web Resources littelfuse.com/t3100

	ORDERING NUMBER	TERMINALS 1-3	TERMINALS 2-3
	T3100.0010	230 V	
ia i	T3100.0020	450 V	400 V
	T3100.0030	110 V	100 V
	T3100.0040	480 V	415 V
	T3100.0060	127 V	120 V

#### T3300 3-Phase Voltage Relay

#### **Features/Benefits**

- Monitors voltage on generators, busbars or other distribution systems
- Signals when voltage is out of its limits
- Consists of two, one for overvoltage and one for undervoltage monitoring
- Accepts high supply voltage variation to ensure correct operation in spite of voltage supply fluctuations

#### **Specifications**

**Overvoltage Level** Delay **Undervoltage Level** Max. Voltage Dimensions

100-120% 1-10 sec. 80-100% 660 V H 70 mm (2.8") **W** 150 mm (5.9") **D** 115 mm (4.5")

#### Web Resources littelfuse.com/t3300

ORDERING NUMBER	TERMINALS 17-19, 21-23, 25-27	TERMINALS 18-19, 22-23, 26-27
T3300.0010	230 V	
T3300.0020	450 V	400 V
T3300.0030	110 V	100 V
T3300.0040	480 V	415 V



8



CE

CE



CE

CE

### **GENERATOR CONTROL**

#### T2600 Dual-Current Relay

#### **Features/Benefits**

- Start or stop the standby diesel generator according to the load situation
- Accepts high supply voltage variation to ensure correct operation in spite of voltage supply fluctuations
- Visual indication of power, pick-up and output trip provides quick and concise status information

#### **Specifications**

Max. Voltage	600 V
Voltage Range	70-110%
Dimensions	<b>H</b> 70 mm (2.
	<b>W</b> 150 mm (
	<b>D</b> 115 mm (/

Web Resources littelfuse.com/t2600





ORDERING NUMBER	<b>TERMINALS 1-3</b>	<b>TERMINALS 2-3</b>	I _N	FUNCTION
T2600.0010	230 V		5 A	30 sec. or 1 sec.*
T2600.0020	450 V	400 V	5 A	30 sec. or 1 sec.*
T2600.0030	480 V	415 V	5 A	30 sec. or 1 sec.*
T2600.0040	450 V	400 V	5 A	30 sec.*, bridge 17-18 = stop current increased 34%
T2600.0050	480 V		5 A	30 sec.*, bridge 17-18 = stop current increased 34%
T2600.0060	110 V	100 V	5 A	30 sec. or 1 sec.*
T2600.0070	110 V	100 V	5 A	30 sec. or 1 sec.*, start current delay 1.0-10 secs
T2600.0080	230 V		5 A	30 sec. or 1 sec.*, normally de-energized start relay
T2600.0090				Extension Unit

#### T4500 Auto Synchronizer for Conventional Governors

#### **Features/Benefits**

- Provides automatic synchronization of a generator to a busbar quickly via speed controller
- Inputs for disabling internal frequency control enables synchronization to external setpoint from other busbar sections, generators or the main grid
- Visual indication of signals provides quick and concise status information

#### **Specifications**

Max. Voltage **Voltage Range** Dimensions

600 V 70-110% H 70 mm (2.8") **W** 100 mm (3.9") **D** 115 mm (4.5")

#### Web Resources littelfuse.com/t4500

ORDERING NUMBER	TERMINALS 1-3, 5-7	TERMINALS 2-3, 6-7
T4500.0010	450 V	400 V
T4500.0020	230 V	
T4500.0030	480 V	415 V
T4500.0040	110 V	63 V
T4500.0050	127 V	120 V
T4500.0060	110 V	100 V
T4500.0070	600 V	

#### T4800 Load Sharer for Conventional Governors

#### **Features/Benefits**

- Provides automatic load sharing and frequency control for parallel running generators
- Inputs for disabling internal frequency control enables operation where system frequency is set externally such as in grid-parallel operation
- Visual indication of signals provides quick and concise status information

#### **Specifications**

Max. Voltage **Voltage Range** Dimensions

600 V 70-110% H 70 mm (2.8") W 150 mm (5.9") **D** 115 mm (4.5")

#### Web Resources littelfuse.com/t4800

ORDERING NUMBER	TERMINALS 1-3	TERMINALS 2-3	I _N
T4800.0010	450 V	400 V	5 A
T4800.0020	230 V		5 A
T4800.0030	480 V	415 V	5 A
T4800.0040	110 V	100 V	1 A
T4800.0050	450 V	400 V	1 A
T4800.0060	127 V	120 V	5 A
T4800.0070	110 V	100 V	5 A



8

### GENERATOR CONTROL

11

#### T4900 VAR Load Sharer

#### Features/Benefits

- Provides automatic load sharing of reactive power and voltage control for parallel running generators
- Inputs for disabling internal voltage control enables operation where system voltage is set externally such as in grid-parallel operation
- Visual indication of voltage increase/decrease provides quick and concise status information

#### Specifications

Max. Voltage Voltage Range Dimensions

Web Resources littelfuse.com/t4900 660 V 110% H 70 mm (2.8″) ₩ 150 mm (5.9″)

**D** 115 mm (4.5")

 $C \in$ 

CE



#### T5000 Paralleling Relay

*************



#### **Features/Benefits**

- Inhibits closure of circuit breaker if synchronizing parameters such as voltage, frequency and phase angle are outside limits
  - Prevents generator damage and disturbance to busbar
- Visual indication of voltage and closing signal provides quick and concise status information

#### Specifications

Web Resources

Max. Voltage Voltage Range Dimensions 600 V 70-110% **H** 70 mm (2.8") **W** 100 mm (3.9") **D** 115 mm (4.5")

littelfuse.com/t5000 **TERMINALS 2-3** FUNCTION **ORDERING NUMBER TERMINALS 1-3** T5000.0010 450 V 400 V T5000.0020 230 V 415 V T5000.0030 480 V T5000.0040 110 V 100 V T5000.0050 127 V 120 V 480 V  $\Delta \phi = 9-13.5^{\circ}, \Delta F = 0.2-0.3 \text{ Hz}$ T5000.0060 415 V T5000.0070 450 V 400 V ΔU=15-20%, Δφ=9-13.5°, ΔF=0.2-0.3 Hz ΔU=15-20%, Δφ=9-13.5°, ΔF=0.2-0.3n Hz T5000.0080 110 V 100 V T5000.0090 450 V 400 V Δφ=9-13.5°, ΔF=0.2-0.3 Hz T5000.0100 660 V

#### E7800 Motorized Potentiometer

#### **Features/Benefits**

- Interface between increase/decrease contacts and a device requiring control/adjustments by an external potentiometer
- Can be used as speed trim of an electric speed governor in generator applications
- Wire would for longer life than carbon potentiometers

#### Specifications

Voltage Range Consumption Dimensions

Web Resources

littelfuse.com/e7800

AC: 90-120% DC: 75-125% AC: 2.5 VA DC: 2 W H 96 mm (3.8") W 96 mm (3.8") D 80 mm (3.1")



ORDERING NUMBER	VOLTAGE	RPM	POTENTIOMETER
E7800.00.xx	230 V-240 Vac	1.0 (50 Hz)	5 kΩ-1 turn
E7800.01.xx	220 V-240 Vac	2.0 (50 Hz)	5 kΩ-10 turn
E7800.02.xx	100 V-110 Vac	1.0 (50 Hz)	5 kΩ-1 turn
E7800.03.xx	24 Vac	2.0 (50 Hz)	5 kΩ-10 turn
E7800.04.xx	100 V-110 Vac	2.0 (50 Hz)	5 kΩ-10 turn
E7800.05.xx	220 V-240 Vac	2.0 (50 Hz)	5 kΩ-1 turn
E7800.09.xx	24 Vac	1.0 (50 Hz)	5 kΩ-1 turn
E7800.23.xx	24 Vdc	0.8-6 Adj.	5 kΩ-1 turn
E7800.24.xx	24 Vdc	0.8-6 Adj.	5 kΩ-10 turn
E7800.90.00	24 Vdc	0.8-6 Adj.	DC output voltage, 0-1.0 V (0-100%)

#### Sp Volt Con Dim

8

**Protection Relays & Controls** 

#### © 2015 Littelfuse POWR-GARD® Products Catalog

₩**\$** 



### **GENERATOR CONTROL**

#### **T7900** Electronic Potentiometer



#### **Features/Benefits**

- Used as a converter between pulse contacts and a device requiring control adjustment by a voltage or current signal
- Wide selection of output ranges including PWM which ensures possible use with a broad variety of speed governors and voltage regulators
- Independent ramp-up and ramp-down time setting provides optimum controllability

#### Specifications

Supply Consumption Dimensions

Web Resources littelfuse.com/t7900 CE

0-30 VUC/ Vac
Max. 120 mA at 24 Vdc
H 70 mm (2.8")
<b>W</b> 100 mm (3.9")
<b>D</b> 115 mm (4.5")

0 26 V/de /V/ee

ORDERING NUMBER	TERMINALS 11-12	TERMINALS 1-3
T7900.0010	24 Vdc/Vac	
T7900.0030		250 Vac

#### M8100 Synchroscope

	110 13	1
J	SYNCHROSCOPE TOO	1
1	SLOW SYNC	Ш
I		P
I	1	
	BUS SELCO GEN	

#### **Features/Benefits**

- Provides illuminated indication of the phase and frequency difference between voltages on two separate AC systems
- High resolutions visual indications by 38 LEDs
- Available with check synchronizer relay which enables use as manual synchronizing unit, or as auto -synchronizing back-up

#### Specifications

Max. Voltage	600 V
Voltage Range	70-110%
Consumption	2x3 VA max.
Dimensions	<b>H</b> 96 mm (3.8")
	<b>W</b> 96 mm (3.8")
	<b>D</b> 80 mm (3.1")

#### Web Resources littelfuse.com/m8100

ORDERING NUMBER	TERMINALS 1-1, 5-7	TERMINALS 1-3, 6-7	FUNCTION
M8100.0010	450 V	400 V	
M8100.0020	230 V		
M8100.0030	480 V	415 V	
M8100.0040	110 V	100 V	
M8100.0050	450 V	400 V	With check synchronizer relay
M8100.0060	230 V		With check synchronizer relay
M8100.0070	480 V	415 V	With check synchronizer relay
M8100.0080	110 V	100 V	With check synchronizer relay

#### **T8400** Blackout Limiter

#### Features/Benefits

- Enables fast clearing of a blackout
- Monitors up to four generators or eight generators with two units
- Independent 24 Vdc supply with wide tolerance operates regardless of system voltage failure

#### Specifications

Supply Voltage Max. Voltage Frequency Range Dimensions

#### Web Resources littelfuse.com/m8400

ORDERING NUMBER	TERMINALS 1-3, 8-10, 17-19, 24-26	FUNCTION
T8400.0010	400 V	1-1.5-2-2.5 sec.
T8400.0020	400 V	3-3.5-4-4.5 sec.
T8400.0030	230 V	1-1.5-2-2.5 sec.
T8400.0040	230 V	3-3.5-4-4.5 sec.
T8400.0050	415 V	1-1.5-2-2.5 sec.
T8400.0060	415 V	3-3.5-4-4.5 sec.



CE

24 Vdc 30%

H 70 mm (2.7")

W 150 mm (5.9")

**D** 115 mm (4.5")

660 Vac

35-70 Hz

### **GENERATOR CONTROL**

#### C6200 FlexGen Standard Generator Control



#### Description

FlexGen controllers are intended for paralleling of generators with each other or with the grid. One FlexGen controller is installed for each generator in the installation and handles all electrical control.

Both Basic and Advanced versions include basic functions such as auto-synchronizing, frequency control, active load sharing, dead bus monitoring and reverse power protection. In addition the FlexGen Advanced contains reactive load sharing, voltage matching, power factor control, grid-parallel operation control, and protection against excitation loss, RoCoF (df/dt), and vector shift.

#### **Features/Benefits**

- 3-phase true RMS measurement is more reliable and immune to high noise
- Analog outputs for speed and voltage control fit most electronic governors and
- 10 programmable inputs and outputs for flexible configuration on wide range of applications

#### **Specifications**

**Auxiliary Supply** 

**Generator Voltage Generator Rated Frequency C/T Secondary Current** Consumption **Ambient Temp Range** Dimensions

### Web Resources

littelfuse.com/c6200

10 Vdc to 36 Vdc (24 Vdc-58%/+50%) 63 V-690 V 50 Hz/60 Hz 5 A 7 W -20°C to +70°C **H** 182 mm (7.2") W 282 mm (11.1") **D** 50 mm (2.0")

CE

ORDERING NUMBER	MODELNAME	ACCESSORIES
C6200.0060	FlexGen Basic	C6500 FlexGen UI User Interface Module
C6200.0100	FlexGen Advanced	

#### S6000 Sigma Advanced Protection Module

E KO P MODULE

#### Description

The SIGMA Generator Control and Protection System is a range of integrated modules for protection and control of marine and land based generators. The modules are marine approved and include all relevant functions, such as protection of generators, synchronizing and active/ reactive load sharing and Power Management.

#### IO/P Module S6000 Input/ Output and Protection Module

The SIGMA S6000 performs all measurements on the generator side (voltages, currents, frequency), does the generator protection, includes a non-essential load trip in two steps and includes three measurement transducers

#### S/LS Module S6100 Synchronizing and Load-Sharing Module

This module performs the control functions like synchronizing and active and reactive load sharing. It performs the measurements on the busbar side.

#### **Features/Benefits**

- 3-phase true RMS measurement is more reliable and immune to high noise
- Analog outputs for speed and voltage control fit most electronic governors and
- Large consumer request inputs with load feedback optimizes quantity of running generators and saves fuel

#### Specifications

**Primary Supply Backup Supply** Environmental -15°C to +70°C **Temp Range** 

+24 Vdc (-30%/+30%) Isolated, 500 mA +24 Vdc (-30%/+30%) Isolated, 500 mA

Dimensions H 145 mm (5.7")

**W** 190 mm (7.5") **D** 64 mm (2.5")

Web Resources littelfuse.com/s6000

ORDERING NUMBER	DESCRIPTION	ACCESSORIES
S6000.0010	Input/ Output and Protection Module- 5 A C/T	
S6000.0020	Input/ Output and Protection Module- 1 A C/T	S6500.0010 Power Manager Module S6610.0010 User Interface Module
S6100.0010	Synchronization and Load Sharing Module	



10011-0203

..............

APPENDIX



### ENGINE CONTROL AND DIAGNOSIS

#### M2000 Engine Control

•••	IN OPERATION	
** *	STARTING.	
	INUMPERS (while )	10
	LOW COL PRESSURE	
	HER WATER TERM.	
•	HOR OL 1987	
	LOW COOLING BATER	
	PERLON, LEAKAGE	
	REPORT AND TERMS	
	EMISCIENCS STD#	10

#### **Features/Benefits**

- Controls start and stop of the engine, monitors and protects the engine during start and operation, and simultaneously indicates the engine and alarm status on the front of the unit
- Eight inputs for monitoring e.g. oil pressure, coolant, temperature and engine speed
- Cable monitoring on sensor inputs for a fail safe system
- Can be combined with M0600 to build a complete control, alarm and safety system for marine engines

#### **Specifications**

Voltage Supply Consumption . Dimensions

Web Resources littelfuse.com/m2000 12-24 Vdc±30% (8-32 Vdc) Max. 180 mA H 144 mm (5.7") W 144 mm (5.7") **D** 35 mm (1.4")

CE

CE

ORDERING NUMBER	CONTROL POWER	ACCESSORIES
M2000.0130	12-24 Vdc, IP54 at front	M0600 Shutdown Unit M0500 Tacho Detector K3452 RS232 Cable

**CONTROL POWER** 

12-24 Vdc

#### M2500 Engine Control and Monitoring Unit

SELCO	ENGINE CONTROLLER	M2500
Frankova Anna Anna Anna Anna Anna Anna Anna An		) ¹ ()
Franc Society 1 France Society 1 France Society Cong Constructional Cong Constructional Cong Construction		

#### **Features/Benefits**

**ORDERING NUMBER** 

M2500.0010

- Control and monitor engines in marine applications such as auxiliary generators, emergency generators and propulsion engines
- Allows manual (local) and automatic (remote) start of the engine and will monitor all engine parameters
- Nine digital alarm/shutdown inputs for monitoring e.g. oil pressure, coolant, temperature and engine speed
- Combine with M2600 to bui Id a complete control, alarm and safety system for marine engines

#### **Specifications** Operation

Operating Temp.	–15°C to +70°C
Humidity	95%
Dimensions	H 137 mm (6.2")
	W 209 mm (8.2")
	<b>D</b> 39 mm (1.5")

ACCESSORIES M2600 Shutdown Unit K2502 SD Card

K1025 USB A to B Cable

Web Resources littelfuse.com/m2500



E5000 Handheld EngineEye Unit

Features/E	Senefits
Reliable ro	bust tool for engine diagnostics,
consisting	of a cylinder pressure analyzer for
collection	of measurements, a pressure sensor,
an optiona	l top dead center sensor and an optional
crank angl	e sensor

- Tune and balance engine during operation
- Large display and intuitive software for
- easy operation

#### **Specifications**

**Pressure Range** Pressure Accuracy **Temperature Range** Dimensions

Web Resources

CE

0-250 Bar 1% –50 to +350°C H 150 mm (5.9")

### littelfuse.com/e5000

W 260 mm (10.2") D 55 mm (2.2")

ORDERING NUMBER	DESCRIPTION	ACCESSORIES
E5000.1000	EngineEye Basic (E5000.0010 and E5100.0010)	
E5000.3000	EngineEye Professional (E5000.0030, E5100.0010 and E5300.0010)	See datasheet at: littelfuse.com/e5000

### ALARM MONITORING

#### M1000 Alarm Monitor



#### Features/Benefits

- Alarm panel with ten digital inputs that trigger a corresponding LED to flash with a common alarm and siren output
- Supports both normally open and normally closed input contacts
- Multiple units can be connected ad one system for a modular and scalable solution

#### Specifications Voltage Supply

Siren Relay Contact Communication Dimensions 12-24 Vdc -30/+30% (8-32 Vdc) 48-110 Vdc -30/+40% (33-155 Vdc) 220 Vac/2 A; 30 Vdc/2 A, 30 W RS485 Interface H 144 mm (5.7") W 144 mm (5.7") D 35 mm (1.4")

Web Resources littelfuse.com/m1000

ORDERING NUMBER	CONTROL POWER	FUNCTION
M1000.0040	48-110 Vdc	IP54 front
M1000.0080	12-24 Vdc	IP54 front
M1000.0220	12-24 Vdc	Internal siren, IP54 at front

#### M3000 Analog Alarm Annunciator



#### Features/Benefits

- 24 inputs that can be configured individually for dry contact (normally open or normally closed) inputs or analog inputs
- Programmable 10-character LCD text so each alarm is indicated clearly
- 24 inputs and 48 alarms allow for individual reference to any input and easy configuration of group and individual alarms

#### Specifications

Voltage Supply
Consumption
Sensor Inputs
Alarms
LEDs
Communication
Dimensions

Max. 400 mA 24 48 24 RS485 Interface H 144 mm (5.7") W 144 mm (5.7") D 70 mm (2.7")

24 Vdc ±30%

Web Resources littelfuse.com/m3000

ORDERING NUMBER	CONTROL POWER	ACCESSORIES
M3000.0010	24 Vdc	M1500 PT100 6-way Transmitter

#### M4200 Alarm Monitor



#### **Features/Benefits**

- Cost effective solution, with the possibility of monitoring eight individual sensors
- Supports both normally open and normally closed input contacts
- Programmable LED color change allows flexible adjustment according to application
- Cable monitoring on sensor inputs indicates sensor health in case a sensor is lost

#### Specifications

Voltage Supply Consumption Relay Output Dimensions

Web Resources littelfuse.com/m4200 8.4-40 Vdc; 8.4-50 Vac Max. 180 mA Max. 250 Vac/6 A H 96 mm (3.8") W 96 mm (3.8") D 20 mm (0.8")

CE

CE



CE

### ALARM MONITORING

#### M4500, M4600 & M4700 Alarm Indicators

#### **Features/Benefits**

The M4500, M4600 and M4700 Indicator Panels are intended for status indication of any process providing on/off outputs. The panels contain 6, 8 or 20 channels.

- Clamping fittings and plug-in terminal blocks allow for easy installation
- RS485 communication available for a remote display or PLCs

#### **Specifications**

**Voltage Supply** Dimensions

24 Vdc ±25% M4500: H 72 mm (2.8") W 72 mm (2.8") D 67 mm (2.6") M4600: **H** 96 mm (3.8) **W** 96 mm (3.8") **D** 67 mm (2.6") M4700: H 144 mm (5.7") W 144 mm (5.7") D 67 mm (2.6")

#### **Web Resources** littelfuse.com/m4500

littelfuse.com/m4600 littelfuse.com/m4700

CARLEN 1 CARLEN 2 CARLEN 2 CARLEN 2 CARLEN 4 CARLEN		TURBO ALT TURBO ALT TURBO ALT ALL OPES DI, MESO DI, MESO	wat the
	0000		

ORDERING NUMBER	CONTROL POWER	INPUT REFERENCE	ACCESSORIES
M4500.0010	24 Vdc/Vac	+24 Vdc	
M4500.0020	48 Vdc/Vac	+48 Vdc	
M4500.0030	12 Vdc/Vac	+12 Vdc	
M4500.0040	24 Vdc/Vac	0 Vdc	
M4500.0050	48 Vdc/Vac	0 Vdc	
M4500.0060	12 Vdc/Vac	0 Vdc	M0845.0010 Front cover for M4500
M4600.0010	24 Vdc/Vac	+24 Vdc	with handle IP54
M4600.0020	48 Vdc/Vac	+48 Vdc	
M4600.0030	12 Vdc/Vac	+12 Vdc	M0845.0020 Front cover for M4500
M4600.0040	110 Vdc	+110 Vdc	with key IP54
M4600.0050	24 Vdc/Vac	0 Vdc	
M4600.0060	48 Vdc/Vac	0 Vdc	M0846.0010 Front cover for M4600
M4600.0070	12 Vdc/Vac	0 Vdc	with handle IP54
M4700.0010	24 Vdc/Vac	+24 Vdc	
M4700.0020	48 Vdc/Vac	+48 Vdc	M0846.0020 Front cover for M4600
M4700.0030	12 Vdc/Vac	+12 Vdc	
M4700.0040	110 Vdc	+110 Vdc	with key IP54
M4700.0050	24 Vdc/Vac	0 Vdc	
M4700.0060	48 Vdc/Vac	0 Vdc	M0847.0010 Front cover for M4700/
M4700.0070	12 Vdc/Vac	0 Vdc	M4780 with handle IP54
M4700.0080	110 Vdc	0 Vdc	
M4700.0090	230 Vac	+24 Vdc	M0847.0020 Front cover for M4700/
M4700.0100	110 Vac	+24 Vdc	M4780 with key IP54
M4700.0110	230 Vac	0 Vdc	
M4700.0120*	24 Vdc	+24 Vdc	
M4700.0120*	24 Vdc	+24 Vdc	
M4700.0130 [†]	230 Vac	+24 Vdc	
M4780.0010 [±]	24 Vdc	24 Vdc	

*With common alarm relay, siren relay and built-in siren.

Inverted reference. With common alarm relay, siren relay and built-in siren.
 Modbus Indicator Panel, 20 channels, 24 Vdc, common alarm relay and built in siren.

#### H4000 HMI Operator Panels



#### **Features/Benefits**

The HMI operator panel is a touch-screen solution for SCADA solutions, designed for applications like engine control and supervision systems, power management systems and alarm systems. They can be integrated with products such as the M2500, Engine Controller, Generator Controllers and Alarm Panels.

Clear, high-resolution screen provides high ٠ level of details

ORDERING NUMBER	DESCRIPTION
H4000.0010	HMI Panel 6,5"
H4000.0020	HMI Panel 6,5", sun readable
H4100.0010	HMI Panel 10,4"
H4100.0020	HMI Panel 10,4" sun readable
H4200.0010	HMI Panel 15,1"
H4200.0020	HMI Panel 15,1" sun readable
H4900.0010	Programming Software

**Specifications** 

Web Resources

littelfuse.com/h4000

Dimensions

CE

M4000: H 219 mm (8.6") W 154 mm (6.0") D 6 mm (0.2")

M4100: H 301 mm (11.9")

M4200: H 398 mm (15.7") **W** 304 mm (12.0") **D** 6 mm (0.2")

W 228 mm (9.0") D 6 mm (0.2")

### CUSTOM-ENGINEERED ELECTRICAL EQUIPMENT

#### **Electrical Modular Building/E-Houses**



#### Description

Littelfuse Startco offers fully integrated electrical and automation systems. Our products include prefabricated, modular, skid-mounted enclosures for switchgear and auxiliary equipment. We deliver self-contained units, which are completely coordinated, assembled and tested inside our controlled factory environment. The primary switchgear and control applications include low- and/or medium-voltage switchgear and motor control centre enclosures; relay panel enclosures; and RTU and SCADA enclosures.

#### Modular Variable-Frequency Drives (VFDs)



#### **Description**

Variable-frequency drives have been used in a variety of industries for years to start motors, optimize load control, and achieve energy savings. Unfortunately, the mining industry has not been able to fully realize these benefits as the combination of the electronics used in VFD's and the dirty or harsh environments found in underground and open-pit mining tends to decrease the drive's reliability and expected life. Littelfuse Startco has solved this problem by designing a low-maintenance modular system that keeps the critical components of the VFD isolated from the harsh mining conditions, yet meets the thermal cooling requirements of the VFD.

#### **SEL-PTO Custom Electrical Panels**



#### Description

Littelfuse Startco is the leading Canadian manufacturer of custom-built electrical equipment for mining and oil & gas. Ground-fault panels, also known as power-take-off or starter panels, are a convenient means of protecting and isolating trailing-cable-fed or hard-wired equipment such as pumps, jumbos, drills, and electric machines. Littelfuse Startco Custom Panels are metal-enclosed, rugged, high-quality, and are intended for use in non-hazardous resistance-grounded systems. Littelfuse Startco has earned a reputation for prompt delivery of Custom Panels.

The Littelfuse Startco custom-products engineering team will assist with your design. All designs are reviewed by engineers prior to quoting.

#### **Underground Portable Power Centres**



#### Description

Littelfuse Startco is the leading Canadian manufacturer of custom-built, portable mine power centres up to 38-kV. Littelfuse Startco portable mine power centres are skid-mounted, metal enclosed, and typically consist of the following:

- Primary medium-voltage section, with fused load-break switch or visible disconnect.
- Dry-type mine-duty power transformer.
- Primary and secondary power-distribution circuit breakers.
  - Control and protection specific to the application.
- The Littelfuse Startco custom-products engineering team will assist with your design. All designs are reviewed by engineers prior to quoting.



### PANEL MOUNT ADAPTERS • SOFTWARE • ACCESSORIES

#### **Panel Mount Adapters**



#### Features/Benefits

- Add communications capability to older switchgear and improve system performance
- Save cost by not calibrating older electromechanical devices
- Conformally coated circuit boards
- Additional protective functions, including reduced overcurrent and dynamic thermal model
- Minimal change-out time by using existing CTs
- PGR-6200 and PGR-6300 can use existing RTDs with an optional RTD module
- Ability to match existing overcurrent curves

#### Software

#### Adapter Plates

RELAY TO REPLACE	PANEL MOUNT	NEW RELAY
AB BULLETIN 1406	PMA-14	MPS
FPL-GFRM	PMA-6	SE-704
FPL-GFRM	PMA-6	SE-701
GE S1 GE S1	PMA-9	MPU-32
GE S1	PMA-9	FPU-32
GE LODTRAK III	PMA-10	MPU-32
	PMA-13	MPS
GE MULTILIN 169, 269, OR 369	PMA-16	MPU-32
	PMA-16	FPU-32
GE MULTILIN 469	PMA-24	MPS
GE MULTILIN P4A	PMA-15	MPU-32
GE MULTILIN P4A	PMA-15	FPU-32
GEC/MCGG	PMA-3	SE-704
GEC/MCGG	PMA-3	SE-701
GE & WESTINGHOUSE FT-11	PMA-12	MPU-32
P&B GOLDS	Contact Factory	FPU-32
WESTINGHOUSE CO9 & CO11	Contact Factory	FPU-32

oonware						
Product	Software For	Produc	Product			
SE-COMIM-RIS Relay Interface Software	MPU-32 MPS FPU-32 FPS	<b>SE-FLASH</b> Firmware Update Utility	and a second sec	MPU-32 MPS FPU-32 FPS		
VMPU Virtual Motor Protection Relay	MPU-32	<b>SE-MON330</b> Relay Interface Software		SE-330 SE-330HV SE-330AU		
VMPS Virtual Motor Protection System	MPS	MPU-32 Tutorial PGR-6200 Online Self-Training Tutorial		MPU-32		
<b>VFPU</b> Virtual Feeder Protection Relay	FPU-32	H4900 Programming Software		H4000 H4100 H4200		
<b>PGW-6150</b> Relay Interface Software	PGR-6150	<b>PGW-8800</b> Relay Interface Software	N Alar	PGR-8800		

#### **Accessories**

Most protective relays require an accessory for operation. Visit littelfuse.com/relayscontrols for a complete listing

iviosi protective relays require an accessory for operation. Vis	an muenuse.com/relayscom		
PRODUCT		PRODUCT	
Current Transformers		Remote Indication and Meters	
Ground Reference Modules		Sensing Resistors	
High Tension Couplers		Terminations and Adapters	$\mathcal{O}$
Protection Relay Testers		Accessories for Controls and Diagnostics	
Input Modules		DIN Mount Adapters	

#### **Section Overview**

System overvoltage is a growing concern in the electrical industry. Component miniaturization has resulted in increased sensitivity to many devices. The majority of these devices are unable to handle high currents that result from Electrostatic Discharge (ESD) and other voltage transients. Littelfuse® offers a broad range of overvoltage protection to safeguard against these conditions.



# SUPPRESSION PRODUCTS #

#### Table of Contents

Industrial Varistor	Products	173

LVSP Series Surge Suppression Fuses ......175

BVSP Series Surge Protection Device......176



### **OVERVOLTAGE SUPPRESSION PRODUCTS**

Varistors, Surge Fuses and Varistor Assemblies





#### What Are Transients?

Transients are short duration surges of electrical energy that result from the sudden release of previously stored energy. In terms of electrical and electronic circuits, this energy can be released through intentional, controlled switching action, or induced into a circuit from external sources. If the voltage magnitude of the transient is large enough, circuit component damage or malfunction of the circuit may result.

	VOLTAGE	CURRENT	<b>RISE-TIME</b>	DURATION
Lightning	25 kV	20 kA	10 µs	50 ms
Switching	600 V	500 A	50 µs	500 ms
EMP	300 kV	10 A	20 ns	1 ms
ESD	15 kV	30 A	1-5 ns	100 ns

#### **Transient Voltage Scenarios**

The switching of inductive loads generates high energy transients that increase in magnitude with increasingly heavy loads. When the inductive load is switched off, the collapsing magnetic field is converted into electrical energy, which takes the form of a double exponential transient. Depending on the source, these transients can be as large as hundreds of volts and hundreds of amps with duration times of 400 milliseconds.

Typical sources of inductive transients are:

- Generators Motors
- Relays
   Transformers

These examples are extremely common in electrical and electronic systems. Because the sizes of the loads vary according to the application, the wave shape, duration, peak current, and peak voltage are all variables which exist in real world transients. Once these variables can be approximated, a suitable suppressor technology can be selected.

#### **Overvoltage Applications**

- Industrial, High Energy AC Products such as Solenoids, Motor Drives and Robotics
- Telecommunications Products
- UPS, AC Panels, Power Supplies, Circuit Breakers (TVSS Products)
- Portable and Automotive Electronic Equipment

#### **Lightning Induced Transients**

Transients induced by lightning are not the result of a direct strike. When a lightning strike occurs, the event creates a magnetic field which can induce transients of large magnitude in nearby electrical cables.

#### Technological Solutions for Transient Threats

Because of the various types of transients and applications, it is necessary to employ protection devices with different characteristics in different applications. Littlefuse offers the broadest range of circuit protection technologies.

#### **Overvoltage Protection Portfolio Includes:**

#### **MOVs (Metal Oxide Varistors)**

A ceramic technology that offers medium to very high energy ratings for a wide range of applications. Available in screw terminal, radial, square and axial leaded connections.

#### **Discrete TVS Diode**

This Silicon Avalanche Diode Technology is available in surface mount and axial leaded packages. It offers protection from medium to very high energy transients and can be used in wide range of applications.

### **OVERVOLTAGE SUPPRESSION PRODUCTS**

Varistors, Surge Fuses and Varistor Assemblies



#### **Radial Leaded MOV**

		OPERATING	OPERATING	PEAK	PEAK	OPERATING	MOUNT/			AGE	NCY			FREE
SERIES NAME ¹		AC VOLTAGE RANGE	DC VOLTAGE RANGE	CURRENT RANGE ² (A)	ENERGY RANGE ³	TEMPERATURE	FORM	DISC SIZE	Л	CSA	VDE	CECC	ROHS	LEAD FF
TMOV®/iTMOV®		115-750	—	6000-10,000	35-480		Badial	14, 20, 34 mm	•	•	•	•	•	•
TMOV® 25S	-	115-750	—	20,000	170-670			25 mm	•				•	•
UltraMOV™	••••	130-625	170-825	1750-10,000	12.5-720	-55 to +85°C		7, 10, 14, 20, 25 mm	•	•	•	•	•	•
UltraMOV™ 25S		115-750	150-970	22,000	230-890	-55 10 +65 0		25 mm	•	•	•	•	•	•
C-III		130-660		3500-9000	40-530			10, 14, 20 mm	•	•	•		•	•
LA		130-1000	175-1200	1200-6500	11-360			7, 10, 14, 20 mm	•	•	•	•	•	•
ZA	3911	4-460	5.5-615	50-6500	0.1-52			5, 7, 10, 14, 20 mm	•		•	•	•	•

#### Industrial High Energy Terminal MOV

		OPERATING	OPERATING	PEAK	PEAK	OPERATING	MOUNT/		AGE	NCY	~	EE	
SERIES NAME ¹		AC VOLTAGE RANGE	DC VOLTAGE RANGE	CURRENT RANGE ² (A)	ENERGY RANGE ³	TEMPERATURE	FORM	DISC SIZE	Ы	CSA	ROHS	LEAD FREE	
BA/BB		130-2800	175-3500	50,000 70,000	450-10,000		Screw /	60 mm	•		•		
DA/DB	2.	130-750	175-970	40,000	270-1050		Clip Terminals	40 mm	•		•	•	
НА	PR	130-750	175-970	25,000 40,000	200-1050		Industrial	32, 40 mm	•	•	•	•	
TM0V34S®	-	115-750	—	40,000	235-1050	-55 to +85°C		34 mm	•		•	•	
HB34, HG34, HF34		130-750	175-970	40,000	270-1050			Packaged Radial Leads	34 mm	•	•	•	•
DHB34	-	250-2800	330-3500	20,000 70,000	330-10,000			34 mm			•		
CA	S	250-2800	330-3500	20,000 70,000	330-10,000		Bare Disc	60 mm			•		

#### **High Power TVS Diodes**

SERIES NAME ¹		PACKAGE TYPE	REVERSE STANDOFF VOLTAGE (V _R )	PEAK PULSE POWER RANGE ¹ (P _{PP} )	PEAK PULSE CURRENT (I _{PP} 8x20µs)	OPERATING TEMPERATURE	HALOGEN FREE	ROHS COMPLIANT
15KPA	000	P600	17-280	15,000 W			•	•
20KPA	220	P600	20.0-300	20,000 W	Not Applicable	-85° to +302° F (-55° to +175° C)	•	•
30KPA	+22	P600	28.0-288	30,000 W			•	•
AK6	× ×	Radial Lead	58-430	NA	6,000 A	-67° to +347° F	•	•
AK10	44	Radial Lead	58-430	NA	10,000 A	(-55° to +150° C)	•	•

1. Detailed information about most product series listed here can be found on littelfuse.com/varistor

2. Not an applicable parameter for Crowbar devices

3. Value shown in Joules



RoHS

### LVSP SURGE SUPPRESSION FUSE

600 Vac • 5-100 kA



#### **Description**

The Littelfuse® Varistor Protection (LVSP) Fuses are intended for the protection of TVSS products. The LVSP series has been designed to survive the 8 x 20 µs lightning surges described in various standards (UL 1449, IEC 61000-4-5 and IEEE C62.41) without opening. This allows the TVSS to perform the necessary suppression. The LVSP is not rated for continuous current and the ratings are specific 8 x 20 µs surge capability. The LVSP series can be used to facilitate TVSS module compliance to UL 1449 in permanently connected applications (abnormal overvoltage, unlimited current conditions).

#### **Features/Benefits**

- Very current limiting under AC short-circuit conditions
- Available in multiple mounting configurations (cartridge, bolt-in, PC board mount)
- Provides short circuit protection in TVSS systems and complements the Littelfuse line of overvoltage products (HA, HB34, TMOV® and iTMOV® varistors as well as the AK-10 series TVS diodes)

#### **Applications**

- TVSS products
- Surge arrestors

#### **Recommended Fuse Blocks**

Ľ	V	S	P	'	5	;-	2(	D)	-2	

101
110
85
111

LFJ60100	open block)8!	5
2.000.00	open 2.00.,	-

#### Web Resources

Download other technical information: littelfuse.com/lvsp

#### **Specifications**

Voltage Rating	600 Vac					
Interrupting Rating	200 kA					
Ratings	5 – 100 kA 8 x 20 µs surge withstand					
Approvals Environmental	UL Recognized (File: E71611) RoHs Compliant					
Electrical Specifications						

CATALOG NUMBER	8 X 20 μS SURGE RATING	NOMINAL MELTING I ² T (A ² S)	NOMINAL CLEARING I ² T (A ² S)	lpeak@100 kA 60 HZ (A)		
LVSP5	5,000	359	981	3,700		
LVSP10	10,000	1,300	3,210	5,823		
LVSP15	15,000	3,267	6,235	7,765		
LVSP20	20,000	4,940	11,710	8,135		
LVSP30	30,000	11,950	35,325	12,478		
LVSP40	40,000	20,550	61,700	15,250		
LVSP60	60,000	39,240	145,555	19,604		
LVSP80	80,000	75,000	254,000	24,600		
LVSP100	100,000	Contact Factory				

#### **Ordering Information**

NG NG	CATALOG/ORDERING NUMBER								
SURGE RATING	CAF	RTRIDGE	LE	EADED	BOLT-IN				
5	LVSP52	LVSP0005TX2	LVSP5R	LVSP0005TXR	-	-			
10	LVSP102	LVSP0010TX2	LVSP10R	LVSP0010TXR	-	-			
15	LVSP152	LVSP0015TX2	LVSP15R	LVSP0015TXR	-	-			
20	LVSP202	LVSP0020TX2	LVSP20R	LVSP0020TXR	-	-			
30	LVSP302	LVSP0030TX2	-	-	LVSP30	LVSP0030T			
40	LVSP402	LVSP0040TX2	-	-	LVSP40	LVSP0040T			
60	LVSP60-2	LVSP0060TX2	-	-	LVSP60	LVSP0060T			
80	LVSP802	LVSP0080TX2	-	-	LVSP80	LVSP0080T			
100	-	-	-	-	LVSP100-L	LVSP0100VXL			

#### **Dimensions Inches (mm)**



Cartridge 30-80 A .812 (20.62) 24 Withelitur Surge Suppression FUSE 2.25 LVSP30-2 600 VAC or LESS



### **BVSP SERIES SURGE PROTECTION DEVICE**

600 Vac • 10 kA



#### **Specifications**

Voltage Rating	600 Vac
Interrupting Rating	200 kA
Ratings	10 kA 8 x 20 µs surge withstand

#### **Ordering Information**

SERIES	8 X 20 μS SURGE RATING (A)	PACKAGE QUANTITY	MOUNTING METHOD	CATALOG NUMBER	ORDERING NUMBER
BVSP	10,000	10	Ferrule	BVSP10-2	BVSP0010TX2
BVSP	10,000	10	PCB Tabs	BVSP10-R	BVSP0010TXR

#### **Electrical Specifications**

CATALOG NUMBER	8 X 20 μS SURGE RATING (A)	NOMINAL MELTING I ² T (A ² S)	NOMINAL CLEARING I²T (A²S)	lpeak @ 200 kA 60 HZ (A)
BVSP10-2	10,000	1,580	9,960	8,160
BVSP10-R	10,000	1,580	9,960	8,160

#### **Dimensions Inches (mm)**

#### **Ferrule Version**

### → .410 ↓ (10.41) → .328 (8.33) ↓ ↓ ↓ 1.5 (38.1) ↓





#### Description

The Littelfuse® BVSP surge protection device (SPD) is intended for the protection of transient voltage surge suppressions (TVSS) systems. The BVSP series has been designed to survive the 8 x 20 µs lightning surges described in various standards (UL 1449, IEC 61000-4-5 and IEEE C62.41) without opening. This allows the TVSS to perform the necessary suppression. The BVSP is not rated for continuous current and the ratings are specific 8 x 20 µs surge capability. The BVSP series can be used to facilitate TVSS module compliance to UL 1449 in permanently connected applications (abnormal overvoltage, unlimited current conditions).

#### **Features/Benefits**

- Very current limiting under AC short-circuit conditions
- Available in ferrule and printed circuit board (PCB) configurations
- Provides short circuit protection in TVSS systems and complements the Littelfuse line of overvoltage products (HA, HB34, TMOV[®] and iTMOV[®] varistors as well as the AK-10 series TVS diodes)

#### Applications

- TVSS products
- Surge arrestors

#### **Recommended Fuse Holders**

L60030M (open block)	101
LFPSM (dead front)	

#### **Section Overview**

Miscellaneous Accessories include custom-built solutions designed specifically to meet code requirements, fuse reducers, box cover units and an assortment of useful fuse and holder accessories.



# MISCELLANEOUS PRODUCTS #

#### **Table of Contents**

Fuse Reducers	178
Box Cover Units	179
Fuse Replacement & Custom Kits	180
Electronic Fuse Display & Spare Fuse Cabinet	181

### **Miscellaneous Accessories**

### **FUSE REDUCERS**



#### **Ordering Information**

#### 250 Volt

CATALOG/O CLASS H/K5	RDERING NUMBER CLASS R	FUSE CLIP	FUSE CASE SIZE
CLASS H/KJ	ULASS II		ON TOL OILL
LRU 263	LRU 263 R	60 A	30 A
LRU 213	LRU 213 R	100 A	30 A
LRU 216	LRU 216 R	100 A	60 A
LRU 226	LRU 226 R	200 A	60 A
LRU 2621	LRU 2621 R	200 A	100 A
LRU 2641	LRU 2641 R	400 A	100 A
LRU 2642	LRU 2642 R	400 A	200 A
LRU 2661	LRU 2661 R	600 A	100 A
LRU 2662	LRU 2662 R	600 A	200 A
LBU 2664	LRU 2664 B*	600 A	400 A

*Only one reducer required.

#### 600 Volt

CATALOG	G/ORDERING I	NUMBER		FUSE
CLASS H/K5	CLASS R	CLASS J	FUSE CLIP	CASE SIZE
LRU 663	LRU 663 R	LRUJ63	60 A	30 A
LRU 216	LRU 216 R	LRUJ13	100 A	30 A
LRU 616	LRU 616 R	LRUJ16¶	100 A	60 A
LRU 626	LRU 626 R	LRUJ26	200 A	60 A
LRU 2621	LRU 2621 R	LRUJ21	200 A	100 A
LRU 2641	LRU 2641 R	LRUJ41	400 A	100 A
LRU 2642	LRU 2642 R	LRUJ42	400 A	200 A
LRU 2661	LRU 2661 R	—	600 A	100 A
LRU 2662	LRU 2662 R	—	600 A	200 A
LRU 2664	LRU 2664 R†	LRUJ64	600 A	400 A

†Only one reducer required.

¶Fuse and reducer combination is slightly larger in diameter than 100 A Class J fuses. For specific applications, contact factory.

Class J reducers cannot be used in bolt-on applications.

#### Description

Littelfuse[®] fuse reducers allow smaller size fuses to be installed into existing fuse clips to prevent overfusing.

#### **Features/Benefits**

- Simple installation
- Reduces inventory requirements
- Silver brazed joints for maximum strength
- UL Listed (File: E136855)
- CSA Certified (File: LR92899)

#### Web Resources

Download technical information: littelfuse.com/lruh littelfuse.com/lrur littelfuse.com/lrur

#### Dimensions

Refer to the fuse section of this catalog for fuse dimensions.

#### **Recommended Fuses**

#### **Class H/K5 Fuse Reducers**

NLN / NLS	
-----------	--

#### Class R Fuse Reducers

FLNR / FLSR	
FLNR_ID / FLSR_ID	
IDSR	
LLNRK / LLSRK	
LLSRK_ID	
KLNR / KLSR	

#### **Class J Fuse Reducers**

JTD_ID / JTD	21
JLS	22


(h)

## BOX COVER UNITS



#### Description

Provide economical method of protecting small motors against overcurrent damage.

#### **Applications**

- Edison-Base plug fuses (TOO, TLO)
- Type S plug fuses (SOO, SLO) with adapters (SAO)

#### **Specifications**

Voltage Rating125 VMax Ampere Rating15 AApprovalsUL Listed parts

#### Web Resources

Additional technical information available at: **littelfuse.com/boxcover** 

		FIGURE	LITTELFUSE	BOX COVER FEATURES			TO BE		
		NUMBER	PART NUMBER	EDISON BASE FUSE HOLDER	GROUNDING RECEPTACLE	SINGLE POLE SWITCH	TWO POLE SWITCH	PILOT LIGHT	MOUNTED ON
			LSOU	1	—	—	—	—	2-1/4" Handy Box
		1	LSOW	1	—	—	-	—	2-3/4" Switch Box
		'	LSOX	1	—	—	-	—	4" Octagon Box
			LSOY	1	—	—	_	—	4" Square Box
Figure 1	Figure 2		LSRU*	1	1	—	-	—	2-1/4" Handy Box
(		2	LSRW	1	1	—	—	—	2-3⁄4" Switch Box
		2	LSRX	1	1	—	_	—	4" Octagon Box
<u>(</u> )			LSRY	1	1	—	—	—	4" Square Box
			LSSU*	1	—	1	-	—	2-1/4" Handy Box
Figure 3	Figure 4	3	LSSW	1	—	1	-	—	2-3/4" Switch Box
		5	LSSX	1	—	1	-	—	4" Octagon Box
			LSSY*	1	—	1	_	—	4" Square Box
		4	LSOY-B	2	—	—	—	_	4" Square Box
e e Figure 5	Figure 6	5	LSSY-L	1	_	1	_	1	4" Square Box
		6	LSSY-RL	1	1	1	_	1	4" Square Box
		7	LSCY	2	—	2	_	—	4" Square Box
Figure 7	Figure 8	8	LSKA	2	1 (250V)	—	_	—	4-1/16" Square Box
		9	LSTY	2	—	_	1	—	4" Square Box
		*UL Listed (Fil	e: E308725)						

Figure 9

## FRCK SERIES FUSE REPLACEMENT & CUSTOM KITS



#### Description

Fuse Replacement and Custom Kits help reduce downtime by providing mobile storage and organization for replacement fuses. The FRCK Series provides a custom solution that can be filled with multiple fuse series that are more common or specific to your needs or application.

#### **Features/Benefits**

- Custom sized compartments fit various fuse series
- Large kit features a convenient handle for carrying
- Kits are sold empty for complete customization
- Each kit comes with a blank label on the inside cover so users can write in part numbers or use bar code labels to help with refills.

#### **Web Resources**

#### Additional information: littelfuse.com/kits

KIT SIZE	DIMENSIONS L X W X H (INCHES)	DESCRIPTION	CATALOG NUMBER
Large	16.00 x 12.00 x 10.00	Mobile organizer with 2 small and 3 medium drawers; Unique FRACK Label for Oil & Gas	FRCK-OG
Large	16.00 x 12.00 x 10.00	Mobile organizer with 2 small and 3 medium drawers	FRCK-LG
Medium	14.00 x 9.13 x 2.00	14" organizer with adjustable dividers	FRCK-MD
Small	8.25 x 4.25 x 1.00	8" organizer with up to 6 compartments	FRCK-SM





FRCK-OG & FRCK-LG

FRCK-MD

FRCK-SM



## FUSE DISPLAYS AND CABINETS

#### **Electronic Fuse Display**



#### **Description**

This wall-mountable or free-standing modular rack system prominently displays Littelfuse glass and automotive fuses. Additional sections can be quickly snapped on for a larger product selection. Each rack features a cross reference guide to help customers locate the proper replacement fuse.

#### **Features/Benefits**

- Holds 720 (144 5-packs) of the most popular glass, ceramic, and automotive fuses
- Designed to save space—measures 14" H × 9"W × 4" D Suitable for wall or counter mounting
- Includes cross reference, product identification guide, and back-up card for easy reordering
- Expandable with modular section that can hold 240 fuses (48 5-packs) per section

#### **Spare Fuse Cabinet**



#### Fully stocked rack includes the following parts

3AG (0 FAST ACTI	ILASS) NG FUSES	3AG (GLASS) SLO-BLO® FUSES			
QUANTITY	CATALOG NUMBER	QUANTITY	CATALOG NUMBER		
25	312 ½A	25	313 ½A		
50	312 1A	25	313 3⁄4A		
25	312 1 ¹ /2A	25	313 1A		
75	312 2A	25	313 1 ¹ / ₂ A		
25	312 2 ¹ /2A	50	313 2A		
75	312 3A	25	313 2 ¹ / ₂ A		
25	312 4A	25	313 3A		
25	312 5A	25	313 4A		
25	312 10A	25	313 5A		

3AB (CE NORMAL-E		3AB (CERAMIC) SLO-BLO® FUSES		
QUANTITY	CATALOG NUMBER	QUANTITY	CATALOG NUMBER	
25	314 15A	25	326 8A	
25	314 20A	20	326 10A	
25	314 30A	—	—	

#### **Ordering Information**

TYPE	CATALOG NUMBER	ORDERING NUMBER
Fully Stocked Display	094324PG	00940324ZXPG
Empty Display Rack	FDR001PG	0FDR0001ZXPG
Additional Sections	MRS001PG	0MRS0001ZXPG

#### Description

- Steel cabinet with piano hinges that can be locked to prevent unauthorized access. Weather stripped to reduce the accumulation of dust, dirt and moisture
- Convenient inventory card located inside door. Measures 30"H × 24"W × 12"D. Keyhole mounting holes 16" on center for easy installation

#### **Ordering Information**

TYPE	CATALOG NUMBER	ORDERING NUMBER
Spare Fuse Cabinet	LSFC	LSFC
Spare Keys	LKEY001	LKEY0001Z

#### Web Resources

Additional information: littelfuse.com/lsfc

#### **Section Overview**

This Technical Application Guide or 'Fuseology' section provides the information needed to select the correct types of Littelfuse POWR-GARD® fuses for most applications. If there are any questions or if additional data is needed for a specific use, call the Littelfuse Technical Support and Engineering Service Group at **1-800-TEC-FUSE** (1-800-832-3873), email them at **techline@littelfuse.com** or visit us at **littelfuse.com**.



# 🔆 TECHNICAL APPLICATION GUIDE 🕷

#### **Table of Contents**

	And I have a	
	HETOMA PROVIDENTIMA	
Тео	chnical Information	

White papers, and a library of technical information is available online at littelfuse.com/technicalcenter

Euseology Fundamentals	183
Selection Considerations	184
Time-current Curves and Peak Let-through Charts	189
Selective Coordination	191
JL/CSA Fuse Classes and Applications	194
Terms and Definitions	196
Notor Protection Tables	203
Alphanumeric Index of Catalog Numbers	206
Condensed Fuse Cross Reference	208



## FUSEOLOGY FUNDAMENTALS

#### I. OVERCURRENT PROTECTION FUNDAMENTALS (FUSES AND HOW THEY WORK)

#### Introduction

An important part of developing quality overcurrent protection is an understanding of system needs and overcurrent protective device fundamentals. This section discusses these topics with special attention to the application of fuses. If you have additional questions, call our Technical Support Group at 1-800-TEC-FUSE (1-800-832-3873). Definitions of terms used in this section are located towards the end of this Technical Application Guide.

#### Why Overcurrent Protection?

All electrical systems eventually experience overcurrents. Unless removed in time, even moderate overcurrents quickly overheat system components, damaging insulation, conductors, and equipment. Large overcurrents may melt conductors and vaporize insulation. Very high currents produce magnetic forces that bend and twist bus bars. These high currents can pull cables from their terminals and crack insulators and spacers.

Too frequently, fires, explosions, poisonous fumes and panic accompany uncontrolled overcurrents. This not only damages electrical systems and equipment, but may cause injury or death to personnel nearby.

To reduce these hazards, the National Electrical Code[®] (NEC[®]), OSHA regulations, and other applicable design and installation standards require overcurrent protection that will disconnect overloaded or faulted equipment.

Industry and governmental organizations have developed performance standards for overcurrent devices and testing procedures that show compliance with the standards and with the NEC. These organizations include: the American National Standards Institute (ANSI), National Electrical Manufacturers Association (NEMA), and the National Fire Protection Association (NFPA), all of which work in conjunction with Nationally Recognized Testing Laboratories (NRTL) such as Underwriters Laboratories (UL).

Electrical systems must meet applicable code requirements including those for overcurrent protection before electric utilities are allowed to provide electric power to a facility.

#### What is Quality Overcurrent Protection?

A system with quality overcurrent protection has the following characteristics:

- 1. Meets all legal requirements, such as NEC[®], OSHA, local codes, etc.
- 2. Provides maximum safety for personnel, exceeding minimum code requirements as necessary.

- 3. Minimizes overcurrent damage to property, equipment, and electrical systems.
- 4. Provides coordinated protection. Only the protective device immediately on the line side of an overcurrent opens to protect the system and minimize unnecessary downtime.
- 5. Is cost effective while providing reserve interrupting capacity for future growth.
- 6. Consists of equipment and components not subject to obsolescence and requiring only minimum maintenance that can be performed by regular maintenance personnel using readily available tools and equipment.

#### **Overcurrent Types and Effects**

An overcurrent is any current that exceeds the ampere rating of conductors, equipment, or devices under conditions of use. The term "overcurrent" includes both overloads and short-circuits.

#### **Overloads**

An overload is an overcurrent confined to normal current paths in which there is no insulation breakdown.

Sustained overloads are commonly caused by installing excessive equipment such as additional lighting fixtures or too many motors. Sustained overloads are also caused by overloading mechanical equipment and by equipment breakdown such as failed bearings. If not disconnected within established time limits, sustained overloads eventually overheat circuit components causing thermal damage to insulation and other system components.

Overcurrent protective devices must disconnect circuits and equipment experiencing continuous or sustained overloads before overheating occurs. Even moderate insulation overheating can seriously reduce the life of the components and/or equipment involved. For example, motors overloaded by just 15% may experience less than 50% of normal insulation life.

Temporary overloads occur frequently. Common causes include temporary equipment overloads such as a machine tool taking too deep of a cut, or simply the starting of an inductive load such as a motor. Since temporary overloads are by definition harmless, overcurrent protective devices should not open or clear the circuit.

It is important to realize that fuses selected must have sufficient time-delay to allow motors to start and temporary overloads to subside. However, should the overcurrent continue, fuses must then open before system components are damaged. Littelfuse POWR-PRO® and POWR-GARD® time-delay fuses are designed to meet these types of protective needs. In general, time-delay fuses hold 500% of the rated current for a minimum of ten seconds, yet will still open quickly on higher values of current.

## FUSEOLOGY FUNDAMENTALS

Applied Answers Delivered

Even though government-mandated high-efficiency motors and NEMA Design E motors have much higher locked rotor currents, POWR-PRO® time-delay fuses such as the FLSR_ ID, LLSRK_ID, or IDSR series have sufficient time-delay to permit motors to start when the fuses are properly selected in accordance with the NEC®.

#### **Short-Circuits**

A short-circuit is an overcurrent flowing outside of its normal path. Types of short-circuits are generally divided into three categories: bolted faults, arcing faults, and ground faults. Each type of short-circuit is defined in the Terms and Definitions section.

A short-circuit is caused by an insulation breakdown or faulty connection. During a circuit's normal operation, the connected load determines current. When a short-circuit occurs, the current bypasses the normal load and takes a "shorter path," hence the term 'short-circuit'. Since there is no load impedance, the only factor limiting current flow is the total distribution system's impedance from the utility's generators to the point of fault.

A typical electrical system might have a normal load impedance of 10 ohms. But in a single-phase situation, the same system might have a load impedance of 0.005 ohms or less. In order to compare the two scenarios, it is best to apply Ohm's Law (I = E/R for AC systems). A 480 volt single-phase circuit with the 10 ohm load impedance would draw 48 amperes (480/10 = 48). If the same circuit has a 0.005 ohm system impedance when the load is shorted, the available fault current would increase significantly to 96,000 amperes (480/0.005 = 96,000).

As stated, short-circuits are currents that flow outside of their normal path. Regardless of the magnitude of overcurrent, the excessive current must be removed quickly. If not removed promptly, the large currents associated with short-circuits may have three profound effects on an electrical system: heating, magnetic stress, and arcing.

*Heating* occurs in every part of an electrical system when current passes through the system. When overcurrents are large enough, heating is practically instantaneous. The energy in such overcurrents is measured in ampere-squared seconds (I²t). An overcurrent of 10,000 amperes that lasts for 0.01 seconds has an I²t of 1,000,000 A²s. If the current could be reduced from 10,000 amperes to 1,000 amperes for the same period of time, the corresponding I²t would be reduced to 10,000 A²s, or just one percent of the original value.

If the current in a conductor increases 10 times, the I²t increases 100 times. A current of only 7,500 amperes can melt a #8 AWG copper wire in 0.1 second. Within eight milliseconds (0.008 seconds or one-half cycle), a current of 6,500 amperes can raise the temperature of #12 AWG THHN thermoplastic insulated copper wire from its operating temperature of 75°C to its maximum short-circuit

temperature of 150°C. Any currents larger than this may immediately vaporize organic insulations. Arcs at the point of fault or from mechanical switching such as automatic transfer switches or circuit breakers may ignite the vapors causing violent explosions and electrical flash.

*Magnetic stress* (or force) is a function of the peak current squared. Fault currents of 100,000 amperes can exert forces of more than 7,000 lb. per foot of bus bar. Stresses of this magnitude may damage insulation, pull conductors from terminals, and stress equipment terminals sufficiently such that significant damage occurs.

Arcing at the point of fault melts and vaporizes all of the conductors and components involved in the fault. The arcs often burn through raceways and equipment enclosures, showering the area with molten metal that quickly starts fires and/or injures any personnel in the area. Additional short-circuits are often created when vaporized material is deposited on insulators and other surfaces. Sustained arcing-faults vaporize organic insulation, and the vapors may explode or burn.

Whether the effects are heating, magnetic stress, and/or arcing, the potential damage to electrical systems can be significant as a result of short-circuits occurring.

#### **II. SELECTION CONSIDERATIONS**

Selection Considerations for Fuses (600 volts and below)

Since overcurrent protection is crucial to reliable electrical system operation and safety, overcurrent device selection and application should be carefully considered. When selecting fuses, the following parameters or considerations need to be evaluated:

- Current Rating
- Voltage Rating
- Interrupting Rating
- Type of Protection and Fuse Characteristics
- Current Limitation
- Physical Size
- Indication

#### **Current Rating**

The current rating of a fuse is the AC or DC current, expressed in amperes, which the fuse is capable of carrying continuously under specified conditions. Fuses selected for a circuit must have ampere ratings that meet NEC[®] requirements, namely those found in NEC[®] Articles 240 and 430. These NEC[®] requirements establish maximum ratings and in some cases, minimum ratings. When selecting a fuse, it is generally recommended to select a current rating as close as possible to the system's normal running current.



#### Voltage Rating

The voltage rating of a fuse is the maximum AC or DC voltage at which the fuse is designed to operate. Fuse voltage ratings must equal or exceed the circuit voltage where the fuses will be installed, and fuses used in DC circuits must be specifically rated for DC applications. In terms of voltage, fuses may be rated for AC only, DC only, or both AC and DC. However, exceeding the voltage ratings or using an AC only fuse in a DC circuit could result in violent destruction of the fuse.

The standard 600 volt rated fuses discussed in this section may be applied at any voltage less than or equal to their rating. For example, a 600 volt fuse may be used in a 277 volt or even a 32 volt system, but not any system exceeding 600 volts.

NOTE: This does not apply to semiconductor fuses and medium voltage fuses. See the semiconductor and medium voltage fuse application information on littelfuse.com for voltage limitations of these fuses.

#### Interrupting Rating

The interrupting rating of a fuse is the highest available symmetrical rms alternating current that the fuse is required to safely interrupt at its rated voltage under standardized test conditions. A fuse must interrupt all overcurrents up to its interrupting rating without experiencing damage. Standard UL fuses are available with interrupting ratings of 10,000 A, 50,000 A, 100,000 A, 200,000 A, and 300,000 A.

NEC® Article 110.9 requires that all equipment intended to break current at fault levels have an interrupting rating sufficient for the system voltage and current available at the equipment's line terminals. Refer to Figure 1. It is vitally important to select fuses with interrupting ratings which equal or exceed the available fault current.



Figure 1 – Interrupting Rating Requirements per NEC

The recommendation to standardize on fuses with at least a 200.000 ampere interrupting rating (AIR) ensures that all fuses have an adequate interrupting rating while providing reserve interrupting capacity for future increases in available fault current.

#### 300,000 AIR Fuses

Littelfuse POWR-PRO® fuse series have a Littelfuse Self-Certified interrupting rating of 300,000 amperes rms symmetrical. The 300,000 ampere testing was performed in a Nationally Recognized Testing Laboratory, and the tests were UL witnessed. UL has ruled that fuses with a UL interrupting rating greater than 200,000 amperes must be marked as "Special Purpose Fuses" and may not be labeled as UL Listed Class RK5, RK1, L, etc.

#### Type of Protection and Fuse Characteristics

Time current characteristics determine how fast a fuse responds to overcurrents. All fuses have inverse time characteristics; that is, the fuse opening time decreases as the magnitude of overcurrent increases. When properly rated in accordance with NEC[®] requirements, fuses provide both overload and short-circuit protection to system conductors and components. However, in some instances such as when fuses are used to backup circuit breakers or to provide motor branch circuit short-circuit and ground fault protection, fuses provide only short-circuit protection. A fuse's response to overcurrents is divided into short-circuits and overloads.

#### Short-Circuits

A fuse's short-circuit response is its opening time on highervalue currents. For power fuses, higher-value currents are generally over 500-600% of the fuse's current rating. As stated earlier, all fuses have inverse time characteristics: the higher the current, the faster the opening time. Since shortcircuits should be removed quickly, inverse time is especially important for short-circuit protection.

#### **Overloads**

While fuses must disconnect overloaded conductors and equipment before the conductors and components are seriously overheated, they should not disconnect harmless temporary overloads. To provide sufficient overload protection for system conductors, UL has established maximum fuse opening times at 135% and 200% of a fuse's current rating. All UL Listed fuses for application in accordance with the National Electrical Code® must meet these limits whether they are fast-acting or time-delay fuses.

As just stated, a fuse is designed to respond to two types of overcurrents - short circuits and overloads. As a result, selecting the proper fuse for a given application usually involves deciding whether to use a time-delay fuse or a fast-acting fuse. A more in-depth review of both possible scenarios is important at this time.

Technica

#### Fast-Acting (Normal-Opening) Fuses

Applied Answers Delivered

Fast-acting fuses (sometimes called "Normal-opening" fuses) have no intentional time-delay. Typical opening times at 500% of the fuse ampere rating range from 0.05 second to approximately 2 seconds. Fast-Acting fuses are suitable for non-inductive loads such as incandescent lighting and general-purpose feeders, or branch circuits with little or no motor load. When protecting motors and other inductive loads, fast-acting fuses must be rated at 200-300% of load currents to prevent nuisance opening on in-rush currents. Fuses with such increased ratings no longer furnish adequate protection from overloads and only provide short-circuit protection. Overload relays or other overload protection devices must be provided to properly protect conductors and equipment from overload conditions.

All fast-acting fuses provide fast short-circuit response within their interrupting rating. Some are considered current-limiting, such as UL Class T and Class J. Others are non-current-limiting, such as UL Class H.

#### Time-Delay (SLO-BLO®) Fuses

Most UL Class CC, CD, G, J, L, RK5 and RK1 fuses, plus some of the UL Listed Miscellaneous fuses are considered time-delay. If so, they are identified as such on the fuse label with the words "Time-Delay", "T-D", "D", or some other suitable marking. Minimum time-delay varies with the fuse class, and to some degree with the fuse ampere rating. UL standards for POWR-GARD® fuse series FLNR, FLNR_ID, FLSR, FLSR_ID, IDSR (UL Class RK5), LLNRK, LLSRK, LLSRK_ID (UL Class RK1), and JTD, JTD_ID (UL Class J) require these fuses to carry 500% rated current for a minimum of 10 seconds. Standards for CCMR and KLDR (UL Class CC and CD) and SLC (UL Class G) fuses require them to carry 200% rated current for a minimum of 12 seconds.

Although there is no UL Classification for time-delay Class L fuses, it is still permissible for them to be marked "Time-Delay." The amount of time-delay is determined by the manufacturer. Littlefuse KLPC series and KLLU series fuses will hold 500% current for 10 seconds or more.

In addition to providing time-delay for surges and short time overloads, time-delay fuses meet all UL requirements for sustained overload protection. On higher values of current, time-delay fuses are current-limiting; meaning they remove large overcurrents in less than one-half cycle (0.00833 seconds). Time-delay fuses provide the best overall protection for both motor and general purpose circuits, and eliminate nuisance fuse opening and most situations of downtime.

Compared to fast-acting fuses, time-delay fuses can be selected with ratings much closer to a circuit's operating current. For example, on most motor circuits Class RK5 and RK1 fuses can be rated at 125-150% of a motor's full load current (FLA). This provides superior overload and short-

circuit protection, and often permits the use of smaller, less expensive disconnect switches. Time-delay fuses have gradually replaced most one-time (UL Class K5) and renewable (UL Class H) fuses. Today, more than 50% of all fuses sold by electrical distributors are time-delay fuses.

#### **Dual Element Fuses**

Littelfuse time-delay FLNR, FLNR_ID, FLSR, FLSR_ID, IDSR (UL Class RK5), and LLNRK, LLSRK, LLSRK_ID (UL Class RK1), and some JTD, JTD_ID (UL Class J) series fuses have true dual-element construction meaning the fuse has an internal construction consisting of separate short-circuit and overload sections or elements. Time-delay elements are used for overload protection, and separate fast acting fuse elements or links are used to provide current-limiting short-circuit protection.

#### Very Fast-Acting Fuses

This category of fuses exists for limited applications. The principle use of very fast acting fuses is to protect solidstate electronic components, such as semiconductors. Fuse series designated as 'High-Speed (Semiconductor) Fuses' have special characteristics including quick overload response, very low I²t and I_{peak} currents, and peak transient voltages, that provide protection for components that cannot withstand line surges, low value overloads, or short-circuit currents. Very fast-acting fuses are designed for very fast response to overloads and short-circuits, and are very current-limiting.

#### Effect of Ambient Temperature on Fuses

The current carrying capacity of fuses is 110% of the fuse rating when installed in a standard UL test circuit and tested in open air at 25°C ambient. This allows for derating to 100% of rating in an enclosure at 40°C ambient.



Figure 2 – Fuse Rerating Curve



#### **Current Limitation**

A current-limiting fuse is one that opens and clears a fault in less than 180 electrical degrees, or in other words, within the first half electrical cycle (0.00833 seconds). See the definition of Current-limiting Fuse and *Figure 13* in the Terms and Definitions section.

NEC[®] Article 240.2 states that a current-limiting overcurrent protective device must reduce the peak let-through current to a value substantially less than the potential peak current that would have occurred if the fuse were not used in the circuit or were replaced with solid conductors of the same impedance. The total destructive heat energy (I²t) to the circuit and its components is greatly minimized as a result of using current-limiting fuses.

It is important to note that UL Class H 'Renewable' fuses designed decades ago are considered non-current limiting. Other than Midget fuses, almost all other fuse types used in today's electrical systems and applications are considered currentlimiting per the above parameters. This selection consideration now involves determining the degree or level of current limitation required to properly protect a given device or system.

It is also important to point out that matching fuse holders and/or fuse blocks must reject non-current-limiting fuses and accept only current-limiting fuses of the stated UL Class.

#### **Physical Size**

While often overlooked, the physical size or overall dimensions of the fuse to be used in a given application is another important selection consideration to evaluate. There is a trend toward reduction of size in almost everything, and electrical equipment is no exception. Fuse size is actually determined by the size and dimensions of the fuse block or disconnect switch in which it is installed.

While saving space may be an important factor when selecting the proper fuses, other considerations should not be overlooked. Some of these include:

- Does the smallest fuse have the most desirable characteristics for the application?
- Does the equipment in which the fuse will be installed provide adequate space for maintenance?
- Do smaller fuses coordinate well with the system's other overcurrent protection?

If looking at just physical dimensions, a 600 volt, 60 ampere, 200,000 AIR, time-delay, dual-element UL Class CD fuse is smaller than a similarly rated UL Class J fuse, which is in turn, considerably smaller than a similarly rated UL Class RK1 or Class RK5 fuse. However, smaller-sized fuses can sometimes have less time-delay or more nuisance openings than their larger counterparts, so it is always important to consider all factors involved.

#### Indication

The newest consideration for selecting the best fuse for a given application is indication. Many of the more commonly used UL fuse classes are now available in both indicating and non-indicating versions. Built-in, blown-fuse indication that quickly identifies which fuse or fuses within an electrical panel or system have blown can be found on the Littelfuse POWR-PRO® LLSRK_ID Class RK1, FLNR_ID, FLSR_ID and IDSR Class RK5, and JTD_ID Class J fuse series.

The indicating feature on these fuses provides reduced downtime, increased safety, and reduced housekeeping or troubleshooting headaches and delays. Littelfuse Indicator[®] fuses will help lower the costs associated with downtime, provide longer fuse life by minimizing nuisance openings, increase system performance by minimizing equipment damage, and improve safety by minimizing accidents.

#### **III. GENERAL FUSING RECOMMENDATIONS**

Based on the above selection considerations, the following is recommended:

Fuses with ampere ratings from 1/10 through 600 amperes

- When available fault currents are less than 100,000 amperes and when equipment does not require the more current-limiting characteristics of UL Class RK1 fuses, FLNR and FLSR_ID Series Class RK5 current-limiting fuses provide superior time-delay and cycling characteristics at a lower cost than RK1 fuses. If available fault currents exceed 100,000 amperes, equipment may need the additional current-limitation capabilities of the LLNRK, LLSRK and LLSRK_ID series Class RK1 fuses.
- Fast-acting JLLN and JLLS series Class T fuses possess space-saving features that make them especially suitable for protection of molded case circuit breakers, meter banks, and similar limited-space applications.
- Time-delay JTD_ID and JTD series Class J fuses are used in OEM motor control center applications as well as other MRO motor and transformer applications requiring spacesaving IEC Type 2 protection.
- Class CC and Class CD series fuses are used in control circuits and control panels where space is at a premium. The Littelfuse POWR-PRO CCMR series fuses are best used for protection of small motors, while the Littelfuse KLDR series fuses provide optimal protection for control power transformers and similar devices.

For questions about product applications, call our Technical Support Group at 800-TEC-FUSE.

#### Fuses with ampere ratings from 601 through 6,000 amperes

For superior protection of most general-purpose and motor circuits, it is recommended to use the POWR-PRO® KLPC series Class L fuses. The Class L fuses are the only time-delay fuse series available in these higher ampere ratings.

Information on all the Littelfuse fuse series referenced above can be found on the UL/CSA Fuse Classes and Applications Charts found later in this Technical Application Guide.

#### IV. SELECTION CONSIDERATIONS FOR FUSE HOLDERS

Equally important to the selection of the proper fuse is the correct selection of the proper fuse holder or fuse block for a given application. Fuse holders are available using most of the same Selection Considerations outlined above for UL fuse classes. Considerations for fuse holders include:

- Current Rating
- Voltage Rating
- Interrupting Rating
- Physical Size
- Indication

Additional selection considerations for fuse holders and fuse blocks include:

- Number of poles
- Mounting configuration
- Connector type

#### **Number of Poles**

The number of poles for each set of fuses is determined by the characteristics of the circuit. Most fuse block series are available in 1, 2, or 3 pole configurations, although some are also available with four or more poles. The option to gang individual fuse blocks into longer strips will be determined by the available space and type of wire being used.

#### **Mounting Configuration**

Depending on the fuse block design, another selection consideration to evaluate is how the fuse block is mounted or inserted into the panel. Historically, fuse blocks simply screwed into the back of the panel, but many newer designs have now added (or replaced the screw-in design with) a DIN rail mounting capability. The DIN rail mounting feature allows the blocks to be quickly installed and removed from the rails.

#### **Connector Type**

For Littelfuse fuse blocks, a choice of three connector types or wire terminations is available:

- Screw for use with spade lugs or ring terminals.
- Screw with Pressure Plate for use with solid or stranded wire without terminal and recommended for applications where vibration will be a factor.
- Box Lug the most durable of the three options and used with all types of solid wire and Class B and Class C stranded wire.

There are a few additional aspects to keep in mind when selecting the fuse holder or fuse block needed for a given application. UL Class H blocks accept Class H, Class K5, and Class R fuses. Similarly, Midget-style fuse blocks accept both Midget and UL Class CC fuses.

Both UL Class R and Class CC fuse holders contain a rejection feature which prevents the insertion of a different Class or type of fuse. The physical size and dimensions of UL Class J and Class T fuses accomplish the same thing in preventing the insertion of a different Class of fuse as well.

#### **V. CIRCUIT PROTECTION CHECKLIST**

To select the proper overcurrent protective device for an electrical system, circuit and system designers should ask themselves the following questions before a system is designed:

- What is the normal or average current expected?
- What is the maximum continuous (three hours or more) current expected?
- What inrush or temporary surge currents can be expected?
- Are the overcurrent protective devices able to distinguish between expected inrush and surge currents, and open under sustained overloads and fault conditions?
- What kind of environmental extremes are possible? Dust, humidity, temperature extremes and other factors need to be considered.
- What is the maximum available fault current the protective device may have to interrupt?
- Is the overcurrent protective device rated for the system voltage?
- Will the overcurrent protective device provide the safest and most reliable protection for the specific equipment?
- Under short-circuit conditions, will the overcurrent protective device minimize the possibility of a fire or explosion?
- Does the overcurrent protective device meet all the applicable safety standards and installation requirements?

Answers to these questions and other criteria will help to determine the type overcurrent protection device to use for optimum safety, reliability and performance.

**Technical** 



## FUSE CHARACTERISTIC CURVES AND CHARTS

The performance capabilities of various fuses are graphically represented by two different types of fuse characteristic curves: time-current curves and peak let-through charts. These curves and charts define the operating characteristics of a given fuse, and assist system designers and engineers in selecting the proper fuse to protect equipment and electrical systems.

#### **Understanding Time-current Curves**

Time-current curves provide a graphical representation or plot of a fuse's average melting (opening) time at any current. Time-current curves for Littelfuse POWR-GARD[®] fuses can be found online at

#### littelfuse.com/technicalcenter.

In order to make the curves more readable, the performance information is presented on log-log paper. The overcurrent values appear across the bottom and increase in magnitude from left to right. Average melting times appear on the left-hand side of the curve and increase in magnitude from bottom to top. The ampere ratings of the individual fuses for a given series are listed at the top and increase in rating from left to right. *Figure 4* shows the average melting time curves for a typical time-delay fuse series.

As discussed earlier in the Fuseology Fundamentals section, time-delay, fast-acting, and very fast-acting fuses all respond differently based on the overcurrents occurring in the systems each is protecting. To illustrate the basic differences between each type of fuse, *Figure 5* compares the average melting times for 100 and 600 amp ratings



Figure 4 – Average Melting Time Curves for Typical Time-Delay Fuse Series



Figure 5 – Comparison of Average Melting Times for Three Fuse Types

of three fuse types: Littelfuse dual-element, time-delay LLSRK series class RK1 fuses (green); Littelfuse normal opening NLS series class K5 fuses (red); and Littelfuse very fast acting L60S series semiconductor fuses (blue).

To better illustrate this point, *Table 3* also compares the opening times for each of these fuses.

AMPERE	FUSE TYPE	OPENING TIME IN SECONDS					
RATING	10021112	500% RATING	800% RATING	1200% RATING			
	TIME-DELAY	12 secs.	0.9 secs.	0.14 secs.			
100	NORMAL OPENING	2 secs.	0.7 secs.	0.3 secs.			
	VERY FAST-ACTING	1.3 secs.	0.02 secs.	>0.01 secs.			
	TIME-DELAY	14 secs.	0.7 secs.	0.045 secs.			
600	NORMAL OPENING	10 secs.	3 secs.	1.1 secs.			
	VERY FAST-ACTING	2 secs.	0.05 secs.	>0.01 secs.			

Table 3 – Comparative Opening Times for Time-Delay, Fast-Acting, and Very Fast-Acting Fuses

#### **Peak Let-through Charts**

Peak let-through charts illustrate the maximum instantaneous current through the fuse during the total clearing time. This represents the current limiting ability of a fuse.

Fuses that are current-limiting open severe short-circuits within the first half-cycle (180 electrical degrees or 0.00833 seconds) after the fault occurs. Current-limiting fuses also reduce the peak current of the available fault current to a value less than would occur without the fuse. This reduction is shown in *Figure 6*.

A fuse's current-limiting effects are shown graphically on Peak Let-through charts such as the one shown in *Figure 7*. The values across the chart's bottom represent the available

## FUSE CHARACTERISTIC CURVES AND CHARTS



Figure 6 – Current limiting effect of fuses

(also referred to as potential or prospective) rms symmetrical fault current. The values on the chart's left side represent the instantaneous available peak current and the peak let-through current for various fuse ratings.

To better explain the function of these charts, let's run through an example. Start by entering the chart on the bottom at 100,000 rms symmetrical amperes and read upwards to the A-B line. From this point, read horizontally to the left and read the instantaneous peak let-thru current of 230,000 amperes. In a circuit with a typical 15% short-circuit power factor, the instantaneous peak of the available current is approximately 2.3 times the rms symmetrical value. This occurs since the A-B line on the chart has a 2.3:1 slope.



Figure 7 – Peak Let-through Charts

The diagonal curves that branch off the A-B line illustrate the current-limiting effects of different fuse ampere ratings for a given fuse series. To continue the example from above, enter the chart in *Figure 7* on the bottom at 100,000 rms symmetrical amperes and read upwards to the intersection of the 200 ampere fuse curve. Now read from this point horizontally to the left and read a peak let-through current of approximately 20,000 amperes.

What this tells us is that the 200 ampere fuse has reduced the peak current during the fault from 230,000 amperes to 20,000 amperes. In other words, this is the current-limiting effect of the 200 ampere fuse. 20,000 amperes is less than one-tenth of the available current. This is important because the magnetic force created by current flow is a function of the peak current squared. If the peak let-through current of a current-limiting fuse is one-tenth of the available peak, the magnetic force is reduced to less than 1/100 of what would occur without the fuse.

# Using the Peak Let-through Charts ("Up-Over-and-Down")

Peak Let-through Charts for Littelfuse POWR-GARD® fuses can be found online at **littelfuse.com/technicalcenter**. These charts are useful in determining whether a given fuse can properly protect a specific piece of equipment.

For example, given an available fault-current of 100,000 rms symmetrical amperes, determine whether 600 amp 250 volt time-delay Class RK1 fuses can sufficiently protect equipment that has a 22,000 amp short-circuit rating. Refer to *Figure 8.* 

Start by locating the 100,000 A available fault-current on the bottom of the chart (Point A) and follow this value upwards to the intersection with the 600 amp fuse curve (Point B). Next, follow this point horizontally to the left to intersect with the A-B line (Point C). Finally, read down to the bottom of the chart (Point D) to read a value of approximately 18,000 amps.

Can the fuse selected properly protect the equipment for this application? Yes, the POWR-PRO® LLNRK 600 ampere RK1 current-limiting fuses have reduced the 100,000 amperes available current to an apparent or equivalent 18,000 amps. When protected by 600 amp LLNRK RK1 fuses, equipment with short-circuit ratings of 22,000 amps may be safely connected to a system having 100,000 available rms symmetrical amperes.

This method, sometimes referred to as the "Up-Over-and-Down" method, may be used to:

- 1. Provide back-up short-circuit protection to large air power circuit breakers.
- 2. Enable non-interrupting equipment such as bus duct to be



## FUSE CHARACTERISTICS CURVES AND CHARTS





installed in systems with available short-circuit currents greater than their short circuit (withstand) ratings.

However, this method may not be used to select fuses for backup protection of molded case or intermediate frame circuit breakers. National Electrical Code® (NEC®) Article 240.86 requires Series Ratings. Refer to the NEC® for more information.

UL Listed fuse-to-circuit breaker series ratings are now available from most national load center and panelboard manufacturers. Listings are shown in their product digests, catalogs, and online. Many local builders have also obtained fuse-to-circuit breaker series ratings. For additional information contact the Littelfuse Technical Support Group at 1-800-TEC-FUSE (1-800-832-3873).

#### **Short-Circuit Current Rating (SCCR)**

Since 2005, the NEC[®] has required Industrial Control Panels to be labeled with their SCCR. These labels allow users and inspectors to compare the SCCR of the equipment to the available fault current in order to avoid potential hazards in facilities.

#### **Selective Coordination**

A "coordinated" or "selective" system is a system whose overcurrent protective devices have been carefully chosen and their time-current characteristics coordinated. Only the overcurrent device immediately on the line side of an overcurrent will open for any overload or short-circuit condition.

To further clarify, refer to the Terms and Definitions section for the definition of Selective Coordination and *Figure 15* for a graphical example.

Since the advent of electrical and electronic equipment, businesses have become entirely dependent on the continuous availability of electric energy. Loss of power halts all production and order processing, yet expenses continue to increase. Even many UPS systems become unintentionally non-selective causing power loss to computers and other critical equipment. Non-selectivity may defeat otherwise well-engineered UPS systems.

In a selective system, none of this occurs. Overloads and faults are disconnected by the overcurrent protective device immediately on the line side of the problem. The amount of equipment removed from service is minimized, the faulted or overloaded circuit is easier to locate, and a minimum amount of time is required to restore full service.

For these and many other reasons, selectivity is the standard by which many systems are judged and designed.

#### **Fuse Selectivity**

To get a better sense of how to ensure that fuses are selectively coordinated within an electrical system, refer to *Figure 4* shown earlier in this Technical Application Guide. This figure shows typical average melting time-current curves for one class of fuses. Note that the curves are roughly parallel to each other and that for a given overcurrent, the smaller fuse ratings respond quicker than the larger ratings. The heat energy required to open a fuse is separated into melting l²t and arcing l²t (see definition of Ampere-Squared-Seconds). The sum of these is the total clearing l²t.

For a system to be considered coordinated, the smaller fuse total clearing l²t must be less than the larger fuse melting l²t. In other words, if the downstream (branch) fuse opens the circuit before the overcurrent affects the upstream (feeder) fuse element, the system will be considered selective. This can be determined by analyzing curves displaying melting and total clearing l²t, or from minimum melting and maximum clearing time-current curves.

But the simplest method of coordinating low voltage power fuses is by using a Fuse Coordination Table such as the one shown in *Table 4*. This table is only applicable for the Littelfuse POWR-PRO® and POWR-GARD® fuse series listed. Tables such as this greatly reduce design time. For example, the coordination table shows that POWR-PRO KLPC Class L fuses coordinate at a two-to-one ratio with other Class L fuses, with POWR-PRO LLNRK / LLSRK / LLSRK_ID series

## SELECTIVE COORDINATION

Applied Answers Delivered

Class RK1 fuses, and POWR-PRO JTD / JTD_ID series Class J fuses.

In the system shown in *Figure 9*, the 3000 amp Class L main fuses are at least twice the ratings of the 1500, 1200, and 1000 amp Class L feeder fuses. Using the 2:1 ratio just referenced above, it is determined that these fuses will coordinate. The Coordination Table also shows that the LLSRK_ID series time-delay RK1 feeder and branch circuit fuses coordinate at a two-to-one ratio with the Class L feeder fuses, so the entire system in *Figure 9* would be considered 100% coordinated.

#### **Circuit Breaker Coordination**

As a result of the numerous types of circuit breakers and circuit breaker trip units available in today's market, developing a coordinated circuit breaker system or coordinating circuit breakers with fuses is beyond the scope of this Technical Application Guide. For further questions, contact the Littlefuse Technical Support Group.

#### **NEC[®] Requirements for Selective** Coordination

#### **Component Short-Circuit Protecting Ability**

As shown in *Figure 10*, the NEC[®] requires equipment protection to be coordinated with overcurrent protective devices and the available fault current in order to prevent extensive damage to the equipment. Essentially, this means that electrical equipment must be capable of withstanding heavy overcurrents without damage or be properly protected by overcurrent protective devices that will limit damage.

When a severe fault occurs in an unprotected circuit, current immediately increases to a very high value. This is the available or prospective fault current. Some fuses respond so quickly to the increasing current that they interrupt current within the first half-cycle - or before the current even reaches its first peak. This is illustrated in *Figure 6* found earlier in the Technical Application Guide. Such fuses are termed "current-limiting fuses."

Current-limiting fuses stop damaging current faster than any other protective device, and greatly reduce or totally prevent component damage from high fault currents. This performance capability helps users meet the NEC[®] Article 110.10 requirements listed in *Figure 10*.

#### **Pre-Engineered Solutions**

Applicable code requirements also continue to expand with each new edition of the National Electrical Code[®]. As of the 2014 edition of the NEC[®], the following requirements need to be met – and can be, utilizing Littelfuse POWR-GARD[®] Pre-Engineered Solutions:

- NEC 517.26 Healthcare Essential Electrical Systems
- NEC 620.82 Elevators
- NEC 700.27 Emergency Systems
- NEC 701.27 Legally Required Standby Systems
- NEC 708.54 Critical Operations Power Systems

LINE-SIDE FUSES			LOAD-SIDE FUSES										
			TIME-DELAY FUSES AMPERE RANGE, UL CLASS AND CATALOG NO.							FAST-ACTING FUSES AMPERE RANGE, UL CLASS AND CATALOG NO.			
AMPERE	ULCLASS	LITTELFUSE CATALOG	601-6000	601-4000	30-600	30-600	30-600	0-30	30-600	30-1200 T	30-600	1-60	
RANGE	UL GLASS	NUMBER	L KLPC LDC	KLLU	RK1 LLNRK LLSRK_ID	J JTD_ID JTD	RK5 FLNR_ID FLSR_ID IDSR	CC CCMR	RK1 KLNR KLSR	JLLN JLLS	JLS	G SLC	
601-6000	L	KLPC	2:1	2:1	2:1	2:1	4:1	2:1	2:1	2:1	2:1	N/A	
601-4000	L	KLLU	2:1	2:1	2:1	2:1	4:1	2:1	2:1	2:1	2:1	N/A	
601-2000	L	LDC	2:1	2:1	2:1	2:1	4:1	2:1	2:1	2:1	2:1	N/A	
30-600	RK1	LLNRK	N/A	N/A	2:1	2:1	8:1	2:1	3:1	3:1	3:1	4:1	
30-600	RK1	LLSRK_ID	N/A	N/A	2:1	2:1	8:1	2:1	3:1	3:1	3:1	4:1	
30-600	J	JTD_ID	N/A	N/A	2:1	2:1	8:1	2:1	3:1	3:1	3:1	4:1	
30-600	RK5	IDSR	N/A	N/A	1.5:1	1.5:1	2:1	2:1	1.5:1	1.5:1	1.5:1	1.5:1	
30-600	RK5	FLNR_ID	N/A	N/A	1.5:1	1.5:1	2:1	2:1	1.5:1	1.5:1	1.5:1	1.5:1	
30-600	RK5	FLSR_ID	N/A	N/A	1.5:1	1.5:1	2:1	2:1	1.5:1	1.5:1	1.5:1	1.5:1	
30-600	RK1	KLNR	N/A	N/A	3:1	3:1	8:1	N/A	3:1	3:1	3:1	4:1	
30-600	RK1	KLSR	N/A	N/A	3:1	3:1	8:1	N/A	3:1	3:1	3:1	4:1	
30-1200	T	JLLN	N/A	N/A	3:1	3:1	8:1	N/A	3:1	3:1	3:1	4:1	
30-1200	Т	JLLS	N/A	N/A	3:1	3:1	8:1	N/A	3:1	3:1	3:1	4:1	
30-600	J	JLS	N/A	N/A	3:1	3:1	8:1	N/A	3:1	3:1	3:1	4:1	
1-60	G	SLC	N/A	N/A	3:1	3:1	4:1	N/A	2:1	2:1	2:1	2:1	

Table 4 – Fuse Coordination Table. Selecting the Correct Fuse Ampere Ratio to Maintain Selectively Coordinated Systems. (Ratios are expressed as Line-Side Fuse to Load-Side Fuse.)

echnical





The Littelfuse product line of Pre-Engineered Solutions includes:

- LPS Series POWR-Switch (single elevator shunt-trip disconnect switch)
- LCP Selective Coordination Panel

These products continue to gain in popularity because they meet NEC[®] requirements and offer simple, economical solutions for a variety of applications.

Visit **littelfuse.com/lcp** for more information on Littelfuse Pre-Engineered Solution products and corresponding selective coordination requirements.



Figure 9 – Example of Selectively Coordinated Fused System

#### NATIONAL ELECTRICAL CODE® ARTICLE 110 – Requirements for Electrical Installations

#### I. General

#### 110.3. Examination, Identification, Installation, and Use of Equipment.

(A) Examination. In judging equipment, considerations such as the following shall be evaluated:

- (5) Heating effects under normal conditions of use and also under abnormal conditions likely to arise in service.
- (6) Arcing effects.
- (B) Installation and Use. Listed or labeled equipment shall be used or installed in accordance with any instructions included in the listing or labeling.

**110.9 Interrupting Rating.** Equipment intended to interrupt current at fault levels shall have an interrupting rating at nominal circuit voltage sufficient for the current that is available at the line terminals of the equipment.

Equipment intended to interrupt current at other than fault levels shall have an interrupting rating at nominal circuit voltage sufficient for the current that must be interrupted.

**110.10 Circuit Impedance, Short-Circuit Current Ratings, and Other Characteristics.** The overcurrent protective devices, the total impedance, the equipment short-circuit current ratings, and other characteristics of the circuit to be protected shall be selected and coordinated to permit the circuit protective devices used to clear a fault to do so without extensive damage to the electrical equipment of the circuit. This fault shall be assumed to be either between two or more of the circuit conductors or between any circuit conductor and the equipment grounding conductor(s) permitted in 250.118. Listed equipment applied in accordance with their listing shall be considered to meet the requirements of this section.

#### **ARTICLE 240 – Overcurrent Protection**

**240.1 Scope.** Parts I through VII of this article provide the general requirements for overcurrent protection and overcurrent protective devices not more than 1000 volts, nominal. Part VIII covers overcurrent protection for those portions of supervised industrial installations operating at voltages of not more than 1000 volts, nominal. Part IX covers overcurrent protection over 1000 volts, nominal.

Informational Note: Overcurrent protection for conductors and equipment is provided to open the circuit if the current reaches a value that will cause an excessive or dangerous temperature in conductors or conductor insulation. See also Articles 110.9 for requirements for interrupting ratings and 110.10 for requirements for protection against fault currents.

(Reproduced by permission of NFPA)

Figure 10 - National Electrical Code Requires Effective Overcurrent Protection

11

## **UL/CSA FUSE CLASSES AND APPLICATIONS**

#### Overcurrent and short-circuit protection of power and lighting feeders and branch circuits

#### Current Limiting

Fuses which meet the requirements for current limiting fuses are required to be labeled "Current Limiting". Fuse labels must include: UL/CSA fuse class, manufacturer's name or trademark, current rating, AC and/or DC voltage rating, and AC and/or DC interrupting rating. "Time Delay," "D," "TD" or equivalent may also be included on the label when the fuse complies with the time delay requirements of its class.

STANDARDS:

**VOLTAGE RATING:** CURRENT RATINGS:

STANDARDS: UL Standard 248-14, CSA Standard C22.2, No. 106, classified as HRCI-L 600 volts, AC and/or DC 601-6000 amps KLPC also available 200-600A; LDC also available 150-600A   INTERRUPTING RATING: AC: 200,000 amps rms symmetrical
VOLTAGE RATING:     600 volts, AC and/or DC       CURRENT RATINGS:     601-6000 amps       KLPC also available 200-600A; LDC also available 150-600A       INTERRUPTING RATING:     AC: 200,000 amps rms symmetrical
CURRENT RATINGS: 601-6000 amps KLPC also available 200-600A; LDC also available 150-600A INTERRUPTING RATING: AC: 200,000 amps rms symmetrical
KLPC also available 200-600A; LDC also available 150-600A INTERRUPTING RATING: AC: 200,000 amps rms symmetrical
INTERRUPTING RATING: AC: 200,000 amps rms symmetrical
DC: 50,000, 100,000, or 200,000 amps
Not interchangeable with any other UL fuse class.
Time delay: Class L fuses may be marked "Time-Delay" although UL does not
investigate time-delay characteristics of Class L fuses.
KLPC & KLLU: 10 seconds at 500% current rating
LDC: 4 seconds at 500% current rating
LF SERIES: KLPC, KLLU, LDC

**PAGE:** 8

STANDARDS:	UL Star
	CSA Sta
VOLTAGE RATINGS:	250 and
CURRENT RATINGS:	0-600 a
INTERRUPTING RATING:	200,000
TWO CLASSES:	RK1 and

#### CLASS R

dard 248-1 andard C22.2, No. 106, classified as HRCI-R d 600 volts, AC; 125 and 300 volts DC mps 0 amps rms symmetrical **RK1** and **RK5** 

Time delay is optional for Class R fuses Time Delay fuses are required to hold 500% current rating for a minimum of ten seconds. Same dimensions as UL Class H fuses, terminals modified to provide rejection feature. Fits UL Class R fuse holders which reject non Class R fuses. Physically interchangeable with UL Class H, NEMA Class H, and UL Classes K1 & K5 when equipment has Class H fuse holders

CLASS RK1 High degree of current limitation. Provides IEC Type 2 (no damage) protection for motor starters and control components. Time Delay optional, LLSRK_ID Series provides visual indication of blown fuse.	CLASS RK5 Moderate degree of current limita- tion, adequate for most applica- tions. Time delay optional. FLNR_ID, FLSR_ID and IDSR series provides visual indication of blown fuse.
LF SERIES: Time Delay: LLNRK, LLSRK, LLSRK_ID Fast Acting: KLNR, KLSR	LF SERIES: FLNR, FLNR_ID, FLSR, FLSR_ID, and IDSR PAGE: 16
<b>PAGE</b> : 13	
CLAS STANDARDS: UL Standard 246 CSA Standard C: CSA Standard C: 600 volts, AC CURRENT RATINGS: 0-600 amps INTERRUPTING RATING: 200,000 amps rr Not interchangeable with any other UL fuse Time delay optional: Minimum of 10 second	-8, 22.2, No. 106, classified as HRCI-J ns symmetrical class.
LF SERIES: Time Delay: JTD_ID, JTD Fast Acting: JLS	

**PAGE:** 21

UL Class CD: 35-60 amps INTERRUPTING RATINGS: 200,000 amps rms symmetrical Time delay optional: Minimum of 12 seconds at 200% current rating LF SERIES: Time Delay: CCMR (motors), KLDR (transformers) Fast Acting: KLKR **PAGE: 27 CLASS T** STANDARDS: UL Standard 248-15 CSA Standard C22.2, No. 106, classified as HRCI-T VOLTAGE RATINGS: 300 and 600 volts AC, 125 and 300 volts DC CUBBENT BATINGS: 0-1200 amps 900 to 1200 amps UL Recognized for 600V version INTERRUPTING RATING: 200,000 amps rms symmetrical Fast-Acting fuses. High degree of current limitation Very small fuses; space-saving and non-interchangeable with any other UL fuse class. LF SERIES: JLLN, JLLS **PAGE**: 24 **CLASS G** STANDARDS: UL Standard 248-5 CSA Standard C22.2, No. 106, classified as HBCI Misc. VOLTAGE RATING: 480 volts, AC CURRENT RATINGS: 0-60 amps INTERRUPTING RATING: 100,000 amps rms symmetrical Not interchangeable with any other UL fuse class Time delay optional: Minimum of 12 seconds at 200% current rating. LF SERIES: SLC **PAGE:** 26 CLASS K STANDARDS: UL Standard 248-9; No CSA Standard 250 and 600 volts, AC VOLTAGE RATINGS: CURRENT RATING: 0-600 amps INTERRUPTING RATINGS: Three permitted: 50,000, 100,000, and 200,000 amps rms symmetrical Time delay is optional for Class K fuses. Time Delay fuses are required to hold 500% current rating for a minimum of ten seconds. Same Dimensions and Physically interchangeable with UL Class H fuse holders Class K fuses are not permitted to be labeled Current Limiting because there is no rejec-tion feature as required by NEC® Article 240-60(B).

CLASS CC/CD

CSA Standard C22.2, No. 106, classified as HRCI Misc.

UL Standard 248-

UL Class CC: 0-30 amps

600 volts, AC

Same prescr limitation as	ELASS K1 ibed degree of current RK1 fuses when 000 or 100,000 amps rical.			
LF SERIES: Time Delay: LLNRK, LLSRK Fast Acting: KLNR, KLSR				
<b>PAGE:</b> 13				

#### **CLASS K5**

Same prescribed degree of current limitation as RK5 fuses when tested at 50,000 or 100,000 amps rms symmetrical.

LF SERIES: NLN, NLS PAGE: 20

11



## **UL/CSA FUSE CLASSES AND APPLICATIONS**

#### Overcurrent and short-circuit protection of power and lighting feeders and branch circuits

FUSES FOR SUPPLEMENTARY OVERCURRENT PROTECTION     STANDARDS:   UL Standard 248-14; CSA Standard C22.2, No. 59-1. Three Classifications covered:     NOTE:   Fuses may be rated for AC and/or DC when suitable for such use.     (1) MICRO FUSES   Voltage ratings:   UL, 125 volts; CSA, 0-250 volts     Current ratings:   UL, 0-10 amps; CSA, 0-60 amps     Interrupting rating:   50 amps symmetrical     (2) MINIATURE FUSES   (CSA classifies these as Supplemental Fuses)     Voltage ratings:   UL, 125 or 250 volts; CSA, 0-600 volts	SPECIAL PURPOSE FUSES     There are no UL Standards covering this category of fuses. These fuses have special characteristics designed to protect special types of electrical or electronic equipment such as diodes, SCR, transistors, thyristors, capacitors, integrally fused circuit breakers, parallel cable runs, etc.     Fuses may be UL Recognized for use as a component in UL Listed equipment. UL Recognized fuses are tested for characteristics such as published interrupting capacity. They are also covered by UL re-examination service.     Non-renewable   VOLTAGE RATINGS:   up to 1000 volts AC and/or DC     AMPERE RATINGS:   up to 6000 amperes
Current ratings: UL, 0-30 amps; CSA, 0-60 amps Interrupting rating: 10,000 amps rms symmetrical (3) <b>MISCELLANEOUS CARTRIDGE FUSES</b> (CSA classifies these as Supplemental Fuses)	AMPERE RATINGS: up to 6000 amperes INTERRUPTING RATINGS: up to 200,000 amperes Many of these fuses are extremely current limiting. When considering application of these fuses, or if you have special requirements, contact Littelfuse Technical Support Group for assistance.
Voltage ratings: UL, 125-1000 volts; CSA, 0-100 volts Current ratings: UL, 0-30 amps; CSA 0-60 amps Interrupting ratings: 10,000, 50,000, or 100,000 amps rms symmetrical Time delay (Optional); Minimum delay at 200% fuse rating:	LF SERIES: KLC, LA15QS, LA30QS, LA50QS, LA60QS, LA60X, LA70QS, LA100P, LA120X, LA070URD, LA130URD, L15S, L25S, L50S, L60S, L70S, JLLS 900 amp through 1200 amp
5 seconds for fuses rated 3 amps or less 12 seconds for fuses rated more than 3 amps	<b>PAGES:</b> 56
LF SERIES: BLF, BLN, BLS, FLA, FLM, FLQ, FLU, KLK, KLQ KLKD, SPF NOTE: Littelfuse electronic fuses are also covered by these standards; see electronic section of this catalog, or littelfuse.com for complete listing.	
PAGE: 30	

#### **Non-Current Limiting**

#### STANDARDS:

VOLTAGE RATINGS: AMPERE BATINGS: INTERRUPTING RATINGS:

**CLASS H** UL Standard 248-6 CSA Standard C22.2, No. 59.1 Also known as NEMA Class H, and sometimes referred to as "NEC" or "Code" fuses 250 and 600 volts, AC 0-600 amps

10,000 amps rms symmetrical Two types: one-time and renewable

Physically interchangeable with UL Classes K1 & K5; Fits UL Class H fuse holders which will also accept K1, K5, RK5, and RK1 fuses. Manufacturers are upgrading Class H One-time fuses to Class K5 per UL Standard 248-9D, See Class K fuses.

#### **ONE-TIME FUSES** (NON-RENEWABLE)

Time delay: Optional Time-delay fuses must hold 500% current rating for a minimum of ten seconds.

LF SERIES: NLKP

**PAGE:** 20

#### **RENEWABLE FUSES**

Only Class H fuses may be renewable. While time delay is optional, no renewable fuses meet requirements for time delay. Some renewable fuses have a moderate amount of time delay, referred to as "time lag" to differentiate from true time delay.

LF SERIES: Discontinued - Please cross to RK5 or RK1 class fuses

P	LUG FUSES
STANDARDS:	UL Standard 248-11,
	CSA Standard C22.2, No. 59.1
VOLTAGE RATINGS:	125 volts AC only
AMPERE RATINGS:	0-30 amps
INTERRUPTING RATINGS:	10,000 amps rms symmetrical. Interrupting rating need not be marked on fuse.
Two types: Edison-base and Type S	
able. NEC [®] permits Edison-base existing fuses, and only when th <b>TYPE S</b> : Not interchangeable w S fuse adapter is installed in Edi adapters have three ampere rati Time delay: Fuses may be time dele for 12 seconds minimum. NOTE: Plug fuses may be used wh	s standard light bulb. All amp ratings interchange plug fuses to be used only as replacements for nere is no evidence of tampering or overfusing. th Edison-base fuses unless non-removable Type son-base fuse socket. To prevent overfusing, ngs: 10-15, 16-20, and 21-30 amps. ay, if so, they are required to hold 200% of rating ere there is not more than 125 volts between from any conductor to ground. This permits their gle-phase circuits.
LF SERIES: Edison-base: TOO, TLG Type S: SOO, SLO Type S Adapters: SAC	
PAGE: 63	



#### Additional Resources and POWR-GARD[®] Products

Littelfuse is continually developing new technical resources and products that meeting evolving industry standards. For the latest information, visit:

littelfuse.com

**Adjustable Alarm Level** – A setting on a protection relay at which an LED or an output contact operates to activate a visual or audible alarm.

**Adjustable Time Delay** – A setting on a protection relay that determines the time between the fault detection and relay operation.

AIC or A.I.C. - See Interrupting Capacity.

AIR or A.I.R. - See Interrupting Rating.

**Alarm Relay Contact** – The output of the relay that acts as a switch and is connected to a visual or audible alarm.

**Ambient Temperature** – The air temperature surrounding a device. For fuses or circuit breakers in an enclosure, the air temperature within the enclosure.

**Ampacity** – The current in amperes that a conductor can carry continuously under the conditions of use without exceeding its temperature rating. It is sometimes informally applied to switches or other devices which are more properly referred to by their ampere rating.

**Ampere Rating** – The current rating, in amperes, that is marked on fuses, circuit breakers, or other equipment.

**Ampere-Squared-Seconds (I²t)** – A means of describing the thermal energy generated by current flow. When a fuse is interrupting a current within its current-limiting range, the term is usually expressed as melting, arcing, or total clearing I²t.

- Melting I²t is the heat energy passed by a fuse after an overcurrent occurs and until the fuse link melts. It equals the rms current squared multiplied by the melting time in seconds. For times less than 0.004 seconds, melting I²t approaches a constant value for a given fuse.
- Arcing l²t is the heat energy passed by a fuse during its arcing time. It is equal to the rms arcing current squared (see definition below), multiplied by arcing time.
- Clearing l²t (also Total Clearing l²t) is the ampere-squared seconds (l²t) through an overcurrent device from the inception of the overcurrent until the current is completely interrupted. Clearing l²t is the sum of the Melting l²t plus the Arcing l²t.

**Analog Output** – A 0–1 mA, 4–20 mA or 0–5 Vdc signal from a protection relay used to pass information to a device or controller.

**Arc-Blast** – A pressure wave created by the heating, melting, vaporization, and expansion of conducting material and surrounding gases or air.

**Arc-Flash** – The sudden release of heat energy and intense light at the point of an arc. Can be considered a short-circuit through the air, usually created by accidental contact between live conductors.

**Arc Gap** – The distance between energized conductors or between energized conductors and ground. Shorter arc gaps result in less energy being expended in the arc, while longer gaps reduce arc current. For 600 volts and below, arc gaps of 1.25 inches (32 mm) typically produce the maximum incident energy.

**Arc Rating** – A rating assigned to material(s) that relates to the maximum incident energy the material can resist before break open of the material or onset of a second-degree burn. The arc rating is typically shown in cal/cm².

**Arcing Current** (See *Figure 11*) – The current that flows through the fuse after the fuse link has melted and until the circuit is interrupted.



Figure 11 – Arcing and melting currents plus arcing, melting and clearing times

Arcing I²t - See Ampere-Squared-Seconds (I²t).

**Arcing Fault** – A short-circuit that arcs at the point of fault. The arc impedance (resistance) tends to reduce the short-circuit current. Arcing faults may turn into bolted faults by welding of the faulted components. Arcing faults may be phase-to-phase or phase-to-ground.

**Arcing Time** (See *Figure 11*) – The time between the melting of a fuse link or parting of circuit breaker contacts, until the overcurrent is interrupted.

**Arc Voltage** (See *Figure 12*) – Arc voltage is a transient voltage that occurs across an overcurrent protection device during the arcing time. It is usually expressed as peak instantaneous voltage ( $V_{\text{peak}}$  or  $E_{\text{peak}}$ ), or on rare occasion as rms voltage.

Asymmetrical Current – See Symmetrical Current.

Available Short-Circuit Current (also Available or

**Prospective Fault Current)** – The maximum rms Symmetrical Current that would flow at a given point in a system under bolted-fault conditions. Short-circuit current is maximum during the first half-cycle after the fault occurs. See definitions of Bolted Fault and Symmetrical Current.





Figure 12 – Transient overvoltage during arcing time

Blade Fuse – See Knife Blade Fuse.

**Body** – The part of a fuse enclosing the fuse elements and supporting the contacts. Body is also referred to as cartridge, tube, or case.

**Bolted Fault** – A short-circuit that has no electrical resistance at the point of the fault. It results from a firm mechanical connection between two conductors, or a conductor and ground. Bolted faults are characterized by a lack of arcing. Examples of bolted faults are a heavy wrench lying across two bare bus bars, or a crossed-phase condition due to incorrect wiring

**Boundaries of Approach** – Protection boundaries established to protect personnel from shock and Arc-Flash hazards.

**Calorie** – The amount of heat needed to raise the temperature of one gram of water by one degree Celsius.1 cal/cm² is equivalent to the exposure on the tip of a finger by a cigarette lighter for one second.

**Cartridge Fuse** – A fuse that contains a current-responsive element inside a tubular fuse body with cylindrical ferrules (end caps).

**Case Size (also Cartridge Size)** – The maximum allowable ampere rating of a cartridge fuse having defined dimensions and shape. For example, case sizes for UL Listed Class H, K, J, RK1, and RK5 are 30, 60, 100, 200, 400, and 600 amperes. The physical dimensions vary with fuse class, voltage, and ampere rating. UL Standards establish the dimensions for each UL Fuse Class. This catalog's product section contains case size dimensions for all Littelfuse POWR-GARD® fuses.

Clearing I²t – See Ampere-Square-Seconds (I²t).

**Clearing Time** (see *Figure 11*) – The time between the initiation of an overcurrent condition to the point at which the overcurrent is interrupted. Clearing Time is the sum of Melting Time and Arcing Time.

**Conformal Coating** – Coating used to protect circuit boards from pollutants, corrosion, and mildew.

**Contacts (Fuse)** – The external metal parts of the fuse used to complete the circuit. These consist of ferrules, caps, blades or terminals, as shown in this catalog.

**Coordination or Coordinated System** – See Selective Coordination.

**Continuous Load** – An electrical load where the maximum current is expected to continue for three hours or more.

**CT Loop** – The electrical circuit between a current transformer and a protection relay or monitoring device.

**Current-Based Protection** – Protection parameters (trip-levels/ data collection etc.) derived from current levels in a circuit.

**Current-limiting Fuse** (See *Figure 13*) – A fuse which, when interrupting currents within its current-limiting range, reduces the current in the faulted circuit to a magnitude substantially less than that obtainable in the same circuit if the device was replaced with a solid conductor having comparable impedance. To be labeled "current limiting," a fuse must mate with a fuse block or fuse holder that has either a rejection feature or dimensions that will reject non-current-limiting fuses.



Figure 13 – Current-limiting Fuse

**Current-limiting Range** - For an individual overcurrent protective device, the current-limiting range begins at the lowest value of rms symmetrical current at which the device becomes current-limiting (the threshold current) and extends to the maximum interrupting capacity of the device. See definitions of Threshold Current and Interrupting Capacity.

Current Rating - See Ampere Rating.

**Current Transformer (CT)** – A transformer that produces a current in its secondary circuit in a known proportion to current in its primary circuit.

**Data Logging** – Collecting and storing information in a format that can be reviewed for trending, troubleshooting and reporting.

#### DFT (Discrete Fourier Transform) Harmonic Filter – An

algorithm used to measure the fundamental component of current and voltage and reject harmonics. This allows lower trip settings and eliminates nuisance trips due to harmonics.

Applied Answers Delivered

**Distance to Arc** – Refers to the distance from the receiving surface to the arc center. The value used for most calculations is typically 18 inches.

**Dual-Element Fuse** – A fuse with internal construction consisting of a separate time-delay overload element(s) that interrupts overcurrents up to approximately 500%-600% of its nominal rating, plus separate fuse links that quickly open higher value currents. All dual-element fuses have time delay, but, since there are other methods of achieving time delay, not all time-delay fuses have dual-element construction. See Time-Delay Fuse.

**EFCT (Earth Fault Current Transformer)** – A current transformer engineered to accurately detect low level ground-fault current.

**Electrical Hazard Analysis** – A study performed to identify the potential electrical hazards to which personnel may be exposed. The analysis should address both shock and Arc-Flash hazards.

**Electrically Safe Work Condition** – Condition where the equipment and or circuit components have been disconnected from electrical energy sources, locked/tagged out, and tested to verify all sources of power are removed.

**Element** – A fuse's internal current-carrying components that melt and interrupt the current when subjected to an overcurrent of sufficient duration or value. Also called fuse link.

#### Fail-Safe Mode (also known as Under Voltage or UV) -

Output relay is energized during normal (not tripped) operation. If the protection relay loses supply voltage, the system will trip or alarm.

**Fast-Acting Fuse** – May also be termed Normal-opening fuse, this is a fuse that has no intentional or built-in time delay. Actual opening time is determined by the fuse class, the overcurrent, and other conditions. Fast-acting is indicated on the fuse label by "Fast-Acting," "F-A," "F," or other suitable marking.

Fault - Same as Short-Circuit and used interchangeably.

**Fault Current** – The current that flows when a phase conductor is faulted to another phase or ground.

**Feeder Protection** – Overcurrent or overvoltage devices installed on a feeder circuit to supplement, compliment or replace downstream protective devices.

**Filler** – A material, such as granular quartz, used to fill a section or sections of a fuse and aid in arc quenching.

**Filter** – An algorithm used to measure the fundamental component of current and voltage and reject harmonics. This allows lower trip settings and eliminates nuisance trips due to harmonics.

**Flash Hazard Analysis** – A study that analyzes potential exposure to Arc-Flash hazards. The outcome of the study establishes Incident Energy levels, Hazard Risk Categories,

Flash Protection Boundaries, and required PPE. It also helps define safe work practices.

**Flash Protection Boundary** – A protection boundary established to protect personnel from Arc-Flash hazards. The Flash Protection Boundary is the distance at which an unprotected worker can receive a second-degree burn to bare skin.

**Fuse** – An overcurrent protective device consisting of one or more current carrying elements enclosed in a body fitted with contacts, so that the fuse may be readily inserted into or removed from an electrical circuit. The elements are heated by the current passing through them, thus interrupting current flow by melting during specified overcurrent conditions.

**Ground Continuity Monitor** - A protection relay that continuously monitors a ground conductor and trips if this conductor opens or shorts to the ground-check conductor.

**Ground-Fault** – Unintentional contact between a phase conductor and ground or equipment frame. The words "ground" and "earth" are used interchangeably when it comes to electrical applications.

**Ground-Fault Current** – The current that returns to the supply neutral through the ground-fault and the ground-return path.

**Ground-Fault Protection** – A system that protects equipment from damaging ground-fault current by operating a disconnecting means to open all ungrounded conductors of a faulted circuit. This protection is at current levels less than those required to operate a supply circuit overcurrent device.

**Ground-Fault Relay** – A protection relay designed to detect a phase-to-ground-fault on a system and trip when current exceeds the pickup setting for greater than the trip time setting.

**Hazard Risk Category** – A classification of risks (from 0 to 4) defined by NFPA 70E[®]. Each category requires PPE and is related to incident energy levels.

**High-Resistance Grounding** – Achieved when a neutralground resistor (NGR) is used to limit the current to a low level. Typically high-resistance grounding is 25 A and lower. See Low-Resistance Grounding.

I²t – See Ampere-Squared-Seconds (I²t).

**IEEE Device Numbers** – The devices in switching equipment are referred to by numbers, according to the functions they perform. These numbers are based on a system which has been adopted as standard for automatic switchgear by IEEE. This system is used on connection diagrams, in instruction books and in specifications.

**IEC Type 2 Protection** – Fused protection for control components that prevents damage to these components under short-circuit conditions. See definition of No Damage.



**Incident Energy** – The amount of thermal energy impressed on a surface generated during an electrical arc at a certain distance from the arc. Typically measured in cal/cm².

**Instantaneous Peak Current (IP or Ipeak)** – The maximum instantaneous current value developed during the first half-cycle (180 electrical degrees) after fault inception. The peak current determines magnetic stress within the circuit. See Symmetrical Current.

**Insulation Monitoring** – Monitoring the resistance from phase to ground to detect insulation breakdown on a system.

**Interrupting Capacity (AIC)** – The highest available symmetrical rms alternating current (for DC fuses the highest direct current) at which the protective device has been tested, and which it has interrupted safely under standardized test conditions. The device must interrupt all available overcurrents up to its interrupting capacity. Also commonly called interrupting rating. See Interrupting Rating below.

**Interrupting Rating (IR, I.R., AIR or A.I.R.)** – The highest RMS symmetrical current, at specified test conditions, which the device is rated to interrupt. The difference between interrupting capacity and interrupting rating is in the test circuits used to establish the ratings.

**Inverse-time Characteristics** – A term describing protective devices whose opening time decreases with increasing current.

IR or I.R. (also AIR or A.I.R.) – See Interrupting Rating above.

Kiloamperes (kA) - 1,000 amperes.

**Knife Blade Fuse** – Cylindrical or square body fuses with flat blade terminals extending from the fuse body. Knife blades may be designed for insertion into mating fuse clips and/or to be bolted in place. Knife blade terminals may include a rejection feature that mates with a similar feature on a fuse block of the same class.

**Leakage Current** – Very low level ground-fault current, typically measured in milliamperes (mA, thousandths of amperes).

**Limited Approach Boundary** – An approach boundary to protect personnel from shock. A boundary distance is established from an energized part based on system voltage. To enter this boundary, unqualified persons must be accompanied with a qualified person and use the proper PPE.

**Low-Resistance Grounding** – A Resistance Grounded System that allows high currents to flow during a ground-fault. Typically 100A and higher is considered Low-Resistance grounding. See High-Resistance Grounding.

**Melting Current** (see *Figure 11*) – The current that flows through the fuse from the initiation of an overcurrent condition to the instant arcing begins inside the fuse.

Melting I²t – See Ampere-Squared-Seconds (I²t).

**Melting Time** (see *Figure 11*) – The time span from the initiation of an overcurrent condition to the instant arcing begins inside the fuse.

**Motor Protection** – Overload protection designed to protect the windings of a motor from high current levels. Modern motor protection relays add many additional features, including metering, data logging and communications.

**NEC** – In general, the National Electrical Code[®] (NEC[®]). Specifically, as referenced herein, NEC refers to NFPA Standard 70, *National Electrical Code*, National Fire Protection Association, Quincy, MA 02269.

Sections of the NEC reprinted herein, and/or quotations there from, are done so with permission. The quoted and reprinted sections are not the official position of the National Fire Protection Association which is represented only by the Standard in its entirety. Readers are cautioned that not all authorities have adopted the most recent edition of the NEC; many are still using earlier editions.

**Neutral Grounding Resistor (NGR)** – A current-limiting resistor connecting the power-system neutral to ground.

**No Damage** – A term describing the requirement that a system component be in essentially the same condition after the occurrence of a short-circuit as prior to the short-circuit.

**Non-renewable Fuse** – A fuse that must be replaced after it has opened due to an overcurrent. It cannot be restored to service.

Normal-opening Fuse - See Fast-Acting Fuse.

**Nuisance Trip** – An undesired change in relay output due to misinterpreted readings.

**One-time Fuse** – Technically, any non-renewable fuse. However, the term usually refers to UL Class H fuses and to fast acting UL Class K5 fuses. Such fuses are not current-limiting and do not have a rejection feature. One-time fuses are also referred to as "Code" fuses.

**Open CT Hazard** – An open-circuited CT secondary can develop a dangerously high voltage when the primary is energized.

**Overcurrent** – Any current larger than the equipment, conductor, or devices are rated to carry under specified conditions.

**Overload** – An overcurrent that is confined to the normal current path (e.g., not a short-circuit), which if allowed to persist, will cause damage to equipment and/or wiring. Additional information regarding fuse applications for overload protection can be found earlier in this Technical Application Guide.

**Technica** 

**Peak Let-through Current** (See *Figure 14*) – The maximum instantaneous current that passes through an overcurrent protective device during its total clearing time when the available current is within its current-limiting range.



Figure 14 – Peak Let-through Current

Phase Current – The current present in a phase conductor.

**Phase Voltage** – The voltage measured between a phase conductor and ground.

Power Factor (X/R) – As used in overcurrent protection, power factor is the relationship between the inductive reactance (X) and the resistance (R) in the system during a fault. Under normal conditions a system may be operating at a 0.85 power factor (85%). When a fault occurs, much of the system resistance is shorted out and the power factor may drop to 25% or less. This may cause the current to become asymmetrical. See definition of Symmetrical Current. The UL test circuits used to test fuses with interrupting ratings exceeding 10,000 amperes are required to have a power factor of 20% or less. Since the power factor of test circuits tends to vary during test procedures, actual test circuits are usually set to a 15% power factor. The resulting asymmetrical current has an rms value of 1.33 times the available symmetrical rms. The instantaneous peak current of the first peak after the fault is 2.309 times the available symmetrical rms.

**PPE** – An acronym for Personal Protective Equipment. It can include clothing, tools, and equipment.

**Primary Rating (for CTs)** – The current rating of the primary side of a current transformer. The first number in the ratio 500:5 is the primary rating. Under ideal conditions 500 A of primary current flow through the CT will produce 5 A of current out the secondary terminals.

**Prohibited Approach Boundary** – An approach boundary to protect personnel from shock. Work in this boundary is considered the same as making direct contact with an energized part. Only qualified persons are allowed to enter this boundary and they must use the proper PPE.

**Protection Boundaries** – Boundaries established to protect personnel from electrical hazards.

**Pulsing** – Modulating the ground-fault current on a resistance grounded system using a contactor to short out part of the NGR elements (or to open one of two NGRs connected in parallel). Another version of pulsing is imposing a higher frequency signal on power lines and using a wand detector to locate the point of fault on a conductor.

**QPL (Qualified Products List)** – A list of approved fuses and holders that meet various Military specifications.

**Qualified Person** – A person who is trained, knowledgeable, and has demonstrated skills on the construction and operation of the equipment, and can recognize and avoid electrical hazards that may be encountered.

**Rating** – A designated limit of operating characteristics based on definite conditions such as current rating, voltage rating and interrupting rating.

Rectifier Fuse – See Semiconductor Fuse.

**Rejection Feature** – The physical characteristic(s) of a fuse block or fuse holder that prevents the insertion of a fuse unless it has the proper mating characteristics. This may be achieved through the use of slots, grooves, projections, or the actual physical dimensions of the fuse. This feature prevents the substitution of fuses of a Class or size other than the Class and size intended.

**Relay** – An electrical switch that opens and closes a contact (or contacts) under the control of another circuit. Typically an electromagnet.

**Renewable Element (also Renewable Link)** – A renewable fuse current-carrying component that is replaced to restore the fuse to a functional condition after the link opens due to an overcurrent condition.

**Renewable Fuse** – A fuse that may be readily restored to service by replacing the renewable element after operation.

**Resistance-Grounded System** – An electrical system in which the transformer or generator neutral is connected to ground through a current-limiting resistor. See Solidly Grounded System, Ungrounded System.

**Restricted Approach Boundary** – An approach boundary to protect personnel from shock. A boundary distance is established from an energized part based on system voltage. Only qualified persons are allowed in the boundary and they must use the proper PPE.

**Selective Coordination** (See *Figure 15*) – In a selectively coordinated system, only the protective device immediately on the line side of an overcurrent opens. Upstream protective devices remain closed. All other equipment remains in service, which simplifies the identification and location of overloaded

echnical

Prospective Current – See Available Short-Circuit Current.



equipment or short-circuits. For additional information, refer to the Selective Coordination pages of this Technical Application Guide.



Figure 15 – Selective Coordination Example

**Semiconductor Fuse** – (Also known as High-Speed Fuses) A fuse specifically designed to protect semiconductors such as silicon rectifiers, silicon-controlled rectifiers, thyristors, transistors, and similar components.

**Sensitive Ground-Fault Protection** – Protection designed to accurately detect extremely low ground-fault current levels without nuisance tripping.

**Shock** – A trauma subjected to the body by electrical current. When personnel come in contact with energized conductors, it can result in current flowing through their body often causing serious injury or death.

**Short-Circuit** (See *Figure 16*) – A current flowing outside its normal path, caused by a breakdown of insulation or by faulty equipment connections. In a short-circuit, current bypasses the normal load. Current is determined by the system impedance (AC resistance) rather than the load impedance. Short-circuit currents may vary from fractions of an ampere to 200,000 amperes or more.

**Short-Circuit Current Rating (SCCR)** – The prospective symmetrical fault current at a nominal voltage to which an apparatus or system is able to be connected without sustaining damage exceeding defined acceptance criteria.

**Short-Circuit Rating** – The maximum RMS symmetrical shortcircuit current at which a given piece of equipment has been tested under specified conditions, and which, at the end of the test is in essentially the same condition as prior to the test. Short-circuit ratings (also called withstand ratings) apply to equipment that will be subjected to fault currents, but which are not required to interrupt them. This includes switches, busway (bus duct), switchgear and switchboard structures, motor control centers and transformers. Most short-circuit ratings are based on tests which last three complete electrical cycles (0.05 seconds). However, if the equipment is protected during the test by fuses or by a circuit breaker with instantaneous trips, the test duration is the time required for the overcurrent protective device to open the circuit.

When protected as such during testing, the equipment instructions and labels must indicate that the equipment shall be protected by a given fuse class and rating or by a specific make, type, and rating of circuit breaker. Circuit breakers equipped with short-delay trip elements instead of instantaneous trip elements have withstand (short-circuit) ratings in addition to their interrupting rating. The breaker must be able to withstand the available fault current during the time that opening is delayed.



Figure 16 – Current Flow in Normal and Short Circuit Situations

**Solidly Grounded System** – An electrical system in which the neutral point of a wye connected supply transformer is connected directly to ground.

**Symmetrical Current** – The terms "Symmetrical Current" and "Asymmetrical Current" describe an AC wave symmetry around the zero axis. The current is symmetrical when the peak currents above and below the zero axis are equal in value, as shown in *Figure 17 (next page)*. If the peak currents are not equal, as shown in *Figure 18*, the current is considered asymmetrical. The degree of asymmetry during a fault is determined by the change in power factor (X/R) and the point in the voltage wave when the fault occurs. See definition of Power Factor. In general, lower short-circuit power factors increase the degree of asymmetry.

Technica



Figure 18 – Asymmetrical Current

**Threshold Current** – The minimum current for a given fuse size and type at which the fuse becomes current-limiting. It is the lowest value of available rms symmetrical current that will cause the device to begin opening within the first 1/4 cycle (90 electrical degrees) and completely clear the circuit within 1/2 cycle (180 electrical degrees). The approximate threshold current can be determined from the fuse's peak let-through charts. (See *Figure 19*.)



Available Fault Current Symmetrical RMS Amperes

Figure 19 – Determining Threshold Current from Peak Let-through Chart **Threshold Ratio** – Consists of the threshold current divided by the ampere rating of a specific type or class of overcurrent device. A fuse with a threshold ratio of 15 becomes currentlimiting at 15 times its current rating.

**Time-Delay Fuse** – Fuses designed with an intentional, built-in delay in opening. When compared to fast-opening fuses, time-delay fuses have an increased opening time for overcurrents between approximately 200% and 600% of the fuse's current rating. Time-delay is indicated on the fuse label by "Time-Delay," "T-D," "D," or other suitable marking. Time-delay in the overload range (200%-600% of the fuse rating) permits the fuse to withstand system switching surges, motor starting currents, and other harmless temporary overcurrents.

UL Standards require time-delay Class H, K, RK1, RK5, and J fuses to hold 500% of their normal current rating for a minimum of 10 seconds. They must also pass the same opening time tests (135% and 200% of current rating) as fast acting fuses.

Time-delay Class CC, CD, G, Plug, and Miscellaneous fuses have different requirements. For more information, please refer to the corresponding descriptions provided in the Product Information Section.

For the UL Standard, Class L fuses have no standard timedelay. The time-delay varies from series to series for a given manufacturer, as well as from manufacturer to manufacturer. For reference, Littelfuse KLPC series POWR-PRO® fuses hold 500% of rated current for a minimum of 10 seconds.

**Ungrounded System** – An electrical system in which no point in the system is intentionally grounded. This was most common in process industries where continuity of service during a singlephase-to-ground-fault was required.

**Unqualified Person** – A person that does not possess all the skills and knowledge or has not been trained for a particular task.

**Voltage Rating** – The maximum rms AC voltage and/or the maximum DC voltage at which the fuse is designed to operate. For example, fuses rated 600 volts and below may be applied at any voltage less than their rating. There is no rule for applying AC fuses in DC circuits such as applying the fuse at half its AC voltage rating. Fuses used on DC circuits must have DC ratings.

Withstand Rating - See Short-Circuit.

BACK-UP MOTOR BUNNING

PROTECTION (USED WITH PROPERLY

SIZED OVERLOAD RELAYS)

MOTOR FULL-LOAD AMPS

## MOTOR PROTECTION TABLES

## Selection of Class RK5 Fuses (FLNR_ID / FLSR_ID / IDSR Series) or POWR-PRO[®] Class RK1 Fuses (LLNRK / LLSRK / LLSRK_ID Series) Based on Motor Full Load Amps

TIME DELAY

III CLASS BK

#### Using AC Motor Protection Tables to Select Fuse Ratings

Time-delay RK1 and RK5 fuse ratings selected in accordance with the following recommendations also meet NEC[®] requirements for Motor Branch circuit and Short-Circuit Protection.

#### Selecting Fuses for Motor Running Protection Based on Motor Horsepower

Motor horsepower and motor Full Load Amperes (FLA) shown are taken from NEC[®] Tables 430.248 through 430.250 covering standard speed AC motors with normal torque characteristics. Fuse ratings for motors with special characteristics may need to vary from given values.

If motor running protection will be provided by the fuses, select fuse ratings for correct type of motor from Motor Protection Table Columns headed, "Without Overload Relays."

If overload relays will provide principal motor running protection, select fuse ratings for correct type of motor from Motor Protection Table Columns headed, "Back-up Running Protection" or "With Overload Relays." Fuse ratings selected from these columns coordinate with most UL Class 10 and 20 overload relays which covers over 90% of motor applications.

#### Selecting Fuses for Motor Running Protection Based on Motor Actual Full Load Currents

Better protection is achieved when fuse ratings are based on motor actual FLA obtained from motor nameplates. Locate motor nameplate FLA in the column appropriate for the type of motor and type of protection required. Then select the corresponding ampere rating of the fuse from the first column of that line.

UL CLASS RK1 OR RK5 FUSE AMPERE RATING	MOTOR SERVICE FACTOR OF 1.15 OR GREATER OR WITH TEMP. RISE NOT OVER 40°C.	MOTOR SERVICE FACTOR LESS THAN 1.15 OR WITH TEMP. RISE GREATER THAN 40°C.	MOTOR SERVICE FACTOR OF 1.15 OR GREATER OR WITH TEMP. RISE NOT OVER 40°C.	MOTOR SERVICE FACTOR LESS THAN 1.15 OR WITH TEMP. RISE GREATER THAN 40°C
1/10	0.08-0.09	0.09-0.10	0-0.08	0-0.09
1/8	0.10-0.11	0.11-0.125	0.09-0.10	0.10-0.11
¹⁵ /100	0.12-0.15	0.14-0.15	0.11-0.12	0.12-0.13
2/10	0.16-0.19	0.18-0.20	0.13-0.16	0.14-0.17
1/4	0.20-0.23	0.22-0.25	0.17-0.20	0.18-0.22
3/10	0.24-0.30	0.27-0.30	0.21-0.24	0.23-0.26
4/10	0.32-0.39	0.35-0.40	0.25-0.32	0.27-0.35
1/2	0.40-0.47	0.44-0.50	0.33-0.40	0.36-0.43
6/10	0.48-0.60	0.53-0.60	0.41-0.48	0.44-0.52
8/10	0.64-0.79	0.70-0.80	0.49-0.64	0.53-0.70
1	0.80-0.89	0.87-0.97	0.65-0.80	0.71-0.87
11/8	0.90-0.99	0.98-1.08	0.81-0.90	0.88-0.98
11/4	1.00-1.11	1.09-1.21	0.91-1.00	0.99-1.09
1 ⁴ /10	1.12-1.19	1.22-1.30	1.01-1.12	1.10-1.22
11/2	1.20-1.27	1.31-1.39	1.13-1.20	1.23-1.30
16/10	1.28-1.43	1.40-1.56	1.21-1.28	1.31-1.39
18/10	1.44-1.59	1.57-1.73	1.29-1.44	1.40-1.57
2	1.60-1.79	1.74-1.95	1.45-1.60	1.58-1.74
21/4	1.80-1.99	1.96-2.17	1.61-1.80	1.75-1.96
21/2	2.00-2.23	2.18-2.43	1.81-2.00	1.97-2.17
28/10	2.24-2.39	2.44-2.60	2.01-2.24	2.18-2.43
3	2.40-2.55	2.61-2.78	2.25-2.40	2.44-2.60
3 ² /10	2.56-2.79	2.79-3.04	2.41-2.56	2.61-2.78
31/2	2.80-3.19	3.05-3.47	2.57-2.80	2.79-3.04
4	3.20-3.59	3.48-3.91	2.81-3.20	3.05-3.48
41/2	3.60-3.99	3.92-4.34	3.21-3.60	3.49-3.91
5	4.00-4.47	4.35-4.86	3.61-4.00	3.92-4.35
56/10	4.48-4.79	4.87-5.21	4.01-4.48	4.36-4.87
6	4.80-4.99	5.22-5.43	4.49-4.80	4.88-5.22
<u>6¼</u> 7	5.00-5.59	5.44-6.08	4.81-5.00 5.01-5.60	5.23-5.43
71/2	5.60-5.99 6.00-6.39	6.09-6.52 6.53-6.95	5.61-6.00	5.44-6.09 6.10-6.52
8	6.40-7.19	6.96-7.82	6.01-6.40	6.53-6.96
9	7.20-7.99	7.83-8.69	6.41-7.20	6.97-7.83
10	8.00-9.59	8.70-10.00	7.21-8.00	7.84-8.70
12	9.60-11.99	10.44-12.00	8.01-9.60	8.71-10.43
15	12.00-13.99	13.05-15.00	9.61-12.00	10.44-13.04
171/2	14.00-15.99	15.22-17.39	12.01-14.00	13.05- 15.21
20	16.00-19.99	17.40-20.00	14.01-16.00	15.22-17.39
25	20.00-23.99	21.74-25.00	16.01-20.00	17.40-21.74
30	24.00-27.99	26.09-30.00	20.01-24.00	21.75-26.09
35	28.00-31.99	30.44-34.78	24.01-28.00	26.10-30.43
40	32.00-35.99	34.79-39.12	28.01-32.00	30.44-37.78
45	36.00-39.99	39.13-43.47	32.01-36.00	37.79-39.13
50	40.00-47.99	43.48-50.00	36.01-40.00	39.14-43.48
60	48.00-55.99	52.17-60.00	40.01-48.00	43.49-52.17
70	56.00-59.99	60.87-65.21	48.01-56.00	52.18-60.87
75	60.00-63.99	65.22-69.56	56.01-60.00	60.88-65.22
80	64.00-71.99	69.57-78.25	60.01-64.00	65.23-69.57
90	72.00-79.99	78.26-86.95	64.01-72.00	69.58-78.26
100	80.00-87.99	86.96-95.64	72.01-80.00	78.27-86.96
110	88.00-99.99	95.65-108.69	80.01-88.00	86.97-95.65
125	100.00-119.99	108.70-125.00	88.01-100.00	95.66-108.70
150	120.00-139.99	131.30-150.00	100.01-120.00	108.71-130.43
175	140.00-159.99	152.17-173.90	120.01-140.00	130.44-152.17
200	160.00-179.99	173.91-195.64	140.01-160.00	152.18-173.91
225	180.00-199.99	195.65-217.38	160.01-180.00	173.92-195.62
250	200.00-239.99	217.39-250.00	180.01-200.00	195.63-217.39
300	240.00-279.99	260.87-300.00	200.01-240.00	217.40-260.87
350	280.00-319.99	304.35-347.82 347.83-391.29	240.01-280.00 280.01-320.00	260.88-304.35
400 450	320.00-359.99 360.00-399.99	347.83-391.29 391.30-434.77	320.01-320.00	304.36-347.83 347.84-391.30
500	400.00-479.99	434.78-500.00	360.01-400.00	391.31-434.78
600	480.00-600.00	521.74-600.00	400.01-480.00	434.79-521.74
000	.00.00 000.00	521.71 000.00	100.01 100.00	101.10 021.14

MOTOR RUNNING PROTECTION

(USED WITHOUT PROPERLY SIZED

**OVERLOAD RELAYS)** 

MOTOR FULL-LOAD AMPS



#### Motor Protection White Paper

Download our white paper on motor protection at littelfuse.com/technicalcenter

## MOTOR PROTECTION TABLES

ttelfuse®

rtise Applied | Answers Delivered

## Selection of Class RK5 Fuses (FLNR_ID / FLSR_ID / IDSR Series) or POWR-PRO[®] Class RK1 Fuses (LLNRK / LLSRK / LLSRK_ID Series) Based on Motor Horsepower

			OVERLOAD	WITH OVERL	0AD RELAYS	
			AYS S.F. = LESS	-	S.F. = LESS	SWITCH OR
MOTOR	FULL LOAD	S.F. = 1.15 OR	THAN 1.15 OR	S.F. = 1.15 OR	THAN 1.15 OR	FUSE CLIP
HP	AMPS	MORE, TEMP	TEMP RISE	MORE, TEMP	TEMP RISE	RATING
		RISE NOT OVER 40°C	MORE THAN	RISE NOT OVER 40°C	MORETHAN	
			40°C		40°C	
14		r	HASE MOTOR			
1/6	4.4	5	5 6¼	5 ^{6/10} 7 ¹ /2	5 ⁶ /10 7	<u>30</u> 30
1/3	7.2	9	8	9	9	30
1/2	9.8	12	10	15	12	30
3/4	13.8	15	15	17½	17½	30
1	16	20	17½	20	20	30
1½	20	25	20	25	25	30
2	24	30	25	30	30	30
1/6	0.0	230 VULI 1-P	HASE MOTOR	28/10	· ·	30
1/4	2.2	31/2	2 /2 3 ² /10	<u>2%10</u> 4	28/10 31/2	30
1/3	3.6	41/2	4	4 4 ¹ /2	4½	30
1/2	4.9	56/10	56/10	61/4	6	30
3/4	6.9	8	7½	9	8	30
1	8	10	9	10	10	30
1½	10	12	10	15	12	30
2	12	15	12	15	15	30
<u>3</u> 5	17 28	20	17½ 30*	25 35	20 35	<u>30</u> 60
7½	40	50	45	50	50	60
10	50	60	50	70	60	60
		200 VOLT 3-P	HASE MOTOR			
1/2	2.5	3	<b>2</b> ⁸ /10	3 ² /10	3	30
3/4	3.7	41/2	4	5	41/2	30
1	4.8	6	5 ⁶ /10	61/4	6	30
1½	6.9	8	7½	7½	8	30
2	7.8	9	8	10 15	<u>9</u> 15	<u>30</u> 30
5	17.5	20	20	25	25	30
7½	25.3	30*	25*	35	30*	60
10	32.2	40	35	45	40	60
15	48.3	60	50	70†	60	60
20	62.1	75	70	80	75	100
25	78.2	90	80	100	90	100
<u>30</u> 40	92 120	110 150	100* 125	125 150	110 150	200
50	120	175	150	200	175	200
60	177	200*	200*	225	225	400
75	221	250	250	300	300	400
100	285	350	300	400	350	400
125	359	400*	400*	450	450	600
150	414	500		600 6 (240)/ CIDC	500	600
1/2	2.2	230 VULI 3-P 28/10	HASE MOTOR	28/10	011) 2 ⁸ /10	30
3/4	3.2	4	31/2	4	4	30
1	4.2	5	41/2	5 ⁶ /10	5	30
1½	6.0	71/2	61⁄4	7½	7½	30
2	6.8	8	7½	9	8	30
3	9.6	12	10	12	12	30
5 71/2	15.2 22	17½	17½ 25	20	17½ 30	30
7½ 10	22	25 35	30*	30 35	30	<u>30</u> 60
15	42	50	45	60	50	60
20	54	60*	60*	70	70	100
25	68	80	75	90	80	100
30	80	100	90	100	100	100
40	104	125	110	150	125	200
50	130 154	150 175	150	175	150 200	200
60 75	192	225	175 200*	200 250	200	200 400
100	248	300	250	350	300	400
125	312	350	350	400	400	400
125						
125 150 200	360 480	450 600	400* 500	450 600	450 600	600 600

		REL	AYS	WITH OVEREDAD RELATS		
MOTOR		0.5 1.15.00	S.F. = LESS	0.5 1.15.00	S.F. = LESS	SWITCH OR
MOTOR	FULL LOAD	S.F. = 1.15 OR	THAN 1.15 OR	S.F. = 1.15 OR	<b>THAN 1.15 OR</b>	FUSE CLIP
HP	AMPS	MORE, TEMP	TEMP RISE	MORE, TEMP	TEMP RISE	RATING
		RISE NOT	MORE THAN	RISE NOT	MORE THAN	
		OVER 40°C	40°C	OVER 40°C	40°C	
		460 VOLT 3-P	HASE MOTOR	S (480V CIRC		
1/2	1.1	14/10	11/4	14/10	14/10	30
3/4	1.6	2	18/10	2	2	30
1	2.1	21/2	21/4	2 ⁸ /10	2 ¹ /2	30
11/2	3.0	31/2	32/10	4	31/2	30
2	3.4	4	31/2	<b>4</b> ¹ /2	4	30
3	4.8	5 ⁶ /10	5	6	56/10	30
5	7.6	9	8	10	9	30
71/2	11	12	12	15	15	30
10	14	17½	15	17½	17½	30
15	21	25	20	30	25	30
20	27	30*	30*	35	35	60
25	34	40	35	45	40	60
30	40	50	45	50	50	60
40	54	60*	60*	70	60*	100
50	65	80	70	90	75	100
60	77	90	80	100	90	100
75	96	110	110	125	125	200
100	124	150	125	175	150	200
125	156	175	175	200	200	200
150	180	225	200*	225	225	400
200	240	300	250	300	300	400
	575 VOLT 3-PHASE MOTORS (600V CIRCUIT)					
1/2	0.9	11/8	1	11/8	11/8	30
3/4	1.3	16/10	1 ⁴ /10	16/10	16/10	30
1	1.7	2	18/10	21/4	2	30
11/2	2.4	3	21/2	3	3	30
2	2.7	32/10	2 ⁸ /10	31/2	32/10	30
3	3.9	41/2	4	5	<b>4</b> ¹ /2	30
5	6.1	7½	7	8	7½	30
7½	9	10	10	12	12	30
10	11	12	12	15	15	30
15	17	20	17½	25	20	30
20	22	25	25	30	30	30
25	27	30*	30*	35	35	60
30	32	40	35	40	40	60
40	41	50	45	60	50	60
50	52	60	60	70†	60	60
60	62	75	70	80	75	100
75	77	90	80	100	90	100
100	99	110	110	125	125	200
125	125	150	125	175	150	200
150	144	175	150	200	175	200
200	192	225	200*	250	225	400

WITHOUT OVERLOAD

WITH OVERLOAD RELAYS

#### NOTES

S.F. = Motor Service Factor

* Fuse Reducers Required

† 100 Amp Switch Required



#### Motor Protection White Paper

Download our white paper on motor protection at littelfuse.com/technicalcenter



## MOTOR PROTECTION TABLES

#### Selection of POWR-PRO[®] Class J Fuses (JTD_ID / JTD Series) Based on Motor Full Load Amps

MOTOR F.L.A.	JTD_ID / JTD AMPERE RATING	MOTOR F.L.A.	JTD_ID / JTD AMPERE RATING	MOTOR F.L.A.	JTD_ID / JTD AMPERE RATING
0.00 - 0.60	8/10	12.1 – 14.5	17 ¹ / ₂	76.1 - 84.0	110
0.61-0.80	1	14.6 - 17.0	20	84.1-90.0	125
0.81 - 1.00	11/4	17.1 – 21.0	25	90.1 - 102	150
1.01 – 1.20	1½	21.1 - 25.0	30	103 – 125	175
1.21 – 1.65	2	25.1 - 28.5	35	126 – 144	200
1.66 - 2.00	21/2	28.6-34.0	40	145 – 162	225
2.01 - 2.40	3	34.1 - 37.0	45	163 – 180	250
2.41-3.30	4	37.1 - 41.0	50	181 - 204	300
3.31 - 4.10	5	41.1 - 48.0	60	205 - 240	350
4.11 - 4.90	6	48.1 - 52.0	70	241 – 288	400
4.91-6.40	8	52.1 - 59.0	80	289-312	450
6.41 - 8.00	10	59.1-66.0	90	313 – 360	500
8.01 - 9.80	12	66.1 - 76.0	100	361 - 432	600
9.81 - 12.0	15				

NOTE: For severe motor starting conditions, fuses may be sized up to 225% motor F.L.A. (See NEC® Article 430.52 for Exceptions)

#### Selection of CCMR Time-Delay Fuses Based on Motor Full Load Amps

MOTOR FULL LOAD CURRENT (F.L.A.)						
FOR MOTORS WITH TIME OF 2 SEC					CCMR AMPERE RATING	
MIN. F.L.A. (1)	MAX F.L.A. (3)	MIN. F.L.A. (1)	MAX F.L.A. (3)	MIN F.L.A. (2)	MAX F.L.A. (3)	
0.2	0.2	0.2	0.2	0.2	0.2	3/10
0.3	0.4	0.3	0.4	0.3	0.3	1/2
0.4	0.6	0.4	0.5	0.4	0.5	8/10
0.5	0.7	0.5	0.6	0.5	0.6	1
0.6	1.0	0.6	0.9	0.6	0.8	11⁄4
0.8	1.1	0.8	1.0	0.7	0.9	1½
0.9	1.3	0.9	1.1	0.8	1.0	18/10
1.1	1.4	1.1	1.2	0.9	1.1	2
1.2	2.1	1.2	2.1	1.2	1.8	21/2
1.5	2.6	1.5	2.6	1.4	2.3	3
1.8	3.0	1.8	3.0	1.6	2.6	3½
2.1	3.4	2.1	3.2	1.8	2.8	4
2.3	3.9	2.3	3.3	2.0	2.8	41/2
2.6	4.3	2.6	3.4	2.3	2.8	5
2.9	4.8	2.9	3.7	2.5	3.1	56/10
3.3	5.2	3.3	4.0	2.7	3.4	6
3.5	5.4	3.5	4.1	2.8	3.5	61⁄4
3.6	5.7	3.6	4.2	3.2	3.7	7
4.1	5.8	4.1	4.3	3.4	3.8	7½
4.3	6.2	4.3	4.6	3.6	4.2	8
4.6	6.9	4.6	5.2	4.0	4.5	9
5.2	7.7	5.2	5.8	4.5	4.9	10
5.8	8.9	5.8	6.6	5.4	5.5	12
6.9	10.0	6.9	7.7	6.7	6.7	15
8.9	13.5	8.9	10.0	6.8	9.0	20
11.5	15.8	11.2 (2)	11.8	9.0	11.0	25
14.3	17.8	13.4 (2)	13.4	10.0	15.0	30
20.7	23.3	16.1	17.9	15.6	15.9	35
23.7	26.7	18.4	20.5	17.8	18.2	40
26.6	30.0	20.7	23.1	20.0	20.4	45
30.0	33.3	23.0	25.6	22.3	22.7	50
35.5	40.0	27.6	30.1	26.7	27.3	60

1 Based on NEC  $^{\odot}$  requirement limiting the rating of time-delay fuses to 175% of motor F.L.A., or next higher rating.

2 Based on NEC[®] exception permitting fuse rating to be increased, but not to exceed, 225% motor F.L.A., however per NEC[®] Article 430.52 Class CC (0-30) fuses can now be sized up to 400% of motor F.L.A.

3 Based on Littelfuse CCMR time-delay characteristics.

NOTE: These values were calculated for motors with Locked Rotor Current (LRA), not exceeding the following values:

MOTOR F.L.A.	*LRA
0.00 - 1.00	850%
1.01 – 2.00	750%
2.01 - 10.0	650%
10.1 – 17.8	600%

*If motor LRA varies from these values, contact Littelfuse.

## ALPHANUMERIC INDEX

Product Name	Page Number
97023	115
150322	131
1LFS, 1LS Series	121
215 Series	35
216 Series	35
217 Series	35
218 Series	35
224 Series	34
225 Series	34
229 Series	34
230 Series	34
235 Series	35
239 Series	35
251 Series	33
273 Series	33
287 Series	36
297 Series	36
299 Series	36
312 Series	34
313 Series	34
314 Series	34
315 Series	34
318 Series	34
324 Series	34
325 Series	34
326 Series	34
342 Series	118
345 Series	119
354 Series	114
451 Series	33
477 Series	33
481 Series	53
505 Series	33
571 Series	117
572 Series	117
Alarm Monitoring	168
Arc-Flash	157
ATO Series	36
BLF Series	30
BLN Series	30
BLS Series	31
Box Cover Units	179
Bus Bar Series	112
BVSP Series	176
C6200	166
Cable Limiters	65
CCMR Series	27
Class CC	27
Class CD	27
Class G	26
Class J	21
Class K5	20
Class L	8
Class RK1	13

Product Name	Page Number
Class RK5	16
Class T	24
CNL Series	62
CNN / CNN E Series	62
Coordination Panels	138
Cylindrical Fuses	66
D0900	157
Definitions	198
Displays	181
Distribution Blocks	122
E-Rated Fuses	42
E5000	167
E7800	164
EL731	150
Electronic Fuses	32
Engine Controls/Diagnosis	167
EngineEye	167
FBDIN1	104
Feeder Protection	156
FLA Series	31
FlexGen	166
FLM Series	30
FLNR Series	17
FLNR ID Series	17
-	
FLQ Series FLSR Series	30
	17
FLSR_ID Series	17
FLU Series	31
Fork-Lift Fuses	62
FPS	156
FPU-32	156
FRCK Series	180
Fuse Blocks, Fuse Holders	82
Fuse Classifications	194
Fuse Reducers	178
Fuseology	183
G2000	158
G3000	158
G3300	159
GDB Series	128
Generator Protection/Control	158
GFP	115
Ground-Fault Protection	143
H4000	169
HAZGARD™	62
High-Speed Fuses	68
IDSR Series	16
In-Line Fuse Holders	131
Industrial Shock-Block	157
JCASE Series	37
JLLN Series	24
JLLS Series	24
JLS Series	22
JTD/JTD_ID Series	21

Product Name	Page Number			
KLC Series	69			
KLDR Series	28			
KLK Series	30			
KLKD Series	30			
KLKR Series	28			
KLLU Series	9			
KLNR Series	15			
KLPC Series	8			
KLQ Series	31			
KLSR Series	15			
L15S Series	69			
L17T Series	50			
L25S Series	69			
L50S Series	69			
L60030C, L60030M Series	101			
L60030MPCB	103			
L60S Series	69			
L70S Series	69			
LA100P Series	76			
LA15QS Series	71			
LA30QS Series	72			
LA50QS Series	73			
LA60Q Series	74			
LA70QS Series	75			
LA70QSF Series	74			
LAxxxURD Series	77			
LCC Series	115			
LCP Series	139			
LD Series	122			
LDC Series	10			
LEB Series	132			
LEC Series	132			
LET Series	132			
LEX Series	132			
LEX YY Series	136			
LEXT YY Series	136			
LEY Series	132			
LF Series Covers	105			
LFC600	101			
LFCL Series	65			
LFFB003	116			
LFG480, LFG600 Series	99			
LFH250, LFH600 Series	88			
LFJ 1000V Series	107			
LFJ600 Series	85			
LFPHV	109			
LFPSC	110			
LFPSJ	111			
LFR250, LFR600 Series	88			
LFT300, LFT600 Series	94			
LGR Series	64			
LHFB	116			
LHR Series	64			
Live Parts	48			



## ALPHANUMERIC INDEX

Product Name	Page Number			
LLNRK Series	13			
LLSRK/ LLSRK_ID Series	13			
LMF Series	64			
LPBC Series	122			
LPFP	115			
LPS	141			
LPSM-QC	113			
LPXV Series	106			
LRU Series	178			
LS Series	122			
LSCR Series	120			
LSCY	179			
LSKA	179			
LSOU	179			
LSOW	179			
LSOX	179			
LSOY	179			
LSOY-B	179			
LSRU	179			
LSRW	179			
LSRX	179			
LSRY	179			
LSSU	179			
LSSW	179			
LSSX	179			
LSSY	179			
LSTY	179			
LTFD Series	54			
LVSP Series	175			
M1000	168			
M2000	167			
M2500	167			
M3000	168			
M4200	168			
M4500	169			
M4600	169			
M4700	169			
M8100	165			
MAXI Series	36			
Medium Voltage	39			
MEGA Series	63			
MFP	115			
Midget Fuses	30			
MINI Series	36			
Motor Protection	154			
MOV	174			
MPS	155			
MPU-32	155			
MROplus	3			
NLKP Series	20			
NLN Series	20			
NLS Series	20			
OEM Products	67			
Overvoltage Suppression	173			

Product Name	Page Number
Panel Mount Adapters	171
PGN-1000	153
PGN-3000	153
PGR-3100	148
PGR-3200	148
PGR-4300	158
PGR-6100	154
PGR-6130	154
PGR-6150	154
PGR-6800	156
PGR-8800	157
Plug Fuses	63
Potential Transformer	47
POWR-PRO® Fuses	3
Pre-Engineered Solutions	138
Protection Relays	143
Pump Protection	156
R-Rated Fuses	40
Resistance Grounding	151
S6000	166
SB6100	157
SE-105	151
SE-107	151
SE-134C	151
SE-145	151
SE-325	152
SE-330	152
SE-330AU	152
SE-502	153
SE-601	148
SE-701	149
SE-703	149
SE-704	149
Semiconductor Fuses	68
Sigma	166
SLC Series	26
Solar Fuses	56
SPF Series	60
SPFI Series	59
SPFJ Series	61
SPL001	104
Splicer Blocks	122
SPXI Series	58
SPXV Series	57
Stud-Mounted Fuse Blocks	120
Suppression Products	172
T2000	158
T2100	159
T2200	160
T2300	160
T2400	160
T2500	161
T2600	163
T2700	161

Product Name	Page Number
T2800	150
T2900	161
T3000	162
T3100	162
T3200	150
T3300	162
T4500	163
T4800	163
T4900	164
T5000	164
T7900	165
T8400	165
Technical Information	182
Telecom Fuses	49
TLN Series	51
TLO Series	63
TLS Series	52
TMOV	174
TOO Series	63
Trailing Cable Protection	148
Varistors	174
WPB Series	133

## **CONDENSED CROSS REFERENCE**

This cross reference covers the most popular fuses for which there is a similar Littelfuse standard item. Furnished for your convenience, it is meant to serve as a guide for product selection. We suggest you check all applicable specifications before making substitutions. For special applications, more complete information, and for fuse block and medium voltage fuse cross referencing, visit Littelfuse.com or call 1-800-TEC-FUSE (1-800-832-3873).



Competitor	Littelfuse	Competitor	Littelfuse	Competitor	Littelfuse	Competitor	Littelfuse	
KOTN	NLN	CJ	JLS	JKS	JLS	NOS	NLS	
KOTS	NLS	CJS	JLS	KAA	L15S	NRN	NLN	
)KOTN	NLN	CLF	KLPC or KLLU	KAB	L25S	NRN (15-60A)	NLKP	
OKOTS	NLS	CLL	KLLU or KLPC	KAC	KLC	NRS	NLS	
.013F	L15S	CLU	KLLU or KLPC	КВН	L50S	OT	NLN	
015F	L15S	CM	BLF	KLM	KLKD	OTM	BLF or BLN	
015R	L15S	CRN-R	FLNR_ID *	KLU	KLLU or KLPC	OTN	NLN	
A025F	L25S	CRS-R	FLSR_ID	KN	KLNR	OTS	NLS	
4050F	L50S	CTN-R	KLNR	KON	NLN	PV-(1-30)A10F	SPF	
.060F	L60S	CTS-R	KLSR	KOS	NLS	REN	FLNR *	
070F	L70S	DCT	SPF [†]	KRP-C	KLPC	RES	FLSR *	
13X	L15S	EBS	BLS	KS	KLSR	RF	FLNR +	
25X	L25S [†]	ECNR	FLNR_ID *	КТК	KLK	RFA	L15S	
2D-R	LLNRK [§]	ECSR	FLSR_ID	KTKR	KLKR	RFC	KLC	
2K-R	KLNR	ERN	FLNR +	KTNR	KLNR	RFL (750V)	L70S (700 V)	
.3T	JLLN	ERS	FLSR +	KTSR	KLSR	RFN (Mersen)	FLNR +	
4BQ	KLPC	FNA	FLA	KTU 601-2000A	LDC	RFS (Mersen)	FLSR +	
4BT	KLLU or KLPC	FNM	FLM	KTU 2500-6000A	KLPC	RFV	L50S	
4BY	KLPC or KLLU	FNQ	FLQ	LCL	KLPC or KLLU	RHN	KLNR	
4J	JLS	FNQ-R	KLDR	LCU	KLPC or KLLU	RHS	KLSR	
.50P (type 1 & 4)	L50S	FRN-R	FLNR_ID *	LENRK	LLNRK	S	S00	
.60X	L60S	FRS-R	FLSR_ID	LESRK	LLSRK_ID	SA	SAO	
.6D-R	LLSRK_ID §	FWA	L15S ^{†§}	LKU	KLLU	SC	SLC	
6K-R	KLSR	FWH	L50S *§	LONRK	LLNRK	SEC	SLC	
.6T	JLLS	FWP	L70S * §	LOSRK	LLSRK_ID	SF13X	L15S	
.70P	L70S	FWX	L25S * †	LPCC	CCMR	SF25X	L25S	
BC	314	GDA	216	LPJ (SP)	JTD_ID	SF50P	L50S	
CK	CCK	GDB	217	LPNRK (SP)	LLNRK §	SF60X	L60S	
.G	SLC	GDC	218	LPSRK (SP)	LLSRK_ID	SF70P	L70S	
GA	AGA	GDL	313	MCL	KLK	SFE	SFE	
GC	312	GEB	LEB	MCR	251	SL	SLO	
.GU (1-30A)	BLN	GEBN	LET	MDA	326	T	T00	
.GW	AGW	GFA	251	MDL	313	TJN	JLLN	
JT	JTD_ID	GFN	FLA	MDQ	313	TJS	JLLS	
MG	MEG	GGC	312	MDV	315	TL	TLO	
MI	MID	GGM	235	MDX	313	TR	FLNR_ID ^{‡/§}	
NL	CNL [§]	GLR	LGR	MEN	FLM	TRM	FLM	
NN	CNN_E	GMA	235	MEQ	FLQ	TRN-R	FLNR_ID ^{‡/§}	
SO	SPF	GMD	235	MID	FLA	TRS	FLSR_ID [§]	
TC	ATO (287)	GMT	481	MOF	BLN	TRS-R	FLSR ID [§]	
T-DE	FLNR_ID [‡]	HCLR	KLKR	MOL	BLN	XL25X	L25S	
TDR		HCTR	KLDR	MTH	312	XL50F	L255 L50S *	
TM (Mersen)	KLKD	HEB	LEB	NCLR	KLNR	XL70F	L70S *	
TMR		HET	LET	NON	NLN			
TQ	FLQ	HLR	LHR	A fuse may be used	in circuits where the fu	se's voltage rating is ec	ual to or greater thar	
ATQR	KLDR	HP10M	SPF		circuit voltage, unless otherwise stated on the fuse. For example, the FLSR_ID indicating f			

A fuse may be used in circuits where the fuse's voltage rating is equal to or greater than the circuit voltage, unless otherwise stated on the fuse. For example, the FLSR_ID indicating fuse has a voltage rating of 75-600 volts. This fuse can be used on 600 volts, 480 volts, 250 volts, 125 volts, or 75 volts. Never use a fuse in a circuit having a higher rated voltage than the fuse.

* Check specific mounting dimensions before substituting.

† Check characteristics and dimensions for application before substituting.

‡ For 1/10 - 30 amperes, order non-indicating FLNR series fuses.

§ Verify voltage for DC applications.

+ Littelfuse product is a non-renewable fuse.

AX

BAF

BAN

BBS

C519

C520

481

BLF

BLN

BLS

229

225

SPFJ *

JTD_ID

JTD_ID

JLLN

JLLS

JLS

HP6J

JDL

JFL

JHC

JJN

JJS

# Additional Resources



#### Littelfuse is in the App Store!

Our free Littelfuse Catalogs and Literature App keeps our products and resources at your finger tips, wherever you are. Find the information you need, quickly and easily!

#### **Experienced Technical Professionals**

For additional questions, call or email the Littelfuse Technical Support and Engineering Service Group at **1-800-TEC-FUSE or techline@littelfuse.com.** 



#### White Papers and Additional Technical Information

Littelfuse is committed to developing technical resources that help improve electrical safety and product knowledge. Gain access to Technical Application Guides, White Papers, and a library of information at **littelfuse.com/technicalcenter**.



#### **Motor Protection**

Effective motor protection is critical in today's highly automated industrial facilities. POWR-GARD[®] fuses and protection relays provide optimum protection for motors in main, feeder, and branch circuits.



#### **Transformer Protection**

POWR-GARD fuses provide optimal overcurrent protection for both the primary and secondary of control transformers and other regular transformers above and below 600 volts.



#### Medium Voltage Fuse Protection

POWR-GARD medium voltage fuses provide short-circuit protection for motors and transformers rated 2,400 to 38,000 Vac.



#### SCCR

The NEC[®] requires Industrial Control Panels be labeled with their Short-Circuit Current Rating so users and inspectors can compare their equipment to available fault currents to avoid potential hazards.



#### **Arc-Flash Protection**

Arc-flash protection relays are intelligent controllers that safeguard equipment and personnel to prevent damage, downtime or injury due to arc flash.



#### **Overvoltage Suppression Basics**

Overvoltage conditions are an increasing concern in the electrical industry. Littelfuse has a diverse portfolio of circuit protection technologies to protect against voltage transients in multiple applications.

# **M** Littelfuse

# Need **more information** about Littelfuse[®] POWR-GARD[®] products?

Littelfuse publishes technical resources to help enhance the productivity and safety of electrical systems. To learn more about a specific product or application, visit our extensive online library at **littelfuse.com** 

- Extended Datasheets
- Time-Current Curves
- Peak Let-Thru Curves
- White Papers
- CAD Drawings
- 3D Models
- Certifications
- Cross References

# WWW.LITTELFUSE.COM

#### Littelfuse Electrical Product Portfolio Includes:

## **POWR-GARD® FUSES**







#### A Full Line of Catalogs:

#### Protection Relays & Controls Catalog (PF130N)

The comprehensive line of electronic and microprocessor-based protection relays safeguard equipment and personnel to prevent expensive damage, downtime or injury due to electrical faults.

#### POWR-GARD[®] Solar Catalog (PF140N)

POWR-GARD Solar Products are designed specifically for photovoltaic applications where issues such as heat, efficiency, longevity and global standards impact the choices in selecting circuit protection.

#### SymCom/SSAC Catalogs

SymCom and SSAC are leaders in electronic control and protection for all types and sizes of motors, pumps, timers and flashers used in many applications.

To view all Littelfuse product catalogs, visit our website at littelfuse.com/Catalogs











©2015 Littelfuse, Inc. Printed in USA.

Specifications, descriptions and illustrative material in this literature are as accurate as known at the time of publication, but are subject to changes without notice. Visit **littelfuse.com** for the most up-to-date technical information.

Form: PF101N Rev: 112415