

TMV-360A/380/381 AC MILLIVOLT METER



TMV-360A

- 1mV ~ 300V 12 Ranges
- -60dB ~ +50dB
- 10Hz ~ 500KHz



TMV-381

- 2-CH, 300 μ V ~ 100V
- -70dB ~ +40dB
- 5Hz ~ 1MHz
- Ground Separate Switch



TMV-380

- 2-CH, 1mV ~ 300V
- -60dB ~ +50dB
- 10Hz ~ 500KHz
- Ground Separate Switch

Specification

ITEM	TMV - 360A	TMV - 380	TMV - 381
Test Range RMS: dB:	1mV ~ 300V, 12 Ranges -60dB ~ +50dB, 12 Ranges		300 μ V ~ 100V, 12 Ranges -70dB ~ +40dB, 12 Ranges
FREQ. Response (RFE. of 1KHz)	10Hz ~ 500KHz $\pm$ 5% 20Hz ~ 200KHz $\pm$ 3% 30Hz ~ 100KHz $\pm$ 2%		5Hz ~ 1MHz $\pm$ 10% 10Hz ~ 500KHz $\pm$ 5% 20Hz ~ 200KHz $\pm$ 3%
Input Impedance	10M Ω // 45pF		10M Ω // 45pF
Channel Isolation	N / A	80dB for Each Channel Operated Separately 50dB for Both Channel Cooperated	
Accuracy Stability Meter Indication Output	$\pm$ 3% of Full Scale (1 KHz) Within $\pm$ 0.5% of Full Scale for $\pm$ 10% Variety of Power Average Type 1Vrms $\pm$ 10% Within 2% Distortion.		
Power Source	ACV 115V / 230V, $\pm$ 10%, 60Hz / 50 Hz		
Dimension	140(W) $\times$ 215(H) $\times$ 250(D)mm		140(W) $\times$ 215(H) $\times$ 250(D)mm
Net Weight	3.0kg		3.5kg
Accessories	ACS-001 X1, Operation Manual X1		ACS-003 X2, Operation Manual X1

勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-54151736
 勝特力电子(深圳) 86-755-83298787

[Http://www.100y.com.tw](http://www.100y.com.tw)