

Type: **9928005-Hathaway**



**General Data**

**Type:** 9928005  
**Brand:** Hathaway (USA)  
**OEM #:** 268256-001 (typical)  
**Frame:** Round/Circular  
**Volts:** 16Vdc (nominal)  
**Current:** \_\_\_ A (cont.) \_\_\_ Amp peak  
**Output:** 100 Watts (nominal)  
**RPM:** 1300 @ 16V, 780 @ 10V (no-load)  
**Torque:** \_\_\_ Nm @ \_\_\_ A ( \_\_\_ oz.in.)  
**Rating:** continuous?  
**Resistance:** 4 Ohms (nominal)  
**Wires:** 2 wire (100~150mm nominal)  
**Shaft:** 9.52mm dia x 28mm long  
**Shaft-Detail:** Plain (optional Bowden-pulley)  
**Size:** 67mm dia. x 160mm (nominal)  
**Weight:** 2.0kg

**Encoder:** 200 lines +1 PPR  
**Wires:** 10 wire (300 mm + nominal) ribbon cable (with headers)




**Condition:** Used (refurbished / tested)

**Comments:** Has 2 encoder gratings, primary 200ppr (with quadrature) + 1ppr (index).

**Note:** For higher resolution gear/down or fit a higher count encoder

**Stall-Current (test-only):**  
 2A @3.2V  
 3A @ 5V  
 \_\_\_ A @ 10V  
 \_\_\_ A @ 16V  
 \_\_\_ A @ 20V

Model: 20-10-2352-(A-8442\*)  
 Brand: Sensor Technology  
 Disc: n/a  
 OEM: 10-10-2401C  
 (\* Varies)



\*-2268 encoder requires ~75k  
 \*-2352C or D encoder requires~5k6  
 \*-2352A encoder requires <5k6

NOTICE - the information on this page is not guaranteed for accuracy - CASA accepts no responsibility (neither expressed nor implied) for any errors or the consequence therefrom.