

Part numbers—Straight outlet cable entry fittings

Aluminium

Shell Size	Code for Ancillary Fittings	Outlet Assembly		Outlet assembly comprises:	
		Part No.	Wt. oz.	Outlet	Union Nut
1	a	508/1/07621/001	-25	508/2/07639/001	508/2/07657/001
	b	508/1/07622/001	-28	508/2/07640/001	508/2/07658/001
	c	508/1/07623/001	-32	508/2/07641/001	508/2/07657/001
2	d	508/1/07624/001	-32	508/2/07642/001	508/2/07659/001
	e	508/1/07625/001	-39	508/2/07643/001	508/2/07660/001
	f	508/1/07626/001	-71	508/2/07644/001	508/2/07661/001
3	g	508/1/07627/001	-46	508/2/07645/001	508/2/07661/001
	h	508/1/07628/001	1-10	508/2/07646/001	508/2/07662/001
	i	508/1/07629/001	-84	508/2/07647/001	508/2/07662/001

Brass




Outlet Assembly		Outlet assembly comprises:	
Part No.	Wt. oz.	Outlet	Union Nut
508/1/07663/001	-71	508/2/07681/001	508/2/07699/001
508/1/07664/001	-78	508/2/07682/001	508/2/07700/001
508/1/07665/001	-95	508/2/07683/001	508/2/07699/001
508/1/07666/001	-99	508/2/07684/001	508/2/07701/001
508/1/07667/001	1-10	508/2/07685/001	508/2/07702/001
508/1/07668/001	1-90	508/2/07686/001	508/2/07703/001
508/1/07669/001	1-40	508/2/07687/001	508/2/07703/001
508/1/07670/001	3-00	508/2/07688/001	508/2/07704/001
508/1/07671/001	2-40	508/2/07689/001	508/2/07704/001

Outlet nuts must be ordered as additional items when using outlets on fixed and fixed coupler plugs and sockets.

Right Angle Outlets

Outlets can only be selected from the same group as the shell size of the plug or socket with which they are to be used.

Shell Size	Recommended Min./Max. cable O/D using suggested cable entry fittings for:						Code for Ancillary Fittings	Dimensions						Thread BS.84	
	Type Cable		Type Cable		Type Cable			Bore: A dia.	B dia.	C dia.	D dia.	E	F	Dia.	T.P.I.
	Uniradio Metvin Coremetvin Corevin		Vinmet Corevinmet		Vin										
	Min.	Max.	Min.	Max.	Min.	Max.									
1	-230	-355	-230	-355	-230	-360	a	-410	-493	-540	-470	-790	-840	-5937	26
	*-295 †-360 x -220	-410 x -275	-340 x -330 x -190	-370 x -410 x -270	-295 x -340 x -200	-385 x -410 x -275	b	-455	-548	-585	-520	1-065	-840	-6406	26
2	-230	-355	-230	-355	-230	-360	c	-410	-485	-540	-470	-850	-940	-5937	26
	-295	-440	-390	-440	-295	-420	d	-468	-578	-635	-565	-930	-940	-6875	26
	-345	-480	-345	-480	-345	-460	e	-515	-625	-680	-610	-980	-940	-7344	26
	-470	-575	-460	-575	-455	-510	f	-600	-735	-790	-695	1-485	1-250	-8437	26
3	-470	-575	-460	-574	-470	-560	g	-620	-735	-790	-695	1-060	1-070	-8437	26
	-690	-745	-685	-740	-690	-710	h	-800	-910	-995	-875	1-960	1-870	1-0625	20
	-690	-745	-685	-740	-690	-710	i	-800	-910	-995	-875	1-270	1-160	1-0625	20



Part numbers Aluminium

Shell Size	Code for Ancillary Fittings	Outlet Assembly		Outlet assembly comprises:	
		Part No.	Wt. oz.	Outlet	Union Nut
1	a	508/1/07630/001	-25	508/2/07648/001	508/2/07657/001
	b	508/1/07631/001	-32	508/2/07649/001	508/2/07658/001
2	c	508/1/07632/001	-35	508/2/07650/001	508/2/07657/001
	d	508/1/07633/001	-39	508/2/07651/001	508/2/07659/001
	e	508/1/07634/001	-46	508/2/07652/001	508/2/07660/001
	f	508/1/07635/001	-53	508/2/07653/001	508/2/07661/001
3	g	508/1/07636/001	-56	508/2/07654/001	508/2/07661/001
	h	508/1/07637/001	1-10	508/2/07655/001	508/2/07662/001
	i	508/1/07638/001	-88	508/2/07656/001	508/2/07662/001

Brass

Outlet Assembly		Outlet assembly comprises:	
Part No.	Wt. oz.	Outlet	Union Nut
508/1/07672/001	-78	508/2/07690/001	508/2/07699/001
508/1/07673/001	-92	508/2/07691/001	508/2/07700/001
508/1/07674/001	-99	508/2/07692/001	508/2/07699/001
508/1/07675/001	1-10	508/2/07693/001	508/2/07701/001
508/1/07676/001	1-30	508/2/07694/001	508/2/07702/001
508/1/07677/001	1-70	508/2/07695/001	508/2/07703/001
508/1/07678/001	1-70	508/2/07696/001	508/2/07703/001
508/1/07679/001	3-10	508/2/07697/001	508/2/07704/001
508/1/07680/001	2-40	508/2/07698/001	508/2/07704/001

Mk 7 *Suffix /001 for Mk 7 drab olive + passivation.
 Mk 4 /003 for Mk 4 Aluminium—clean finish.
 Mk 4 /005 for Mk 4 Brass—cadmium plate + passivation.