

# SUHNER® COAXIAL CONNECTOR DATA SHEET TYPE 24\_BNC-50-3-1/133\_N

### **Description**

Straight panel bulkhead cable jack, flange mount

### SUHNER full crimp cable attachement Rear mount chassis connector



General Information BNC Interface dims acc. to: IEC 60169-8 MIL-STD-

348A/301\_CECC 22120

Weight: 0.0163 Kg / 0.57 oz

Cable Cable type: RG\_58C/U

Cable type: GX\_03272
Cable type: G\_03232

Cable Entry Centre contact: crimped

Outer contact: crimped

**Electrical Data** 

Impedance:  $50\Omega$  Interface frequency max.: 4 GHz

Piece Parts Material Surface Plating

Center contact:

Copper Beryllium Alloy
Outer contact:

Copper Beryllium Alloy
Succeptate (R) Plating
Succeptate (R) Plating

Body: Brass SUCOPLATE (R) Plating

Insulator: PFA / PTFE

Fastening nut: Brass SUCOPLATE (R) Plating

Gasket: MQ (Silicon Rubber)

Washer: Bronze SUCOPLATE (R) Plating Crimp Ferrule: SUCOPLATE (R) Plating

**Attachments** Outline drawing: DOU-00009723

Catalogue drawing: DCA-00008942
Assembly instruction: DCC-0000179061

WAIVER!

While the information contained in this folder has been carefully compiled to the best of our present knowledge, it is not intended as representation or warranty of any kind on our part regarding the fitness of the products concerned for any particular use or purpose and neither shall any statement contained herein be constructed as a recommendation to infringe any industrial property rights or as a license to use any such rights. The fitness of each product for any particular purpose must be checked beforehand with our specialists.

I	Issued: 03.10.03 10:57		Document: DOC-0000186539
F	RF_Ca_Pa_C_PDF	uncontrolled copy	Page 1



HUBER+SUHNER AG Interconnect Division CH-9100 Herisau Phone +41 (0)71 353 41 11 Fax +41 (0)71 353 45 90 http://www.hubersuhner.com



## **SUHNER® COAXIAL CONNECTOR DATA SHEET**

**Notes** Mounting hole:

DOU-00008751

Order as Order as 24\_BNC-50-3-1/133\_NH

for Bulk 100 pcs for Single

**24\_BNC-50-3-1/133\_NE** for Single

#### WAIVER!

While the information contained in this folder has been carefully compiled to the best of our present knowledge, it is not intended as representation or warranty of any kind on our part regarding the fitness of the products concerned for any particular use or purpose and neither shall any statement contained herein be constructed as a recommendation to infringe any industrial property rights or as a license to use any such rights. The fitness of each product for any particular purpose must be checked beforehand with our specialists.

Issued: 03.10.03 10:57		Document: DOC-0000186539
RF_Ca_Pa_C_PDF	uncontrolled copy	Page 2



HUBER+SUHNER AG Interconnect Division CH-9100 Herisau Phone +41 (0)71 353 41 11 Fax +41 (0)71 353 45 90 http://www.hubersuhner.com