

TravelMate | B

B115-M / B115-MP

Be cool on the move

- Eye-catching new FlowCurve design
- Making mobility even better
- Everything you need for work
- Manage with ease



TravelMate B115-M / B115-MP

SPECIFICATIONS





Product views	1 Webcam 6 Headphone/speaker jack 11 USB 2.0 port 2 11.6" HD 1366 x 768 resolution LCD 7 USB 2.0 port 12 USB 3.0 port 3 FineTip keyboard 8 SD Card reader 13 HDMI® port with HDCP support 4 Precision touchpad 9 DC-in jack for AC adapter 14 Kensington lock slot 5 Power button 10 Ethernet (RJ-45) LAN port
Operating system ^{1, 2}	Windows 8.1 Pro 64-bit or Windows 8.1 64-bit
CPU and chipset ¹	Intel® Pentium® N3530 processor Intel® Celeron® N2830 processor Intel® Celeron® N2930 processor
Memory ^{1, 3, 4, 5}	DDR3L SDRAM support with up to 8 GB of DDR3L system memory
Display	11.6" HD 1366 x 768 resolution, high-brightness Acer ComfyView [™] LED- backlit TFT LCD With integrated multi-touch, supporting 10-finger touch (B115-MP)
	16:9 aspect ratio, ultra-slim design Mercury free, environment friendly
Graphics ^{1, 6}	Intel® HD Graphics with 64 MB of dedicated system memory HDMI® (High-Definition Multimedia Interface) with HDCP 1.3 (High- bandwidth Digital Content Protection) support
Audio	High-definition audio support Two built-in stereo speakers
Storage ⁷	Hard disk drive: 320 / 500 GB / 1 TB 2.5-inch 5400 RPM , or, SSD: 128 GB SSD
Webcam ¹	Video conferencing: Webcam with 1280 x 780 resolution, 720p HD audio/video recording with HDR support
Wireless and networking ^{1, 8, 9}	WLAN WPAN LAN • Acer InviLink™ Nplify™ 802.11a/b/g/n wireless LAN • Bluetooth® 4.0 • Gigabit Ethernet, Wake-on-LAN ready
Privacy control ¹	Kensington lock slot
Dimensions and weight ¹⁰	Dimensions: 291 (W) x 211 (D) x 21.2/21.2 (H) mm (11.46 x 8.31 x 0.83/0.83 inches)[B115-M]; 291 (W) x 211 (D) x 21.7/21.7 (H) mm (11.46 x 8.31 x 0.83/0.83 inches)[B115-MP] Weight: 1.32 kg (2.91 lbs.) with 4-cell battery pack [B115-M]; 1.39 kg (3.06 lbs.) with 4-cell battery pack [B115-MP]
Power adapter and battery ¹¹	Power adapter: 3-pin 40 W AC adapter Battery: 48 Wh 3220 mAh 15.2 V 4-cell Li-ion battery pack, battery life up to 7 hours
Input and control	Keyboard: 83-/84-/87-key full-size Acer FineTip keyboard with international language support Touchpad: Precision touchpad, supporting two-finger scroll and pinch. Swipes access charms, application commands and previous applications
Windows Store Apps ¹²	Productivity • Evernote® • Skitch Utilities • Acer Explorer • Intel® Experience Center
Windows Desktop Apps ^{12, 13}	Content • Microsoft Office trial • Microsoft Office trial • McAfee® Internet Security Suite • McAfee® LiveSafe™ Internet Security Suite • Acer Office Manager Agent Search • Yahoo search • Acer Power Management • Acer Office Manager Console Utilities • Acer ProShield • Acer ProShield • Acer Power Management • Acer Power Management • Acer Power Management • Acer Power Management • Acer Accessory Store
Options and accessories	Acer HDMI®-to-VGA converter
System compliance	ENERGY STAR® Wi-Fi®
Warranty	One-year International Travelers Warranty (ITW)
Quality and reliability tests	Temperature and humidity Weight and pressure Spillage Shock and vibration Keyboard-switch life Hinge life Acoustics Free drop Electrostatic discharge immunity MTBF (Mean Time Between Failure)
Shared system memory may factors. Actual system memo	g on model. enjoy the advantages of 64-bit processing. be allocated to support graphics, depending on system memory size and other oray available to the operating system will be reduced by any memory used by the ces required by the operating environment. 8. Actual throughput may vary depending on network conditions and environmental factors such as network traff or overhead, building construction and access point settings. 9. Subject to availability. 10. Weight may vary depending on product configuration, vendor components, manufacturing variability, and selected options.

- graphics solution and resources required by the operating environment.

 Memory speed may vary, depending on the CPU, chipset or memory fitted.

 A 64-bit operating system is required to enjoy the ultimate performance of 4 GB or higher memory.

 Resolution/refresh rates depend on display capability and color/depth settings.

 1 GB is 1 billion bytes, 1 TB is 1000 GB. Actual formatted capacity is less and may vary depending on preloaded materials and operating environment. Acer Recovery Management uses a portion of the stated hard disk capacity as dedicated backup space.
- - selected options.

 11. The listed battery life is based on MobileMark 2012® productivity mode testing with wireless on. Details of MobileMark 2012® testing are available at www.bapco.com. Battery life rating is for comparison purposes only. Actual battery life varies by model, configuration, applications, power management settings, operating conditions, and utilized features. A battery's maximum capacity decreases with time and use.

 12. Bundled software may vary depending on hardware configuration, OS and regional availability.

As a phenomenon known to thin-film transistors (TFTs), liquid crystal displays (LCDs) commonly exhibit a small number of discoloration dots, as so-called "non-conforming pixels." This phenomenon is a limitation of TFT LCD technology, not a product defect, and as such is not covered by Acer's warranty.

In a continuing effort to improve the quality of our products, information in this document is subject to change without notice. Images shown are only representations of some of the configurations available for this model. Availability may vary depending on region.

© 2014. All rights reserved.

Microsoft and Windows are registered trademarks of Microsoft Corporation. Intel, Pentium, Pentium Inside and Celeron are trademarks of Intel Corporation in the U.S. and other countries.



