
BASIC CORDED TELEPHONE USER'S MANUAL

(Please read before operation)

Features Introduction

- ☒ One-touch & two-touch call memories
- ☒ Handsfree and Handset speaker
- ☒ Flash function (specially for PABX)
- ☒ Mute, Redial, Hold on Music function
- ☒ Ringer volume Hi/Low switch, Pulse/Tone dialing mode selectable
- ☒ Anti-thunder design

Operation

1. Connect Line cord and Coil cord (Be careful about difference of the two cords socket)

2. One-touch call memories

--To store number in one touch memory button

On-hook state, press STORE key and last 3-5 seconds, input the desired telephone number by digit number button, press STORE key again and then press M button.

--To dial number from one touch memory button

Off-hook state, press M button directly, the stored number will be dialed directly automatically.

--To store number in two touch memory button

On-hook state, press STORE key and last 3-5 seconds, input the desired telephone number by digit number button, press STORE key again and then press NUMBER button (0-9)

--To dial number from one touch memory button

Off-hook state, press EXTRACT+NUMBER button directly, the stored number will be dialed directly automatically.

3. Flash function

-When this set is used as main telephone, please set PABX time to be same as this set, when call is coming and want to contact branch telephone, press FLASH+branch number, the incoming call will transfer to the branch telephone.

4. Mute/Hold on music

During conversation, press MUTE(HOLD) button, the receiver can not hear your voice, to recover, press MUTE (HOLD) again. (Some sets need keep pressing the button)

5. Redial function

Press REDIAL button to redial the last dialed number.